



www.mipow.com



## LUZ100 Revolutionary Bluetooth Mono Headset

Thank you for purchasing MiPow LUZ 100, we hope you have a pleasant experience with our product

Please view this user manual carefully before use.



LUZ 100

### English


### Contents

Thank you	2
About LUZ Charging Dock	2
Choose your Fit	3
Charging	4
Pairing	5
Pair LUZ with your SECOND Phones	6
LUZ Voice Guidance	7
Pair LUZ by Voice Guide	8
Talking	9
Listening to Music using LUZ	10
LUZ Specifications	10
Troubleshooting & FAQ	11
Taking care of your LUZ	12

### Thank you

Thank you for purchasing MiPow LUZ 100, you will enjoy its unique design with crystal, tubular shape body and features.


### About MiPow LUZ



#### NOTE

The Talk Button is the "SWARVOSKI" crystal.

### About LUZ Charging Dock



2

## 1. Choose your Fit

### Fit for You !

We have given you 3 earbuds. Try all the options. Pick the one that is most comfortable and fit for you.

#### Earbuds

3 different size



### Put on your Earbud

MiPow LUZ come with multiple earbud options and choose the one you feel most comfortable.

To fit a new earbud, position the earbud over the speaker housing and gently press down on the earbud.



3



## 2. Charging

### Power up !

To power up your LUZ, just put it into the included charging dock. Plug DC jack to the dock and then plug the USB cable to your computer or wall charger (not included).

### Power up your Charging Dock

Blue light power indicator will be seen on the bottom of the charging dock when you plug the USB cable to your computer USB or wall charger USB



### Charging your LUZ

- LUZ's Indicator light flashes BLUE when battery is low.
- To charge, place the LUZ headset into the charging dock with the CRYSTAL facing you.
- Charge time is 120 minutes (for full).
- Indicator light will be solid BLUE while the LUZ is charging.
- Indicator light will turn OFF when the LUZ is fully charged.

4

## 3. Pairing

### Pair LUZ with your FIRST phone

1. Activate pairing mode on your LUZ.
2. Turn on Bluetooth

**On an iPhone**  
Go to SETTINGS > GENERAL > and enable Bluetooth.

**On an Blackberry**  
Go to SETTINGS/OPTIONS > BLUETOOTH and enable Bluetooth.

**On an Android Phone**  
Go to SETTINGS > WIRELESS & NETWORK > Bluetooth Settings and enable Bluetooth.

**Other Cell Phones**  
Review the instruction manual that come with your phone

3. Press & Hold the TALK Button for 7 Seconds to activate pairing mode on your LUZ.

• Go to your phone's Bluetooth settings, ADD or SEARCH FOR DEVICES when "MiPow-LUZ" appears, select it or enter passcode "0000" if asked

• Announced "Phone ONE Connected" when paired.


When pairing, the blue indicator light flashes quickly.



Bluetooth	<input checked="" type="checkbox"/>	Bluetooth	<input type="checkbox"/>	Bluetooth	<input type="checkbox"/>	Bluetooth	<input type="checkbox"/>
Device name	XXXXXXXXXX	Device name	XXXXXXXXXX	Device name	XXXXXXXXXX	Device name	XXXXXXXXXX
Visible	<input type="checkbox"/>	Visible	<input checked="" type="checkbox"/>	Visible	<input type="checkbox"/>	Visible	<input checked="" type="checkbox"/>
Visible time-out	120 seconds (0-1800)	Visible time-out	120 seconds (0-1800)	Visible time-out	120 seconds (0-1800)	Visible time-out	120 seconds (0-1800)
Search for devices	<input type="checkbox"/>	Search for devices	<input type="checkbox"/>	Search for devices	<input type="checkbox"/>	Search for devices	<input type="checkbox"/>
			<input checked="" type="checkbox"/> MiPow-LUZ				<input checked="" type="checkbox"/> MiPow-LUZ

5

Battery meter on iPhone shows up automatically when connected.



This is a one-time event per phone. To pair your LUZ to another phone, repeat these steps. Pair MiPow LUZ with your second phone.

### Pair LUZ with your SECOND Phones

Power off your LUZ by Press & Hold TALK button for 6 seconds.

Press & Hold the TALK Button for 7 Seconds to activate pairing mode on your LUZ.

• Go to your phone's Bluetooth settings, ADD or SEARCH FOR DEVICES when "MiPow-LUZ" appears, select it or enter passcode "0000" if asked.

• Announced "Phone TWO Connected" when paired.

• Then Press the TALK button for 2 seconds to pair the FIRST phone again, announce "Phone ONE Connected" when paired. Now LUZ is connected to 2 Phones. It can answer calls from both phones

**NOTE :** If your LUZ is connected before, then you just need to press the TALK button for 2 seconds to reconnect.



6

## 4. LUZ Voice Guidance


The Luz is loaded with voice announcements that talks you through setup and daily operation, in the table below you can see the most common announcements.

"Power On"	Announced when Luz is turned on.
"Power Off"	Announced when Luz is shut down.
"Redial"	You do last number redial.
"Phone One Connected"	Announced when Luz is connected to your FIRST phone.
"Phone Two Connected"	Announced when Luz is connected to your SECOND phone.
"Disconnected"	Announced if a connected phone or device is turned off, goes out of range or has bluetooth disabled.
"Battery low"	"Battery level is low" is announced when battery has remained below one-third of the battery power.
"Battery medium"	"Battery level is medium" is announced when battery has remained below two-third of the battery power.
"Battery high"	"Battery level is high" is announced when battery has remained above two-third of the battery power.

7

## Pair LUZ by Voice Guide

Wear your LUZ and press the TALK button as the picture shown on the left. Press & Hold the TALK button for 7 seconds - about 2 seconds interval. It will announce "Power On" and carry on another 4 seconds interval. It will announce "Pairing" and then release TALK button and Go to your phone's Bluetooth settings.




Mobile phone's Bluetooth settings:

- ADD or SEARCH FOR DEVICES when "MiPow-LUZ" appears, select it or enter passcode "0000" if asked.
- Announced "Phone ONE Connected" when paired.

Bluetooth	<input checked="" type="checkbox"/>	Bluetooth	<input type="checkbox"/>	Bluetooth	<input type="checkbox"/>	Bluetooth	<input type="checkbox"/>
Device name	XXXXXXXXXX	Device name	XXXXXXXXXX	Device name	XXXXXXXXXX	Device name	XXXXXXXXXX
Visible	<input type="checkbox"/>	Visible	<input checked="" type="checkbox"/>	Visible	<input type="checkbox"/>	Visible	<input checked="" type="checkbox"/>
Visible time-out	120 seconds (0-1800)	Visible time-out	120 seconds (0-1800)	Visible time-out	120 seconds (0-1800)	Visible time-out	120 seconds (0-1800)
Search for devices	<input type="checkbox"/>	Search for devices	<input type="checkbox"/>	Search for devices	<input type="checkbox"/>	Search for devices	<input type="checkbox"/>
			<input checked="" type="checkbox"/> MiPow-LUZ				<input checked="" type="checkbox"/> MiPow-LUZ

Battery meter on iPhone shows up automatically when connected.

Adjust the LUZ Speaker Volume  
Press  $\oplus$  to increase the LUZ speaker loudness  
Press  $\ominus$  to decrease the LUZ speaker loudness



8

## 5. Talking

Press the Crystal (TALK button) on your LUZ to start all functions.

• **POWER ON** Press TALK Button for 2 seconds or more.

• **POWER OFF** Press & Hold TALK Button for 6 seconds.

• **ANSWER A CALL** Press TALK Button

**NOTE** This will also answer an incoming call while on a call. When your LUZ is connected to TWO phones, this will answer the phone on the call form either phone.

• **REJECT A CALL** Press TALK Button for 2 seconds while phone is ringing.

• **MAKE A CALL** Select or dial the number from your phone or phonebook.

• **TRANSFER A CALL** When you talk on the LUZ, press 2 seconds to transfer the call to the phone, press 2 seconds again to transfer the call back to LUZ.



• **REDIAL LAST NUMBER CALLED** Double Click TALK Button when you hear music or in standby mode

• **INITIATE VOICE DIALING** While in standby mode, press TALK Button for 2 seconds, and then speak a command.

**NOTE** When connected to multiple phones, Redial and Voice Dial will work on the phone with last active call.

• **SLEEP** When LUZ is put into the charging dock, LUZ is in sleep mode and the pairing is disconnected. You can take the call from mobile phone.

• **WAKE** When LUZ is taken out of the charging dock, LUZ is in wake mode and the pairing is auto-connected. You can take the call from LUZ.



9

• **Stand** When LUZ is put into the charging dock with no charging power connected, the charging dock is worked as a stand, and LUZ is still in Standby mode that you can take call from LUZ.



## 6. Listening to Music using LUZ

LUZ is capable of streaming over Bluetooth - either from a mobile phone or any other Bluetooth device supporting A2DP.

Once you have paired your LUZ with your mobile phone or with a Bluetooth music player, use your phone or music player to play and pause. When you receive call, the music will automatically be suspended and you will be able to answer or reject a call through the LUZ. Once you end a call, the music should recommence.

## 7. LUZ Specifications

**TALKING** Up to 7 hours  
**STANDBY** Time Up to 5 days  
**CHARGING** 2 hours (full)  
**WIRELESS RANGE** 33ft (10m)  
**BLUETOOTH** Bluetooth 3.0, 2.1+EDR  
**CONNECTIONS** Supports up to 8 paired devices and 2 active HP and A2DP connections with Multipoint

**SPEAKER** Wideband-capable  
**AUDIO QUALITY** HD Audio (16kHz)  
**WEIGHT** 7 grams  
**DIMENSIONS** 48(L) x 24(W) x 8.8(+) mm

10

## 8. Troubleshooting & FAQ

### I hear crackling noises

For the best audio quality, always wear your headset on the same side if your body as your mobile phone.

### I cannot hear anything in my headset

- Ensure that the headset is paired with the phone.
- Make sure that the phone is connected to the headset-if it does not connect either from the phone's bluetooth menu or by pressing the TALK button, following the pairing instructions in Section 3 or 4.

### I have pairing problems

The Luz is designed to work with Bluetooth mobile phones. It can also work with other devices that are compliant with Bluetooth version 3.0 and support a headset, hands-free profile, A2DP media play.

**Will the LUZ 100 work with other Bluetooth devices ?**  
The LUZ is designed to work with Bluetooth mobile phones. It can also work with other devices that are compliant with Bluetooth version 3.0 and support a headset, hands-free profile, A2DP media play.

**I cannot use reject call, redial or voice dialing, battery App meter**  
These functions are depend on your phone supporting them. Please check your mobile phone's manual for further details.

changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

## 9. Taking care of your LUZ

- Always store the LUZ with the power off and safely protected.
- Avoid storage at extreme temperatures (above 45°C or below -10°C). This can shorten battery life and may affect operation.
- Do not expose the LUZ to rain or other liquids.

### Notes on Environmental Protection

After the implementation of the European Directive 2002/96/EU in the national legal system, the following applies: Electrical and electronic devices must not be disposed of with domestic waste.

Consumers are obliged by law to return electrical and electronic devices at the end of their service lives to the public collection points that are set up for this purpose or designated points of sale.

However, such details are defined by the national law of the respective country. This symbol on the product, the instruction manual or the packaging indicates that the product is subject to these regulations.

By recycling, reusing the materials, or other forms of utilizing old devices, you are making an important contribution in protecting our environment.

11

12

## FCC Statement

This equipment complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

## Warranty Card

### Limited Warranty

Thank you for your purchase of MIPOW's product. MIPOW warrants that the product is at the time of its original purchase free of defects in workmanship and material. This Limited Warranty for the product shall last for twelve(12) months from the date of original purchase.

This original warranty card and original invoice must be presented at the time you require warranty service or such warranty will be voided.

This limited warranty is valid only if the product is used for the purpose for which it was designed. It does not apply to damage or loss caused by negligence; physical abuse; misuse; accident; exposure to moisture; dampness or extreme thermal; unauthorized modifications; unauthorized opening or repair; forces of nature; or other actions beyond the reasonable control of MIPOW.

In case of when the warranty does not apply, a repair or replacement charge will be incurred. the customer shall be responsible for sending the defective product to and collecting the repaired or replaced product from the service centre.

**NB: MIPOW reserves the right to interpret the terms and conditions contained herein; and the right for any changes without prior notice.**



## Service Centre