

Memory Modules

---

User Guide

© Copyright 2007 Hewlett-Packard  
Development Company, L.P.

The information contained herein is subject  
to change without notice. The only  
warranties for HP products and services are  
set forth in the express warranty statements  
accompanying such products and services.  
Nothing herein should be construed as  
constituting an additional warranty. HP shall  
not be liable for technical or editorial errors  
or omissions contained herein.

First Edition: January 2007

Document Part Number: 431177-001

Antenna House XSL Formatter

# Table of contents

Adding or replacing a memory module

Index ..... 5

# EVALUATION XSL FORMATTER

# Adding or replacing a memory module

The computer has one memory module compartment, which is located on the bottom of the computer. The memory capacity of the computer can be upgraded by adding a memory module to the vacant expansion memory module slot or by upgrading the existing memory module in the primary memory module slot.

---

 **WARNING!** To reduce the risk of electric shock and damage to the equipment, unplug the power cord and remove all batteries before installing a memory module.

---

 **CAUTION** Electrostatic discharge (ESD) can damage electronic components. Before beginning any procedure, ensure that you are discharged of static electricity by touching a grounded metal object.

---

To add or replace a memory module:


1. Save your work.
2. Shut down the computer and close the display.

Vista version. If we ship with XP, this will say "in Standby"

If you are not sure whether the computer is off or **in the Sleep state**, turn the computer on by pressing the power button. Then shut down the computer through the operating system.

3. Disconnect all external devices connected to the computer.
4. Unplug the power cord from the AC outlet.
5. Turn the computer upside down on a flat surface.
6. Remove the battery from the computer.
7. Loosen the 2 memory module compartment screws **(1)**.

8. Lift the memory module compartment cover (2) away from the computer.



9. If you are replacing a memory module, remove the existing memory module:


- a. Pull away the retention clips (1) on each side of the memory module.

The memory module tilts up.

 **CAUTION** To prevent damage to the memory module, hold the memory module by the edges only. Do not touch the components on the memory module.

- b. Grasp the edge of the memory module (2), and gently pull the module out of the memory module slot.

To protect a memory module after removal, place it in an electrostatic-safe container.



**10.** Insert a new memory module:

- a. Align the notched edge (1) of the memory module with the tab in the memory module slot.




**CAUTION** To prevent damage to the memory module, hold the memory module by the edges only. Do not touch the components on the memory module.

- b. With the memory module at a 45-degree angle from the surface of the memory module compartment, press the module (2) into the memory module slot until it is seated.

- c. Gently press the memory module (3) down, applying pressure to both the left and right edges of the memory module, until the retention clips snap into place.




**CAUTION** To prevent damage to the memory module, be sure that you do not bend the memory module.



- 11.** Align the tabs (1) on the memory module compartment cover with the notches on the computer.

- 12.** Close the cover (2).

- 13.** Tighten the 2 memory module compartment screws (3).



14. Replace the battery.
15. Reconnect external power and external devices.
16. Turn on the computer.

Antenna House XSL Formatter

# Index

## M

### memory

- adding memory modules 1
- replacing memory modules 1
- upgrading memory modules 1

### memory module

- adding 1
- inserting 3
- removing 2
- replacing 1
- upgrading 1

### memory module compartment

#### cover

- removing 2
- replacing 3

ANTENNA HOUSE XSL FORMATTER EVALUATION