

# RSTi-EP User Manual

GFK-2958D

July 2017



*These instructions do not purport to cover all details or variations in equipment, nor to provide for every possible contingency to be met during installation, operation, and maintenance. The information is supplied for informational purposes only, and GE makes no warranty as to the accuracy of the information included herein. Changes, modifications, and/or improvements to equipment and specifications are made periodically and these changes may or may not be reflected herein. It is understood that GE may make changes, modifications, or improvements to the equipment referenced herein or to the document itself at any time. This document is intended for trained personnel familiar with the GE products referenced herein.*

*Public – This document is approved for public disclosure.*

*GE may have patents or pending patent applications covering subject matter in this document. The furnishing of this document does not provide any license whatsoever to any of these patents.*

***GE provides the following document and the information included therein as-is and without warranty of any kind, expressed or implied, including but not limited to any implied statutory warranty of merchantability or fitness for particular purpose.***

Revised: July 2017

Issued: Dec 2015

© 2015 - 2017 General Electric Company.

\* Indicates a trademark of General Electric Company and/or its subsidiaries. All other trademarks are the property of their respective owners.

## *Safety Symbol Legend*

---



### ***Warning***

---

Indicates a procedure or condition that, if not strictly observed, could result in personal injury or death.



### ***Caution***

---

Indicates a procedure or condition that, if not strictly observed, could result in damage to or destruction of equipment.



### ***Attention***

---

Indicates a procedure or condition that should be strictly followed to improve these applications.

## Contact Information

If you purchased this product through an Authorized Channel Partner, contact the seller directly.

### General Contact Information

Online technical support and GlobalCare	<a href="http://support.ge-ip.com">http://support.ge-ip.com</a>
Additional information	<a href="http://www.geautomation.com/">http://www.geautomation.com/</a>
Solution Provider	<a href="mailto:solutionprovider.ip@ge.com">solutionprovider.ip@ge.com</a>

### Technical Support

If you have technical problems that cannot be resolved with the information in this manual, contact us by telephone or email, or on the web at <http://support.ge-ip.com>

### Americas

Online Technical Support	<a href="http://support.ge-ip.com">http://support.ge-ip.com</a>
Phone	1-800-433-2682
International Americas Direct Dial	1-780-420-2010 (if toll free 800 option is unavailable)
Technical Support Email	<a href="mailto:support.ip@ge.com">support.ip@ge.com</a>
Customer Care Email	<a href="mailto:customercare.ip@ge.com">customercare.ip@ge.com</a>
Primary language of support	English

### Europe, the Middle East, and Africa

Online Technical Support	<a href="http://support.ge-ip.com">http://support.ge-ip.com</a>
Phone	+800-1-433-2682
EMEA Direct Dial	+420 239015850 (if toll free 800 option is unavailable or if dialing from a mobile telephone)
Technical Support Email	<a href="mailto:support.emea.ip@ge.com">support.emea.ip@ge.com</a>
Customer Care Email	<a href="mailto:customercare.emea.ip@ge.com">customercare.emea.ip@ge.com</a>
Primary languages of support	English, French, German, Italian, Czech, Spanish

### Asia Pacific

Online Technical Support	<a href="http://support.ge-ip.com">http://support.ge-ip.com</a>
Phone	+86-400-820-8208 +86-21-3877-7006 (India, Indonesia, and Pakistan)
Technical Support Email	<a href="mailto:support.cn.ip@ge.com">support.cn.ip@ge.com</a> (China) <a href="mailto:support.jp.ip@ge.com">support.jp.ip@ge.com</a> (Japan) <a href="mailto:support.in.ip@ge.com">support.in.ip@ge.com</a> (remaining Asia customers)
Customer Care Email	<a href="mailto:customercare.apo.ip@ge.com">customercare.apo.ip@ge.com</a> <a href="mailto:customercare.cn.ip@ge.com">customercare.cn.ip@ge.com</a> (China)



## Table of Contents

<b>RSTi-EP USER MANUAL .....</b>	<b>III</b>
<b>TABLE OF CONTENTS .....</b>	<b>I</b>
<b>CHAPTER 1 INTRODUCTION.....</b>	<b>7</b>
1.1 DOCUMENT UPDATES.....	7
1.2 SYSTEM OVERVIEW .....	8
1.2.1 Double-click Installation.....	9
1.3 GENERAL DESCRIPTION OF THE FIELDBUS NETWORK ADAPTERS.....	10
1.4 GENERAL TECHNICAL DATA FOR THE FIELDBUS NETWORK ADAPTER .....	11
1.5 GENERAL DESCRIPTION OF I/O MODULES.....	13
1.5.1 Standard Connector.....	14
1.5.2 HD Connector EP-8360.....	14
1.5.3 Cable Protection.....	15
1.6 GENERAL TECHNICAL DATA FOR I/O MODULES .....	16
1.7 MECHANICAL FIXING ELEMENTS.....	17
1.8 TYPE PLATE.....	17
1.9 MARKERS .....	18
1.9.1 Swivel Marker.....	18
<b>CHAPTER 2 SAFETY .....</b>	<b>20</b>
2.1 GENERAL SAFETY NOTICE.....	20
2.1.1 Electrostatic Discharge.....	20
2.1.2 Open Equipment.....	20
2.1.3 Fusing.....	21
2.1.4 Earthing (functional earth FE).....	21
2.1.5 Shielding.....	21
2.1.6 Overcurrent.....	21
2.2 INTENDED USE.....	21
2.3 USE IN A POTENTIALLY EXPLOSIVE ATMOSPHERE.....	22
2.3.1 ATEX Zone 2 .....	23
2.3.2 ATEX & IECEx Marking.....	23
2.4 LEGAL NOTICE.....	23
2.5 USE OF RSTi-EP STATIONS ABOVE 2000M SEA LEVEL.....	23
<b>CHAPTER 3 CONFIGURATION.....</b>	<b>24</b>
3.1 ORDER AND ARRANGEMENT OF THE MODULES.....	24
3.1.1 Arrangement of Safe Power-feed Modules .....	25
3.1.2 Power Supply Concept.....	26
3.2 INSTALLATION DISTANCES .....	26
3.2.1 Calculation of Space Requirements.....	28
3.3 USE IN A POTENTIALLY EXPLOSIVE ATMOSPHERE.....	28
3.3.1 ATEX & IECEx Marking.....	29
3.4 SPRING-STYLE SYSTEM CABLING.....	29
3.5 CURRENT DEMAND AND POWER SUPPLY .....	29
3.5.1 Power Supply Derating.....	29
3.6 EXAMPLE CALCULATION FOR THE POWER SUPPLY.....	31

3.6.1	Calculation of the Current Demand for the Input Current .....	31
3.6.2	Calculation of the Current Demand for the Output Current .....	32
3.7	CALCULATION OF POWER LOSS.....	34
3.7.1	Calculation of Power Loss for Use in a Potentially Explosive Atmosphere .....	34
3.8	FEEDBACK ENERGY IN DO MODULES.....	34
3.8.1	Calculation of Feedback Energy .....	35
3.9	PARAMETER OVERVIEW .....	36
3.10	DATA WIDTH OF I/O MODULE, DEPENDENT ON THE NETWORK ADAPTER USED .....	46
<b>CHAPTER 4</b>	<b>DETAILED DESCRIPTIONS OF THE FIELDBUS NETWORK ADAPTERS.....</b>	<b>52</b>
4.1	PROFIBUS DP NETWORK ADAPTER EPXPBS001 .....	52
4.1.1	LEDs.....	53
4.1.2	Addressing.....	55
4.1.3	Connection Diagrams.....	56
4.1.4	Specifications .....	57
4.1.5	Supported Modules and Power Supplies.....	59
4.2	PROFINET IRT NETWORK ADAPTER EPXPNS001 .....	61
4.2.1	LEDs.....	61
4.2.2	Connection Diagrams.....	63
4.2.3	Specifications .....	64
4.2.4	Supported Modules and Power Supplies.....	65
4.3	ETHERCAT® NETWORK ADAPTER EPXETC001 .....	67
4.3.1	LEDs.....	68
4.3.2	Connection Diagrams.....	69
4.3.3	Specifications .....	71
4.3.4	RSTi-EP Status Messages.....	72
4.3.5	Module Status Messages .....	73
4.3.6	Module Diagnosis.....	73
4.3.7	Supported Modules and Power Supplies.....	74
4.4	MODBUS® TCP NETWORK ADAPTER EPXMBE001 .....	75
4.4.1	LEDs.....	75
4.4.2	Connection Diagrams.....	77
4.4.3	Specifications .....	78
4.4.4	Configuration of the IP Address.....	79
4.4.5	Packed Process Data .....	83
4.4.6	0x1000 – 0x1006 Network adapter Identifier.....	85
4.4.7	0x1000 – 0x1006 Network adapter Status.....	85
4.4.8	0x1010 Process Image Length in Bits for the Output Modules.....	85
4.4.9	0x1010 Process Image Length in Bits for the Input Modules.....	85
4.4.10	0x1017 Register – Mapping Revision.....	85
4.4.11	0x1018 – 0x101B Collective Diagnostics Message for I/O Modules .....	85
4.4.12	0x101C – 0x101F Collective Process Message for I/O Modules.....	86
4.4.13	0x1028 – 0x102F Module Status.....	86
4.4.14	0x1030 MODBUS DATA EXCHANGE Watchdog, Current Time.....	86
4.4.15	0x1120 MODBUS DATA EXCHANGE watchdog, predefined time.....	86
4.4.16	0x1121 MODBUS DATA EXCHANGE Watchdog Reset Register .....	86
4.4.17	0x1122 Lock force Mode on Web Server.....	86
4.4.18	0x1031 MODBUS CONNECTION Mode Register .....	87
4.4.19	0x1131 MODBUS CONNECTION Timeout in Sec .....	87
4.4.20	0x1132 Check Reference List prior to Data Exchange .....	87

4.4.21	0x1133 Process Alarm .....	87
4.4.22	0x1134 Diagnostic Alarm .....	87
4.4.23	0x1135 Field Bus or Reference List Error Behavior .....	87
4.4.24	0x1136 Module Removal Behavior .....	87
4.4.25	0x1137 Data Format.....	88
4.4.26	0x113C – 0x113F Save Module Parameters.....	88
4.4.27	0x27FE Number of Entries in the Current Module List.....	88
4.4.28	0x27FF Number of Entries in the Reference Module List.....	88
4.4.29	0x2800 – 0x287F Reference Module List.....	88
4.4.30	0x2A00 – 0x2A7F Current Module List .....	88
4.4.31	0x2B00 – 0x2B7F Module offsets of process data .....	88
4.4.32	0x8000 – 0x87FF Process Data Inputs.....	89
4.4.33	0x9000 – 0x97FF Process Data Outputs .....	89
4.4.34	0xA000 – 0xA7FF Diagnostics.....	89
4.4.35	0xB000 – 0xB7FF Process Alarms .....	89
4.4.36	0xC000 – 0xFFFF Parameters.....	89
<b>CHAPTER 5</b>	<b>DETAILED DESCRIPTIONS OF I/O MODULES.....</b>	<b>90</b>
5.1	DIGITAL INPUT MODULE EP-1214.....	90
5.2	DIGITAL INPUT MODULE EP-1218.....	94
5.3	DIGITAL INPUT MODULE EP-1318.....	98
5.4	DIGITAL INPUT MODULE EP-1804.....	102
5.5	DIGITAL INPUT MODULE EP-125F .....	108
5.6	DIGITAL INPUT MODULE EP-12F4.....	113
5.6.1	Time Stamp Function.....	117
5.6.2	Structure of an ETS Entry .....	117
5.6.3	Example for the Mode of Operation.....	118
5.7	DIGITAL OUTPUT MODULE EP-2214.....	121
5.8	DIGITAL OUTPUT MODULE EP-2614.....	126
5.9	DIGITAL OUTPUT MODULE EP-2634.....	131
5.10	DIGITAL OUTPUT MODULE EP-2218.....	136
5.11	DIGITAL OUTPUT MODULE EP-225F.....	141
5.12	DIGITAL OUTPUT MODULE EP- 2814.....	146
5.13	DIGITAL OUTPUT MODULE EP- 2714.....	151
5.14	DIGITAL OUTPUT MODULE EP- 5111.....	157
5.14.1	Setting Up the Counter.....	165
5.14.2	Counter Functions.....	165
5.14.3	Additional Functions Features.....	172
5.15	DIGITAL COUNTER MODULE EP- 5112 .....	178
5.15.1	Setting Up the Counter.....	185
5.15.2	Counter Functions.....	185
5.15.3	Additional Counter Features.....	190
5.16	DIGITAL FREQUENCY COUNTER MODULE EP- 5212 .....	196
5.16.1	Function Frequency Counting.....	202
5.17	SERIAL COMMUNICATION MODULE EP-5261.....	205
5.18	SSI ENCODER INTERFACE MODULE EP- 5311.....	215
5.19	DIGITAL PULSE WIDTH MODULATION OUTPUT MODULE EP- 5422.....	220
5.20	DIGITAL PULSE WIDTH MODULATION OUTPUT MODULE EP- 5442.....	225
5.21	ANALOG INPUT MODULE EP- 3164.....	230
5.22	ANALOG INPUT MODULE EP- 3264.....	236

5.23	ANALOG INPUT MODULE EP- 3124.....	243
5.24	ANALOG INPUT MODULE EP-3368.....	249
5.25	ANALOG INPUT MODULE EP-3468.....	254
5.26	ANALOG OUTPUT MODULE EP-4164.....	260
5.27	ANALOG OUTPUT MODULE EP-4264.....	266
5.28	ANALOG INPUT MODULE EP-3704.....	273
5.29	ANALOG INPUT MODULE EP-3804.....	282
5.30	POWER-FEED MODULE FOR INPUT CURRENT PATH EP-7631.....	290
5.31	POWER-FEED MODULE FOR OUTPUT CURRENT PATH EP-7641.....	293
5.32	SAFE FEED-IN MODULES EP-1901, EP-1902, AND EP-1922 .....	296
5.33	POTENTIAL DISTRIBUTION MODULE FOR INPUT CURRENT PATH EP-711F .....	297
5.34	POTENTIAL DISTRIBUTION MODULE FOR OUTPUT CURRENT PATH EP-751F.....	299
5.35	POTENTIAL DISTRIBUTION MODULE FOR FUNCTIONAL EARTH EP-700F.....	301
5.36	0-V POTENTIAL DISTRIBUTION MODULE FOR INPUT CURRENT PATH EP-710F.....	303
5.37	0-V POTENTIAL DISTRIBUTION MODULE FOR OUTPUT CURRENT PATH EP-750F.....	305
5.38	EMPTY SLOT MODULE EP-8310.....	307
5.39	TERMINATION KIT EP-8301 .....	308
<b>CHAPTER 6</b>	<b>INSTALLATION.....</b>	<b>310</b>
6.1	PREPARATIONS FOR ASSEMBLY.....	310
6.1.1	<i>Environmental Conditions.....</i>	310
6.1.2	<i>DIN Rail.....</i>	310
6.1.3	<i>Stripping Lengths.....</i>	310
6.1.4	<i>Unpacking and Delivery.....</i>	311
6.1.5	<i>Use in a Potentially Explosive Atmosphere.....</i>	311
6.1.6	<i>Installation Position.....</i>	312
6.1.7	<i>Installation Distances.....</i>	312
6.1.8	<i>Calculation of Space Requirements.....</i>	314
6.1.9	<i>Installation Sequence.....</i>	314
6.1.10	<i>Arrangement of SIL Modules.....</i>	315
6.1.11	<i>Preparation and the required tool.....</i>	315
6.2	ASSEMBLING THE RSTi-EP STATION .....	315
6.3	ATTACHING THE MARKER.....	319
6.3.1	<i>Attaching the Swivel Marker .....</i>	319
6.4	WIRING .....	320
6.4.1	<i>Wiring of Modules with Standard Connectors.....</i>	320
6.4.2	<i>Wiring of Modules with HD Connectors EP-8360.....</i>	321
6.5	INSULATION TEST .....	322
<b>CHAPTER 7</b>	<b>EARTHING AND SHIELDING.....</b>	<b>324</b>
7.1	EARTHING OF SHIELDED CABLES.....	325
7.1.1	<i>Shielded Cables Increase Interference Resistance.....</i>	326
7.1.2	<i>Proper Use of Shielded Cables.....</i>	326
7.1.3	<i>Effective shielding.....</i>	327
7.2	POTENTIAL RATIOS.....	329
7.2.1	<i>Basic aspects.....</i>	329
7.2.2	<i>Potential-free Design .....</i>	329
7.2.3	<i>Non-isolated Design.....</i>	330
7.3	ELECTROMAGNETIC COMPATIBILITY (EMC).....	331
7.3.1	<i>Ensuring EMC.....</i>	331

7.3.2	<i>Earthing of Inactive Metal Parts</i> .....	331
7.3.3	<i>PE connection</i> .....	331
7.3.4	<i>Unearthed Operation</i> .....	332
7.3.5	<i>DIN Rails</i> .....	332
7.3.6	<i>Cabinet Design According to EMC Guidelines</i> .....	333
7.4	<i>SHIELDING OF CABLES</i> .....	335
7.4.1	<i>Equipotential Bonding</i> .....	336
7.4.2	<i>Inductance wiring</i> .....	336
<b>CHAPTER 8</b>	<b>COMMISSIONING</b> .....	<b>339</b>
8.1	<i>REQUIREMENTS</i> .....	339
8.2	<i>CONFIGURING EPXPNS001</i> .....	340
8.2.1	<i>Configuring EPXPNS001 Parameters</i> .....	342
8.2.2	<i>Adding EPXPNS001 Modules to a Remote Node</i> .....	344
8.2.3	<i>Configuring EPXPNS001 Module Parameters</i> .....	345
8.3	<i>CONFIGURING EPXPBS001</i> .....	346
8.3.1	<i>Adding Slaves and Modules</i> .....	346
8.3.2	<i>Configuring Module Data Areas</i> .....	349
8.3.3	<i>Configuring DP-V1 Settings for a Slave</i> .....	350
8.4	<i>CONFIGURING EPXECT001</i> .....	352
8.5	<i>CONFIGURING EPXMBE001</i> .....	356
<b>CHAPTER 9</b>	<b>WEB SERVER</b> .....	<b>357</b>
9.1	<i>REQUIREMENTS</i> .....	358
9.1.1	<i>Operating System</i> .....	358
9.1.2	<i>Browser</i> .....	358
9.1.3	<i>Device Drivers</i> .....	358
9.2	<i>INSTALLING THE USB DRIVER</i> .....	358
9.3	<i>STARTING THE WEB SERVER</i> .....	359
9.3.1	<i>Activating the Ethernet Socket</i> .....	360
9.4	<i>SETTING UP REGISTRATION DATA AND PASSWORD PROTECTION</i> .....	361
9.5	<i>NAVIGATION AND OPERATING INSTRUCTIONS</i> .....	363
9.5.1	<i>Setting the Language</i> .....	363
9.5.2	<i>Zooming the View In/Out</i> .....	363
9.5.3	<i>Quick View (Tooltip) of Detailed Values</i> .....	364
9.6	<i>DISPLAYING AND EDITING THE NETWORK ADAPTER STATUS</i> .....	365
9.6.1	<i>Resetting the Web Server</i> .....	366
9.6.2	<i>Resetting the Network Adapter to Factory Settings</i> .....	366
9.6.3	<i>Accessing Network Adapter Parameters</i> .....	367
9.7	<i>DISPLAYING MODULE DATA AND EDITING PARAMETERS</i> .....	367
9.8	<i>DISPLAYING NODE INFORMATION</i> .....	368
9.8.1	<i>Displaying Process Data</i> .....	369
9.8.2	<i>Displaying Diagnostic Data</i> .....	369
9.9	<i>WEB SERVER IN FORCE MODE</i> .....	370
9.9.1	<i>Open the Detail View of the Station in Force Mode</i> .....	371
9.9.2	<i>Filtering the Module View</i> .....	371
9.9.3	<i>Resetting Filters</i> .....	372
9.9.4	<i>Manually Switching Outputs (Forcing)</i> .....	372
9.9.5	<i>Modules with Registers</i> .....	373
9.9.6	<i>Ending/Deactivating Forced Operations</i> .....	373

9.10	UPDATING FIRMWARE .....	374
9.11	WEB SERVER ABOUT HELP.....	377
9.11.1	<i>Exporting Log Data, Saving a Service File</i> .....	377
<b>CHAPTER 10</b>	<b>REPLACING COMPONENTS.....</b>	<b>379</b>
10.1	REMOVING/REPLACING THE PLUG-IN UNIT.....	379
10.2	REPLACING THE ELECTRONIC UNIT .....	380
10.3	REPLACING AN I/O MODULE .....	386
10.4	REMOVING/REPLACING CONNECTORS .....	388
10.5	REMOVING/REPLACING CABLES .....	390
<b>CHAPTER 11</b>	<b>DISASSEMBLY AND DISPOSAL .....</b>	<b>392</b>
11.1	DISASSEMBLING THE RSTi-EP STATION .....	392
11.2	DISPOSING OF THE RSTi-EP STATION.....	393
<b>CHAPTER 12</b>	<b>LED INDICATORS AND TROUBLESHOOTING.....</b>	<b>395</b>
12.1	FIELDBUS NETWORK ADAPTERS .....	395
12.2	I/O MODULES .....	400
<b>CHAPTER 13</b>	<b>ACCESSORIES AND REPLACEMENT PARTS.....</b>	<b>407</b>
13.1	ACCESSORIES .....	407
13.2	REPLACEMENT PARTS .....	407
<b>CHAPTER 14</b>	<b>: STANDALONE CONTROLLER FOR RSTi-EP .....</b>	<b>410</b>
14.1	HARDWARE INSTALLATION .....	413
14.1.1	<i>Initial Checks</i> .....	413
14.1.2	<i>Installation Location</i> .....	413
14.2	GROUNDING.....	415
14.3	REPLACEMENT OF INTERNAL SUPER CAPACITOR (EPSACC001).....	415
14.4	REPLACEMENT OF RTC BATTERY .....	416
<b>APPENDIX A</b>	<b>DECIMAL/HEXADECIMAL CONVERSION TABLE .....</b>	<b>417</b>

# Chapter 1 Introduction

This manual describes the RSTi-EP remote I/O system. The products of the RSTi-EP series are intended for use in industrial automation. A RSTi-EP station with network adapter and connected modules is intended for the decentralized control of systems or sub-systems. Via the network adapter every module of a station is integrated into a fieldbus structure and connected to the primary control unit. The RSTi-EP products conform to protection class IP 20 (in accordance with DIN EN 60529), they can be used in potentially explosive atmospheres rated as Zone 2 (as per Directive 2014/34/EU) and in safe zones.

The observance of the supplied documentation is part of the intended use. The products described in this manual may only be used for the intended applications and only in connection with certified third-party devices or components.

Introductory material may be found in this chapter along with a system overview. Chapter 2 provides information about safety. Chapter 3 provides configuration instruction. Chapter 4 provides detailed descriptions of the network adapters. Chapter 5 provides detailed descriptions of the I/O modules. Chapter 6 provides information on installation and setup. Chapter 7 provides information on earthing and shielding. Chapter 8 provides information on commissioning. Chapter 9 covers the Web Server. Chapter 10 provides detailed instructions for replacing components. Chapter 11 describes disassembly and disposal of the RSTi-EP station. Chapter 12 covers the LEDs and troubleshooting. Chapter 13 provides ordering information for accessories and replacement parts. Appendix A is a decimal/hexadecimal conversion table.



## Caution

Prior to hot-swapping I/O modules, refer to section *Replacing the Electronic Unit*.

---

## 1.1 Document Updates

Rev	Date	Description
D	July 2017	Added support for CE100, including the following procedures: <ul style="list-style-type: none"><li>• Replacement of Internal Super Capacitor (EPSACC001)</li><li>• Replacement of RTC Battery</li></ul>
C	Sept-2016	Added three new modules: <ul style="list-style-type: none"><li>• Digital Input Module EP-1804</li><li>• Serial Communication Module EP-5261</li><li>• SSI Encoder Interface Module EP-5311</li></ul>
B	Apr-2016	Changes required as part of ATEX certificate update
A	Feb-2016	Added EtherCat logo after certification
-	Dec-2015	Initial release



## 1.2 System Overview



The modular RSTi-EP system supports common fieldbus systems and conforms to IEC 61131-2. Each station is assigned a bus address in the fieldbus structure. Only the network adapter is fieldbus-specific; the I/O modules are independent of the fieldbus.


Up to 64 active I/O modules can be combined in a RSTi-EP station. The largest expansion possible depends on the maximum amount of data transmitted by the selected fieldbus, in particular the configuration, parameter, or process data for the module types provided.

The following components belong to the RSTi-EP product series:

- Fieldbus network adapter (gateway): Head station for converting the respective fieldbus protocol on the RSTi-EP system bus
- Active I/O modules:
  - Modules with digital input (DI) or digital output (DO) with 2, 4, 8 or 16 channels
  - Modules with analogue input (AI) or analogue output (AO) with 4 or 8 channels
  - Pulse width modulation modules (PWM)
  - Digital counter modules (CNT)
- Passive I/O modules (no fieldbus communication)
  - 24 V power-feed modules (PF) for input or output current
  - Potential distribution modules (AUX)
  - Empty modules acting as placeholders (ES)
- Functional safety modules
  - Safe power-feed modules (EP-19xx) 24 V for output current, providing one or two inputs (with two channels each) for safety circuits
- Mechanical fixing elements
  - End bracket
  - End plate



*Dimensions of the RSTi-EP Components*

	<i>Height (H)</i>	<i>Width (W)</i>	<i>Depth (D)</i>
Network adapter	120.0 mm (4.72 in)	52.0 mm (2.05 in)	76.0 mm (2.99 in)
I/O module	120.0 mm (4.72 in)	11.5 mm (0.45 in)	76.0 mm (2.99 in)
End plate	120.0 mm (4.72 in)	3.5 mm (0.14 in)	76.0 mm (2.99 in)
End bracket	120.0 mm (4.72 in)	8.0 mm (0.32 in)	36.0 mm (1.42 in)


### 1.2.1 Double-click Installation

The RSTi-EP station modules can be installed quickly and simply. When attaching the module to the DIN rail, a clear clicking noise can be heard, which means that the module has clicked into place. In the second step, which involves pushing the module being installed together with the neighboring module, a further clicking noise indicates that the modules have been correctly connected to each other.

### 1.3 General Description of the Fieldbus Network Adapters

A fieldbus network adapter is used to connect the station I/O modules to the fieldbus. All of the data traffic with the programmable logic controller including the diagnostic messages is exchanged via the network adapter. The integrated power supply provides the network adapter and all connected modules with power.

A detailed description of the individual network adapter types is available in Chapter 4, *Detailed Descriptions of the Fieldbus Network Adapter*.



**Fieldbus Network Adapter (example: EPXPNS001)**


- 1 - Catch lever for securing the DIN rail
- 2 - Rotary switch (only PROFIBUS®)
- 3 - Data line connection (e.g. SUB-D socket)
- 4 - Seats for module markers
- 5 - Type designation
- 6 - Optional: swivel marker for labelling modules and channels
- 7 - Connector frame unlocking device
- 8 - LED power supply network adapter
- 9 - Network adapter status LEDs
- 10 - Power supply connector for the system and input modules
- 11 - Power supply connector for output modules
- 12 - Service flap
- 13 - Latching hook for latching onto module sides
- 14 - System bus
- 15 - System current path
- 16 - Input current path
- 17 - Type plate with block diagram
- 18 - Output current path

## 1.4 General Technical Data for the Fieldbus Network Adapter

<b>Type of connection</b>	<i>Spring-style</i>	Single-wired, Fine-wired
		Conductor cross-section 0.14 – 1.5 mm <sup>2</sup> (AWG 16 – 26)
Configuration interface	USB 2.0	
<b>Dimensions</b>	Height	120,0 mm (4.72 in) (with release lever: 128,0 mm / 5,04 in)
	Width	52,0 mm (2.05 in)
	Depth	76,0 mm (2.99 in)
<b>Protection class (DIN EN 60529)</b>	IP 20	
<b>Flammability rating UL 94</b>	V-0	
<b>Temperature data (Network Adapter Power Supply)</b>	Operation (horizontal installation)	-20°C to +60°C (- 4 to +140 °F) (8-A power supply) -20°C to +55°C (- 4 to +131 °F) (10-A power supply)
	Operation (vertical installation)	-20°C to +55°C (- 4 to +131 °F) (6-A power supply) -20°C to +50°C (- 4 to +122 °F) (8-A power supply)
	Storage, transport	-40°C to +85°C (- 40 to +185 °F)
<b>Humidity</b>	Operation	95 %, non-condensing as per IEC 61131-2
	Storage, transport	95 %, non-condensing as per IEC 61131-2
<b>Air pressure</b>	Operation	≥ 795 hPa (altitude ≤ 2000 m) as per IEC 61131-2
	Storage, transport	≥ 700 hPa (altitude ≤ 3000 m) as per IEC 61131-2
<b>Vibration resistance</b>	5 Hz ≤ f ≤ 8.4 Hz: 3.5 mm amplitude as per IEC 60068-2-6 8.4 Hz ≤ f ≤ 150 Hz: 1 g acceleration as per IEC 60068-2-6	
<b>Shock resistance</b>	15 g over 11 ms, half sinewave, as per IEC 60068-2-27	
<b>Potential isolation</b>	Test voltage	max. 28,8 V within one channel 500 V DC field/system
	Pollution severity level	2
	Overvoltage category	II
<b>Approvals and Standards</b>	cULus Ordinary Locations	UL 508, CSA C22.2 No. 0-M91
	cULus Hazardous Locations Class 1 Division 2, Gr. A, B, C, D	ISA 12.12.01: 2007 CSA C22.2 No. 213-M1987 (Reaffirmed 2008)
	Potentially explosive atmosphere Zone 2 <sup>†</sup>	ATEX Directive 2014/34/EU
	Explosion protection	IEC 60079-0:2012 and IEC 60079-15:2010
	EMC	IEC 61000 (partial standards as per the requirements of IEC 61131-2)
	FCC Compliance	47 CFR 15: 2011 (Class A)
<sup>†</sup> Unless otherwise noted within the product-specific technical data.		


All product-specific technical data is available in the corresponding product description in *Chapter 4, Detailed Descriptions of the Fieldbus Network Adapters*.

## 1.5 General Description of I/O Modules



*I/O module (Example EP-1214)*

- 1 Catch lever for securing the DIN rail
- 2 System bus
- 3 System current path
- 4 Input current path
- 5 Output current path
- 6 Seats for module markers
- 7 Type designation
- 8 Optional: swivel marker for labelling modules and channels
- 9 Connector frame unlocking device
- 10 Module status LED (collective message)
- 11 Connector
- 12 Channel status LEDs
- 13 Latching hook for latching onto module sides
- 14 DIN rail foot
- 15 Type plate



*I/O Module Components*

### **Color Coding**

The removal levers for the electronic unit and the connectors are color-coded as follows:


- Blue standard
- White power supply
- Red 230 V
- Yellow SIL products

- 1 Basic module
- 2 Electronic unit
- 3 Removal lever for electronic unit
- 4 Connector frame
- 5 Connector
- 6 Plug-in unit

A detailed description of the individual module types is available in Chapter 5, *Detailed Descriptions of I/O Modules*.

### 1.5.1 Standard Connector

The connection frame can take up to four connectors, and four conductors can be connected to each connector. *Spring-style* technology allows for fine-wired conductors with crimped wire-end ferrules or ultrasonically welded conductors, each with a maximum cross-section of 1.5 mm<sup>2</sup>, to be inserted easily through the opening in the clamping terminal without having to use tools. To insert fine-wired conductors without wire-end ferrules, the pusher must be pressed in with a screwdriver (refer to the section, *Wiring*).



Connector with Four Conductor Connectors

#### Features and Specifications:


- conductor cross-section 0.14 to 1.5 mm<sup>2</sup> (AWG 16 – 26)
- maximum ampacity: 10 A
- 4-pole

The pushers are color-coded for the following connections:

- White Signal
- Blue GND
- Red 24 V DC
- Green Functional earth (FE)

### 1.5.2 HD Connector EP-8360

The connection frame can take up to four times two HD connectors EP-8360, and qualified SAI cables<sup>†</sup> with a cross-section from 0.14 to 0.35 mm<sup>2</sup> can be connected to each connector via insulation displacement contact (IDC). (wiring refer to section, *Wiring*)



Connector EP-8360 for HD Modules

#### Features and Specifications:

- conductor cross-section: 0.14 to 0.35 mm<sup>2</sup> (AWG 22-26)
- insulation diameter 1.0 to 1.6 mm (0.04 to 0.06")
- maximum current capacity: 1 A
- 4-pole

### 1.5.3 Cable Protection

The modules listed in the following table do not have a fused sensor/actuator power supply. Here, all cables to the connected sensors/actuators must be fused corresponding to their conductor cross-sections (as per Standard DIN EN 60204-1, section 12).

Description	Order No.
<b>Digital input modules</b>	
Digital Input, 4 Points, Positive Logic 24VDC, 2,3, or 4 Wire	EP-1214
Digital Input, 8 Points, Positive Logic, 24VDC 2 Wire	EP-1218
Digital Input, 8 Points, Positive Logic, 24VDC 3 Wire	EP-1318
Digital Input, 4 Points, Positive Logic 24VDC, 2,3, or 4 Wire, Time stamp	EP-12F4
Digital Input, 4 Points 110/230 VAC (65 – 277 VAC), 2 Wire, Isolated	EP-1804
<b>Digital output modules</b>	
Digital Output, 4 Points, Positive Logic 24VDC, 0.5A, 2,3, or 4 Wire	EP-2214
Digital Output, 4 Points, Positive Logic 24VDC, 2.0A, 2,3, or 4 Wire	EP-2614
Digital Output, 4 Points, Positive/Negative Logic 24VDC, 2.0A, 2,3, or 4 Wire	EP-2634
<b>Analog input modules</b>	
Analog Input, 4 Channels Voltage/Current 16 Bits 2, 3, or 4 Wire	EP-3164
Analog Input, 4 Channels Voltage/Current 12 Bits 2, 3, or 4 Wire	EP-3124
<b>Functional modules</b>	
2 Channels PWM Output, Positive Logic, 24VDC, 2.0 A	EP-5422
2 Channels PWM Output, Positive Logic, 24VDC, 0.5 A	EP-5442
1 Channel High Speed Counter, AB 100 kHz 1 DO 24VDC, 0.5A	EP-5111
2 Channel High Speed Counter, AB 100 kHz	EP-5112
2 Channel Frequency Measurement, 100 kHz	EP-5212
1 Channel Serial Communications, 232, 422, 485	EP-5261
1 Channel SSI Encoder, BCD or Gray-Code Format, 5/24 VDC	EP-5311
<b>Potential distribution modules</b>	
Power Module, 16 Channels 24VDC Potential Distribution +24 VDC from Input Current Path	EP-711F
Power Module, 16 Channels 24VDC Potential Distribution +24 VDC from Output Current Path	EP-751F
Power Module, 16 Channels 24VDC Potential Distribution +0VDC from Input Current Path	EP-710F
Power Module, 16 Channels 24VDC Potential Distribution +0VDC from Output Current Path	EP-750F

## 1.6 General Technical Data for I/O Modules

Type of connection	Spring-style	Single-wired, fine-wired
		Conductor cross-section 0.14 – 1.5 mm <sup>2</sup> (AWG 16 – 26)
	IDC (EP-3368, EP-3468)	Single-wired, fine-wired
		Conductor cross-section 0.14 – 0.35 mm <sup>2</sup> (AWG 22 – 26)
Dimensions	Height	4.72 in (120.0 mm) w/ release lever: 128.0 mm (5.04 in)
	Width	11.5 mm (0.45 in)
	Depth	76.0 mm (2.99 in)
Protection class (DIN EN 60529)	IP 20	
Flammability rating UL 94	V-0	
Temperature data	Operation	-20°C to +60°C (- 4 to +140 °F)
	Storage, transport	-40°C to +85°C (- 40 to +185 °F)
Humidity	Operation, storage, transport	5 % to 95 %, non-condensing as per IEC 61131-2
Air pressure	Operation	≥ 795 hPa (altitude ≤ 2000 m) as per IEC 61131-2
	Storage, transport	≥ 700 hPa (altitude ≤ 3000 m) as per IEC 61131-2
Vibration resistance	5 Hz ≤ f ≤ 8.4 Hz: 3.5-mm amplitude as per IEC 60068-2-6 8.4 Hz ≤ f ≤ 150 Hz: 1-g acceleration as per IEC 60068-2-6	
Shock resistance	15 g over 11 ms, half sinewave, as per IEC 60068-2-27	
Potential isolation	Test voltage	max. 28.8 V within one channel 500 V DC field/system
	Pollution severity level	2
	Overvoltage category	II
Approvals and Standards	cULus Ordinary Locations	UL 508, CSA C22.2 No. 0-M91
	cULus Hazardous Locations Class 1 Division 2, Gr. A, B, C, D	ISA 12.12.01: 2007 CSA C22.2 No. 213-M1987 (Reaffirmed 2008)
	Potentially explosive atmosphere Zone 2 <sup>†</sup>	ATEX Directive <b>2014/34/EU</b>
	Explosion protection	IEC 60079-0:2012 and IEC 60079-15:2010
	EMC	IEC 61000 (partial standards as per the requirements of IEC 61131-2)
	FCC Compliance	47 CFR 15: 2011 (Class A)
Type of connection	Spring-style	Single-wired, fine wired
	ICES Compliance	ICES-003:2012 (Class A)
	PLC	IEC 61131-2


<sup>†</sup> Unless otherwise noted within the product-specific technical data.

All product-specific technical data is available in the corresponding product description in Chapter 5, *Detailed Descriptions of I/O Modules*.




## 1.7 Mechanical Fixing Elements

The station is fixed in the installation position by an end bracket at either side. The last I/O module is protected against dust by a cover plate, into which the second end bracket is inserted and screwed to the mounting rail. Every RTSi-EP network adapter is supplied with a termination kit.



## 1.8 Type Plate

Each network adapter and each module features a type plate, which includes identification information, the key technical specifications and a block diagram. In addition, a QR code allows for direct online access to the associated documentation. The software for reading the QR code must support inverted QR codes. A breakdown of the serial numbers can be found in the table provided in the annex.



## 1.9 Markers

A wide range of markers are available as accessories for labelling equipment.

### 1.9.1 Swivel Marker

RSTi-EP I/O Label Markers (EP-8100) allow for modules and all respective channels and lines to be labelled in detail. They are attached to the connector frame.



**Module with Swivel Marker**

The following labels are available for the labelling:

- Paper labels for printing with laser printers (Part No. EP-8101)
  - White
  - Yellow

## Notes

## Chapter 2 Safety

This section includes general safety instructions for handling the RSTi-EP system. Specific safety instructions for specific tasks and situations are given at the appropriate places in the documentation.

When using remote I/O RSTi-EP modules, refer to the *Module for Functional Safety Manual* (GFK-2956).

### 2.1 General Safety Notice

Work on the RSTi-EP products may only be performed by qualified personnel with the support of trained persons. As a result of their professional training and experience, an personnel is qualified to perform the necessary work and identify any potential risks.

Before any work is carried out on the products (installation, maintenance, retrofitting), the power supply must be switched off and secured against being switched on again. Work may be carried out with safety extra-low voltage.

The manual provided with the equipment shall be followed in detail to assure proper and safe operation.

A stabilized 24V DC power supply shall be used.

All field wiring intended for connection to the power terminal shall consist of copper conductors with the insulation locally removed. Additional intermediate connecting parts, other than ferriles, shall not be used.

When working during continued operations, the emergency stop mechanisms must not be made ineffective. If you need technical help, contact Technical Support. For phone numbers and email addresses, refer to the *General Contact Information* page in the front of this manual.

If a malfunction on a RSTi-EP product cannot be fixed after following the recommended measures (refer to the Chapter, *LED Indicators and Troubleshooting*), the product in question must be sent back to GE. GE does not assume any liability if the base or electronic module has been tampered with.

#### 2.1.1 Electrostatic Discharge

RSTi-EP products can be damaged or destroyed by electrostatic discharge. When handling the products, the necessary safety measures against electrostatic discharge (ESD) according to IEC 61340-5-1 and IEC 61340-5-2 must be observed.

All devices are supplied in ESD-protected packaging. The packing and unpacking as well as the installation and disassembly of a device may only be carried out by qualified personnel and in accordance with the ESD information.

#### 2.1.2 Open Equipment

RSTi-EP products are open equipment (having live electrical parts that may be accessible to users) that may only be installed and operated in lockable housings, cabinets or electrical operations rooms. Only trained and authorized personnel may access the equipment.

For applications requiring functional safety or in order to maintain compliance with the ATEX Directive [Class 1, Zone 2 area (Category 3)], the surrounding housing must meet at least IP 54.

The standards and guidelines applicable for the assembly of switch cabinets and the arrangement of data and supply lines must be complied with.

### 2.1.3 Fusing

The operator must set up the equipment so that it is protected against overloading. The upstream fuse must be designed such that it does not exceed the maximum load current. The maximum permissible load current of the RSTi-EP components can be found in the technical data.

In the case of modules without fused sensor/actuator power supplies, all lines to the connected sensors/actuators must be fused corresponding to their conductor cross-section (as per DIN VDE 0298 Part 4).

To meet UL-specifications in accordance with UL 248-14, a UL-certified automatic fuse or a 10 A fuse with a medium time-lag must be used.

All connections of the RSTi-EP components are protected against voltage pulses and overcurrent in accordance with IEC 61131-2, Zone B. The operator has to decide whether additional overvoltage protection according to IEC 62305 is required. Voltages that exceed +/-30 V may cause the destruction of network adapters and modules.

A feed-in power supply with secure isolation must be used.

### 2.1.4 Earthing (functional earth FE)

Each RSTi-EP I/O module is fitted with an FE spring on the underside which creates an electrical connection to the DIN rail. In order to establish a secure connection, the assembly must be carried out carefully in accordance with the instructions (refer to *Chapter 6, Installation*). The module is earthed by connecting the DIN rail to the protective earth via the earth terminal.

Modules EP-700F, EP-1214, EP-2214, EP-3124 and EP-3164 have connections with green pushers. An FE potential is also provided at these connections. They must not be used as a PE.

### 2.1.5 Shielding

Shielded lines are to be connected with shielded plugs and fixed on a shield bus in compliance with the relevant standard (refer to *Chapter 7, Earthing and Shielding*).

### 2.1.6 Overcurrent

Potentials of network adapters and power-feed modules must be disconnected either simultaneously or in the order 24 V supply first, then the GND potential.

## 2.2 Intended Use

The products of the RSTi-EP series are intended for use in industrial automation. A RSTi-EP station with network adapter and connected modules is intended for the decentralized control of systems or sub-systems. Via the network adapter every module of a station is integrated into a fieldbus structure and connected to the primary control unit. The RSTi-EP products conform to protection class IP 20 (in accordance with DIN EN 60529), they can be used in potentially explosive atmospheres rated as Zone 2 (as per Directive 2014/34/EU) and in safe zones.

The observance of the supplied documentation is part of the intended use. The products described in this manual may only be used for the intended applications and only in connection with certified third-party devices or components.

## 2.3 Use in a Potentially Explosive Atmosphere

If RSTi-EP products are used in potentially explosive atmospheres, the following notes are **also** applicable:

- Staff involved in assembly, installation and operation must be qualified to perform safe work on electrical systems protected against potentially explosive atmospheres.
- The remote I/O-System RSTi-EP shall only be used in an area of not more than pollution degree 2, as defined in IEC 60664-1.
- For applications in potentially explosive atmospheres, the requirements according to IEC 60079-15 must be observed, in particular the housing enclosing the system must meet the requirements of explosion protection type Ex n or Ex e and protection class IP54. The IP54 enclosure must be accessible only by the use of a tool.
- Sensors and actuators that are located in Zone 2 or in a safe zone can be connected to the RSTi-EP station.
- The ambient temperature range -20°C to +60°C shall not be exceeded.
- When the temperature under rated conditions exceeds 70 °C at the conductor or conduit entry point, or 80 °C at the contact, the temperature specification of the selected cable shall be in compliance with the actual measured temperature values.
- A stabilized 24V DC power supply with double or reinforced insulation shall be used.
- When using relay modules EP-2714, EP-2814, and EP-1804 in explosive atmosphere:
  - Device shall be installed in an environment free of condensation, corrosives and conducting dusts.
  - If the switching or input voltage exceeds 63V, a transient protection device shall be provided that limits the transients to a peak voltage of 500V or less.
- For EP-2714 (Relay Module) only:
  - Since relays are subject to wear, it must be ensured, by appropriate maintenance intervals, that the temperatures do not exceed the limits of temperature class T4.  
**Note:** A contact resistance of more than 110 milli-ohm will be considered as a fault.
  - Resistive Loads Only
  - Transient protection shall be provided that is set at a level not exceeding 140% of the peak rated voltage value at the supply terminals to the equipment.
- A visual inspection of the RSTi-EP station is to be performed once per year.
- A visual inspection of the RSTi-EP station is to be performed once per year.
- If mounted in other directions than horizontal (reference mounting rail), restrictions to the max. operating temperature, max. output currents may apply.
- While explosive atmosphere is present:
  - No electrical connection shall be separated in energized condition.
  - The USB interface shall not be used.
  - Dip-switches, binary-switches and potentiometers shall not be actuated.
- Only power supplies with secure isolation shall be used.
- Refer manufacturers manual.



### Warning

**EXPLOSION HAZARD - SUBSTITUTION OF COMPONENTS MAY IMPAIR SUITABILITY FOR CLASS I, DIVISION 2.**

**WHEN IN HAZARDOUS LOCATIONS, TURN OFF POWER BEFORE REPLACING OR WIRING MODULES; AND**

**DO NOT CONNECT OR DISCONNECT EQUIPMENT UNLESS POWER HAS BEEN SWITCHED OFF OR THE AREA IS KNOWN TO BE NONHAZARDOUS.**

## 2.3.1 ATEX Zone 2

The module must be mounted in an enclosure certified in accordance with EN60079-15 for use in Zone 2, Group IIC and rated IP54. The enclosure shall only be able to be opened with the use of a tool.

## 2.3.2 ATEX & IECEx Marking

WI 15ATEX0001 X

Ⓔ II 3 G Ex nA T4 Gc

II 3 G Ex nA nC T4 Gc

IECEx ULD 16.0022x

Ta: -20°C to +60°C

## 2.4 Legal Notice

The RSTi-EP series products are CE-compliant in accordance with Directive 2014/30/EU (EMC Directive) and Directive 2014/35/EU (Low Voltage Directive). They also meet the requirements of the ATEX Directive 2014/34/EU.

## 2.5 Use of RSTi-EP Stations Above 2000m Sea Level

The RSTi-EP remote I/O system is able to operate in height >2000 m (6561.68 ft) above sea level, with the following limitations:

There is a derating for ambient temperatures while the RSTi-EP Station is in operating mode. Refer to the following derating table.

Altitude (m, ft)	Factor for Temperature Derating
< 2000 m (6561.68 ft)	1
2001 to 3000 m (6564.96 to 9842.52 ft)	0.88
3001 to 4000 m (9845.80 to 13123.36 ft)	0.78
4001 to 5000 m (13126.64 to 16404.20 ft)	0.68

Example:

Height 3000 m (9842.52 ft): maximum operational temperature is 60° C (140 °F) x 0.88 = **52.8°C (136.76 °F)** at maximum 8A.


## Chapter 3 Configuration

### 3.1 Order and Arrangement of the Modules

The RSTi-EP system elements are designed to be installed on a profile rail according to EN 60715 [1.4 x 0.26 in (35 x 7.5 mm)], a steel strip in accordance with Annex A of EN 60715, or a tin-plated steel strip.

**Note:** A RSTi-EP station may be built up to a maximum length of 3.28 ft (1 m). Therefore, at most 82 modules (including max. 64 active modules) can be aligned on a network adapter.


The RSTi-EP station is usually installed on a horizontally positioned DIN rail.



***Installation Position of the RSTi-EP Station on the DIN Rail (Horizontal Installation)***

Installation on vertically positioned DIN rails is also possible. In this case however, the heat dissipation is reduced such that the derating values change (refer to the section *Current Demand and Power Supply*). In the case of vertical mounting, the network adapter must always be arranged as the first module at the bottom and secured with an end bracket for vertical mounting.






*Installation Position of the RSTi-EP Station on the DIN Rail (Vertical Installation)*

A RSTi-EP station may only be installed in this sequence (starting from the left/bottom):

- End bracket
- Network adapter
- Up to 82 modules (including max. 64 active modules)
- End plate and end bracket



### **Attention**

A maximum of three passive modules (potential distribution module, power-feed module or blank module) may be placed in successive positions. Then at least one active module must follow.

### **3.1.1 Arrangement of Safe Power-feed Modules**


A safe power-feed module EP-19xx module can be positioned anywhere in the RSTi-EP station. All the following output modules (except for the EP-2814 and EP-2714 relay modules) up to the next EP-19xx module are safely disconnected (safety segment). Multiple EP-19xx modules/safety segments can be arranged within a station.

**Note:** When using RSTi-EP EP-19xx modules, also refer to the *Modules for Functional Safety Manual* (GFK-2956).

### 3.1.2 Power Supply Concept


The RSTi-EP system uses three internal current paths as described in the following chapter, *Detailed Descriptions of the Fieldbus Network Adapters*. Input and output paths are supplied separately, therefore a custom-fit refreshing by power-feed modules is easily feasible.

The following figure shows the general supply concept. For detailed description and calculation of the current demand refer to the sections, *Example Calculation for the Power Supply* and *Calculation of Power Loss* of this manual.



### 3.2 Installation Distances


In order to be able to carry out the installation and subsequent maintenance work and to ensure sufficient ventilation, the RSTi-EP station must be installed while observing the following minimum distances (refer to the following figures).




#### Attention

Depending on how the station shielding is implemented, the specified distances may have to be made larger, where necessary.


The minimum permissible conductor bending radii must also be observed. Earth terminals already installed can be ignored when calculating the distance.



Minimum Distances for Horizontal Installation




Minimum Distances for Vertical Installation



Minimum Distance for Electrical Cabinet Door (Without/With Swivel Marker)

### 3.2.1 Calculation of Space Requirements


The space requirements for a RSTi-EP station with n modules (**horizontal installation**) is calculated as follows:

		
Height:	120 mm (4.72 in) + 40 mm (2 x 1.57 in) = <b>200 mm (7.87 in)</b>	distances at top and bottom
Width:	8 mm (1.57 in) + 52 mm (2.05 in) + n x 11.5 mm (0.45 in) + 11.5 mm (0.45 in) + 2 x 20 mm (0.79 in) = <b>111.5 mm (4.39 in) + n x 11.5 mm (0.45 in)</b>	end bracket network adapter n modules end plate and end bracket distances to the sides

For vertical installation interchange height and width. When calculating the width, 4.5 mm (0.18 in) for the must be added for the end bracket.


### 3.3 Use in a Potentially Explosive Atmosphere

If the RSTi-EP is used in a potentially explosive atmosphere rated as Zone 2, the housing must meet the requirements of explosion protection type Ex n or Ex e and protection class IP54. Sensors and actuators that are located in Zone 2 or in a safe zone can be connected. All cable glands on the housing must be approved for Ex e.



Use in a Potentially Explosive Atmosphere

### 3.3.1 ATEX & IECEx Marking

 II 3 G Ex nA IIC T4 Gc  
 II 3 G Ex nA nC IIC T4 Gc  
 WI 15ATEX0001 X  
 Ta: -20°C ... +60°C

## 3.4 Spring-style System Cabling

RSTi-EP modules (except HD modules) and network adapters are equipped with the *spring-style* connector system. Single-strand and fine-strand lines with wire-end ferrules can be inserted without the need for a tool. Lines with a cross-section measuring between 0.14 mm<sup>2</sup> and 1.5 mm<sup>2</sup> (AWG 26 – 16) can be connected.

The external dimensions of the crimped wire-end ferrules must conform to IEC-60947-1.

## 3.5 Current Demand and Power Supply

The RSTi-EP system uses three internal current paths:

The **I<sub>sys</sub> system current path** supplies the communication part of the I/O modules; it is fed from the network adapter input supply and cannot be interrupted by any module. The maximum current-carrying capacity of I<sub>sys</sub> allows a RSTi-EP station to be expanded with a maximum of 64 active modules without having to refresh the power.

The **I<sub>in</sub> input current path** supplies the input circuit of the input modules as well as the connected I<sub>s</sub> sensors. The current must be refreshed with EO-7631 (power feed in) modules as required. These EP-7631 modules isolate the input current path towards the left (towards the network adapter), and as a result start a new electricity segment towards the right.

The **I<sub>out</sub> output current path** supplies the output circuit of the output modules with power, as well as the connected I<sub>a</sub> actuators. The current must be refreshed with the EP-7641 (power feed-out), as required. These EP-7641 modules isolate the output current path to the left (towards the network adapter), and as a result start a new electricity segment to the right.

**Note:** The design of the power supply being used must take start-up peaks into account.

### 3.5.1 Power Supply Derating

The power supply is restricted according to the temperature. The following values apply for the horizontal and vertical positioning of the RSTi-EP station:

**Temperature-dependent Values for the Power Supply**

	Horizontal	Vertical
Network Adapter power supply	60 °C / 140 °F : 2 × 8 A 55 °C / 131 °F : 2 × 10 A	55 °C / 131 °F : 2 × 6 A 50 °C / 122 °F : 2 × 8 A
Power-feed module power supply	60 °C / 140 °F : 1 × 10 A	55 °C / 131 °F : 1 × 8 A

## Current Demand

Product group	Product	I <sub>sys</sub>	I <sub>IN</sub>	I <sub>OUT</sub>	I <sub>s</sub>	I <sub>L</sub>
Network adapters	EPXPBS001	100 mA				
	EPXPNS001	116 mA				
	EPXETC001	110 mA				
	EPXMBE001	112 mA				
Digital input modules	EP-1214	8 mA	18 mA		x	
	EP-1218	8 mA	30 mA		x	
	EP-1318	8 mA	30 mA		x	
	EP-125F	8 mA	52 mA			
	EP-12F4	8 mA	18 mA		x	
	EP-1804	8 mA				
Digital output modules	EP-2214, EP-2714, EP-2634	8 mA		20 mA		x
	EP-2218	8 mA		35 mA		x
	EP-225F, EP-2614	8 mA		25 mA		x
	EP-2814	11 mA				
Analog input modules	EP-3164, EP-3124, EP-3264	8 mA	25 mA		x	
	EP-3804, EP-3704, EP-3368, EP-3468	8 mA	20 mA			
Analog output modules	EP-4164, EP-4264	8 mA		85 mA		
Functional modules	EP-5111, EP-5112	8 mA	35 mA			x
	EP-5212	8 mA	35 mA		x	x
	EP-5422, EP-5442	8 mA		40 mA		
	EP-5261	8 mA	16 mA			
	EP-5311	8 mA	25 mA			
Power-feed modules	EP-7641			10 mA		
	EP-7631		10 mA			
	EP-1901, EP-1902, EP-1922	8 mA	45 mA			x
Potential distribution modules	EP-751F	-	-	-	-	-
	EP-711F	-	-	-	-	-
I <sub>sys</sub>	Current consumption from the system current path					
I <sub>IN</sub>	Power consumption from input current path					
I <sub>OUT</sub>	Power consumption from output current path					
I <sub>s</sub>	Current demand of the connected sensors					
I <sub>L</sub>	Current demand of the connected actuators					
x	Must be included when calculating the power supply					

### 3.6 Example Calculation for the Power Supply

The power supply must be calculated individually for each station installation. Therefore the simultaneity factor  $g$  and the current demand of each module, as well as the devices to be connected must be established (refer to the example calculation table).

In the **example station**, an EPXPNS001 network adapter is configured with four EP-1214 modules and eight EP-2218 modules. The cumulative current demand for each module is now calculated to determine whether and at which point a EP-7631 power-feed module must be positioned to refresh the current path. A power-feed module must always be used where the current demand exceeds 10 A.

**Note:** The power refresh must be separately calculated for the input and output current paths. The system voltage need not be considered during this step.

**Note:** Use the *RSTi-EP Power Supply Configuration Guide* to perform this calculation automatically.

#### 3.6.1 Calculation of the Current Demand for the Input Current

The current consumption of the network adapter must be considered for the **main power supply**, and the sum of consumption values is multiplied by the simultaneity factor  $g$  for each following module:

$I_{SYS}$ network adapter $+ (I_{SYS} + I_{IN}) + (I_S \times g)$ module 1 $+ (I_{SYS} + I_{IN}) + (I_S \times g)$ module 2 $+ \sum ((I_{SYS} + I_{IN}) + (I_S \times g))$ modules 3 to $\underline{4}$ <b>= Cumulative current demand</b>	$I_{SYS}$ Current consumption from the system current path $I_{IN}$ Current consumption from the input current path $I_S$ Power supplies for the connected sensors
---	--

In the case of an additional power supply (power refresh) with a EP-7631 power-feed module, only the sensor power supplies and the module current consumption have to be considered:

$((I_{IN} + I_S \text{ module } x) \times g)$ $+ ((I_{IN} + I_S \text{ module } y) \times g)$ $+ \sum ((I_{IN} + I_S) \times g) \text{ } n \text{ modules}$ <b>= Cumulative current demand</b>	$I_{SYS}$ Current consumption from the system current path $I_S$ Power supplies for the connected sensors
---	--

### 3.6.2 Calculation of the Current Demand for the Output Current

The current consumption of each module and the current demand of the connected actuators must be considered for the output current. There is no difference in the calculation of the main power supply and power refresh:

$(I_{OUT} + (I_L \times g)$ module 1 $+ (I_{OUT} + (I_L \times g)$ module 2 $+ \Sigma (I_{OUT} + (I_L \times g))$ n modules <b>= Cumulative current demand</b>	$I_{OUT}$ module current consumption from the output current path $I_L$ Current demand of the connected actuators
---	--

#### Example:

The values in the following table are used to calculate the current demand of the example station (cumulative for each module). The input current is:

Module 1:

$$I = 0.116 \text{ A} + (0.008 \text{ A} + 0.012 \text{ A}) + (0.06 \text{ A} \times 1) = 0.196 \text{ A}$$

Module 2:

$$I = 0.196 \text{ A} + (0.008 \text{ A} + 0.012 \text{ A}) + (0.06 \text{ A} \times 1) = 0.276 \text{ A}$$

The values for the other modules are calculated accordingly. The result shows that the accumulated value for up to 12 modules remains under 10 A, and therefore a power supply module need not be used for the input current path. Results for the output current path:

Module 5:

$$I = 0.015 \text{ A} + (0.5 \text{ A} \times 2) = 1.015 \text{ A}$$

Module 6:

$$I = 1.015 \text{ A} + (0.015 \text{ A} + (0.5 \text{ A} \times 4)) = 3.03 \text{ A}$$

Module 10:

$$I = 6.175 \text{ A} + (0.015 \text{ A} + (0.5 \text{ A} \times 4)) = 8.19 \text{ A}$$

Module 11 (without power refresh):

$$I = 8.19 \text{ A} + (0.015 \text{ A} + (0.5 \text{ A} \times 4)) = \mathbf{10.205 \text{ A}}$$

Therefore the available 10 A would be exceeded. As a result, an EP-7641 power supply module must be positioned as the 11th module, which will supply the required power to the subsequent modules after the power feed module. Unused current values may not be included.

Module 11 (as per PF-O):

$$I = (0.015 \text{ A} + (0.5 \text{ A} \times 4)) = 2.015 \text{ A}$$

Module 12 (as per PF-O):

$$I = 2.015 \text{ A} + (0.015 \text{ A} + (0.5 \text{ A} \times 4)) = 4.030 \text{ A}$$



## Example Calculation for the Current Demand (all Current Values in A)

Module no.	GE part number	I <sub>sys</sub>	I <sub>IN</sub>	I <sub>OUT</sub>	I <sub>s</sub>	I <sub>L</sub>	Simultaneity factor g	Cumulative current demands of the input current path	Cumulative current demand of the output power path network adapter	Cumulative current demand of the EP-7641 output power path
	EPXPNS 001	0.116						0.116	0	
1	EP-1214	0.008	0.018		0.06		1	0.202	0	
2	EP-1214	0.008	0.018		0.06		1	0.288	0	
3	EP-1214	0.008	0.018		0.12		1	0.434	0	
4	EP-1214	0.008	0.018		0.18		1	0.64	0	
5	EP-2218	0.008		0.035		2	0.5	0.648	1.035	
6	EP-2218	0.008		0.035		4	0.5	0.656	3.07	
7	EP-2218	0.008		0.035		3	0.5	0.664	4.605	
8	EP-2218	0.008		0.035		2	0.5	0.672	5.64	
9	EP-2218	0.008		0.035		1.2	0.5	0.68	6.275	
10	EP-2218	0.008		0.035		4	0.5	0.688	8.29	
	EP-7641									
11	EP-2218	0.008		0.035		4	0.5	0.696		2.035
12	EP-2218	0.008		0.035		4	0.5	0.70		4.07
I <sub>sys</sub> I <sub>IN</sub> I <sub>OUT</sub> I <sub>s</sub> I <sub>L</sub>	Current consumption from the system power supply Power consumption from input current path Power consumption from output current path Current demand of the connected sensors Current demand of the connected actuators									
	The current demand is just under 10 A. The output current path must therefore be refreshed <b>before the 11th module</b> .									
	10 A is supplied by the EP-7641 module. The 1.81 A calculated as remaining after the 10th module must <b>not</b> be added to the 10 A after the EP-7641 module!									

### 3.7 Calculation of Power Loss

The power loss of the network adapter is calculated als follows:

$$P_{\text{network adapter}} = P_0 + N * P_{\text{mod}} + I_{\text{in}} * \Delta U_{\text{in}} + I_{\text{out}} * \Delta U_{\text{out}}$$

$P_0$	Static power loss in the network adapter	2,3 W
$N$	Number of modules	
$P_{\text{mod}}$	Power loss due to module supply from the system current path	0,02 W
$P_{\text{module}}$	Maximum power loss module	
$I_{\text{in}}$	Current fed in through the input current path	
$\Delta V_{\text{in}}$	Voltage drop across the contacts in the input current path	0,18 V
$I_{\text{out}}$	Current fed in through the output current path	
$\Delta V_{\text{out}}$	Voltage drop across the contacts in the output current path	0,18 V

The power loss of a RSTi-EP station is calculated using the power loss of the network adapter and the power loss of the individual modules. It depends on the current in both current paths. It is assumed that there is a maximum power loss of 2 watts for the module

Maximum values were assumed for these calculations. If you need detailed calculations, please contact GE technical support or GlobalCare.

$$P_{\text{station}} = P_{\text{network adapter}} + N * P_{\text{module}}$$

#### 3.7.1 Calculation of Power Loss for Use in a Potentially Explosive Atmosphere

The module specific data, needed to calculate the output power loss, are provided in the ATEX certificate which you can download from the GE website.

### 3.8 Feedback Energy in DO Modules

With digital output modules, power is fed back through the channels when inductive loads are switched off. The respective permissible breaking energy is noted in the technical data of the DO modules. Depending on the switching frequency, the breaking energy leads to additional energy loss in the output module.

If the maximum permissible feedback energy for a module is exceeded, the module shuts down temporarily.

**Note:** Feedback energy can be prevented by installing external freewheeling protection. With it, the same switching rate can be achieved with an inductive load as with a resistive load.


### 3.8.1 Calculation of Feedback Energy

The feedback energy for a digital output module can be calculated as follows:

$$P = \sum_{\text{all channels}} \frac{1}{2} n_i * L_i * I_i^2$$

P	Feedback energy of the module
$N_i$	Switching cycles of Channel i in 1/seconds
$E_i$	Feedback energy when shutting off Channel i during a shutdown procedure
$I_i$	Current through the load connected to Channel i
$L_i$	Inductance of the load connected to Channel i

Once the maximum permissible feedback energy  $E_{\max}$  is reached, the module shuts down.



*Maximum Feedback Energy Varies with Ambient Temperature*

### 3.9 Parameter Overview

#### Overview of the Editable Parameters

Product	Part No.	Parameter	Optional values	Default value
PROFIBUS DP-V1 Network Adapter	EPXPBS001	DP-Alarm mode	V0 / V1	V1
		DP alarm mode V0	<b>For mode V0, the alarm triggers are set in the parameter data.</b>	
		Diagnostic alarm <sup>†</sup>	enabled / disabled	disabled
		Process alarm <sup>†</sup>	enabled / disabled	disabled
		Hot-plug alarm <sup>†</sup>	enabled / disabled	enabled
		<sup>†</sup> These switches are always selectable, but they only have a function in mode V0. Diagnostic messages are generated which are not acknowledged by the PLC.		
		DP alarm mode V1	<b>In mode V1, the alarm triggers are set in the engineering environment.</b>	
		Diagnostic alarm <sup>††</sup>	enabled / disabled	disabled
		Process alarm <sup>††</sup>	enabled / disabled	disabled
		Hot-plug alarm <sup>††</sup>	enabled / disabled	enabled
		<sup>††</sup> These switches can be selected only in mode V1, in V0 they are inactive. Diagnostic messages are generated which are acknowledged by the PLC.		
		Identifier-related diagnosis <sup>†††</sup>	enabled / disabled	enabled
		Channel-related diagnosis <sup>†††</sup>	enabled / disabled	enabled
		Module status <sup>†††</sup>	enabled / disabled	enabled
		<sup>†††</sup> A diagnostic block is attached to the diagnostic message.		
		Data format	Motorola / Intel	Motorola
		Fieldbus error output behavior	All outputs off / activate replacement values / retain last value	All outputs off
		Module behavior during hot swap	Continue data exchange / behavior as with fieldbus error	Continue data exchange
Product	Part No.	Parameter	Optional values	Default value
PROFINET IRT Network Adapter, 2 Cu RJ45 Ports, 1024 bytes (Input + Output)	EPXPNS001	Process alarm	enabled / disabled	disabled
		Diagnostic alarm	enabled / disabled	disabled
		Type of diagnostic	Extended channel diagnostic (short diagnostic) Manufacturer-specific diagnostic (complete diagnostic)	Extended channel diagnostic (short diagnostic)
		Behavior of outputs on fieldbus errors	All outputs off / Enable substitute value / Hold last value	All outputs off

		Module behavior on hot swap	Continue data exchange / Behavior like fieldbus error	Continue data exchange
		Data format	Motorola / Intel	Motorola
		Webserver via Ethernet	enabled / disabled	disabled
Product	Part No.	Parameter	Optional values	Default value
Ethercat Network Adapter, 2 Cu RJ45 Ports, 1024 bytes (Input + Output)	EPXETC001	Process alarm	enabled / disabled	disabled
		Diagnostic alarm	enabled / disabled	disabled
		Behavior of outputs on fieldbus errors	All outputs off / Enable substitute value / Hold last value	All outputs off
		Module behavior on hot swap	Continue data exchange / Behavior like fieldbus error	Continue data exchange
		Data format	Motorola / Intel	Intel
		Webserver via Ethernet	enabled / disabled	disabled
		Network adapter control	Reserved	Off
Product	Part No.	Parameter	Optional values	Default value
Modbus TCP Network Adapter, 2 Cu RJ45 Ports, 2048 bytes (Input + Output)	EPXMBE001	IP-Address	4 numbers between 0-255	192.168.0.222
		Subnet mask	4 numbers between 0-255	255.255.255.0
		Gateway	4 numbers between 0-255	192.168.0.1
		IP Configuration	Static, DHCP, BootP Firmware 02.00.00 and higher: additionally DHCP and static	Static (firmware 01.xx.xx) DHCP and static (firmware 02.00.00 or higher)
		Modbus DHCP Timeout	Waiting time, 1 to 1000 s	30 s
		IP-Address USB-Port	192.168.1.202; 192.168.2.202, 192.168.3.202, 192.168.4.202, 192.168.5.202	192.168.1.202
		Webserver via Ethernet	disabled / enabled	disabled
		Save module parameters	no / yes / Standard	no, see register 0x113C-0x113F
		Status Modbus watchdog	Watchdog time in steps of 10 ms	0 *10 ms, see register 0x1120
		Modbus Connection Timeout	Connection watchdog time in sec	1 s, see register 0x1131
		Writing access with multiclient	write for all, 1stWr1stServe, 1stConn1stServe	write for all, see register 0x1130

		Check reference list before exchanging data	disabled / enabled	disabled, see register 0x1132
		Process alarm	disabled / enabled	see register 0x1133
		Diagnostic alarm	disabled / enabled	see register 0x1134
		Behavior of outputs on fieldbus error	All outputs off / Enable substitute values / Hold last value	All outputs off, see register 0x1135
		Module behavior on hot swap	Continue data exchange / Behavior like fieldbus error	Continue data exchange, see register 0x1136
		Data format	Motorola / Intel	Motorola, see fieldbus register 0x1137
Product	Part No.	Parameter	Optional values	Default value
Digital Input, 4 Points, Positive Logic 24VDC, 2, 3, or 4 Wire	EP-1214	Ch 0 ... Ch 3: Input delay	no (0)/0,3 ms (1) (not at PROFIBUS-DP)/3ms (2)/10 ms (3)/20 ms (4)/40 ms (5) (not at PROFIBUS-DP)	3 ms
Product	Part No.	Parameter	Optional values	Default value
Digital Input, 8 Points, Positive Logic, 24VDC 2 Wire	EP-1218	Ch 0 ... Ch 7: Input delay	no (0) / 0,3 ms (1) (not at PROFIBUS-DP) / 3 ms	3 ms
Digital Input, 8 Points, Positive Logic, 24VDC 3 Wire	EP-1318		(2) / 10 ms (3) / 20 ms (4) / 40 ms (5) (not at PROFIBUS-DP)	
Product	Part No.	Parameter	Optional values	Default value
Digital Input, 4 Points, Positive Logic 24VDC, 2, 3, or 4 Wire, Time stamp	EP-12F4	Ch 0 ... Ch 3: Input delay	no (0) / 0,3 ms (1) (not at PROFIBUS-DP) / 3 ms	3 ms
		Ch 0 ... Ch 3: TimeStamp at edge 0-1	disabled (0) / enabled (1)	disabled
		Ch 0 ... Ch 3: TimeStamp at edge 1-0	disabled (0) / enabled (1)	disabled
Product	Part No.	Parameter	Optional values	Default value
Digital Output, 4 Points, Positive Logic 24VDC, 0.5A, 2, 3, or 4 Wire	EP-2214	Ch 0 ... Ch 3: Substitute value	Off (0) / On (1)	Off
Digital Output, 4 Points, Positive Logic 24VDC, 2.0A, 2, 3, or 4 Wire	EP-2614			

Product	Part No.	Parameter	Optional values	Default value
Digital Output, 4 Points, Positive/Negative Logic 24VDC, 2.0A, 2, 3, or 4 Wire	EP-2634	Ch 0 ... Ch 3: Substitute value OP-Mode	Sinking (0) / Sourcing (1)	Sourcing
		Ch 0 ... Ch 3: Substitute value	Off (0) / On (1)	Off
Product	Part No.	Parameter	Optional values	Default value
Digital Output, 8 Points, Positive Logic, 24VDC, 0.5A, 2 Wire	EP-2218	Ch 0 ... Ch 7: Substitute value	Off (0) / On (1)	Off
Product	Part No.	Parameter	Optional values	Default value
Digital Output, 4 Points, Positive Logic, 230 VAC, 0.5A  Digital Relay Output, 4 Points, Positive Logic, 24 - 220 VDC/VAC, 6A, 2 Wire	EP-2814	Ch 0 ... Ch 3: Substitute value	Off (0) / On (1)	Off
	EP-2714			
Product	Part No.	Parameter	Optional values	Default value
1 Channel High Speed Counter, AB 100 kHz 1 DO 24VDC, 0.5A	EP-5111	Diagnostic alarm	disabled (0) / enabled (1)	disabled
		Ch 0: Filter time signal A	0,01 ms [100 kHz] (0) / 0,017 ms [50 kHz] (1) / 0,033 ms [30 kHz] (2) / 0,1 ms [10 kHz] (3) / 0,2 ms [5 kHz] (4) / 0,5 ms [2 kHz] (5) / 1 ms [1 kHz] (6)	0,01 ms
		Ch 0: Filter time signal B	0,01 ms [100 kHz] (0) / 0,017 ms [50 kHz] (1) / 0,033 ms [30 kHz] (2) / 0,1 ms [10 kHz] (3) / 0,2 ms [5 kHz] (4) / 0,5 ms [2 kHz] (5) / 1 ms [1 kHz] (6)	0,01 ms
		Ch 0: Filter time latch	0,01 ms (0) / 0,017 ms (1) / 0,033 ms (2) / 0,1 ms (3) / 0,2 ms (4) / 0,5 ms (5) / 1 ms (6)	0,01 ms
		Ch 0: Filter time gate	0,01 ms (0) / 0,017 ms (1) / 0,033 ms (2) / 0,1 ms (3) / 0,2 ms (4) / 0,5 ms (5) / 1 ms (6)	0,01 ms
		Ch 0: Filter time reset	0,01 ms (0) / 0,017 ms (1) / 0,033 ms (2) / 0,1 ms (3) / 0,2 ms (4) / 0,5 ms (5) / 1 ms (6)	0,01 ms
		Ch 0: Process alarm HW gate open	disabled (0) / enabled (1)	disabled
		Ch 0: Process alarm HW gate closed	disabled (0) / enabled (1)	disabled

		Ch 0: Process alarm overflow	disabled (0) / enabled (1)	disabled
		Ch 0: Process alarm underflow	disabled (0) / enabled (1)	disabled
		Ch 0: Process alarm comp. value	disabled (0) / enabled (1)	disabled
		Ch 0: Process alarm end value	disabled (0) / enabled (1)	disabled
		Ch 0: Process alarm latch value	disabled (0) / enabled (1)	disabled
		Ch 0: Counting mode	count endless (0) / once - forward (1) / once - backwards (2) / once - no main direction (3) / periodic - forward (4) / periodic - backwards (5) / periodic - no main direction (6)	count endless
		Ch 0: Condition for DO	disabled (0) / higher equal comparison value (1) / lower equal comparison value (2) / equal comparison value (3)	disabled
		Ch 0: Counter dir. signal B inv.	disabled (0) / enabled (1)	disabled
		Ch 0: Reset	disabled (0) / high level (1) / rising edge 0-1 (2) / rising edge once 0-1 (3)	disabled
		Ch 0: Signal mode	Rotary transducer - single (0) / Rotary transducer - double (1) / Rotary transducer - quadruple (2) / Pulse and Direction (3) / disabled (4)	disabled
		Ch 0: HW gate	disabled (0) / enabled (1)	disabled
		Ch 0: Counter behavior internal gate	Interrupt counting (0) / Cancel counting (1)	interrupt counting
		Ch 0: End value	-2147483648 ... 2147483647	2147483647
		Ch 0: Load value	-2147483648 ... 2147483647	0
		Ch 0: Hysteresis	0 ... 255	0
		Ch 0: Pulse duration	0 ... 255 [Input value x 2 = output time; corresponds to 0 ... 510 ms]	0



Product	Part No.	Parameter	Optional values	Default value
2 Channel High Speed Counter, AB 100 kHz	EP-5112	Diagnostic alarm	disabled (0) / enabled (1)	disabled
		Ch 0 ... Ch 1: Filter time signal A	0,01 ms [100 kHz] (0) / 0,017 ms [50 kHz] (1) / 0,033 ms [30 kHz] (2) / 0,1 ms [10 kHz] (3) / 0,2 ms [5 kHz] (4) / 0,5 ms [2 kHz] (5) / 1 ms [1 kHz] (6)	0,01 ms
		Ch 0 ... Ch 1: Filter time signal B	0,01 ms [100 kHz] (0) / 0,017 ms [50 kHz] (1) / 0,033 ms [30 kHz] (2) / 0,1 ms [10 kHz] (3) / 0,2 ms [5 kHz] (4) / 0,5 ms [2 kHz] (5) / 1 ms [1 kHz] (6)	0,01 ms
		Ch 0 ... Ch 1: Process alarm overflow	disabled (0) / enabled (1)	disabled
		Ch 0 ... Ch 1: Process alarm underflow	disabled (0) / enabled (1)	disabled
		Ch 0 ... Ch 1: Process alarm comp. value	disabled (0) / enabled (1)	disabled
		Ch 0 ... Ch 1: Process alarm end value	disabled (0) / enabled (1)	disabled
		Ch 0 ... Ch 1: Counting mode	count endless (0) / once - forward (1) / once - backwards (2) / once - no main direction (3) / periodic - forward (4) / periodic - backwards (5) / periodic - no main direction (6)	count endless
		Ch 0 ... Ch 1: Comparison function	disabled (0) / higher equal comparison value (1) / lower equal comparison value (2) / equal comparison value (3)	disabled
		Ch 0 ... Ch 1: Counter dir. signal B inv.	disabled (0) / enabled (1)	disabled
		Ch 0 ... Ch 1: Signal mode	Rotary transducer - single (0) / Rotary transducer - double (1) / Rotary transducer - quadruple (2) / Pulse and Direction (3) / disabled (4)	disabled

		Ch 0 ... Ch 1: Counter behavior internal gate	Interrupt counting (0) / Cancel counting (1)	interrupt counting
		Ch 0 ... Ch 1: Set value	-2147483648 ... 2147483647	0
		Ch 0 ... Ch 1: End value	-2147483648 ... 2147483647	2147483647
		Ch 0 ... Ch 1: Load value	-2147483648 ... 2147483647	0
		Ch 0 ... Ch 1: Hysteresis	0 ... 255	0
Product	Part No.	Parameter	Optional values	Default value
2 Channel Frequency Measurement, 100 kHz	EP-5212	Ch 0 ... Ch 1: Input filter	5 µs [187 kHz] (0) / 11 µs [94 kHz] (1) / 21 µs [47 kHz] (2) / 43 µs [23 kHz] (3) / 83 µs [12 kHz] (4) / 167 µs [6 kHz] (5) / 333 µs [3 kHz] (6) / 667 µs [1,5 kHz] (7) / 1 ms [732 Hz] (8) / 3 ms [366 Hz] (9) / 5 ms [183 Hz] (10) / 11 ms [92 Hz] (11) / 22 ms [46 Hz] (12) / 43 ms [23 Hz] (13) / 91 ms [11 Hz] (14) / 167 ms [6 Hz] (15) / 333 ms [3 Hz] (16)	5 µs [187 kHz]
Product	Part No.	Parameter	Optional values	Default value
2 Channels PWM Output, Positive Logic, 24VDC, 2.0 A	EP-5422	Ch 0 ... Ch 1: Period duration = n*20,83 ns	1202 ... 8388607	1202
2 Channels PWM Output, Positive Logic, 24VDC, 0.5 A	EP-5442			
Product	Part No.	Parameter	Optional values	Default value
Analog Input, 4 Channels Voltage/ Current 16 Bits 2, 3, or 4 Wire	EP-3164	Frequency suppression	disabled (0) / 50 Hz (1) / 60 Hz (2) / Average over 16 values (3)	disabled
Analog Input, 4 Channels Voltage/ Current 12 Bits 2, 3, or 4 Wire	EP-3124	Ch 0 ... Ch 3: Measurement range	0 to 20 mA (0) / 4 to 20 mA (1) / 0 V to 10 V (2) / -10 to 10 V (3) / 0 to 5 V (4) / -5 to 5 V (5) / 1 to 5 V (6) / 2 to 10 V (7) / disabled (8)	disabled
Product	Part No.	Parameter	Optional values	Default value
Analog Input, 4 Channels Voltage/ Current 16 Bits with Diagnostics 2, 3, or 4 Wire	EP-3264	Frequency suppression	disabled (0) / 50 Hz (1) / 60 Hz (2) / Average over 16 values (3)	disabled
		Ch 0 ... Ch 3: Channel diagnosis	disabled (0) / enabled (1)	disabled
		Ch 0 ... Ch 3: Diag short circuit 24 V	disabled (0) / enabled (1)	disabled

		Ch 0 ... Ch 3: Diag line break 24 V	disabled (0) / enabled (1)	disabled
		Ch 0 ... Ch 3: Measurement range	0 to 20 mA (0) / 4 to 20 mA (1) / 0 V to 10 V (2) / -10 to 10 V (3) / 0 to 5 V (4) / -5 to 5 V (5) / 1 to 5 V (6) / 2 to 10 V (7) / disabled (8)	disabled
Product	Part No.	Parameter	Optional values	Default value
Analog Input, 8 Channels Current 16 Bits 2, 3, or 4 Wire	EP-3368	Frequency suppression	disabled (0) / 50 Hz (1) / 60 Hz (2) / Average over 16 values (3)	disabled
		Ch 0 ... Ch 3: Measurement range	0 to 20 mA (0) / 4 to 20 mA (1) / disabled (2)	disabled
Product	Part No.	Parameter	Optional values	Default value
Analog Input, 8 Channels Current 16 Bits 2, 3, or 4 Wire, Channel Diagnostic	EP-3468	Frequency suppression	disabled (0) / 50 Hz (1) / 60 Hz (2) / Average over 16 values (3)	disabled
		K 0 ... K 7: Channel diagnosis	disabled (0) / enabled (1)	disabled
		K 0 ... K 7: Diag short circuit 24 V	disabled (0) / enabled (1)	disabled
		Ch 0 ... Ch 3: Measurement range	0 to 20 mA (0) / 4 to 20 mA (1) / disabled (2)	disabled
Product	Part No.	Parameter	Optional values	Default value
Analog Input, 4 Channels Voltage/ Current 16 Bits 2, 3, or 4 Wire	EP-3164	Ch 0 ... Ch 3 Data format	S5 Data format (0) / S7 Data format (1)	S7 Data format
		Ch 0 ... Ch 3 Output range	0 to 20 mA (0) / 4 to 20 mA (1) / 0 to 10 V (2) / -10 to 10 V (3) / 0 to 5 V (4) / -5 to 5 V (5) / 1 to 5 V (6) / 2 to 10 V (7) / disabled (8)	disabled
		Ch 0 ... Ch 3 Substitute value	depending on the channels data format (S5/S7), refer to the Tables "Value range" within the module descriptions	0
Product	Part No.	Parameter	Optional values	Default value
		Ch 0 ... Ch 3 Output range	0 to 20 mA (0) / 4 to 20 mA (1) / 0 to 10 V (2) / -10 to 10 V (3) / 0 to 5 V (4) / -5 to 5 V (5)	disabled

			/ 1 to 5 V (6) / 2 to 10 V (7) / disabled (8)	
		Ch 0 ... Ch 3 Substitute value	depending on the channels data format (S5/S7), refer to the Table "Value range"	0
		Ch 0 ... Ch 3 Channel diagnosis	disabled (0) / enabled (1)	disabled
Product	Part No.	Parameter	Optional values	Default value
Analog Input, 4 Channels RTD 16 Bits with Diagnostics 2, 3, or 4 Wire	EP-3704	Temperature unit	Degree Celsius (0) / Degree Fahrenheit (1) / Kelvin (2)	Degree Celsius
		Ch 0 ... Ch 3 Measurement range	PT100 -200 ... 850 Degree Celsius (0) / PT200 -200 ... 850 Degree Celsius (1) / PT500 -200 ... 850 Degree Celsius (2) / PT1000 -200 ... 850 Degree Celsius (3) / NI100 -60 ... 250 Degree Celsius (4) / NI120 -80 ... 260 Degree Celsius (5) / NI200 -60 ... 250 Degree Celsius (6) / NI500 -60 ... 250 Degree Celsius (7) / NI1000 -60 ... 250 Degree (8) / Cu10 - 100 ... 260 Degree Celsius (9) / Resistance 40 Ω (10) / Resistance 80 Ω (11) / Resistance 150 Ω (12) / Resistance 300 Ω (13) / Resistance 500 Ω (14) / Resistance 1000 Ω (15) / Resistance 2000 Ω (16) / Resistance 4000 Ω (17) / disabled (18)	disabled
		Ch 0 ... Ch 3 Connection type	2-wire (0) / 3-wire (1) / 4-wire (2)	2-wire
		Ch 0 ... Ch 3 Conversion time	240 ms (0) / 130 ms (1) / 80 ms (2) / 55 ms (3) / 43 ms (4) / 36 ms (5)	80 ms
		Ch 0 ... Ch 3 Channel diagnostics	disabled (0) / enabled (1)	disabled
		Ch 0 ... Ch 3 Limit value monitoring	disabled (0) / enabled (1)	disabled

		Ch 0 ... Ch 3 High limit value	-32768 ... 32767	0
		Ch 0 ... Ch 3 Low limit value	-32768 ... 32767	0

Product	Part No.	Parameter	Optional values	Default value
Analog Input, 4 Channels TC 16 Bits with Diagnostics 2, 3, or 4 Wire	EP-3804	Temperature unit	Degree Celsius (0) / Degree Fahrenheit (1) / Kelvin (2)	Degree Celsius
		Ch 0 ... Ch 3 Measurement range	TC Type J (0) / TC Type K (1) / TC Type N (2) / TC Type R (3) / TC Type S (4) / TC Type T (5) / TC Type B (6) / TC Type C (7) / TC Type E (8) / TC Type L (9) / TC Type U (10) / ± 15,625 mV (11) / ± 31,25 mV (12) / ± 62,5 mV (13) / ± 125 mV (14) / ± 250 mV (15) / ± 500 mV (16) / ± 1000 mV (17) / ± 2000 mV (18) / disabled (19)	disabled
		Ch 0 ... Ch 3 Cold junction compensation	internal (0) / external Channel 0 (1) / external Channel 1 (2) / external Channel 2 (3) / external Channel 3 (4)	internal
		Ch 0 ... Ch 3 Conversion time	240 ms (0) / 130 ms (1) / 80 ms (2) / 55 ms (3) / 43 ms (4) / 36 ms (5)	80 ms
		Ch 0 ... Ch 3 Channel diagnostics	disabled (0) / enabled (1)	disabled
		Ch 0 ... Ch 3 Limit value monitoring	disabled (0) / enabled (1)	disabled
		Ch 0 ... Ch 3 High limit value	-32768 ... 32767	0
		Ch 0 ... Ch 3 Low limit value	-32768 ... 32767	0

### 3.10 Data Width of I/O module, Dependent on the Network Adapter Used

#### EPXPBS001

Part No.	Module	Configuration Bytes	Parameter Bytes	Diagnostics Bytes	Process data	
					Input Bytes	Output Bytes
EPXPBS001	PROFIBUS DP-V1 Network Adapter	--	8	47	--	--
EP-1214	Digital Input, 4 Points, Positive Logic 24VDC, 2,3, or 4 Wire	3	7	47	1	--
EP-1218	Digital Input, 8 Points, Positive Logic, 24VDC 2 Wire	3	11	47	1	--
EP-1318	Digital Input, 8 Points, Positive Logic, 24VDC 3 Wire	3	11	47	1	--
EP-125F	Digital Input, 16 Points, Positive Logic, 24VDC, 1 Wire	3	--	47	2	--
EP-12F4	Digital Input, 4 Points, Positive Logic 24VDC, 2,3, or 4 Wire, Time stamp	3	11	47	60	--
EP-1804	Digital Input, 4 Points 110/230 VAC (65 – 277 VAC), 2 Wire, Isolated	3	--	47	1	--
EP-2214	Digital Output, 4 Points, Positive Logic 24VDC, 0.5A, 2,3, or 4 Wire	3	4	47	--	1
EP-2614	Digital Output, 4 Points, Positive Logic 24VDC, 2.0A, 2,3, or 4 Wire	3	4	47	--	1
EP-2634	Digital Output, 4 Points, Positive/ Negative Logic 24VDC, 2.0A, 2,3, or 4 Wire	3	4	47	--	1
EP-2218	Digital Output, 8 Points, Positive Logic, 24VDC, 0.5A, 2 Wire	3	4	47	--	1
EP-225F	Digital Output, 16 Points, Positive Logic, 24VDC, 0.5A, 1 Wire	3	--	47	--	2
EP-2814	Digital Output, 4 Points, Positive Logic, 230 VAC, 0.5A	3	4	47	--	1
EP-2714	Digital Relay Output, 4 Points, Positive Logic, 24 - 220 VDC/VAC, 6A, 2 Wire	3	4	47	--	1
EP-5111	1 Channel High Speed Counter, AB 100 kHz 1 DO 24VDC, 0.5A	3	24	47	12	10
EP-5112	2 Channel High Speed Counter, AB 100 kHz	3	43	47	12	12
EP-5212	2 Channel Frequency Measurement, 100 kHz	3	5	47	20	12
EP-5261	1 Channel Serial Communications, 232, 422, 485	3	9	47	16	16
EP-5311	1 Channel SSI Encoder, BCD or Gray-Code Format, 5/24 VDC	3	11	47	6	0
EP-5422	2 Channels PWM Output, Positive Logic, 24VDC, 2.0 A	3	11	47	4	12

EP-5442	2 Channels PWM Output, Positive Logic, 24VDC, 0.5 A	3	11	47	4	12
EP-3164	Analog Input, 4 Channels Voltage/Current 16 Bits 2, 3, or 4 Wire	3	9	47	8	--
EP-3264	Analog Input, 4 Channels Voltage/Current 16 Bits with Diagnostics 2, 3, or 4 Wire	3	11	47	8	--
EP-3124	Analog Input, 4 Channels Voltage/Current 12 Bits 2, 3, or 4 Wire	3	9	47	8	--
EP-3804	Analog Input, 4 Channels TC 16 Bits with Diagnostics 2, 3, or 4 Wire	3	31	47	8	--
EP-3368	Analog Input, 8 Channels Current 16 Bits 2, 3, or 4 Wire	3	13	47	16	--
EP-3468	Analog Input, 8 Channels Current 16 Bits 2, 3, or 4 Wire, Channel Diagnostic	3	13	47	16	--
EP-4164	Analog Output, 4 Channels Voltage/Current 16 Bits 2, 3, or 4 Wire	3	15	47	--	8
EP-4264	Analog Output, 4 Channels Voltage/Current 16 Bits with Diagnostics 2, 3, or 4 Wire	3	16	47	--	8
EP-3704	Analog Input, 4 Channels RTD 16 Bits with Diagnostics 2, 3, or 4 Wire	3	31	47	8	--
EP-1901	1 Safe Feed-Input, 24 VDC	3	--	47	4	--
EP-1922	1 Safe Feed-Input, 24 VDC	3	--	47	4	--
EP-1902	2 Safe Feed-Inputs, 24 VDC	3	--	47	4	--
Max. data (in bytes)		244	244	244	244	244

## EPXPNS001

Part No.	Module	Configuration Bytes	Parameter Bytes	Diagnostics Bytes	Process data	
					Input Bytes	Output Bytes
EPXPNS001	PROFINET IRT Network Adapter, 2 Cu RJ45 Ports, 1024 bytes (Input + Output)	4	10	47	4	4
EP-1214	Digital Input, 4 Points, Positive Logic 24VDC, 2,3, or 4 Wire	4	8	47	2	1
EP-1218	Digital Input, 8 Points, Positive Logic, 24VDC 2 Wire	4	12	47	2	1
EP-1318	Digital Input, 8 Points, Positive Logic, 24VDC 3 Wire	4	12	47	2	1
EP-125F	Digital Input, 16 Points, Positive Logic, 24VDC, 1 Wire	4	--	47	3	1
EP-12F4	Digital Input, 4 Points, Positive Logic 24VDC, 2,3, or 4 Wire, Time stamp	4	12	47	61	1
EP-1804	Digital Input, 4 Points 110/230 VAC (65 – 277 VAC), 2 Wire, Isolated	4	--	47	2	1
EP-2214	Digital Output, 4 Points, Positive Logic 24VDC, 0.5A, 2,3, or 4 Wire	4	5	47	1	2
EP-2614	Digital Output, 4 Points, Positive Logic 24VDC, 2.0A, 2,3, or 4 Wire	4	5	47	1	2
EP-2634	Digital Output, 4 Points, Positive/Negative Logic 24VDC, 2.0A, 2,3, or 4 Wire	4	5	47	1	2
EP-2218	Digital Output, 8 Points, Positive Logic, 24VDC, 0.5A, 2 Wire	4	5	47	1	2
EP-225F	Digital Output, 16 Points, Positive Logic, 24VDC, 0.5A, 1 Wire	4	--	47	1	3
EP-2814	Digital Output, 4 Points, Positive Logic, 230 VAC, 0.5A	4	5	47	1	2
EP-2714	Digital Relay Output, 4 Points, Positive Logic, 24 - 220 VDC/VAC, 6A, 2 Wire	4	5	47	1	2
EP-5111	1 Channel High Speed Counter, AB 100 kHz 1 DO 24VDC, 0.5A	4	25	47	13	11
EP-5112	2 Channel High Speed Counter, AB 100 kHz	4	44	47	13	13
EP-5212	2 Channel Frequency Measurement, 100 kHz	4	6	47	21	13
EP-5261	1 Channel Serial Communications, 232, 422, 485	4	10	47	17	17
EP-5311	1 Channel SSI Encoder, BCD or Gray-Code Format, 5/24 VDC	4	12	47	7	1
EP-5422	2 Channels PWM Output, Positive Logic, 24VDC, 2.0 A	4	12	47	5	13
EP-5442	2 Channels PWM Output, Positive Logic, 24VDC, 0.5 A	4	12	47	5	13
EP-3164	Analog Input, 4 Channels Voltage/Current 16 Bits 2, 3, or 4 Wire	4	10	47	9	1



EP-3264	Analog Input, 4 Channels Voltage/Current 16 Bits with Diagnostics 2, 3, or 4 Wire	4	12	47	9	1
EP-3124	Analog Input, 4 Channels Voltage/Current 12 Bits 2, 3, or 4 Wire	4	10	47	9	1
EP-3804	Analog Input, 4 Channels TC 16 Bits with Diagnostics 2, 3, or 4 Wire	4	32	47	9	1
EP-3368	Analog Input, 8 Channels Current 16 Bits 2, 3, or 4 Wire	4	14	47	17	1
EP-3468	Analog Input, 8 Channels Current 16 Bits 2, 3, or 4 Wire, Channel Diagnostic	4	16	47	17	1
EP-4164	Analog Output, 4 Channels Voltage/Current 16 Bits 2, 3, or 4 Wire	4	16	47	1	9
EP-4264	Analog Output, 4 Channels Voltage/Current 16 Bits with Diagnostics 2, 3, or 4 Wire	4	17	47	1	9
EP-3704	Analog Input, 4 Channels RTD 16 Bits with Diagnostics 2, 3, or 4 Wire	4	32	47	9	1
EP-1901	1 Safe Feed-Input, 24 VDC	4	--	47	5	1
EP-1922	2 Safe Feed-Inputs, 24 VDC, Programmable Delay	4	--	47	5	1
EP-1902	2 Safe Feed-Inputs, 24 VDC	4	--	47	5	1
Max. data (in bytes)		260	4362	1408	512	512

**EPXETC001**

Part No.	Module	Configuration	Parameter	Diagnostics	Process data	
		Bytes	Bytes	Bytes	Input Bytes	Output Bytes
EPXETC001	Ethercat Network Adapter, 2 Cu RJ45 Ports, 1024 bytes (Input + Output)	256	4096	3328	1024	1024
EP-1214	Digital Input, 4 Points, Positive Logic 24VDC, 2,3, or 4 Wire	4	4	47	1	--
EP-1218	Digital Input, 8 Points, Positive Logic, 24VDC 2 Wire	4	8	47	1	--
EP-1318	Digital Input, 8 Points, Positive Logic, 24VDC 3 Wire	4	8	47	1	--
EP-125F	Digital Input, 16 Points, Positive Logic, 24VDC, 1 Wire	4	--	47	2	--
EP-12F4	Digital Input, 4 Points, Positive Logic 24VDC, 2,3, or 4 Wire, Time stamp	4	1	47	61	1
EP-1804	Digital Input, 4 Points 110/230 VAC (65 – 277 VAC), 2 Wire, Isolated	4	4	47	2	--
EP-2214	Digital Output, 4 Points, Positive Logic 24VDC, 0.5A, 2,3, or 4 Wire	4	1	47	1	1
EP-2614	Digital Output, 4 Points, Positive Logic 24VDC, 2.0A, 2,3, or 4 Wire	4	1	47	1	1
EP-2634	Digital Output, 4 Points, Positive/Negative Logic 24VDC, 2.0A, 2,3, or 4 Wire	4	62	47	1	1

EP-2218	Digital Output, 8 Points, Positive Logic, 24VDC, 0.5A, 2 Wire	4	1	47	1	1
EP-225F	Digital Output, 16 Points, Positive Logic, 24VDC, 0.5A, 1 Wire	4	--	47	1	2
EP-2814	Digital Output, 4 Points, Positive Logic, 230 VAC, 0.5A	4	1	47	1	1
EP-2714	Digital Relay Output, 4 Points, Positive Logic, 24 - 220 VDC/VAC, 6A, 2 Wire	4	1	47	1	1
EP-5111	1 Channel High Speed Counter, AB 100 kHz 1 DO 24VDC, 0.5A	4	82	47	13	10
EP-5112	2 Channel High Speed Counter, AB 100 kHz	4	97	47	13	12
EP-5212	2 Channel Frequency Measurement, 100 kHz	4	6	47	21	12
EP-5261	1 Channel Serial Communications, 232, 422, 485	4	10	47	17	16
EP-5311	1 Channel SSI Encoder, BCD or Gray-Code Format, 5/24 VDC	4	11	47	7	--
EP-5422	2 Channels PWM Output, Positive Logic, 24VDC, 2.0 A	4	8	47	4	12
EP-5442	2 Channels PWM Output, Positive Logic, 24VDC, 0.5 A	4	8	47	4	12
EP-3164	Analog Input, 4 Channels Voltage/Current 16 Bits 2, 3, or 4 Wire	4	6	47	8	--
EP-3264	Analog Input, 4 Channels Voltage/Current 16 Bits with Diagnostics 2, 3, or 4 Wire	4	8	47	8	--
EP-3124	Analog Input, 4 Channels Voltage/Current 12 Bits 2, 3, or 4 Wire	4	6	47	8	--
EP-3804	Analog Input, 4 Channels TC 16 Bits with Diagnostics 2, 3, or 4 Wire	4	28	47	8	--
EP-3368	Analog Input, 8 Channels Current 16 Bits 2, 3, or 4 Wire	4	17	20	17	--
EP-3468	Analog Input, 8 Channels Current 16 Bits 2, 3, or 4 Wire, Channel Diagnostic	4	33	20	17	--
EP-4164	Analog Output, 4 Channels Voltage/Current 16 Bits 2, 3, or 4 Wire	4	12	47	1	8
EP-4264	Analog Output, 4 Channels Voltage/Current 16 Bits with Diagnostics 2, 3, or 4 Wire	4	13	47	1	8
EP-3704	Analog Input, 4 Channels RTD 16 Bits with Diagnostics 2, 3, or 4 Wire	4	28	47	8	--
EP-1901	1 Safe Feed-Input, 24 VDC	4	--	47	4	--
EP-1922	2 Safe Feed-Inputs, 24 VDC, Programmable Delay	4	--	47	4	--
EP-1902	2 Safe Feed-Inputs, 24 VDC	4	--	47	4	--
Max. data (in bytes)		1514 per message + CoE	1514 per message + CoE	1514 per message + CoE	1024	1024

## Notes


## ***Chapter 4 Detailed Descriptions of the Fieldbus Network Adapters***

### ***4.1 Profibus DP Network Adapter EPXPBS001***

The EPXPBS001 network adapter is a PROFIBUS-DP device certified by the PROFIBUS user organization. The network adapter is the head module for the RSTi-EP communication bus, to which up to 64 active RSTi-EP modules can be connected. The PROFIBUS-DP network adapter has a Sub-D socket and supports all services in accordance with the DP-V1 specification.


The network adapter can be accessed with a system-independent web server application via the USB service interface. Thus, all information, such as diagnostics, status values and parameters, can be read and all connected modules can be simulated or forced.

The station's main power supply is integrated in the network adapter. Power is supplied via two 4-pole connectors, separated into the input and output current paths.



***Fieldbus Network Adapter EPXPBS001***

### 4.1.1 LEDs




LED Status Indicators EPXPBS001

LED Status Indicators

LED	Indication	LED State/Description
PWR	Power LED	<b>Green:</b> Supply voltage connected
SF	System fault	<b>Red:</b> Configuration error, or error in the network adapter, or error in a module, or there is a new diagnostic report <b>Red flashing:</b> Station in Force mode
BF	Bus fault	<b>Red:</b> No connection to the fieldbus <b>Red flashing:</b> Configuration error, no connection to the control unit, or error in the parameter set or slave address error or firmware update is running
MT	Maintenance Required	<b>Yellow:</b> Error on the system bus or fieldbus

LED Indicators EPXPBS001

	LED	EPXPBS001
	<b>Power Supply</b>	<b>Green:</b> Supply voltage > 18 V DC <b>Red:</b> At least one current path < 18 V
	3.1	<b>Green:</b> Input current path supply voltage > 18 V DC
	3.2	<b>Red:</b> Input current path supply voltage < 18 V DC
	3.3	
	3.4	<b>Red:</b> Internal fuse defective
	4.1	<b>Green:</b> Output current path supply voltage > 18 V DC
	4.2	<b>Red:</b> Output current path supply voltage < 18 V DC
	4.3	
	4.4	<b>Red:</b> Internal fuse defective

For error messages, refer to the Chapter, *LED Indicators and Troubleshooting*

## 4.1.2 Addressing


The network adapter on the PROFIBUS-DP is addressed via the two rotary switches.

**Note:** A maximum of 125 addresses (1 to 125) can be assigned. Each address may be assigned only once in the overall bus structure. Addresses 1 and 2 are generally used by the control systems. Bus addresses 000 plus 126 and higher may not be used.

The most significant digit is set with rotary switch **H**, the least significant digit with rotary switch **L**.


The switches are labelled in the hexadecimal numbering system (0 to 9, A=10, B=11, C=12, ... F = 15). A hexadecimal to decimal conversion table is provided in the annex.

**Coding:** Address = (H\*16) + L



Default Setting EPXPBS001: Address = 3

Addressing examples:




Examples for Addressing the EPXPBS001

PROFIBUS address **15**: H = 0, L = F


PROFIBUS address **112**: H = 7, L = 0

PROFIBUS address **44**: H = 2, L = C

### 4.1.3 Connection Diagrams



Connection Diagram EPXPBS001



Block Diagram EPXPBS001





In the case of a maximum power supply of >8 A and a maximum temperature of > +55°C (131 °F), all four contacts must be connected with 1.5 mm<sup>2</sup> wiring.

### Caution

## 4.1.4 Specifications

### EPXPBS001

System data		
Connection	9-pole SUB-D socket	
Fieldbus protocol	PROFIBUS-DP V1	
Process image	Input data width	max. 244 bytes
	Output data width	max. 244 bytes
	Parameter data	max. 244 bytes
	Diagnostic data	max. 244 bytes
Number of modules	Max. 64 active	
Configuration interface	Micro USB 2.0	
Transfer rate	Fieldbus	Max. 12 Mbps
	RTSi-EP system bus	Max. 48 Mbps
Supply		
Supply voltage for system and inputs	20.4V – 28.8V	
Supply voltage for outputs	20.4V – 28.8V	
Max. feed-in current for input modules	10 A	
Max. feed-in current for output modules	10 A	
Current consumption from system current path I <sub>sys</sub>	100 mA	
Connection data		
Type of connection	Spring style	
Conductor cross-section	Single-wired, fine-wired	0.14 – 1.5 mm <sup>2</sup> (AWG 16 – 26)
Weight		
Operating temperature	-20°C to +60°C (-4 °F to +140 °F)	
Storage temperature	-40°C to +85°C (-40 °F to +185 °F)	
Air humidity (operation/transport)	5% to 95%, noncondensing as per DIN EN 61131-2	
Width	52 mm (2.05 in)	
Depth	76 mm (2.99 in)	
Height	120 mm (4.72 in)	
Weight	223 g (7.87 oz)	
Configuration	The GSD file is available on the <i>Support</i> website <a href="http://support.ge-ip.com">http://support.ge-ip.com</a> for download and import into Proficy Machine Edition. The GSD supporting a firmware release is part of the firmware upgrade kit available on the <i>Support</i> website.	
General data, refer to the Section, <i>General Technical Data for the Fieldbus Network Adapter</i>		

## Overview of Editable Parameters EPXPBS001

Parameter	Additional explanations	Optional values	Default
IP address USB port <sup>†</sup>		192.168.1.202; 192.168.2.202, 192.168.3.202, 192.168.4.202, 192.168.5.202	192.168.1.202
DP-Alarm mode		V0 / V1	V1
DP alarm mode V0	<b>For mode V0, the alarm triggers are set in the parameter data.</b>		
Diagnostic alarm	These switches are always selectable, but they only have a function in mode V0. Diagnostic messages are generated which are not acknowledged by the PLC.	enabled / disabled	disabled
Process alarm		enabled / disabled	disabled
Hot-plug alarm		enabled / disabled	enabled
DP alarm mode V1	<b>In mode V1, the alarm triggers are set in the engineering environment.</b>		
Diagnostic alarm	These switches can be selected only in mode V1, in V0 they are inactive. Diagnostic messages are generated which are acknowledged by the PLC.	enabled / disabled	disabled
Process alarm		enabled / disabled	disabled
Hot-plug alarm		enabled / disabled	enabled
Identifier-related diagnosis	A diagnostic block is attached to the diagnostic message.	enabled / disabled	enabled
Channel-related diagnosis	A diagnostic block is attached to the diagnostic message.	enabled / disabled	enabled
Module status	A diagnostic block is attached to the diagnostic message.	enabled / disabled	enabled
Data format		Motorola / Intel	Motorola
Output behavior fieldbus error		All outputs off / activate replacement values / retain last value	All outputs off
Module behavior on hot swap		Continue data exchange / behavior as with fieldbus error	Continue data exchange
<sup>†</sup> Change requires restart of the network adapter.			

### 4.1.5 Supported Modules and Power Supplies

The following modules can be used with this release of the RSTi-EP Profibus Network Adaptor.

Catalog Number	Module Description
<b>Digital Input Modules</b>	
EP-1214	Digital Input, 4 Points, Positive Logic 24VDC, 2, 3, or 4 Wire
EP-1218	Digital Input, 8 Points, Positive Logic, 24VDC 2 Wire
EP-1318	Digital Input, 8 Points, Positive Logic, 24VDC 3 Wire
EP-125F	Digital Input, 16 Points, Positive Logic, 24VDC, 1 Wire
EP-12F4	Digital Input, 4 Points, Positive Logic, 24VDC, 2,3, or 4 Wire, Time stamp
EP-1804	Digital Input, 4 Points 110/230 VAC (65 – 277 VAC), 2 Wire, Isolated
<b>Digital Output Modules</b>	
EP-2214	Digital Output, 4 Points, Positive Logic 24VDC, 0.5A, 2,3, or 4 Wire
EP-2614	Digital Output, 4 Points, Positive Logic 24VDC, 2.0A, 2,3, or 4 Wire
EP-2634	Digital Output, 4 Points, Positive/Negative Logic 24VDC, 2.0A, 2,3, or 4 Wire
EP-2218	Digital Output, 8 Points, Positive Logic, 24VDC, 0.5A, 2 Wire
EP-225F	Digital Output, 16 Points, Positive Logic, 24VDC, 0.5A, 1 Wire
<b>Digital Relay Output Modules</b>	
EP-2714	Digital Relay Output, 4 Points, Positive Logic, 24 – 220 VDC/VAC, 6A, 2 Wire
EP-2814	Solid-state Relay Output Module

<b>Analog Input Modules</b>	
EP- 3164	Analog Input, 4 Channels Voltage/Current 16 Bits 2, 3, or 4 Wire
EP- 3264	Analog Input, 4 Channels Voltage/Current 16 Bits with Diagnostics 2, 3, or 4 Wire
EP- 3124	Analog Input, 4 Channels Voltage/Current 12 Bits 2, 3, or 4 Wire
EP-3368	Analog Input, 8 Channels Current 16 Bits 2, 3, or 4 Wire
EP-3468	Analog Input, 8 Channels Current 16 Bits 2, 3, or 4 Wire, Channel Diagnostic
EP-3704	Analog Input, 4 Channels RTD 16 Bits with Diagnostics 2, 3, or 4 Wire
EP-3804	Analog Input, 4 Channels TC 16 Bits with Diagnostics 2, 3, or 4 Wire
<b>Analog Output Modules</b>	
EP-4164	Analog Output, 4 Channels Voltage/Current 16 Bits 2, 3, or 4 Wire
EP-4264	Analog Output, 4 Channels Voltage/Current 16 Bits with Diagnostics 2, 3, or 4 Wire
<b>Speciality Modules</b>	
EP-5111	1 Channel High Speed Counter, AB 100 kHz 1 DO 24VDC, 0.5A
EP-5112	2 Channel High Speed Counter, AB 100 kHz
EP-5212	2 Channel Frequency Measurement, 100 kHz
EP-5261	1 Channel Serial Communications, 232, 422, 485
EP-5311	1 Channel SSI Encoder, BCD or Gray-Code Format, 5/24 VDC
EP-5422	2 Channels PWM Output, Positive Logic, 24VDC, 2.0 A
EP-5442	2 Channels PWM Output, Positive Logic, 24VDC, 0.5 A
<b>Power Feed Modules for Input Current Path</b>	
EP-7631	Power Module, 1 Channel 24VDC Input Flow 10A
<b>Power Feed Modules for Output Current Path</b>	
EP-7641	Power Module, 1 Channel 24VDC Output Flow 10A
<b>Safe Feed-input Modules</b>	
EP-1901	1 Safe Feed-Input, 24 VDC
EP-1902	2 Safe Feed-Inputs, 24 VDC, Programmable Delay

EP-1922	2 Safe Feed-Inputs, 24 VDC
<b>Potential Distribution Modules</b>	
EP-711F	Power Module, 16 Channels 24VDC Potential Distribution +24 VDC from Input Current Path
EP-751F	Power Module, 16 Channels 24VDC Potential Distribution +24 VDC from Output Current Path
EP-700F	Power Module, 16 Channels 24VDC Potential Distribution Functional Earth
EP-710F	Power Module, 16 Channels 24VDC Potential Distribution +0VDC from Input Current Path
EP-750F	Power Module, 16 Channels 24VDC Potential Distribution +0VDC from Output Current Path

## 4.2 PROFINET IRT Network Adapter EPXPNS001

The EPXPNS001 PROFINET Scanner is a PROFINET I/O device certified by the PROFINET user organization. The network adapter is the head module for the RSTi-EP system bus, to which up to 64 active RSTi-EP modules can be connected. The PROFINET network adapter has two Ethernet ports, and an integrated switch.


The PROFINET Scanner can be accessed with a system-independent web server application via the USB service interface or the Ethernet. Thus, all information, such as diagnostics, status values and parameters, can be read and all connected modules can be simulated or forced.

The station's main power supply is integrated in the PROFINET Scanner. Power is supplied via two 4-pole connectors, separated into the input and output current paths.



Network Adapter EPXPNS001

### 4.2.1 LEDs



LED Status Indicators EPXPNS001

### LED Status Indicators EPXPNS001


LED	Indication	LED State/Description
PWR	Power LED	<b>Green:</b> Supply voltage connected
SF	System fault	<b>Red:</b> Configuration error, or error in the PROFINET Scanner, or error in a module, or there is a new diagnostic report <b>Red flashing:</b> Station in Force mode
BF	Bus fault	<b>Red:</b> No connection to the fieldbus <b>Red flashing:</b> Configuration error, no connection to the control unit, or error in the parameter set
MT	Maintenance Required	<b>Yellow:</b> Error on the system bus or the fieldbus
LINK 1	Connection	<b>Green:</b> Connection established between port 1 of the PROFINET Scanner and another field device
ACT 1	Active	<b>Yellow flashing:</b> Data being exchanged on port 1
LINK 2	Connection	<b>Green:</b> Connection established between port 2 of the PROFINET Scanner and another field device
ACT 2	Active	<b>Yellow flashing:</b> Data being exchanged on port 2

### LED Indicators

[illegible]

For error messages, refer to the Chapter, *LED Indicators and Troubleshooting*.

## 4.2.2 Connection Diagrams




Connection Diagram EXPNS001



In the case of a maximum power supply of >8 A and a maximum temperature of > +55°C, all four contacts must be connected with 1.5 mm<sup>2</sup> wiring.

### Caution



Block Diagram EPXPNS001

## 4.2.3 Specifications

### EPXPNS001

System data		
Connection	2 x RJ-45	
Fieldbus protocol	PROFINET Version 2.3 Class C I/O Device (IRT, RT)	
Process image	Input data width	max. 512 bytes
	Output data width	max. 512 bytes
	Parameter data	max. 4362 bytes
	Diagnostic data	max. 1408 bytes
Number of modules	max. 64 active	
Configuration interface	Micro USB 2.0	
Transfer rate	Fieldbus	Max. 100 Mbps
	RTSi-EP system bus	Max. 48 Mbps
Fast start-up	< 500 ms	With a maximum of 10 modules
Data format	Default: Motorola	Configurable: Intel
PROFINET I/O Update Rate	Configurable selections: 1ms, 2ms, 4ms, 8ms, 16ms, 32ms, 64ms, 128ms, 256ms and 512ms	
Supports MRP	Yes	
Supply		
Supply voltage for system and inputs	20.4V – 28.8V	
Supply voltage for outputs	20.4V – 28.8V	
Max. feed-in current for input modules	10 A	
Max. feed-in current for output modules	10 A	
Current consumption from system current path I <sub>sys</sub>	116 mA	
Connection data		
Type of connection	Spring style	
Conductor cross-section	Single-wired, fine-wired	0.14 – 1.5 mm <sup>2</sup> (AWG 26 – 16)
General data		
Operating temperature	-20°C to +60°C (-4 °F to +140 °F)	
Storage temperature	-40°C to +85°C (-40 °F to +185 °F)	
Air humidity (operation/transport)	5% to 95%, noncondensing as per DIN EN 61131-2	
Width	52 mm (2.05 in)	
Depth	76 mm (2.99 in)	
Height	120 mm (4.72 in)	
Weight	220 g (7.76 oz)	
Configuration	The V2.3 GSDML file is available on the Support website <a href="http://support.ge-ip.com">http://support.ge-ip.com</a> for download and import into Proficy Machine Edition. The GSDML supporting a firmware release is part of the firmware upgrade kit available on the Support website.	



Overview of Editable Parameters EPXPNS001

Parameter	Optional values	Default
IP address†	4 numbers between 0 and 255	
Subnet mask	4 numbers between 0 and 255	
Gateway	4 numbers between 0 and 255	
Webserver via Ethernet	disabled / enabled	disabled
IP address USB port	192.168.1.202; 192.168.2.202, 192.168.3.202, 192.168.4.202, 192.168.5.202	192.168.1.202
Process alarm	disabled / enabled	disabled
Diagnostic alarm	disabled / enabled	disabled
Type of diagnostic	Extended channel diagnostic (short diagnostic) Manufacturer-specific diagnostic (complete diagnostic)	Extended channel diagnostic (short diagnostic)
Behavior of outputs on fieldbus errors	All outputs off / Enable substitute value / Hold last value	All outputs off
Module behavior on hot swap	Continue data exchange / Behavior like fieldbus error	Continue data exchange
Data format	Motorola / Intel	Motorola
Lock force mode	Force mode unlocked / Force mode locked	Force mode unlocked
† Change requires restart of the network adapter.		

#### 4.2.4 Supported Modules and Power Supplies

The following modules can be used with this release of the RSTi-EP PROFINET Network Adaptor:

Catalog Number	Module Description
<b>Digital Input Modules</b>	
EP-1214	Digital Input, 4 Points, Positive Logic 24VDC, 2,3, or 4 Wire
EP-1218	Digital Input, 8 Points, Positive Logic, 24VDC 2 Wire
EP-1318	Digital Input, 8 Points, Positive Logic, 24VDC 3 Wire
EP-125F	Digital Input, 16 Points, Positive Logic, 24VDC, 1 Wire
EP-12F4	Digital Input, 4 Points, Positive Logic 24VDC, 2,3, or 4 Wire, Time stamp
EP-1804	Digital Input, 4 Points 110/230 VAC (65 – 277 VAC), 2 Wire, Isolated
<b>Digital Output Modules</b>	
EP-2214	Digital Output, 4 Points, Positive Logic 24VDC, 0.5A, 2,3, or 4 Wire
EP-2614	Digital Output, 4 Points, Positive Logic 24VDC, 2.0A, 2,3, or 4 Wire
EP-2634	Digital Output, 4 Points, Positive/Negative Logic 24VDC, 2.0A, 2,3, or 4 Wire
EP-2218	Digital Output, 8 Points, Positive Logic, 24VDC, 0.5A, 2 Wire
EP-225F	Digital Output, 16 Points, Positive Logic, 24VDC, 0.5A, 1 Wire
<b>Digital Relay Output Modules</b>	
EP-2714	Digital Relay Output, 4 Points, Positive Logic, 24 - 220 VDC/VAC, 6A, 2 Wire
EP-2814	Solid-state Relay Output Module

<b>Analog Input Modules</b>	
EP- 3164	Analog Input, 4 Channels Voltage/Current 16 Bits 2, 3, or 4 Wire
EP- 3264	Analog Input, 4 Channels Voltage/Current 16 Bits with Diagnostics 2, 3, or 4 Wire
EP- 3124	Analog Input, 4 Channels Voltage/Current 12 Bits 2, 3, or 4 Wire
EP-3368	Analog Input, 8 Channels Current 16 Bits 2, 3, or 4 Wire
EP-3468	Analog Input, 8 Channels Current 16 Bits 2, 3, or 4 Wire, Channel Diagnostic
EP-3704	Analog Input, 4 Channels RTD 16 Bits with Diagnostics 2, 3, or 4 Wire
EP-3804	Analog Input, 4 Channels TC 16 Bits with Diagnostics 2, 3, or 4 Wire
<b>Analog Output Modules</b>	
EP-4164	Analog Output, 4 Channels Voltage/Current 16 Bits 2, 3, or 4 Wire
EP-4264	Analog Output, 4 Channels Voltage/Current 16 Bits with Diagnostics 2, 3, or 4 Wire
<b>Speciality Modules</b>	
EP-5111	1 Channel High Speed Counter, AB 100 kHz 1 DO 24VDC, 0.5A
EP-5112	2 Channel High Speed Counter, AB 100 kHz
EP-5212	2 Channel Frequency Measurement, 100 kHz
EP-5261	1 Channel Serial Communications, 232, 422, 485
EP-5311	1 Channel SSI Encoder, BCD or Gray-Code Format, 5/24 VDC
EP-5422	2 Channels PWM Output, Positive Logic, 24VDC, 2.0 A
EP-5442	2 Channels PWM Output, Positive Logic, 24VDC, 0.5 A
<b>Power Feed Modules for Input Current Path</b>	
EP-7631	Power Module, 1 Channel 24VDC Input Flow 10A
<b>Power Feed Modules for Output Current Path</b>	
EP-7641	Power Module, 1 Channel 24VDC Output Flow 10A
<b>Safe Feed-input Modules</b>	
EP-1901	1 Safe Feed-Input, 24 VDC
EP-1902	2 Safe Feed-Inputs, 24 VDC, Programmable Delay
EP-1922	2 Safe Feed-Inputs, 24 VDC
<b>Potential Distribution Modules</b>	
EP-711F	Power Module, 16 Channels 24VDC Potential Distribution +24 VDC from Input Current Path
EP-751F	Power Module, 16 Channels 24VDC Potential Distribution +24 VDC from Output Current Path
EP-700F	Power Module, 16 Channels 24VDC Potential Distribution Functional Earth
EP-710F	Power Module, 16 Channels 24VDC Potential Distribution +0VDC from Input Current Path
EP-750F	Power Module, 16 Channels 24VDC Potential Distribution +0VDC from Output Current Path

### 4.3 EtherCAT® Network Adapter EPXETC001



The EPXETC001 network adapter is an EtherCAT<sup>1</sup> device certified by the EtherCAT Technology Group. The network adapter is the head module for the RSTi-EP system bus, to which up to 64 active RSTi-EP modules can be connected. The EtherCAT network adapter has two Ethernet ports and an integrated switch.

The network adapter can be accessed with a system-independent web server application via the USB service interface or the EtherCAT. Thus, all information, such as diagnostics, status values and parameters, can be read and all connected modules can be simulated or forced.

The station's main power supply is integrated in the network adapter. Power is supplied via two 4-pole connectors, separated into the input and output current paths.




**Network Adapter EPXETC001**

---

<sup>1</sup> EtherCAT® is registered trademark and patented technology, licensed by Beckhoff Automation GmbH, Germany

### 4.3.1 LEDs



**LED Status Indicators EPXETC001**

#### LEDs


LED	Indication	LED State/Description
PWR	Power LED	<b>Green:</b> Supply voltage connected
SF	System Fault	<b>Red:</b> Configuration error, or error in the network adapter, or error in a module, or there is a new diagnostic report <b>Red flashing:</b> Station in Force mode
BF	Bus fault	<b>Red:</b> No connection to the fieldbus <b>Red flashing:</b> Configuration error, no connection to the control unit, or error in the parameter set
MT	Maintenance Required	<b>Yellow:</b> Error on the system bus or fieldbus
L/A IN	Connection/Activity	<b>Green:</b> Connection established between port 1 of the network adapter and another field device <b>Green flashing:</b> Data being exchanged on port 1
LA OUT	Connection/Activity	<b>Green:</b> Connection established between port 2 of the network adapter and another field device <b>Green flashing:</b> Data being exchanged on port 2
RUN	Network adapter state	<b>Off:</b> INIT <b>Green flashing:</b> PRE-OPERATIONAL <b>Green lights up briefly:</b> SAFE-OPERATIONAL <b>Green:</b> OPERATIONAL
ERROR	Internal error	<b>Red:</b> Critical error in the network adapter <b>Red lights up briefly:</b> Error in network adapter application <b>Red briefly lights up twice:</b> Output Syncmanager Watchdog expired <b>Red flashing:</b> Configuration error

### LED Indicators

LED	EPXETC001
Power Supply	<b>Green:</b> Supply voltage > 18 V DC
	<b>Red:</b> At least one current path < 18 V
3.1	<b>Green:</b> Input current path supply voltage > 18 V DC
3.2	<b>Red:</b> Input current path supply voltage < 18 V DC
3.3	
3.4	<b>Red:</b> Internal fuse defective
4.1	<b>Green:</b> Output current path supply voltage > 18 V DC
4.2	<b>Red:</b> Output current path supply voltage < 18 V DC
4.3	
4.4	<b>Red:</b> Internal fuse defective

For error messages, refer to the Chapter, *LED Indicators and Troubleshooting*.

### 4.3.2 Connection Diagrams




Connection Diagram EPXETC001



**Caution**

In the case of a maximum power supply of >8 A and a maximum temperature of > +55°C 131 °F, all four contacts must be connected with 1.5 mm<sup>2</sup> wiring.



Block Diagram EPXETC001

### 4.3.3 Specifications

#### EPXETC001

System data		
Connection	2 × RJ-45	
Fieldbus protocol	EtherCAT	
Process image	Process data	max. 1024 bytes
	Parameter data	max. 64*64 = 4 KB
	Diagnostic data	max. 64*50 = 3200 bytes
Number of modules	max. 64 active	
Configuration interface	Micro USB 2.0	
Transfer rate	Fieldbus	Max. 100 Mbps
	RTSi-EP system bus	Max. 48 Mbps
Supply		
Supply voltage for system and inputs	20.4V – 28.8V	
Supply voltage for outputs	20.4V – 28.8V	
Max. feed-in current for input modules	10 A	
Max. feed-in current for output modules	10 A	
Current consumption from system current path I <sub>sys</sub>	110 mA	
Connection data		
Type of connection	Spring style	
Conductor cross-section	Single-wired, fine-wired	0.14 – 1.5 mm² (AWG 26 – 16)
General data		
Operating temperature	-20°C to +60°C (-4 °F to +140 °F)	
Storage temperature	-40°C to +85°C (-40 °F to +185 °F)	
Air humidity (operation/transport)	5% to 95%, noncondensing as per IEC 61131-2	
Width	52 mm (2.05 in)	
Depth	76 mm (2.99 in)	
Height	120 mm (4.72 in)	
Weight	227 g (8 oz)	
Configuration	ESI file is available on the Support website <a href="http://support.ge-ip.com">http://support.ge-ip.com</a> for download and import into Programmer Tool which supports EtherCAT. The ESI supporting a firmware release is part of the firmware upgrade kit available on the Support website.	

#### Overview of the Editable Parameters EPXETC001

Parameter	Optional values	Default
IP address USB port <sup>†</sup>	192.168.1.202; 192.168.2.202, 192.168.3.202, 192.168.4.202, 192.168.5.202	192.168.1.202
Process alarm	disabled / enabled	disabled
Diagnostic	disabled / enabled	disabled
Behavior of outputs on fieldbus error	All outputs off / Enable substitute value/ Hold last value	All outputs off
Module behavior on hot swap	Continue data exchange / behavior like fieldbus error	Continue data exchange
Data format	Motorola / Intel	Motorola
Webserver via Ethernet	disabled / enabled / enabled	disabled / enabled
Coupler control	Reserved	Off
<sup>†</sup> Change requires restart of the network adapter.		

#### 4.3.4 RSTi-EP Status Messages

In addition to the process input data a network adapter status word as well as module status bytes are transferred to the SPS. Thus diagnostics and status messages can be read directly.

The network adapter status word describes the status of the RSTi-EP station including the following information:

**Network Adapter Status Bits EPXETC001**

Bit	Name	Description
0	Summarized module diagnosis	Module diagnostic is present. A diagnosis is available for at least one module with diagnostics functionality.
1	Errorbit 1	Reserve bit 1, currently not used
2	Errorbit 2	Reserve bit 2, currently not used
3	Systembus error	Error on the system bus. Communication with the connected modules is disrupted.
4	Errorbit 4	Reserve bit 4, currently not used
5	Errorbit 5	Reserve bit 5, currently not used
6	I/O-Configuration error	Deviation in the configuration. The module list has changed. The list of configured modules (Configured Module Ident List 0xF030) differs from the module list detected by the network adapter (Detected Module Ident List 0xF050).
7	Master configuration error	Master configuration error. The list of configured modules (Configured Module Ident List 0xF030) differs significantly from the module list detected by the network adapter (Detected Module Ident List 0xF050). No process data can be exchanged with the modules. The station switches into PRE OPERATIONAL state.
8	Errorbit 8	Reserve bit 8, currently not used
9	Errorbit 9	Reserve bit 9, currently not used
10	Force mode active	Web server Force mode is active. Force mode was activated through the web server. Process data cannot be exchanged between the EtherCAT master and forced channels.
11	Errorbit 11	Reserve bit 11, currently not used
12	Errorbit 12	Reserve bit 12, currently not used
13	Voltage U <sub>OUT</sub> error	Error in the supply voltage of outputs
14	Voltage U <sub>IN</sub> error	Error in the supply voltage of system and inputs
15	Errorbit 15	Reserve bit 15, currently not used





### 4.3.7 Supported Modules and Power Supplies

The following modules can be used with this release of the RSTi-EP EtherCat Network Adaptor:

Catalog Number	Module Description
<b>Digital Input Modules</b>	
EP-1214	Digital Input, 4 Points, Positive Logic 24VDC, 2,3, or 4 Wire
EP-1218	Digital Input, 8 Points, Positive Logic, 24VDC 2 Wire
EP-1318	Digital Input, 8 Points, Positive Logic, 24VDC 3 Wire
EP-125F	Digital Input, 16 Points, Positive Logic, 24VDC, 1 Wire
EP-12F4	Digital Input, 4 Points, Positive Logic 24VDC, 2,3, or 4 Wire, Time stamp
EP-1804	Digital Input, 4 Points 110/230 VAC (65 – 277 VAC), 2 Wire, Isolated
<b>Digital Output Modules</b>	
EP-2214	Digital Output, 4 Points, Positive Logic 24VDC, 0.5A, 2,3, or 4 Wire
EP-2614	Digital Output, 4 Points, Positive Logic 24VDC, 2.0A, 2,3, or 4 Wire
EP-2634	Digital Output, 4 Points, Positive/Negative Logic 24VDC, 2.0A, 2,3, or 4 Wire
EP-2218	Digital Output, 8 Points, Positive Logic, 24VDC, 0.5A, 2 Wire
EP-225F	Digital Output, 16 Points, Positive Logic, 24VDC, 0.5A, 1 Wire
<b>Digital Relay Output Modules</b>	
EP-2714	Digital Relay Output, 4 Points, Positive Logic, 24 – 220 VDC/VAC, 6A, 2 Wire
EP-2814	Solid-state Relay Output Module
<b>Analog Input Modules</b>	
EP- 3164	Analog Input, 4 Channels Voltage/Current 16 Bits 2, 3, or 4 Wire
EP- 3264	Analog Input, 4 Channels Voltage/Current 16 Bits with Diagnostics 2, 3, or 4 Wire
EP- 3124	Analog Input, 4 Channels Voltage/Current 12 Bits 2, 3, or 4 Wire
EP-3368	Analog Input, 8 Channels Current 16 Bits 2, 3, or 4 Wire
EP-3468	Analog Input, 8 Channels Current 16 Bits 2, 3, or 4 Wire, Channel Diagnostic
EP-3704	Analog Input, 4 Channels RTD 16 Bits with Diagnostics 2, 3, or 4 Wire
EP-3804	Analog Input, 4 Channels TC 16 Bits with Diagnostics 2, 3, or 4 Wire
<b>Analog Output Modules</b>	
EP-4164	Analog Output, 4 Channels Voltage/Current 16 Bits 2, 3, or 4 Wire
EP-4264	Analog Output, 4 Channels Voltage/Current 16 Bits with Diagnostics 2, 3, or 4 Wire
<b>Speciality Modules</b>	
EP-5111	1 Channel High Speed Counter, AB 100 kHz 1 DO 24VDC, 0.5A
EP-5112	2 Channel High Speed Counter, AB 100 kHz
EP-5212	2 Channel Frequency Measurement, 100 kHz
EP-5261	1 Channel Serial Communications, 232, 422, 485
EP-5311	1 Channel SSI Encoder, BCD or Gray-Code Format, 5/24 VDC
EP-5422	2 Channels PWM Output, Positive Logic, 24VDC, 2.0 A
EP-5442	2 Channels PWM Output, Positive Logic, 24VDC, 0.5 A
<b>Power Feed Modules for Input Current Path</b>	
EP-7631	Power Module, 1 Channel 24VDC Input Flow 10A
<b>Power Feed Modules for Output Current Path</b>	
EP-7641	Power Module, 1 Channel 24VDC Output Flow 10A
<b>Safe Feed-input Modules</b>	
EP-1901	1 Safe Feed-Input, 24 VDC
EP-1902	2 Safe Feed-Inputs, 24 VDC, Programmable Delay
EP-1922	2 Safe Feed-Inputs, 24 VDC
<b>Potential Distribution Modules</b>	
EP-711F	Power Module, 16 Channels 24VDC Potential Distribution +24 VDC from Input Current Path
EP-751F	Power Module, 16 Channels 24VDC Potential Distribution +24 VDC from Output Current Path
EP-700F	Power Module, 16 Channels 24VDC Potential Distribution Functional Earth
EP-710F	Power Module, 16 Channels 24VDC Potential Distribution +0VDC from Input Current Path
EP-750F	Power Module, 16 Channels 24VDC Potential Distribution +0VDC from Output Current Path

## 4.4 Modbus® TCP Network Adapter EPXMBE001

The EPXMBE001 network adapter is a Modbus TCP participant developed according to IEC 61158. The network adapter is the head module for the RSTi-EP communication bus, to which up to 64 active RSTi-EP modules can be connected. The Modbus TCP network adapter has two Ethernet ports and an integrated switch.


The network adapter can be accessed with a system-independent web server application via the USB service interface or the Ethernet. Thus, all information, such as diagnostics, status values and parameters, can be read and all connected modules can be simulated or forced.

The station's main power supply is integrated in the network adapter. Power is supplied via two 4-pole connectors, separated into the input and output current paths.



Network Adapter EPXMBE001

### 4.4.1 LEDs



LED Status Indicators EPXMBE001

LED Status Indicators


LED	Indication	LED State/Description
PWR	Power LED	<b>Green:</b> Supply voltage connected
SF	System Fault	<b>Red:</b> Configuration error, or error in the network adapter, or error in a module, or there is a new diagnostic report <b>Red flashing:</b> Station in Force mode
BF	Bus fault	<b>Red:</b> No connection to the fieldbus <b>Red flashing:</b> Configuration error, no connection to the control unit, or error in the parameter set
MT	Maintenance Required	<b>Yellow:</b> Error on the system bus or fieldbus
L/A X1	Connection/Active	<b>Green / Yellow†:</b> Connection established between port 1 of the network adapter and another field device <b>Green flashing / Yellow flashing†:</b> Data being exchanged on port 1
L/A X2	Connection/Active	<b>Green:</b> Connection established between port 2 of the network adapter and another field device <b>Green flashing:</b> Data being exchanged on port 2
† <b>Green:</b> Transfer rate 100 MBit/s <b>Yellow:</b> Transfer rate 10 MBit/s		

LED Indicators

LED	EPXMBE001	
	LED	Indication
	Power Supply	<b>Green:</b> Supply voltage > 18 V DC <b>Red:</b> At least one current path < 18 V
3.1		<b>Green:</b> Input current path supply voltage > 18 V DC
	3.2	<b>Red:</b> Input current path supply voltage < 18 V DC
	3.3	
	3.4	<b>Red:</b> Internal fuse defective
4.1		<b>Green:</b> Output current path supply voltage > 18 V DC
	4.2	<b>Red:</b> Output current path supply voltage < 18 V DC
	4.3	
	4.4	<b>Red:</b> Internal fuse defective

For error messages, refer to the Chapter, *LED Indicators and Troubleshooting*.

## 4.4.2 Connection Diagrams




Connection Diagram EPXMBE001



### Caution

In the case of a maximum power supply of >8 A and a maximum temperature of > +55°C 131 °F, all four contacts must be connected with 1.5 mm<sup>2</sup> wiring.



EPXMBE001

Block Diagram EPXMBE001

### 4.4.3 Specifications

#### EPXMBE001

System data		
Connection	2 x RJ-45	
Fieldbus protocol	Modbus TCP	
Process image	Input data width	max. 8 kBytes
	Parameter data	max. 1024 kBytes
	Diagnostic data	max. 1024 kBytes
Number of modules	max. 64 active	
Configuration interface	Micro USB 2.0	
Transfer rate	Fieldbus	10 Mbps/100 Mbps
	RTSi-EP system bus	Max. 48 Mbps
Supply		
Supply voltage for system and inputs	20.4V – 28.8V	
Supply voltage for outputs	20.4V – 28.8V	
Max. feed-in current for input modules	10 A	
Max. feed-in current for output modules	10 A	
Current consumption from system current path I <sub>sys</sub>	112 mA	
Connection data		
Type of connection	Spring style	
Conductor cross-section	Single-wired, fine-wired	0.14 – 1.5 mm <sup>2</sup> (AWG 26 – 16)
General data		
Operating temperature	-20°C to +60°C (-4 °F to +140 °F)	
Storage temperature	-40°C to +85°C (-40 °F to +185 °F)	
Air humidity (operation/transport)	5% to 95%, noncondensing as per IEC 61131-2	
Width	52 mm (2.05 in)	
Depth	76 mm (2.99 in)	
Height	120 mm (4.72 in)	
Weight	223 g (7.87 oz)	

#### 4.4.4 Configuration of the IP Address

The web server can be used to define whether a static IP address shall be used or the address shall be assigned automatically (DHCP/BootP).

Network adapters using firmware version 01.xx.xx are preset to the static IP address 192.168.0.222.

Network adapters using firmware version 02.00.00 or higher will by default send a DHCP discover first. If no assignment by a DHCP server follows during the next 30 seconds, the static IP address 192.168.0.222 will be set.

**Overview of the Editable Parameters EPXMBE001**

Parameter	Optional values	Default
IP-Address	4 numbers between 0-255	192.168.0.222
Subnet mask	4 numbers between 0-255	255.255.255.0
Gateway	4 numbers between 0-255	192.168.0.1
IP Configuration	Static, DHCP, BootP	DHCP and static
MODBUS DHCP Timeout	Waiting time, 1 to 1000 s	30 s
Additional TCP port <sup>1</sup>	0 (disabled) / Value from 1 to 65535 <sup>†</sup> (except for 80 and 161)	0
IP-Address USB Port <sup>†</sup>	192.168.1.202; 192.168.2.202, 192.168.3.202, 192.168.4.202, 192.168.5.202	192.168.1.202
Webserver via Ethernet <sup>†</sup>	disabled / enabled	disabled
Save module parameters <sup>2</sup>	no / yes / Standard	no, refer to register 0x113C – 0x113F <i>Save Module Parameters</i>
Status Modbus watchdog	Watchdog time in steps of 10 ms	0 *10 ms, refer to register 0x1120 MODBUS DATA EXCHANGE watchdog, predefined time
Modbus Connection Timeout	Connection watchdog time in sec	1 s, refer to register 0x1131 MODBUS CONNECTION Timeout in Sec
Write access in multi-client operation	write for all, 1stWr1stServe, 1stConn1stServe	write for all, refer to register 0x1031 MODBUS CONNECTION Mode Register
Check reference list before exchanging data	disabled / enabled	disabled, refer to register 0x1132 <i>Check Reference List prior to Data Exchange</i>
Process alarm	disabled / enabled	refer to register 0x1133 <i>Process Alarm</i>
Diagnostic alarm	disabled / enabled	refer to register 0x1134 <i>Diagnostic Alarm</i>
Behavior of outputs on fieldbus error	All outputs off / Enable substitute values / Hold last value	All outputs off, refer to register 0x1135 <i>Field Bus or Reference List Error Behavior</i>
Module behavior on hot swap	Continue data exchange / Behavior like fieldbus error	Continue data exchange, refer to register 0x1136 <i>Module Removal Behavior</i>
Data format	Motorola / Intel	Motorola, refer to register 0x1137 <i>Data Format</i>
Lock force mode	Force mode unlocked / Force mode locked	Force mode unlocked, refer to register <i>General Contact Information</i>
<sup>†</sup> Change requires restart of the network adapter.		

##### **<sup>1</sup> Parameter "Additional TCP port"**

Another TCP port additionally to the standard port (502) can be enabled using this parameter. Apart from the values 80 (reserved for http) and 161 (reserved for SNMP) every number from 1 to 65535 can be used. Value 0 deactivates the port. The standard port 502 will remain open in any case.

##### **<sup>2</sup> Parameter "Save module parameters" in the web server**

The choice *Yes* or *Standard* cannot be displayed in the web server, caused by the data structure of this parameter. The display will be reset to *No* anytime.



Option Yes: The current image of all module parameters is saved in the network adapter and will be sent to the modules again during the Network adapter's next restart. Subsequent changes of the module parameters are considered and saved only if the option Yes will be chosen again.

Option *Standard*: The default parameters will be loaded to the modules immediately. Subsequent changes of the module parameters are possible, but they will get loss during the network adapter's next restart.

### Parameter "Restore module parameters"

This parameter is not editable. It will be automatically set to Yes as soon as the network adapter will have sent saved parameter data to the modules.

#### Register Structure

(ro: read only = input register, rw: read write = holding register, wo: Write only = holding register)

Register address (in hex)	Access	Data width	Description	Remarks
0x0000 – 0x01FF	ro	Module-dependent	Packed process data for inputs	byte granularly
0x0800 – 0x09FF	rw	Module-dependent	Packed process data for outputs	byte granularly
0x1000 – x1006	ro	Byte	Network adapter identifier	
0x100C	ro	Word	Network adapter status	Bit assignment as with EPXETC001
0x1010	ro	Word	Process image length in bits for the output modules	
0x1011	ro	Word	Process image length in bits for the input modules	
0x1017	ro	Word	Register mapping revision	
0x1018 – 0x101B	ro	Byte	Collective diagnostics message for I/O modules (1 bit per I/O module)	
0x101C – 0x101F	ro	Byte	Collective process alarm message for I/O modules (1 bit per I/O module)	
0x1028 – 0x102F	ro	Byte	Module status (2 bits per I/O module) 00 = module OK, 01 = module error 10 = incorrect module 11 = module not plugged in	Structure as in PROFIBUS module status
0x1030	ro	Word	MODBUS DATA EXCHANGE watchdog, current time (x*10 ms) 0 = watchdog has expired 0xFFFF = watchdog deactivated	Time still remaining for monitoring the exchange of process data
0x1120	rw	Word	MODBUS DATA EXCHANGE watchdog, predefined time (x*10 ms), default = 0 ms (no watchdog active)	Time for monitoring the exchange of process data
0x1121	rw	Word	MODBUS DATA EXCHANGE watchdog reset register Bit0 = 1: watchdog reset at predefined time Bit8 = 1: restart after expired watchdog	Bit 0: reset watchdog while it is running (retrigger) Bit 8: restart of expired watchdog
0x1130	rw	Word	MODBUS CONNECTION mode register	
0x1131	rw	Word	MODBUS CONNECTION timeout in sec. Default = 1 (0 not allowed)	
0x1132	rw	Word	Check the reference list before data exchange 0x0000 = disable, 0x0001 = enable	
0x1133	rw	Word	Process alarm 0x0000 = disable, 0x0001 = enable	
0x1134	rw	Word	Diagnostics alarm 0x0000 = disable, 0x0001 = enable	
0x1135	rw	Word	Behavior in case of field bus error and reference list error 0x0000 = all outputs to 0, 0x0001 = set error values 0x0002 = retain process data	
0x1136	rw	Word	Behavior when module removed	



			0x0000 = process data continues to run 0x0001 = behavior as with field bus error	
0x1137	rw	Word	Data format 0x0000 = Motorola, 0x0001 = Intel	
0x113C – 0x113D	wo	Long	Restore module parameters Motorola = "LOAD", Intel = "DAOL"	Corresponds to the "DEFAULT" in the web server
0x113E – 0x113F	wo	Long	Save module parameters Motorola = "SAVE", Intel = "EVAS"	Corresponds to "SAVE" in the web server
0x27FE	ro	Word	Number of entries in the current module list	
0x27FF	ro	Word	Number of entries in the reference module list	
0x2800 – 0x287F	rw	Long	Reference module list (max. 64 modules per station * 2 registers per module)	There must always be 2, 4, 6 etc. registers transferred
0x2A00 – 0x2A7F	ro	Long	Current module list (max. 64 modules per station * 2 registers per module)	There must always be 2, 4, 6 etc. registers transferred
0x8000 – 0x87FF	ro	Module	Process data inputs (max. 64 modules per station * 32 registers per module)	
0x9000 – 0x97FF	rw	Module	Process data outputs (max. 64 modules per station * 32 registers per module)	
0xA000 – 0xA7FF	ro	Byte	Diagnostics (max. 64 modules per station * 32 registers per module)	Confirmation by readout
0xB000 – 0xB7FF	ro	Byte	Process alarms (max. 64 modules per station * 32 registers per module)	Confirmation by readout
0xC000 – 0xC7FF (Firmware 01.xx.xx) 0xC000 – 0xFFFF (Firmware 02.00.00 or higher)	rw	Byte	Module parameters (Firmware 01.xx.xx: max. 64 modules per station * 32 registers per module; Firmware 02.00.00 or higher: max. 64 modules per station * 256 registers per module)	
Note: If the user wants to access the DWORD for EP-5111, EP-5112, EP-5212, EP-5442 and EP-5422 modules use SWAP_DWORD function block.				

#### Implemented Modbus Functions

Function code no.	Function	Description
1	Read Coils	Reading of output bits in the range of 0x0800 – 0xFFFF†
2	Read Discrete Inputs	Reading of input bits in the range of 0x0000 – 0x07FF†
3	Read Holding Registers	Reading of multiple holding registers
4	Read Input Registers	Reading of multiple input registers
5	Write Single Coil	Writing of an individual output bit in the range of 0x0800 – 0xFFFF†
6	Write Single Registers	Writing of individual holding registers
15	Write Multiple Coils	Writing of output bits in the range of 0x0800 – 0xFFFF†
16	Write Multiple Registers	Writing of multiple holding registers
22	Mask Write Register	Bitwise changing of one holding register
23	Read/Write Multiple Registers	Reading of multiple input registers and writing of multiple holding registers simultaneously
† Function codes 1, 2, 5 and 15 for bit-wise access to registers. For the usage of these codes please note: In MODBUS protocol bit addressing separated from register addressing has not been specified. Bit and register address need to be implemented within the access address as follows: dismiss the most significant digit of the register address, shift the three less significant digits to the left and use the vacant least significant digit for bit addressing. Example: register access with function code 1 to address 0x80AB would be a read access to register 0x080A bit 11. Therefore the usage of function codes 1, 2, 5, 15 is limited to the address range of 0x0000 – 0x0FFF.		

**Supported Modules and Power Supplies**

<b>Part Number</b>	<b>Module Description</b>
<b>Digital Input Modules</b>	
EP-1214	Digital Input, 4 Points, Positive Logic 24VDC, 2,3, or 4 Wire
EP-1218	Digital Input, 8 Points, Positive Logic, 24VDC 2 Wire
EP-1318	Digital Input, 8 Points, Positive Logic, 24VDC 3 Wire
EP-125F	Digital Input, 16 Points, Positive Logic, 24VDC, 1 Wire
EP-12F4	Digital Input, 4 Points, Positive Logic 24VDC, 2,3, or 4 Wire, Time stamp
EP-1804	Digital Input, 4 Points 110/230 VAC (65 – 277 VAC), 2 Wire, Isolated
<b>Digital Output Modules</b>	
EP-2214	Digital Output, 4 Points, Positive Logic 24VDC, 0.5A, 2,3, or 4 Wire
EP-2614	Digital Output, 4 Points, Positive Logic 24VDC, 2.0A, 2,3, or 4 Wire
EP-2634	Digital Output, 4 Points, Positive/Negative Logic 24VDC, 2.0A, 2,3, or 4 Wire
EP-2218	Digital Output, 8 Points, Positive Logic, 24VDC, 0.5A, 2 Wire
EP-225F	Digital Output, 16 Points, Positive Logic, 24VDC, 0.5A, 1 Wire
<b>Digital Relay Output Modules</b>	
EP-2714	Digital Relay Output, 4 Points, Positive Logic, 24 – 220 VDC/VAC, 6A, 2 Wire
EP-2814	Solid-state Relay Output Module

<b>Analog Input Modules</b>	
EP- 3164	Analog Input, 4 Channels Voltage/Current 16 Bits 2, 3, or 4 Wire
EP- 3264	Analog Input, 4 Channels Voltage/Current 16 Bits with Diagnostics 2, 3, or 4 Wire
EP- 3124	Analog Input, 4 Channels Voltage/Current 12 Bits 2, 3, or 4 Wire
EP-3368	Analog Input, 8 Channels Current 16 Bits 2, 3, or 4 Wire
EP-3468	Analog Input, 8 Channels Current 16 Bits 2, 3, or 4 Wire, Channel Diagnostic
EP-3704	Analog Input, 4 Channels RTD 16 Bits with Diagnostics 2, 3, or 4 Wire
EP-3804	Analog Input, 4 Channels TC 16 Bits with Diagnostics 2, 3, or 4 Wire
<b>Analog Output Modules</b>	
EP-4164	Analog Output, 4 Channels Voltage/Current 16 Bits 2, 3, or 4 Wire
EP-4264	Analog Output, 4 Channels Voltage/Current 16 Bits with Diagnostics 2, 3, or 4 Wire
<b>Speciality Modules</b>	
EP-5111	1 Channel High Speed Counter, AB 100 kHz 1 DO 24VDC, 0.5A
EP-5112	2 Channel High Speed Counter, AB 100 kHz
EP-5212	2 Channel Frequency Measurement, 100 kHz
EP-5261	1 Channel Serial Communications, 232, 422, 485
EP-5311	1 Channel SSI Encoder, BCD or Gray-Code Format, 5/24 VDC
EP-5422	2 Channels PWM Output, Positive Logic, 24VDC, 2.0 A
EP-5442	2 Channels PWM Output, Positive Logic, 24VDC, 0.5 A
<b>Power Feed Modules for Input Current Path</b>	
EP-7631	Power Module, 1 Channel 24VDC Input Flow 10A
<b>Power Feed Modules for Output Current Path</b>	
EP-7641	Power Module, 1 Channel 24VDC Output Flow 10A
<b>Safe Feed-input Modules</b>	
EP-1901	1 Safe Feed-Input, 24 VDC
EP-1902	2 Safe Feed-Inputs, 24 VDC, Programmable Delay
EP-1922	2 Safe Feed-Inputs, 24 VDC

Potential Distribution Modules	
EP-711F	Power Module, 16 Channels 24VDC Potential Distribution +24 VDC from Input Current Path
EP-751F	Power Module, 16 Channels 24VDC Potential Distribution +24 VDC from Output Current Path
EP-700F	Power Module, 16 Channels 24VDC Potential Distribution Functional Earth
EP-710F	Power Module, 16 Channels 24VDC Potential Distribution +0VDC from Input Current Path
EP-750F	Power Module, 16 Channels 24VDC Potential Distribution +0VDC from Output Current Path

#### 4.4.5 Packed Process Data

##### Packed input process data

Input register range: 0x0000 to 0x01FF

**Note:** Access to all 512 registers is always possible regardless of the I/O structure. Unused registers respond with "0".

##### Packed output process data

Output register range: 0x0800 to 0x09FF

**Note:** Access to all 512 registers is always possible regardless of the I/O structure. Unused registers send "0" during a read access, write accesses are ignored.

##### Structure of packed process data

The byte granularly packed process data contains all input data (register range 0x0000 to 0x01FF) and output data (register range 0x0800 to 0x09FF) of the RSTi-EP station.

**Note:** The start address(es) of each module's process data are listed in register 0x2B00 – 0x2B7F (refer to the section *0x2B00 – 0x2B7F Module offsets of process data*).

**Note:** Process data is mapped according to how the modules are arranged. To avoid larger gaps in the process data, the different modules should be arranged in an optimal manner.

##### Example of an Optimal Module Arrangement

Product	Input data	Output data	Number of input registers	Number of output registers	Remarks
EPXMBE001			0	0	
EP-4164	--	4 words	0	4	allocated 4 registers
EP-3164	4 words	--	4	0	allocated 4 registers
EP-1214	1 Byte	--	1	0	allocated 1/2 register low byte (1 byte)
EP-1214	1 Byte	--	0	0	allocated 1/2 register high byte (1 byte)
EP-125F	2 Byte		1		allocated 1 register
Total			6	4	

Example of an Suboptimal Module Arrangement

Product	Input data	Output data	Number of input registers	Number of output registers	Remarks
EPXMBE001			0	0	
EP-1214	1 Byte	--	1	0	allocated 1 register
EP-4164	--	4 words	0	4	allocated 4 registers
EP-3164	4 words	--	4	0	allocated 4 registers
EP-1214	1 Byte	--	1	0	allocated 1 register
EP-125F	2 Byte		1		allocated 1 register
Total			7	4	

Data Widths of I/O Modules in the Modbus Register Range

Module	Process data	
	Input	Output
EP-1214	1 Byte	--
EP-1218	1 Byte	--
EP-1318	1 Byte	--
EP-125F	2 Byte	--
EP-12F4	15*(2 Byte, 1 Word)	--
EP-2214	--	1 Byte
EP-2614	--	1 Byte
EP-2634	--	1 Byte
EP-2218	--	1 Byte
EP-225F	--	2 Byte
EP-2814	--	1 Byte
EP-2714	--	1 Byte
EP-5111	2 DWord, 2 Word	2 DWord, 1 Word
EP-5112	2 DWord, 2 Word	2 DWord, 2 Word
EP-5212	4 DWord, 2 Word	2 DWord, 2 Word
EP-5422	2 Word	2 DWord, 2 Word
EP-5442	2 Word	2 DWord, 2 Word
EP-3164	4 Word	--
EP-3264	4 Word	--
EP-3124	4 Word	--
EP-3804	4 Word	--
EP-3368	8 Word	--
EP-3468	8 Word	--
EP-4164	--	4 Word
EP-4264	--	4 Word
EP-3704	4 Word	--
EP-1901	4 Byte	--
EP-1922	4 Byte	--
EP-1902	4 Byte	--

#### 4.4.6 0x1000 – 0x1006 Network adapter Identifier

The identifier is the product designation: EPXMBE001.

#### 4.4.7 0x1000 – 0x1006 Network adapter Status

Bit	Name	Meaning
0	Summarized module diagnosis	A diagnosis is available on at least one module with diagnostics functionality.
1	Errorbit 1	Reserve bit 1, currently not used
2	Errorbit 2	Reserve bit 2, currently not used
3	Systembus error	Error on system bus. Communication with the connected modules is disrupted.
4	Errorbit 4	Reserve bit 4, currently not used
5	Errorbit 5	Reserve bit 5, currently not used
6	I/O-Configuration error	Differing configuration. The module list has changed. The list of configured modules (reference module list 0x2800 – 0x287F) differs from the module list detected by the network adapter (current module list 0x2A00 – 0x2A7F).
7	Master configuration error	Master configuration error. The list of configured modules (reference module list 0x2800 – 0x287F) differs significantly from the module list detected by the network adapter (current module list 0x2A00 – 0x2A7F). Process data cannot be exchanged with the modules.
8	Errorbit 8	Reserve bit 8, currently not used
9	Errorbit 9	Reserve bit 9, currently not used
10	Force mode active	Force mode was activated via the web server. Forced channels do not exchange data with the master.
11	Errorbit 11	Reserve bit 11, currently not used
12	Errorbit 12	Reserve bit 12, currently not used
13	Voltage U <sub>OUT</sub> error	Error in the supply voltage of outputs
14	Voltage U <sub>IN</sub> error	Error in the supply voltage of system and inputs
15	Errorbit 15	Reserve bit 15, currently not used

#### 4.4.8 0x1010 Process Image Length in Bits for the Output Modules

#### 4.4.9 0x1010 Process Image Length in Bits for the Input Modules

#### 4.4.10 0x1017 Register – Mapping Revision

Version of the register structure

#### 4.4.11 0x1018 – 0x101B Collective Diagnostics Message for I/O Modules

If a diagnostic alarm is activated (register 0x1134) and there is a diagnostic message for a module, it is indicated here with a set bit. A module's slot position corresponds to its position in the 64-bit data field (minus passive modules without slot recognition). Example: 0x0000 0000 0000 0002 = There is a diagnostic alarm for module 2.

Reading the module's diagnostic memory (0xAxxx) confirms the diagnosis and resets the corresponding bit. In case of multiple diagnoses for one module, only the most up-to-date diagnosis is displayed. The next diagnostic is then placed in a wait loop and only becomes active once the current one has been confirmed.

#### **4.4.120x101C – 0x101F Collective Process Message for I/O Modules**

If a process alarm is activated (register 0x1133) and there is an alarm for a module, this is indicated here with a set bit. A module's slot position corresponds to its position in the 64-bit data field (minus passive modules without slot recognition). Example: 0x0000 0000 0000 0002 = There is a process alarm for module 2.

Reading the module's process alarm memory (0xBXXX) confirms the alarm and resets the corresponding bit. In case of multiple process alarms for one module, only the latest alarm is displayed. The next alarm is then placed in a wait loop and only becomes active once the current one has been confirmed.

#### **4.4.130x1028 – 0x102F Module Status**

The module status (2 bits per module) is displayed in the corresponding bit positions of the 128 bits.

0 0 Valid data from this module

0 1 Invalid data, faulty module

1 0 Invalid data, incorrect module

1 1 Invalid data, missing module

#### **4.4.140x1030 MODBUS DATA EXCHANGE Watchdog, Current Time**

Amount of time (input value \* 10 ms) still remaining on the active watchdog to monitor the exchange of process data. If a 0 is read, the watchdog has expired and must be restarted.

If 0xFFFF is read, the watchdog is deactivated.

#### **4.4.150x1120 MODBUS DATA EXCHANGE watchdog, predefined time**

In this register, the watchdog is activated/deactivated and the watchdog time is set. Process data can be exchanged as long as the watchdog is deactivated or it is activated and still running. But it is accepted only after a watchdog reset to the current time. The length is calculated with the input value \* 10 ms. Entering 0 deactivates the watchdog.

#### **4.4.160x1121 MODBUS DATA EXCHANGE Watchdog Reset Register**

If Bit 0 in this register is set, the predefined time is loaded into the watchdog time (watchdog reset).

If Bit 8 in this register is set, an expired watchdog (value 0 in register 1030) is reactivated.

#### **4.4.170x1122 Lock force Mode on Web Server**

In default setting the force mode can be enabled via the web server (after Login). The force mode can be locked by writing the double word "LOCK" (0x4C4F, 0x434B). Writing of "FREE" (0x4652, 0x4545) will unlock the force mode again.

#### 4.4.180x1031 MODBUS CONNECTION Mode Register

Bit	Name/Description
2 to 15	reserved
1	<b>MB_ImmediateWritePermission</b>
	<ul style="list-style-type: none"> <li>– 0: during the first write access, write authorization is requested for the corresponding Modbus connection. If this is not successful, an exception response with the exception code 0x01 is generated. If it is successful, the write access is executed and write authorization remains in effect until the end of the connection.</li> <li>– 1: write authorization for the corresponding Modbus connection is already requested when the connection is being established. As a result, the first Modbus connection receives the write authorization, and nothing happens for all those that follow (as long as Bit 0 = 1).</li> </ul>
0	<b>MB_OnlyOneWritePermission</b>
	<ul style="list-style-type: none"> <li>– 0: all Modbus connections have write authorization</li> <li>– 1: in all cases only one Modbus connection can be assigned write authorization. Once assigned, write authorization is retained until there is a disconnect. After the connection that has write authorization is disconnected, the next connection which attempts write access receives write authorization.</li> </ul>

#### 4.4.190x1131 MODBUS CONNECTION Timeout in Sec

This register determines how long a Modbus connection must be inactive before it is ended with a disconnect.

#### 4.4.200x1132 Check Reference List prior to Data Exchange

If the value in register 0x1132 is set to 0, the data exchange begins without checking the reference module list (0x2800 and the following) against the current module list (0x2A00 and the following). The reference module list must also not be described.

If the value in register 0x1132 is set to 1, the data exchange only starts if the reference module list (0x2800 and the following) matches the current module list (0x2A00 and the following).

#### 4.4.210x1133 Process Alarm

If the value in this register is set to 0, process alarms are reported, but it is not necessary to confirm or read them. If the value in this register is set to 1, process alarms are reported and they must be confirmed by reading the corresponding register.

#### 4.4.220x1134 Diagnostic Alarm

If the value 0 is set in this register, the diagnostic alarm is deactivated. Pending diagnostics do not have any effect on the exchange of process data and must not be confirmed. They are, however, displayed locally on the RSTi-EP hardware with red LEDs (SF and module) and also can be read in the module-specific diagnostic registers 0xAXXX.

If the value in this register is set to 1, diagnostics alarms are reported, and they must be confirmed by reading the corresponding register.

#### 4.4.230x1135 Field Bus or Reference List Error Behavior

If the value in this register is set to 0, in case of a field bus or reference list error all outputs are set to 0.

If the value in this register is set to 1, in case of a field bus error all outputs are set to the substitute values.

If the value in this register is set to 2, in case of a field bus error all outputs are held at the last process value.

#### 4.4.240x1136 Module Removal Behavior

If the value in this register is set to 0, the exchange of process data continues.

If the value in this register is set to 1, the behavior during a field bus error is used.

#### 4.4.250x1137 Data Format

If the value in this register is set to 0, data is transferred in Motorola format.

If the value in this register is set to 1, data is transferred in Intel format.

#### 4.4.260x113C – 0x113F Save Module Parameters

**Load default module parameters** (0x113C – 0x113D) loads the default parameter set of all modules (LOAD). This conforms to the *Standard* option in the web server.

**Save module parameters** (0x113E – 0x113F) stores the current image of all module parameters in the network adapter (SAVE). Subsequent changes will not be considered unless they are saved again. There is no need to enter parameters again after restarting the network adapter. This conforms to the *Yes* option in the web server.

Inputs in both register in the Motorola format follow this scheme:

	"LOAD"				"SAVE"			
Letter of the alphabet	L	O	A	D	S	A	V	E
ASCII code decimal	076	079	065	068	083	065	086	069
ASCII hexadecimal	4C	4F	41	44	53	41	56	45
<b>Input in register no.</b>	<b>0x113C</b>		<b>0x113D</b>		<b>0x113E</b>		<b>0x113F</b>	
Hexadecimal	4C4F		4144		5341		5645	
Decimal	19535		16708		21313		22085	

Using the Intel format the inputs follow "DAOL" and "EVAS":

	"DAOL"				"EVAS"			
Letter of the alphabet	D	A	O	L	E	V	A	S
ASCII code decimal	068	065	079	076	069	086	065	083
ASCII hexadecimal	44	41	4F	4C	45	56	41	53
<b>Input in register no.</b>	<b>0x113C</b>		<b>0x113D</b>		<b>0x113E</b>		<b>0x113F</b>	
Hexadecimal	4441		4F4C		4556		4153	
Decimal	17473		20300		17750		16723	

The not editable parameter *Restore module parameters* in the web server will be set to *Yes* as soon as the network adapter has sent saved parameters to the modules.

#### 4.4.270x27FE Number of Entries in the Current Module List

This displays the number of modules that were connected when the network adapter was started.

#### 4.4.280x27FF Number of Entries in the Reference Module List

This displays the number of modules that were entered into the reference list.

#### 4.4.290x2800 – 0x287F Reference Module List

Each module identifier is made up of 4 bytes (2 registers). If a 1 is set in register 1132, the reference module list must be identical to the current module list before the data exchange can begin.

#### 4.4.300x2A00 – 0x2A7F Current Module List

Each module identifier is made up of 4 bytes (2 registers) (refer to the Overview of module IDs). The modules that were connected when the network adapter was started are entered here. To simplify configuration, the current module list can be copied into the reference module list.

#### 4.4.310x2B00 – 0x2B7F Module offsets of process data

For each module there are two registers reserved to indicate the offset between the start address within the packed process data and the address 0x0000: The first register indicates the bit-offset of the outputs, the second one indicates the bit-offset of the inputs. Thus, it is possible to use these



information directly for the access to coils or Discrete Inputs. Converting the address syntax is necessary for a register- wise access (refer to the table "Implemented modbus functions").

In case there are no outputs or inputs, the register entry is 0xFFFF.

#### **4.4.320x8000 – 0x87FF Process Data Inputs**

For each module a data length of 64 bytes (32 registers) is reserved.

Example: Module 3 starts at address 0x8040.

#### **4.4.330x9000 – 0x97FF Process Data Outputs**

For each module a data length of 64 bytes (32 registers) is reserved.

Example: Module 3 starts at address 0x9040.

#### **4.4.340xA000 – 0xA7FF Diagnostics**

For each module a diagnostics data length of 64 bytes (32 registers) is reserved.

Example: Module 3 starts at address 0xA040.

In case of a diagnostics message, the 47 bytes of the module diagnosis are entered here from the corresponding tables (see the table of diagnostic data in the corresponding module description in the module chapter).

If a 1 is set in register 0x1134, reading out the corresponding diagnosis results in a confirmation of the alarm.

#### **4.4.350xB000 – 0xB7FF Process Alarms**

For each module a process alarm data length of 64 bytes (32 registers) is reserved.

Example: Module 3 starts at address 0xB040.

In case of a process alarm, the 4 bytes of the module are entered here from the corresponding table (see the table of process alarms in the corresponding module description in the module chapter).

#### **4.4.360xC000 – 0xFFFF Parameters**

For each module a parameter data length of 256 registers is reserved. Example: Module 3 starts with address 0xC040. The modules can be parametrized via the web server (s. Chapter 10) or via the Modbus master.

One register is assigned to each module parameter with a size of max. 16 bit. 32 bit parameters use two subsequent registers (consider Motorola format!). The sequence of parameters as well as the optional values are listed in the parameter tables of the individual module descriptions (s. Chapter 6).

Example: Parameter 8 of module 3 has the address 0xC207 (provided that there is no 32 bit parameter prior to it in the same module). Examples for 32 bit parameters are "Period duration" of the pulse width modulation modules and „End value" of the counter modules.


## Chapter 5 Detailed Descriptions of I/O Modules

This chapter contains detailed descriptions and technical specification of the various RSTi-EP modules.

### 5.1 Digital Input Module EP-1214




**Digital Input Module EP-1214**




**Connection Diagram EP-1214**

The digital input module EP-1214 can detect up to 4 input signals. One sensor can be connected to each connector using a 2-wire, 3-wire or 3-wire + FE connection. A status LED is assigned to each channel. The module electronics supply the connected sensors with power from the input current path ( $I_{IN}$ ).

LED Indicators EP-1214

	Module Status	<b>Green:</b> Communication over the system bus <b>Red:</b> Module System Fault or Diagnostic Fault
	1.1	<b>Yellow:</b> Input 0 active
	1.2	--
	1.3	--
	1.4	--
	2.1	<b>Yellow:</b> Input 1 active
	2.2	--
	2.3	--
	2.4	--
	3.1	<b>Yellow:</b> Input 2 active
	3.2	--
	3.3	--
	3.4	--
	4.1	<b>Yellow:</b> Input 3 active
	4.2	--
	4.3	--
	4.4	--

For error messages, refer to the chapter, *Accessories and Replacement Parts*.



Block Diagram EP-1214

**Specifications EP-1214**

<b>System data</b>	
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in the section <i>Order and Arrangement of the Modules</i> )
Interface	RSTi-EP I/O communication bus
System bus transfer rate	48 Mbps
<b>Inputs</b>	
Channels	4
Sensor types	Type 1 and Type 3 sensors as per IEC 61131-2
Input filter	Input delay adjustable from 0 to 40 ms (PROFIBUS-DP to 20 ms)
Off voltage	< 5 V
On voltage	> 11 V
Sensor supply	max. 2 A per plug, total max. 8 A
Sensor connection	2-wire, 3-wire, 3-wire + FE
Reverse polarity protection	Yes
Module diagnosis	Yes
Individual channel diagnosis	No
<b>Supply</b>	
Supply voltage	20.4V – 28.8V
Current consumption from system current path $I_{sys}$	8 mA
Current consumption from input current path $I_{IN}$	18 mA + sensor supply current
<b>General data</b>	
Weight	87 g (3.07 oz)
For additional general data, refer to the section <i>General Technical Data for I/O Modules</i> ,	

**Overview of the Editable Parameter EP-1214**

<b>Channel</b>	<b>Description</b>	<b>Options</b>	<b>Default</b>
0 to 3	Input delay	no (0) / 0,3 ms (1) (not at PROFIBUS-DP) / 3 ms (2) / 10 ms (3) / 20 ms (4) / 40 ms (5) (not at PROFIBUS-DP)	3 ms

## Diagnostic Data EP-1214

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x0F
		1		
		2		
		3		
		4	Reserved	0
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	0
		4-7	Reserved	0
Channel type	4	0-6	Channel type	0x70
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	0
Number of channels	6		Number of similar channels per module	4
Channel error	7-10	0-31	Reserved	0
Channel 0 error to Channel 31 error	11 to 42	0-7	Reserved	0
Time stamp	43-46		Time stamp [ $\mu$ s] (32 bit)	


Process Data Inputs EP-1214

Byte	Bit	Description
IB0	IX0.0	DI0
	IX0.1	DI1
	IX0.2	DI2
	IX0.3	DI3
	IX0.4	reserved
	IX0.5	reserved
	IX0.6	reserved
	IX0.7	reserved

## 5.2 Digital Input Module EP-1218




Digital Input Module EP-1218




Connection Diagram EP-1218

The digital input module EP-1218 can detect up to 8 input signals. Two sensors can be connected to each connector using a 2-wire connection. A status LED is assigned to each channel. The module electronics supply the connected sensors with power from the input current path ( $I_{IN}$ ).

### LED Indicators EP-1218

	Module Status	<b>Green:</b> Communication over the system bus <b>Red:</b> Module System Fault or Diagnostic Fault
	1.1	<b>Yellow:</b> Input 0 active
	1.2	--
	1.3	<b>Yellow:</b> Input 1 active
	1.4	--
	2.1	<b>Yellow:</b> Input 2 active
	2.2	--
	2.3	<b>Yellow:</b> Input 3 active
	2.4	--
	3.1	<b>Yellow:</b> Input 4 active
	3.2	--
	3.3	<b>Yellow:</b> Input 5 active
	3.4	--
	4.1	<b>Yellow:</b> Input 6 active
	4.2	--
	4.3	<b>Yellow:</b> Input 7 active
	4.4	--

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



**Specifications EP-1218**

System data	
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in the section, <i>Order and Arrangement of the Modules</i> )
Interface	RSTi-EP I/O communication bus
System bus transfer rate	48 Mbps
Inputs	
Number	8
Sensor types	Type 1 and Type 3 sensors as per IEC 61131-2
Input filter	Input delay adjustable from 0 to 40 ms (PROFIBUS-DP to 20 ms)
Low input voltage	< 5 V
High input voltage	> 11 V
Sensor supply	max. 15 mA per channel
Sensor connection	2-wire
Reverse polarity protection	Yes
Module diagnosis	Yes
Individual channel diagnosis	No
Supply	
Supply voltage	20.4V – 28.8V
Current consumption from system current path $I_{sys}$	8 mA
Current consumption from input current path $I_{IN}$	30 mA + sensor supply current
General data	
Weight	85 g (2.99 oz)
For additional general data, refer to the section, <i>General Technical Data for I/O Modules</i> .	

**Overview of the Editable Parameter EP-1218**

Channel	Description	Options	Default
0 to 7	Input delay	no (0) / 0,3 ms (1) (not at PROFIBUS-DP) / 3 ms (2) / 10 ms (3) / 20 ms (4) / 40 ms (5) (not at PROFIBUS-DP)	3 ms





## Diagnostic Data EP-1218

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x0F
		1		
		2		
		3		
		4	Reserved	0
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	0
		4-7	Reserved	0
Channel type	4	0-6	Channel type	0x70
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	0
Number of channels	6		Number of similar channels per module	8
Channel error	7-10	0-31	Reserved	0
Channel 0 error to Channel 31 error	11 to 42	0-7	Reserved	0
Time stamp	43-46		Time stamp [ $\mu$ s] (32 bit)	

Process Data Inputs EP-1218

Byte	Bit	Description
IB0	IX0.0	DI0
	IX0.1	DI1
	IX0.2	DI2
	IX0.3	DI3
	IX0.4	DI4
	IX0.5	DI5
	IX0.6	DI6
	IX0.7	DI7

### 5.3 Digital Input Module EP-1318




Digital Input Module EP-1318


Connection Diagram EP-1318

The digital input module EP-1318 can detect up to 8 input signals. Two sensors can be connected to each connector using a 2-wire or 3-wire connection. A status LED is assigned to each channel. The module electronics supply the connected sensors with power from the input current path ( $I_{IN}$ ).

LED Indicators EP-1318

	Module Status	<b>Green:</b> Communication over the system bus <b>Red:</b> Module System Fault or Diagnostic Fault
	1.1	<b>Yellow:</b> Input 0 active
	1.2	--
	1.3	--
	1.4	<b>Yellow:</b> Input 1 active
	2.1	<b>Yellow:</b> Input 2 active
	2.2	--
	2.3	--
	2.4	<b>Yellow:</b> Input 3 active
	3.1	<b>Yellow:</b> Input 4 active
	3.2	--
	3.3	--
	3.4	<b>Yellow:</b> Input 5 active
	4.1	<b>Yellow:</b> Input 6 active
	4.2	--
	4.3	--
	4.4	<b>Yellow:</b> Input 7 active

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



Block Diagram EP-1318

**Specifications EP-1318**

System data	
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in the section, <i>Order and Arrangement of the Modules</i> )
Interface	RSTi-EP I/O communication bus
System bus transfer rate	48 Mbps
Inputs	
Number	8
Sensor types	Type 1 and Type 3 sensors as per IEC 61131-2
Input filter	Input delay adjustable from 0 to 40 ms (PROFIBUS-DP to 20 ms)
Low input voltage	< 5 V
High input voltage	> 11 V
Sensor supply	max. 2 A per plug, total max. 8 A
Sensor connection	2-wire, 3-wire
Reverse polarity protection	Yes
Module diagnosis	Yes
Individual channel diagnosis	No
Supply	
Supply voltage	20.4V – 28.8V
Current consumption from system current path $I_{sys}$	8 mA
Current consumption from input current path $I_{IN}$	30 mA + sensor supply current
General data	
Weight	83 g (2.93 oz)
For additional general data, refer to the section <i>General Technical Data for I/O Modules</i> .	

**Overview of the Editable Parameter EP-1318**

Channel	Description	Options	Default
0 to 7	Input delay	no (0) / 0,3 ms (1) (not at PROFIBUS-DP) / 3 ms (2) / 10 ms (3) / 20 ms (4) / 40 ms (5) (not at PROFIBUS-DP)	3 ms


**Diagnostic Data EP-1318**

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x0F
		1		
		2		
		3		
		4	Reserved	0
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	0
		4-7	Reserved	0
Channel type	4	0-6	Channel type	0x70
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	0
Number of channels	6		Number of similar channels per module	8
Channel error	7-10	0-31	Reserved	0
Channel 0 error to Channel 31 error	11 to 42	0-7	Reserved	0
Time stamp	43-46		Time stamp [ $\mu$ s] (32 bit)	


**Process Data Inputs EP-1318**

Byte	Bit	Description
IB0	IX0.0	DI0
	IX0.1	DI1
	IX0.2	DI2
	IX0.3	DI3
	IX0.4	DI4
	IX0.5	DI5
	IX0.6	DI6
	IX0.7	DI7

## 5.4 Digital Input Module EP-1804



**Digital Input Module EP-1804**



**Connection Diagram EP-1804**

The digital input module EP-1804 can detect up to 4 binary control signals. One sensor can be connected to each connector using a 2-wire connection. Both L and N connections of each input are bridged internally. The four inputs are galvanic isolated, they can be supplied with input voltages between 110V AC and 230V AC. Solely AC measurements can be run.



A status LED is assigned to each channel. All signal lines must be supplied from the same power system.

**Warning**

---



The module can be destroyed by too high frequencies.

The input frequency may be 65 Hz at maximum, the switching frequency 15 Hz at maximum.

**Attention**

---




The module can be destroyed by too high input currents of the signal lines.

The inputs must be ensured using a slow fuse max. 4 A.


**Attention**

---

LED Indicators EP-1804

	Module Status	Green: Communication over the system bus Red: Module System Fault or Diagnostic Fault
	1.1	Yellow: Input 0 active
	1.2	--
	1.3	--
	1.4	--
	2.1	Yellow: Input 1 active
	2.2	--
	2.3	--
	2.4	--
	3.1	Yellow: Input 2 active
	3.2	--
	3.3	--
	3.4	--
	4.1	Yellow: Input 3 active
	4.2	--
	4.3	--
	4.4	--

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



Block Diagram EP-1804



**Specifications EP-1804**

<b>System data</b>	
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in the section, <i>Order and Arrangement of the Modules</i> )
Interface	RSTi-EP I/O communication bus
System bus transfer rate	48 Mbps
Galvanic isolation	4kV between the channels as well as between channels and power supply
Line-to-line voltage	400V between the channels possible
<b>Inputs</b>	
Number	4
Input type	P-switching, for Type 3 sensors as per IEC 61131-2
Input filter	Input delay 10 ms
Low input voltage	< 65V
High input voltage	> 80V
Input voltage maximum	277V AC (UL); 264,5V AC (VDE)
Input frequency, typical	50 Hz, 60 Hz
Sensor supply	No
Sensor connection	2-wire
Module diagnosis	Yes
Individual channel diagnosis	No
<b>Supply</b>	
Supply voltage	20.4V – 28.8V
Current consumption from system current path $I_{sys}$	8 mA
Current consumption from input current path $I_{IN}$	Nil
<b>General data</b>	
Weight	89 g (3.07 oz)


**Diagnostic Data EP-1804**

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x05
		1		
		2		
		3		
		4	Reserved	0
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	0
		4	Power supply fault	0
		5-7	Reserved	0
Channel type	4	0-6	Channel type	0x70
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	8
Number of channels	6		Number of similar channels per module	4
Channel error	7-10	0-31	Reserved	0
Channel 0 error to Channel 31 error	11 to 42	0-7	Reserved	0
Time stamp	43-46		Time stamp [ $\mu$ s] (32 bit)	


*Process Data Inputs EP-1804*

Byte	Bit	Description
IB0	IX0.0	DI0
	IX0.1	DI1
	IX0.2	DI2
	IX0.3	DI3
	IX0.4	Reserved
	IX0.5	Reserved
	IX0.6	Reserved
	IX0.7	Reserved

## 5.5 Digital Input Module EP-125F




*Digital Input Module EP-125F*




*Connection Diagram EP-125F*

The EP-125F digital input module can detect up to 16 input signals. Four sensors can be connected to each connector in a 1-wire connection. A status LED is assigned to each channel. The connected sensors must be supplied with power from the input current path IIN (e.g. with potential distribution modules).

LED Indicators EP-125F

	Module Status	<b>Green:</b> Communication over the system bus <b>Red:</b> Module System Fault or Diagnostic Fault
	1.1	<b>Yellow:</b> Input 0 active
	1.2	<b>Yellow:</b> Input 1 active
	1.3	<b>Yellow:</b> Input 2 active
	1.4	<b>Yellow:</b> Input 3 active
	2.1	<b>Yellow:</b> Input 4 active
	2.2	<b>Yellow:</b> Input 5 active
	2.3	<b>Yellow:</b> Input 6 active
	2.4	<b>Yellow:</b> Input 7 active
	3.1	<b>Yellow:</b> Input 8 active
	3.2	<b>Yellow:</b> Input 9 active
	3.3	<b>Yellow:</b> Input 10 active
	3.4	<b>Yellow:</b> Input 11 active
	4.1	<b>Yellow:</b> Input 12 active
	4.2	<b>Yellow:</b> Input 13 active
	4.3	<b>Yellow:</b> Input 14 active
	4.4	<b>Yellow:</b> Input 15 active

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



Block Diagram EP-125F

**Specifications EP-125F**

<b>System data</b>	
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in the section, <i>Order and Arrangement of the Modules</i> )
Interface	RSTi-EP I/O communication bus
System bus transfer rate	48 Mbps
<b>Inputs</b>	
Number	16
Sensor types	Type 1 and Type 3 sensors as per IEC 61131-2
Input filter	Input delay 3 ms
Low input voltage	< 5 V
High input voltage	> 11 V
Sensor supply	No
Sensor connection	1-conductor
Reverse polarity protection	Yes
Module diagnosis	Yes
Individual channel diagnosis	No
<b>Supply</b>	
Supply voltage	20.4V – 28.8V
Current consumption from system current path $I_{sys}$	8 mA
Current consumption from input current path $I_{IN}$	52 mA
<b>General data</b>	
Weight	87 g (3.07 oz)

## Diagnostic Data EP-125F

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x0F
		1		
		2		
		3		
		4	Reserved	0
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	0
		4-7	Reserved	0
Channel type	4	0-6	Channel type	0x70
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	0
Number of channels	6		Number of similar channels per module	8
Channel error	7-10	0-31	Reserved	0
Channel 0 error to Channel 31 error	11 to 42	0-7	Reserved	0
Time stamp	43-46		Time stamp [ $\mu$ s] (32 bit)	

Process<sup>†</sup> Data Inputs EP-125F


Byte	Bit	Description
IB0	IX0.0	DI0
	IX0.1	DI1
	IX0.2	DI2
	IX0.3	DI3
	IX0.4	DI4
	IX0.5	DI5
	IX0.6	DI6
	IX0.7	DI7
IB1	IX1.0	DI8
	IX1.1	DI9
	IX1.2	DI10
	IX1.3	DI11
	IX1.4	DI12
	IX1.5	DI13
	IX1.6	DI14
	IX1.7	DI15
<sup>†</sup> Internal process data mapping with data format <i>Standard</i> . Depending on the fieldbus specification and the data format of the communicating fieldbus components the bytes and/or words can be reversed during data transfer.		



## 5.6 Digital Input Module EP-12F4



**Digital Input Module EP-12F4**




**Connection Diagram EP-12F4**


The digital input module with time stamp functionality EP-12F4 can detect up to 4 binary control signals and provide them with a time stamp (resolution 1  $\mu$ s). Depending on the configuration of the module, up to 5 or 15 time stamp entries can be evaluated.

One sensor can be connected to each connector using a 2-wire, 3-wire, or 3-wire connection + FE. A status LED is assigned to each channel. The module electronics supply the connected sensors with power from the input current path ( $I_{IN}$ ).

LED Indicators EP-12F4

	Module Status	Green: Communication over the system bus Red: No communication on system bus or there is a diagnostic message displayed
	1.1	Yellow: Input 0 active
	1.2	--
	1.3	--
	1.4	--
	2.1	Yellow: Input 1 active
	2.2	--
	2.3	--
	2.4	--
	3.1	Yellow: Input 2 active
	3.2	--
	3.3	--
	3.4	--
	4.1	Yellow: Input 3 active
	4.2	--
	4.3	--
	4.4	--

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



**Specifications EP-12F4**

<b>System data</b>	
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in the section, <i>Order and Arrangement of the Modules</i> )
Interface	RSTi-EP I/O communication bus
System bus transfer rate	48 Mbps
<b>Inputs</b>	
Number	4
Sensor types	Type 1 and Type 3 sensors as per IEC 61131-2
Input filter	Input delay adjustable from 0 to 40 ms (PROFIBUS-DP to 20 ms)
Low input voltage	< 5 V
High input voltage	> 11 V
Max. input current per channel	3 mA
Sensor supply	Yes
Sensor connection	2-wire, 3-wire, 3-wire + FE
Reverse polarity protection	Yes
Module diagnosis	Yes
Individual channel diagnosis	No
Time stamp data width	16 bits
Time stamp resolution	1 µs
<b>Supply</b>	
Supply voltage	20.4V – 28.8V
Current consumption from system current path $I_{sys}$	8 mA
Current consumption from input current path $I_{IN}$	18 mA + sensor supply current
<b>General data</b>	
Weight	87 g (3.07 oz)
For additional general data, refer to the section, <i>General Technical Data for I/O Modules</i>	

**Overview of the Editable Parameter EP-12F4**

Channel	Description	Options	Default
0 - 3	Input delay	no (0) / 0,3 ms (1) (not at PROFIBUS-DP) / 3 ms (2) / 10 ms (3) / 20 ms (4) / 40 ms (5) (not at PROFIBUS-DP)	3 ms
0 - 3	TimeStamp at edge 0-1	disabled (0) / enabled (1)	disabled
0 - 3	TimeStamp at edge 1-0	disabled (0) / enabled (1)	disabled

**Diagnostic Data EP-12F4**

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x0F
		1		
		2		
		3		
		4	Reserved	0
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	0
		4-7	Reserved	0
Channel type	4	0-6	Channel type	0x70
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	0
Number of channels	6		Number of similar channels per module	8
Channel error	7-10	0-31	Reserved	0
Channel 0 error to Channel 31 error	11 to 42	0-7	Reserved	0
Time stamp	43-46		Time stamp [ $\mu$ s] (32 bit)	

**Process† Data Inputs EP-12F4**

Byte	Format	Name	Remark
IB0	Byte	Input image 1	Bit0 = DI0 ... Bit3 = DI3, Bit4 ... 7 reserved
IB1	Byte	Running number 1	0 ... 127 rotating
IB2	Word	Time stamp 1	0 ... 65535 µs rotating
IB3			
IB4	Byte	Input image 2	
IB5	Byte	Running number 2	
IB6	Word	Time stamp 2	
IB7			
IB8	Byte	Input image 3	
IB9	Byte	Running number 3	
IB10	Word	Time stamp 3	
IB11			
--	--	--	
IB56	Byte	Input image 15	
IB57	Byte	Running number 15	
IB58	Word	Time stamp 15	
IB59			
† Internal process data mapping with data format "Standard". Depending on the fieldbus specification and the data format of the communicating fieldbus components the bytes and/or words can be reversed during data transfer.			

### 5.6.1 Time Stamp Function

With time stamp function (ETS = edge time stamp) enabled, at every corresponding edge the time value of the timer is stored in the process image as an ETS entry together with the status of the inputs and a running number.

The module does not use any bytes in the output range. It uses 60 Bytes in the input range for 15 ETS entries each with 4 bytes.

### 5.6.2 Structure of an ETS Entry

#### Input image PII

After the edge transition, the status of the inputs is stored here. The input byte has the following bit assignments:


- Bit 0: DI 0
- Bit 1: DI 1
- Bit 2: DI 2
- Bit 3: DI 3
- Bit 4 ... 7: reserved (0)

#### Running Number RN

The RN (running number) is a consecutive number from 0 to 127. It describes the chronological sequence of the edges

#### Time stamp ETS\_US

The 16-bit timer (0 ... 65535µs) in the u-remote module is started as soon as the power supply is switched on and after (2<sup>16</sup> -1) µs restarts at 0.



Structure of ETS Entries in Input Range in Chronological Order

### 5.6.3 Example for the Mode of Operation

The following example shows the sequence in which ETS entries are stored. The input channels are predefined as follows:

DI 0 and DI 1: time stamp at edge 0-1 enabled


DI 2 and DI 3: time stamp at edge 0-1 disabled

DI 0 and DI 1: time stamp at edge 1-0 enabled

DI 2 and DI 3: time stamp at edge 1-0 disabled


The ETS entries available at time "t" are designated by the green area in the diagram. ETS entries that are not (or no longer) available have a grey background

**Process Image is Empty at  $t_0$**




#### 1st ETS Entry at $t_1$

A rising 0-1 edge on DI 0 causes the 1st ETS entry at address + 0.




**2nd ETS Entry at  $t_2$** 

A rising 0-1 edge on DI 1 causes the 2nd ETS entry at address + 0. The 1st ETS entry is shifted by 4 bytes.

**3rd ETS Entry at  $t_3$** 


A falling 1-0 edge on DI 0 causes the 3rd ETS entry.



... 4th to 14th ETS Entry ...


**15th ETS Entry at  $t_{15}$** 

A rising 0-1 edge on DI 0 causes the 15th ETS entry.




**16th ETS Entry at  $t_{16}$** 

A rising 0-1 edge on DI 1 causes the 16th ETS entry. The 1<sup>st</sup> ETS entry is deleted and not available anymore.


**17th ETS Entry at  $t_{17}$** 

A falling 1-0 edge on DI 1 causes the 17th ETS entry. The 2nd ETS entry is deleted and not available anymore.






## 5.7 Digital Output Module EP-2214



**Digital Output Module EP-2214**




**Connection Diagram EP-2214**

The EP-2214 digital output module can control up to 4 discrete outputs, each with a maximum of 0.5 A. One discrete output can be connected to each connector using a 2-wire, 3-wire or 3-wire connection + FE. A status LED is assigned to each channel. The outputs are supplied with power from the output current path ( $I_{OUT}$ ).

LED Indicators EP-2214

	Module Status	Green: Communication over the system bus Red: Module System Fault or Diagnostic Fault
1.1	Yellow: Output 0 active	
1.2	--	
1.3	--	
1.4	--	
2.1	Yellow: Output 1 active	
2.2	--	
2.3	--	
2.4	--	
3.1	Yellow: Output 2 active	
3.2	--	
3.3	--	
3.4	--	
4.1	Yellow: Output 3 active	
4.2	--	
4.3	--	
4.4	--	

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



**Specifications EP-2214**

System data		
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in the section, <i>Order and Arrangement of the Modules</i> )	
Interface	RSTi-EP I/O communication bus	
System bus transfer rate	48 Mbps	
Inputs		
Number	4	
Type of load	ohmic, inductive, lamp load	
Response time	low » high max. 100 µs; high » low max. 250 µs	
Max. output current	per channel	0.5 A
	per module	2 A
Breaking energy (inductive)	150 mJ per channel	
Switching frequency	Resistive load (min. 47 Ω)	1 kHz
	Inductive load (DC 13)	0.2 Hz without free-wheeling diode 1 kHz with suitable free-wheeling diode
	Lamp load (12 W)	1 kHz
Actuator connection	2-wire, 3-wire, 3-wire + FE	
Actuator supply	max. 2 A per plug, total max. 8 A	
Short-circuit-proof	Yes	
Protective circuit	Constant current with thermal switch-off and automatic restart	
Response time of the current limiting circuit	< 100 µs	
Module diagnosis	Yes	
Individual channel diagnosis	No	
Reactionless	Yes	
Can be used with EP-19xx	Yes	
Supply		
Supply voltage	20.4V – 28.8V	
Current consumption from system current path I <sub>sys</sub>	8 mA	
Current consumption from output current path I <sub>out</sub>	20 mA + load	
General data		
Weight	86 g (3.03 oz)	
For additional general data, refer to the section, <i>General Technical Data for I/O Modules</i>		

## Overview of the Editable Parameter EP-2214

Channel	Description	Options	Default
0 - 3	Substitute Value	Off (0) / On (1)	Off

## Diagnostic Data EP-2214

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x0F
		1		
		2		
		3		
		4	Reserved	0
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	0
		4-7	Reserved	0
Channel type	4	0-6	Channel type	0x72
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	0
Number of channels	6		Number of similar channels per module	4
Channel error	7-10	0-31	Reserved	0
Channel 0 error to Channel 31 error	11 to 42	0-7	Reserved	0
Time stamp	43-46		Time stamp [ $\mu$ s] (32 bit)	


*Process Data Outputs EP-2214*

Byte	Bit	Description
OB0	OX0.0	DO0
	OX0.1	DO1
	OX0.2	DO2
	OX0.3	DO3
	OX0.4	reserved
	OX0.5	reserved
	OX0.6	reserved
	OX0.7	reserved

## 5.8 Digital Output Module EP-2614




**Digital Output Module EP-2614**




**Connection Diagram EP-2614**

The digital output module EP-2614 can control up to 4 discrete outputs, each with a maximum of 2 A. One discrete output can be connected to each connector using a 2-wire, 3-wire or 3-wire connection + FE. A status LED is assigned to each channel. The outputs are supplied with power from the output current path ( $I_{OUT}$ ).

LED Indicators EP-2614

	Module Status	<b>Green:</b> Communication over the system bus <b>Red:</b> Module System Fault or Diagnostic Fault
	1.1	<b>Yellow:</b> Output 0 active
	1.2	--
	1.3	--
	1.4	--
	2.1	<b>Yellow:</b> Output 1 active
	2.2	--
	2.3	--
	2.4	--
	3.1	<b>Yellow:</b> Output 2 active
	3.2	--
	3.3	--
	3.4	--
	4.1	<b>Yellow:</b> Output 3 active
	4.2	--
	4.3	--
	4.4	--

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



Block Diagram EP-2614

**Specifications EP-2614**

System data		
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in section, <i>Order and Arrangement of the Modules</i> )	
Interface	RSTi-EP I/O communication bus	
System bus transfer rate	48 Mbps	
Inputs		
Number	4	
Type of load	ohmic, inductive, lamp load	
Response time	low » high max. 100 µs; high » low max. 250 µs	
Max. output current	per channel	2 A
	per module	8 A
Breaking energy (inductive)	150 mJ per channel	
Switching frequency	Resistive load (min. 47 Ω)	1 kHz
	Inductive load (DC 13)	0.2 Hz without free-wheeling diode 1 kHz with suitable free-wheeling diode
	Lamp load (12 W)	1 kHz
Actuator connection	2-wire, 3-wire, 3-wire + FE	
Actuator supply	max. 2 A per plug, total max. 8 A	
Short-circuit-proof	Yes	
Protective circuit	Constant current with thermal switch-off and automatic restart	
Response time of the current limiting circuit	< 100 µs	
Module diagnosis	Yes	
Individual channel diagnosis	No	
Can be used with EP-19xx	Yes	
Supply		
Supply voltage	20.4V – 28.8V	
Current consumption from system current path I <sub>sys</sub>	8 mA	
Current consumption from output current path I <sub>out</sub>	25 mA + load	
General data		
Weight	86 g (3.03 oz)	
For additional general data, refer to the section <i>General Technical Data for I/O Modules</i>		

**Overview of the Editable Parameter EP-2614**

Channel	Description	Options	Default
0 - 3	Substitute value	Off (0) / On (1)	Off




## Diagnostic Data EP-2614

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x0F
		1		
		2		
		3		
		4	Reserved	0
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	0
		4-7	Reserved	0
Channel type	4	0-6	Channel type	0x72
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	0
Number of channels	6		Number of similar channels per module	4
Channel error	7-10	0-31	Reserved	0
Channel 0 error to Channel 31 error	11 to 42	0-7	Reserved	0
Time stamp	43-46		Time stamp [ $\mu$ s] (32 bit)	


Process Data Outputs EP-2614

Byte	Bit	Description
OB0	OX0.0	DO0
	OX0.1	DO1
	OX0.2	DO2
	OX0.3	DO3
	OX0.4	reserved
	OX0.5	reserved
	OX0.6	reserved
	OX0.7	reserved

## 5.9 Digital Output Module EP-2634



**Digital Output Module EP-2634**




**Connection Diagram EP-2634**

The digital output module EP-2634 can control up to 4 discrete outputs each with a maximum of 2 A. One discrete output can be connected to each connector in a 2-wire or 3-wire + FE connection. A status LED is assigned to each channel. The outputs are supplied with power from the output current path ( $I_{OUT}$ ).


Each channel can be switched between positive and negative switching. This allows, among other things, a switch in rotational direction if a DC motor is connected between two outputs. For this purpose, an output byte is reserved for the physical outputs, and each channel is assigned two bits in this byte. The switching characteristics of each output are set in the low nibble of the byte. If a bit is set, the corresponding channel has positive switching, if it is 0 then it has negative switching. The outputs are switched in the high nibble. Example: If you write the value 185 decimal (1011 1001 binary) in the output byte, channel 1 is set to 24 V, channel 2 is set to GND, channel 3 is deactivated and channel 4 is set to 24 V.

The module is protected against external voltages between 0 V and the operating voltage.

LED Indicators EP-2634

	Module Status	<b>Green:</b> Communication over the system bus <b>Red:</b> Module System Fault or Diagnostic Fault
	1.1	<b>Yellow:</b> Output 0 active
	1.2	--
	1.3	--
	1.4	--
	2.1	<b>Yellow:</b> Output 1 active
	2.2	--
	2.3	--
	2.4	--
	3.1	<b>Yellow:</b> Output 2 active
	3.2	--
	3.3	--
	3.4	--
	4.1	<b>Yellow:</b> Output 3 active
	4.2	--
	4.3	--
	4.4	--

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



Block Diagram EP-2634

**Specifications EP-2634**

System data		
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in the section, <i>Order and Arrangement of the Modules</i> )	
Interface	RSTi-EP I/O communication bus	
System bus transfer rate	48 Mbps	
Inputs		
Number	4	
Type of load	ohmic, inductive, lamp load	
Response time	low » high max. 100 µs; high » low max. 250 µs	
Max. output current	per channel	2 A
	per module	8 A
Breaking energy (inductive)	150 mJ per channel	
Switching frequency	Resistive load (min. 47 Ω)	1 kHz
	Inductive load (DC 13)	0.2 Hz without free-wheeling diode 1 kHz with suitable free-wheeling diode
	Lamp load (12 W)	1 kHz
Actuator connection	2-wire, 3-wire, 3-wire + FE	
Actuator supply	max. 2 A per plug, total max. 8 A	
Short-circuit-proof	Yes	
Protective circuit	Constant current with thermal switch-off and automatic restart	
Response time of the current limiting circuit	< 100 µs	
Module diagnosis	Yes	
Individual channel diagnosis	No	
Reactionless	Yes	
Can be used with EP-19xx	Yes	
Supply		
Supply voltage	20.4V – 28.8V	
Current consumption from system current path I <sub>sys</sub>	8 mA	
Current consumption from output current path I <sub>out</sub>	20 mA + load	
General data		
Weight	86 g (3.03 oz)	
For additional general data, refer to the section <i>General Technical Data for I/O Modules</i> .		

**Overview of the Editable Parameter EP-2634**

Channel	Description	Options	Default
0 - 3	Substitute value OP-Mode	Sinking (0) / Sourcing (1)	Sourcing
0 - 3	Substitute value	Off (0) / On (1)	Off

**Diagnostic Data EP-2634**

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x0F
		1		
		2		
		3		
		4	Reserved	0
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	0
		4-7	Reserved	0
Channel type	4	0-6	Channel type	0x72
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	0
Number of channels	6		Number of similar channels per module	4
Channel error	7-10	0-31	Reserved	0
Channel 0 error to Channel 31 error	11 to 42	0-7	Reserved	0
Time stamp	43-46		Time stamp [μs] (32 bit)	


**Process Data Outputs EP-2634**

Byte	Format	Name	Remark
OB0	OX0.0	OP-mode DO0	0: Sinking, 1: Sourcing
	OX0.1	OP-mode DO1	0: Sinking, 1: Sourcing
	OX0.2	OP-mode DO2	0: Sinking, 1: Sourcing
	OX0.3	OP-mode DO3	0: Sinking, 1: Sourcing
	OX0.4	DO0	
	OX0.5	DO1	
	OX0.6	DO2	
	OX0.7	DO3	

## 5.10 Digital Output Module EP-2218



**Digital Output Module EP-2218**



**Connection Diagram EP-2218**


The EP-2218 digital output module can control up to 8 discrete outputs, each with a maximum of 0.5A. Discrete outputs can be connected to each connector in a 2-wire connection. A status LED is assigned to each channel. The outputs are supplied with power from the output current path ( $I_{OUT}$ ).



LED Indicators EP-2218

	Module Status	Green: Communication over the system bus Red: Module System Fault or Diagnostic Fault
1.1	Yellow: Output 0 active	
1.2	--	
1.3	Yellow: Output 1 active	
1.4	--	
2.1	Yellow: Output 2 active	
2.2	--	
2.3	Yellow: Output 3 active	
2.4	--	
3.1	Yellow: Output 4 active	
3.2	--	
3.3	Yellow: Output 5 active	
3.4	--	
4.1	Yellow: Output 6 active	
4.2	--	
4.3	Yellow: Output 7 active	
4.4	--	

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



Block Diagram EP-2218

**Specifications EP-2218**

System data		
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in the section <i>Order and Arrangement of the Modules.</i> )	
Interface	RSTi-EP I/O communication bus	
System bus transfer rate	48 Mbps	
Inputs		
Number	8	
Type of load	ohmic, inductive, lamp load	
Response time	low » high max. 100 µs; high » low max. 250 µs	
Max. output current	per channel	0.5 A
	per module	4 A
Breaking energy (inductive)	150 mJ per channel	
Switching frequency	Resistive load (min. 47 Ω)	1 kHz
	Inductive load (DC 13)	0.2 Hz without free-wheeling diode 1 kHz with suitable free-wheeling diode
	Lamp load (12 W)	1 kHz
Actuator connection	2-wire	
Short-circuit-proof	Yes	
Protective circuit	Constant current with thermal switch-off and automatic restart	
Response time of the current limiting circuit	< 100 µs	
Module diagnosis	Yes	
Individual channel diagnosis	No	
Reactionless	Yes	
Supply		
Supply voltage	20.4V – 28.8V	
Current consumption from system current path <i>I</i> <sub>sys</sub>	8 mA	
Current consumption from output current path <i>I</i> <sub>out</sub>	35 mA + load	
General data		
Weight	86 g (3.03 oz)	
For additional general data, refer to the section, <i>General Technical Data for I/O Modules.</i>		

**Overview of the Editable Parameter EP-2218**

Channel	Description	Options	Default
0 - 7	Substitute value	Off (0) / On (1)	Off (0)

## Diagnostic Data EP-2218

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x0F
		1		
		2		
		3		
		4	Reserved	0
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	0
		4-7	Reserved	0
Channel type	4	0-6	Channel type	0x72
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	0
Number of channels	6		Number of similar channels per module	8
Channel error	7-10	0-31	Reserved	0
Channel 0 error to Channel 31 error	11 to 42	0-7	Reserved	0
Time stamp	43-46		Time stamp [ $\mu$ s] (32 bit)	


Process Data Outputs EP-2218

Byte	Bit	Description
OB0	OX0.0	DO0
	OX0.1	DO1
	OX0.2	DO2
	OX0.3	DO3
	OX0.4	DO4
	OX0.5	DO5
	OX0.6	DO6
	OX0.7	DO7

## 5.11 Digital Output Module EP-225F



**Digital Output Module EP-225F**




**Connection Diagram EP-225F**

The EP-225F digital output module can control up to 16 discrete outputs, each with a maximum of 0.5 A. Four discrete outputs can be connected to each connector. A status LED is assigned to each channel. The outputs are supplied with power from the output current path ( $I_{OUT}$ ).

LED Indicators EP-225F

	Module Status	<b>Green:</b> Communication over the system bus <b>Red:</b> Module System Fault or Diagnostic Fault
	1.1	<b>Yellow:</b> Output 0 active
	1.2	<b>Yellow:</b> Output 1 active
	1.3	<b>Yellow:</b> Output 2 active
	1.4	<b>Yellow:</b> Output 3 active
	2.1	<b>Yellow:</b> Output 4 active
	2.2	<b>Yellow:</b> Output 5 active
	2.3	<b>Yellow:</b> Output 6 active
	2.4	<b>Yellow:</b> Output 7 active
	3.1	<b>Yellow:</b> Output 8 active
	3.2	<b>Yellow:</b> Output 9 active
	3.3	<b>Yellow:</b> Output 10 active
	3.4	<b>Yellow:</b> Output 11 active
	4.1	<b>Yellow:</b> Output 12 active
	4.2	<b>Yellow:</b> Output 13 active
	4.3	<b>Yellow:</b> Output 14 active
	4.4	<b>Yellow:</b> Output 15 active

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



Block Diagram EP-225F

## Technical Data EP-225F

System data		
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in the section, Order and Arrangement of the Modules)	
Interface	RSTi-EP I/O communication bus	
System bus transfer rate	48 Mbps	
Inputs		
Number	16	
Type of load	ohmic, inductive, lamp load	
Response time	low » high max. 100 µs; high » low max. 250 µs	
Max. output current	per channel	0.5 A
	per module	8 A
Breaking energy (inductive)	150 mJ per channel	
Switching frequency	Resistive load (min. 47 Ω)	1 kHz
	Inductive load (DC 13)	0.2 Hz without free-wheeling diode 1 kHz with suitable free-wheeling diode
	Lamp load (12 W)	1 kHz
Actuator connection	1-conductor	
Short-circuit-proof	Yes	
Protective circuit	Constant current with thermal switch-off and automatic restart	
Response time of the current limiting circuit	< 100 µs	
Module diagnosis	Yes	
Individual channel diagnosis	No	
Reactionless	Yes	
Supply		
Supply voltage	20.4V – 28.8V	
Current consumption from system current path <i>I</i> <sub>sys</sub>	8 mA	
Current consumption from output current path <i>I</i> <sub>out</sub>	25 mA + load	
General data		
Weight	83 g (2.93 oz)	
For additional general data, refer to the section, <i>General Technical Data for I/O Modules</i>		

## Diagnostic Data EP-225F

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x0F
		1		
		2		
		3		
		4	Reserved	0
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	0
		4-7	Reserved	0
Channel type	4	0-6	Channel type	0x72
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	0
Number of channels	6		Number of similar channels per module	0
Channel error	7-10	0-31	Reserved	0
Channel 0 error to Channel 31 error	11 to 42	0-7	Reserved	0
Time stamp	43-46		Time stamp [ $\mu$ s] (32 bit)	




*Process<sup>†</sup> Data Inputs EP-225F*

Byte	Bit	Description
OB0	OX0.0	DO0
	OX0.1	DO1
	OX0.2	DO2
	OX0.3	DO3
	OX0.4	DO4
	OX0.5	DO5
	OX0.6	DO6
	OX0.7	DO7
OB1	OX1.0	DO8
	OX1.1	DO9
	OX1.2	DO10
	OX1.3	DO11
	OX1.4	DO12
	OX1.5	DOI13
	OX1.6	DO14
	OX1.7	DO15
<sup>†</sup> Internal process data mapping with data format "Standard". Depending on the fieldbus specification and the data format of the communicating fieldbus components the bytes and/or words can be reversed during data transfer.		

## 5.12 Digital Output Module EP- 2814



**Digital Output Module EP-2814**




**Connection Diagram EP-2814**


The solid-state relay output module EP-2814 uses four semiconductor switches to control up to 4 discrete outputs, each with a maximum of 0.5 A at 255 V AC. The switching characteristics of the semiconductor switch have it as being closed when the voltage crosses zero and open when the current crosses zero. Each connector features a potential-free NO (Normally Open) contact.

For protection against extreme disturbance level, use surge protection terminals with varistor (refer to the connection diagram).

LED Indicators EP-2814

	Module Status	Green: Communication over the system bus Red: Module System Fault or Diagnostic Fault
	1.1	Yellow: Output 0 active
	1.2	--
	1.3	--
	1.4	--
	2.1	Yellow: Output 4 active
	2.2	--
	2.3	--
	2.4	--
	3.1	Yellow: Output 8 active
	3.2	--
	3.3	--
	3.4	--
	4.1	Yellow: Output 12 active
	4.2	--
	4.3	--
	4.4	--

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



**Specifications EP-2814**

System data		
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in the section, <i>Order and Arrangement of the Modules</i> )	
Interface	RSTi-EP I/O communication bus	
System bus transfer rate	48 Mbps	
Inputs		
Number	4	
Type	SSR / triac	
Switching characteristic	closing when the voltage crosses zero, opening when the current crosses zero	
Response time	10 ms	
Minimum switching current	per channel	50 mA
Maximum switching current	per channel	0.5 A
	per module	4 A
Holding current	25 mA	
Installation	external surge voltage protection circuit recommended for overvoltage category II and overvoltage category III	
Switching frequency	up to 20 Hz	
Actuator connection	1-conductor	
Short-circuit-proof	No	
Defined trip behavior of the prescribed external fuse	1 A super quick-acting	
Module diagnosis	Yes	
Individual channel diagnosis	No	
Maximum switching voltage	255 V AC, UL: 277 AC	
Reactionless	Yes	
Supply		
Supply voltage	20.4V – 28.8V	
Current consumption from system current path I <sub>sys</sub>	11 mA	
General data		
Weight	83 g (2.93 oz)	
For additional general data, refer to the section, <i>General Technical Data for I/O Modules</i>		

## Overview of the Editable Parameter EP-2814

Channel	Description	Options	Default
0 - 3	Substitute value	Off (0) / On (1)	Off (0)


## Diagnostic Data EP-2814

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x0F
		1		
		2		
		3		
		4	Reserved	0
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	0
		4-7	Reserved	0
Channel type	4	0-6	Channel type	0x72
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	0
Number of channels	6		Number of similar channels per module	4
Channel error	7-10	0-31	Reserved	0
Channel 0 error to Channel 31 error	11 to 42	0-7	Reserved	0
Time stamp	43-46		Time stamp [ $\mu$ s] (32 bit)	


*Process Data Inputs EP-2814*

Byte	Bit	Description
OB0	OX0.0	DO0
	OX0.1	DO1
	OX0.2	DO2
	OX0.3	DO3
	OX0.4	reserved
	OX0.5	reserved
	OX0.6	reserved
	OX0.7	reserved

### 5.13 Digital Output Module EP- 2714



**Digital Relay Output Module EP-2714**



**Connection Diagram EP-2714**

The digital relay output module EP-2714 can control up to 4 discrete outputs, each with a maximum of 6 A. Each connector features a potential-free changeover contact. The relay coils are supplied with power from the output current path ( $I_{OUT}$ ).




**Caution**

**When using relay modules EP-2714 in explosive atmosphere:**


- Condensation shall be avoided.
- If the switching voltage exceeds 63 V, a transient protection device shall be provided that limits the transients to a peak voltage of 500 V or less.

**LED Indicators EP-2714**


	Module Status	<b>Green:</b> Communication over the system bus <b>Red:</b> Module System Fault or Diagnostic Fault
	1.1	<b>Yellow:</b> Output 0 active
	1.2	--
	1.3	--
	1.4	--
	2.1	<b>Yellow:</b> Output 1 active
	2.2	--
	2.3	--
	2.4	--
	3.1	<b>Yellow:</b> Output 2 active
	3.2	--
	3.3	--
	3.4	--
	4.1	<b>Yellow:</b> Output 3 active
	4.2	--
	4.3	--
	4.4	--

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.





Derating Curve



Block Diagram EP-2714

**Specifications EP-2714**

System data		
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in <i>Section Order and Arrangement of the Modules</i> ).	
Interface	RSTi-EP I/O communication bus	
System bus transfer rate	48 Mbps	
Inputs		
Number	4	
Type	CO contact	
Material for power and data contacts	Ni-Au, 3 µm	
Response time	20 ms	
Maximum output current	per channel	5 A at 60°C (140 °F) / 6 A at 55°C (131 °F)
	per module	20 A at 60°C (140 °F) / 24 A at 55°C (131 °F)
Switching frequency	max. 5 Hz	
Short-circuit-proof	No	
Protective circuit	External fusing with 6 A prescribed	
Service life with AC-15 load and 1-A switching current	> 300.000 switching cycles	
Module diagnosis	Yes	
Individual channel diagnosis	No	
Maximum switching voltage	255 V AC, UL: 277 AC, DC corresponding to the derating curve	
Reactionless	Yes	
Supply		
Supply voltage	20.4V – 28.8V	
Current consumption from system current path I <sub>sys</sub>	8 mA	
Current consumption from output current path I <sub>out</sub>	20 mA	
General data		
Weight	83 g (2.93 oz)	
For additional general data, refer to the section <i>General Technical Data for I/O Modules</i> .		

**Overview of the Editable Parameter EP-2714**

Channel	Description	Options	Default
0 - 3	Substitute value	Off (0) / On (1)	Off (0)

## Diagnostic Data EP-2714

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x0F
		1		
		2		
		3		
		4	Reserved	0
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	0
		4-7	Reserved	0
Channel type	4	0-6	Channel type	0x72
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	0
Number of channels	6		Number of similar channels per module	4
Channel error	7-10	0-31	Reserved	0
Channel 0 error to Channel 31 error	11 to 42	0-7	Reserved	0
Time stamp	43-46		Time stamp [ $\mu$ s] (32 bit)	


*Process Data Inputs EP-2714*

Byte	Bit	Description
OB0	OX0.0	DO0
	OX0.1	DO1
	OX0.2	DO2
	OX0.3	DO3
	OX0.4	reserved
	OX0.5	reserved
	OX0.6	reserved
	OX0.7	reserved

## 5.14 Digital Output Module EP- 5111



Counter Module EP-5111



Connection Diagram EP-5111

In reference to the Connection Diagram:

**1** Track A

**2** Track B

**3** Cycle

**4** Direction 0/1 (24 V)

- One 32-bit counter (AB) invertible, 24 V DC
- Counting frequency 100 kHz max (AB 1/2/4-times sampling or pulse and direction)
- Latch value, comparison value, setting value, input filter (parametrizable)
- HW gate reset, digital output for comparison
- Alarm and diagnostic function with  $\mu$ s time stamp
- $\mu$ s time stamp for counting value (for example, for speed measurements)

The counter module EP-5111 can read one square-wave signal (1 channel) (for example, from an incremental encoder) with a maximum input frequency of 100 kHz. The 32-bit counter can count up or down within a predetermined range of values.


The counter can be controlled using software or externally through the latch, gate, and reset inputs. A digital output can be parameterized to be activated immediately upon either dropping below, meeting, or exceeding the set comparison value. An overrun time can be provided with the parameter *Pulse duration*. Thus the PLC will recognize even signals succeeding extremely fast.

In mode *Pulse and Direction*, channel CH0 A is used as the input and channel CH0 B as a direction-determining input. In incremental mode, an *incremental* encoder with track A and B can be connected. A status LED is assigned to each channel. The module electronics supply the connected sensors with power from the input current path ( $I_{IN}$ ).

**LED Indicators EP-5111**

	Module Status	<b>Green:</b> Communication over the system bus <b>Red:</b> Module System Fault or Diagnostic Fault
	1.1	<b>Yellow:</b> A/pulse controlled
	1.2	--
	1.3	--
	1.4	<b>Yellow:</b> B/direction controlled
	2.1	<b>Yellow:</b> output set
	2.2	--
	2.3	--
	2.4	<b>Yellow:</b> reset input controlled
	3.1	<b>Yellow:</b> latch input controlled
	3.2	--
	3.3	--
	3.4	<b>Yellow:</b> gate input (HW gate) controlled

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



**Specifications EP-5111**

<b>System data</b>	
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in <i>Section Order and Arrangement of the Modules</i> ).
Interface	RSTi-EP I/O communication bus
System bus transfer rate	48 Mbps
Galvanic isolation	500 V DC between the current paths
<b>Inputs</b>	
Number of counter inputs	1
Type	Incremental encoders and other input characteristics for sensor types 1 and 3 are in accordance with EN 61131-2
Input filter	Filter time adjustable from 0,01 to 1 ms
Low input voltage	< 5 V
High input voltage	> 11 V
Max. input current per channel	3.5 mA
Sensor supply	Yes
Sensor connection	2- and 3-wire
Reverse polarity protection	Yes
Module diagnosis	Yes
Individual channel diagnosis	Yes
Counter width	32 bits
Maximum input frequency	100 kHz
Latch, gate, reset input	Yes
Mode of operation	Pulse and direction / AB mode with 1-, 2-, 4-times sampling
<b>Status, alarm, diagnostics</b>	
Status indicator	Yes
Process alarm	Yes, parametrizable
Diagnostic alarm	Yes
<b>Outputs</b>	
Number	1
Output current	0.5 A
Reverse polarity protection	Yes
Module diagnosis	Yes
Individual channel diagnosis	Yes
<b>Supply</b>	
Supply voltage	20.4V – 28.8V
Current consumption from system current path $I_{SYS}$	8 mA
Current consumption from input current path $I_{IN}$	35 mA (plus output current for the digital output)



General data	
Weight	83 g (2.93 oz)
For additional general data, refer to the section <i>General Technical Data for I/O Modules</i> .	

**Overview of the Editable Parameter EP-5111**

Channel	Description	Options	Default
	Diagnostic alarm	disabled (0) / enabled (1)	disabled
0	Filter time signal A	0,01 ms [100 kHz] (0) / 0,017 ms [50 kHz] (1) / 0,033 ms [30 kHz] (2) / 0,1 ms [10 kHz] (3) / 0,2 ms [5 kHz] (4) / 0,5 ms [2 kHz] (5) / 1 ms [1 kHz] (6)	0,01 ms
0	Filter time signal B	0,01 ms [100 kHz] (0) / 0,017 ms [50 kHz] (1) / 0,033 ms [30 kHz] (2) / 0,1 ms [10 kHz] (3) / 0,2 ms [5 kHz] (4) / 0,5 ms [2 kHz] (5) / 1 ms [1 kHz] (6)	0,01 ms
0	Filter time latch	0,01 ms (0) / 0,017 ms (1) / 0,033 ms (2) / 0,1 ms (3) / 0,2 ms (4) / 0,5 ms (5) / 1 ms (6)	0,01 ms
0	Filter time gate	0,01 ms (0) / 0,017 ms (1) / 0,033 ms (2) / 0,1 ms (3) / 0,2 ms (4) / 0,5 ms (5) / 1 ms (6)	0,01 ms
0	Filter time reset	0,01 ms (0) / 0,017 ms (1) / 0,033 ms (2) / 0,1 ms (3) / 0,2 ms (4) / 0,5 ms (5) / 1 ms (6)	0,01 ms
0	Process alarm HW gate open	disabled (0) / enabled (1)	disabled
0	Process alarm HW gate closed	disabled (0) / enabled (1)	disabled
0	Process alarm overflow	disabled (0) / enabled (1)	disabled
0	Process alarm underflow	disabled (0) / enabled (1)	disabled
0	Process alarm comp. value	disabled (0) / enabled (1)	disabled
0	Process alarm end value	disabled (0) / enabled (1)	disabled
0	Process alarm latch value	disabled (0) / enabled (1)	disabled
0	Counting mode	count endless (0) / once - forward (1) / once - backwards (2) / once - no main direction (3) / periodic - forward (4) / periodic - backwards (5) / periodic - no main direction (6)	count endless
0	Condition for DO	disabled (0) / higher equal comparison value (1) / lower equal comparison value (2) / equal comparison value (3)	disabled
0	Counter dir. signal B inv.	disabled (0) / enabled (1)	disabled
0	Reset	disabled (0) / high level (1) / rising edge 0-1 (2) / rising edge once 0-1 (3)	
0	Signal mode	Rotary transducer - single (0) / Rotary transducer - double (1) / Rotary transducer - quadruple (2) / Pulse and Direction (3) / disabled (4)	disabled
0	HW gate	disabled (0) / enabled (1)	disabled
0	Counter behavior internal gate	Interrupt counting (0) / Cancel counting (1)	interrupt counting
0	End value	-2147483648 to 2147483647	2147483647
0	Load value	-2147483648 to 2147483647	0
0	Hysteresis	0 to 255	0

0	Pulse duration	0 to 255 [Input value x 2 = output time; corresponds to 0 ... 510 ms]	0
---	----------------	---	---

**Note:** The parameter setting in the network adapter for the **Behavior of outputs on fieldbus error** affects the control word and thus the behavior of the EP-5111:

- The **Hold last value** setting

The output continues working or switches as parametrized respectively.

The counter continues to count during the error. Once normal operating conditions have been restored, the counter continues to count starting at the previous value.

- The **Enable substitute value** setting

The output is switched off.

The counter value is frozen. Once normal operating conditions have been restored, the counter value is reset to the parameterised load value.

- The **All outputs off** setting

The output is switched off. The counter behaves in the same way as for Hold last value.

#### Diagnostic Data EP-5111

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	
		4	External auxiliary supply error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x08
		1		
		2		
		3		
		4	Channel information available	1
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	
		4	Reserved	0
		5	Reserved	0
		6	Process alarm lost	
		7	Reserved	0
Channel type	4	0-6	Channel type	0x76

		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	8
Number of channels	6		Number of similar channels per module	1
Channel error	7	0	Error at channel 0	
		1-7	Reserved	0
Channel 0 error	11	0	Hardware gate opened	
		1	Hardware gate closed	
		2	Overflow/underflow/end value	
		3	Comparison value reached	
		4	Latch value saved	
		5-7	Reserved	0
Channel 1 error to Channel 31 error	12 to 42	0-7	Reserved	0
Time stamp	43-46		Time stamp [ $\mu$ s] (32 bit)	

**Process Data<sup>†</sup> Inputs EP-5111**

Byte	Format	Name	Bit	Function when active	Remark
IB0 ... IB3	Double word	Counter value			current count value
IB4 ... IB7	Double word	Latch value			Count value image at the point of edge 0-1 at latch input
IB8	Word	Counter status	IX8.0	Reset was active	remains until reset mode is disabled
			IX8.1	DO released	
			IX8.2	SW gate active	
			IX8.3	Reset input active	depending only of the parameter <i>reset</i> but not of the reset mode
			IX8.4	HW gate active	
			IX8.5	internal gate active	
			IX8.6	DO set	
			IX8.7	Counter direction down	
IB9			IX9.0	Counter direction up	
			IX9.1	Comparison condition met	remains until reset of the status bits
			IX9.2	End value reached	remains until reset of the status bits
			IX9.3	Overflow performed	remains until reset of the status bits
			IX9.4	Underflow performed	remains until reset of the status bits
			IX9.5	Zero crossing performed	remains until reset of the status bits
			IX9.6	Latch input active	
			IX9.7	reserved	
IB10	Word	Time stamp			

IB11					0 ... 65535 µs rotating, updated when counter value changes
† Internal process data mapping with data format <i>Standard</i> . Depending on the fieldbus specification and the data format of the communicating fieldbus components the bytes and/or words can be reversed during data transfer.					

**Process Data† Outputs EP-5111**

Byte	Format	Name	Bit	Function when edge 0-1	Remark
QB0 ... QB3	Double word	Comparison value			depending on parametrization for triggering of process alarm or setting the DO, as soon as the condition is met
QB4 ... QB7	Double word	Set value			this value is copied into counter value in the event of edge 0-1 at bit 5 of the control word
QB8	Word	Counter word	QX8.0	Activate reset mode	
			QX8.1	Release DO	
			QX8.2	Set SW gate	
			QX8.3 - 84	reserved	
			QX8.5	Load set value	loads set value into counter value
			QX8.6	Reset status bits	counter status bits 9.1 - 9.5
			QX8.7	reserved	
			QX9.0	Deactivate reset mode	
QB9			QX9.1	Block DO	
			QX9.2	Reset SW gate	
			QX9.3 - 9.7	reserved	

† Internal process data mapping with data format *Standard*. Depending on the fieldbus specification and the data format of the communicating fieldbus components the bytes and/or words can be reversed during data transfer.

**Process Alarm Data EP-5111**

Byte	Bit	Function
B0	X0.0	HW gate activated
	X0.1	HW gate deactivated
	X0.2	Overflow, underflow or end value reached
	X0.3	Comparison value reached
	X0.4	Latch value reached
	X0.5 - X0.7	reserved
B1	X1.0	Status input channel 0 A (track A)
	X1.1	Status input channel 0 B (track B)
	X1.2	Status input "Latch"
	X1.3	Status input "Gate"
	X1.4	Status input "Reset"
	X1.5- X1.7	reserved
B2		16 bit time stamp 0 ... 65535µs, rotating
B3		

### 5.14.1 Setting Up the Counter

To start a counting process at least the signal mode needs to be parameterised and a rising flank at the bit QX8.2 ("Set SW gate") of the control word is required.

You can define the counter functions by parameterizing: the counting mode, a primary direction (counting up or down), the counting behavior, and the hardware gate's function (input *gate*). In addition, you can parameterise output setting options (comparison function, hysteresis) as well as producing a process alarm (refer to the section, *Additional Functions Features*).

#### Counting Range, Count Limits

The maximum count limits are predetermined by the register size and cannot be changed.

**Maximum Counting Range**

Limit	Value
Lower count limit	-2 147 483 648 ( $-2^{31}$ )
Upper count limit	+2 147 483 647 ( $2^{31} - 1$ )

### 5.14.2 Counter Functions

#### Counting Mode

Depending on the application you can chose the counting mode:

- Endless counting, for example, for position detection with a rotary encoder
- 1-time counting with or without primary direction, for example, for counting products up to a maximum limit
- Periodic counting with or without primary direction, for example, repeated identical pick-and-place operations

For both counting modes *1-time counting* and *periodic counting* you can parameterize the counting range with load value and end value.

Via bit QX8.5 of the control word you can load a set value into the counting value. You can define the set value in the second double word of the process data outputs.

#### Counting Direction

##### No primary direction

The entire counting range is available when using a counting mode without primary direction.

##### Primary Direction Up

The counting range is limited at the top by a parameterized end value. Starting from 0, a set value or a parameterized load value, the counter counts until the end value -1 and is reset to the load value with the next encoder pulse.

##### Primary Direction Down

The counting range is limited at the bottom by a parameterized end value. Starting from 0, a set value or a parameterized load value, the counter counts until the end value +1 and is reset to the load value with the next encoder input.

#### Gate Function: Activate / Deactivate Counter

The counter is activated and deactivated using an internal gate. If the hardware gate (HW gate) is deactivated in the parameters, the internal gate is identical to the software gate (SW gate).


With activated hardware gate, there is a logic AND connection of SW gate and HW gate, so that the gate functions operate exclusively on the HW gate. In this case, opening and closing of the SW gate has an interrupting effect only.

The software gate is activated using a 0-1 edge at the bit *Set SW gate* in the control word and deactivated with a 0-1 edge at the bit *Reset SW gate* in the control word (refer to the table *Process Data Outputs*).

### Counting Behavior: Cancel/Interrupt Counting

You can parameterize the counting behavior after a new gate start: Using *Interrupt counting*, the counter continues from the last counting value. Using *Cancel counting*, counting starts again from the load value.


### Endless Counting




*Continuous Counting*

- Counting starts at the load value, the entire counting range is used.
- If the upper count limit is reached during up-counting, an additional counting pulse in the positive direction leads to a jump to the lower count limit. Counting continues from there.
- If the lower count limit is reached during down-counting, an additional counting pulse in the negative direction leads to a jump to the upper count limit. Counting continues from there.
- Upon exceeding the upper or lower counting limit, the status bit *Overflow performed* or *Underflow performed* is set and a process alarm is triggered if it is parameterized. The status bits remain set until they are reset with the bit "Reset status bits" in the control word.

## 1-time Counting/ No primary Direction




1-time Counting, Interrupted Counting



1-time Counting, Cancelled Counting

- Counting (up and down) starts at the load value, the entire counting range is used.
- Upon exceeding the upper or lower count limit, the counter jumps to the other count limit respectively. The internal gate is automatically closed, the status bit *Overflow performed* or *Underflow performed* is set and a process alarm will be triggered if it is parameterised.
- To restart counting, the internal gate must be reopened. Depending on the parameters set, counting continues from the current counting value (*Interrupt counting*) or it starts again from the load value (*Cancel counting*).

### 1-time Counting / Primary Direction Up




**1-time Counting, Primary Direction Up**

- Up-counting starts at the load value.
- If the parametrised end value -1 is reached during counting in the positive direction, the counter jumps back to the load value at the next positive count pulse. The internal gate is automatically closed, the status bit *End value reached* is set and a process alarm will be triggered if it is parameterized.
- To restart counting, the internal gate must be reopened. Counting starts again at the load value.
- Upon reaching the lower count limit the counter jumps to the upper count limit to continue counting from there. The status bit *Underflow performed* is set and a process alarm will be triggered if it is parameterised. All status bits remain set until they are reset with the bit *Reset status bits* in the control word.

**Counting Range**

Limits	Valid range of values
End value	-2 147 483 647 ( $-2^{31} + 1$ ) to +2 147 483 647 ( $2^{31} - 1$ )
Upper count limit	+2 147 483 648 ( $2^{31}$ )

### 1-time Counting/ Primary Direction Down



**1-time Counting, Primary Direction Down**




- Down-counting starts at the load value.
- If the parameterized end value +1 is reached during counting in the negative direction, the counter jumps back to the load value at the next count pulse. The internal gate is automatically closed, the status bit *End value reached* is set and a process alarm will be triggered if it is parameterised.
- To restart counting, the internal gate must be reopened. Counting starts again at the load value.
- Upon reaching the upper count limit the counter jumps to the lower count limit to continue counting from there. The status bit *Overflow performed* is set and a process alarm will be triggered if it is parameterised. All status bits remain set until they are reset with the bit *Reset status bits* in the control word.

#### Counting Range

Limits	Valid range of values
End value	-2 147 483 648 ( $-2^{31}$ ) to +2 147 483 647 ( $2^{31} - 2$ )
Upper count limit	+2 147 483 647 ( $2^{31} - 1$ )


#### Periodic Counting/ No Primary Direction



#### Periodic Counting, No Primary Direction

- Counting (up or down) starts at the load value, the entire counting range is used.
- Upon reaching a count limit, the counter jumps to the load value and starts counting again from there. The status bit *Overflow performed* or *Underflow performed* is set and a process alarm will be triggered if it is parameterized. All status bits remain set until they are reset with the bit *Reset status bits* in the control word.

### Periodic Counting/ Primary Counting Direction Up




**Periodic Counting, Primary Counting Direction Up**

- Up-counting starts at the load value.
- If the parameterized end value -1 is reached during counting in the positive direction, the counter jumps back to the load value at the next positive count pulse and continues counting from there. The status bit *End value reached* is set and a process alarm will be triggered if it is parameterized.
- Upon reaching the lower count limit the counter jumps to the upper count limit to continue counting from there. The status bit *Underflow performed* is set and a process alarm will be triggered if it is parameterized. All status bits remain set until they are reset with the bit *Reset status bits* in the control word.

#### Counting Range

Limits	Valid range of values
End value	$-2\,147\,483\,647 (-2^{31} + 1)$ to $+2\,147\,483\,647 (2^{31} - 1)$
Lower count limit	$+2\,147\,483\,648 (2^{31})$

### Periodic Counting/ Primary Direction Down



*Periodic Counting, Primary Counting Direction Down*

- Down-counting starts at the load value.
- If the parametrized end value +1 is reached during counting in the negative direction, the counter jumps back to the load value at the next count pulse and continues counting from there. The status bit *Endvalue reached* is set and a process alarm will be triggered if it is parameterised.
- Upon reaching the upper count limit the counter jumps to the lower count limit to continue counting from there. The status bit *Overflow performed* is set and a process alarm will be triggered if it is parameterized. All status bits remain set until they are reset with the bit *Reset status bits* in the control word.


#### Counting Range

Limits	Valid range of values
End value	-2 147 483 647 ( $-2^{31}$ ) to +2 147 483 646 ( $2^{31} - 2$ )
Upper count limit	+2 147 483 648 ( $2^{31} - 1$ )

### 5.14.3 Additional Functions Features

You can define the additional features for the counter listed below by parameterising or via the process data outputs:

- Reset: resets the counting value to the load value during counting.
- Latch function: stores the current counting value in the latch register.
- Comparator: Upon meeting the comparison condition, the digital output is activated or a process alarm is triggered.
- Hysteresis: reduces frequent switching of the output and/ or excessive triggering of process alarms, e.g. when the value of a sensor signal fluctuates around the comparison value. The figure illustrates how counting behavior is affected by the additional features. These additional features are explained in the following pages.



*Additional Counter Functions*

#### Reset

The load value will be load into the counting value once there is a signal at the reset input. To use this feature you have to release the reset mode in the control word (bit QX8.0) in addition to the parameterization.

The status bit IX8.3 indicates that there is a signal at the reset input. Once a reset is done, the status bit IX8.0 is set. This bit will be reset by deactivating the reset mode (control bit QX9.0).

#### Latch Function

If a 0-1 edge appears at the *latch* input during a counting process, the current counter value is stored in the latch register. The latch register is accessed through the process data inputs. With every activation of the counter the latch value is set to 0.

### Comparison Function

Via the parameter *Condition for DO* you can deactivate the output (*never switching*) or define a comparison condition for the output's switching:

- Counter value higher or equal comparison value
- Counter value lower or equal comparison value
- Counter value equal comparison value

To use the comparison function, you have to preset the comparison value in the first double word of the process data outputs and release the digital output via the control word (bit QX8.1).

The bit IX9.1 *Comparison condition met* of the status word is activated as soon as the comparison condition is met. The output switches and remains set as long as the comparison condition is met accordingly to the parameterized hysteresis and pulse duration.

When using *Counter value equal comparison value* the output remains set during the pulse duration parameterized. With pulse duration = 0, the output remains set until the comparison condition is not met any more. When using a counting mode with primary direction, the output will be switched only upon reaching the comparison value from the primary direction.

### Pulse duration

Via the parameter *Pulse duration* you can determine how long the digital output should remain set. The pulse duration can be preselected between 0 and 510 ms with an inaccuracy of less than 2.048 ms. With pulse duration = 0 the output behaves exclusively according to the comparison conditions. If the comparison value is left during a pulse output and is reached again, there is no post-triggering of the pulse duration.

**Note:** The bit *Comparison condition met* is activated together with the bit *DO set* of the status word. In contrast to the *DO set* bit it remains active until it is reset with the bit *Reset status bits* of the control word.

### Hysteresis


It is possible to reduce frequent switching of the output and/ or triggering of a process alarm, e.g. if the value of a sensor signal fluctuates around the comparison value, by setting the hysteresis. Thereby you define a range above and below a reference value (zero crossing, overflow/underflow or comparison value), within which the output will not be reset.

A limit value between 0 and 255 can be parameterised for the hysteresis. With hysteresis = 3 for example, all values differing less than 3 from the reference value are smoothed. Hysteresis is deactivated with the values 0 and 1.

The hysteresis is activated upon reaching the comparison condition. The comparison result remains unchanged during active hysteresis until the counting value reaches the predetermined hysteresis limit. After leaving the hysteresis range, hysteresis is reactivated only upon reaching the comparison condition again.


After changing the hysteresis value, an active hysteresis remains active. The new hysteresis value is activated during the next hysteresis event.

The behavior of the output for hysteresis = 0 (hysteresis deactivated) and hysteresis = 3 is shown in the following diagrams (legends describe the behavior for hysteresis = 3):




**Operating Principle of the Hysteresis when Counter Value  $\geq$  Comparison Value, Pulse Duration 0**

- 1 Comparison condition met  $\rightarrow$  output is set and hysteresis activated
- 2 Comparison condition not met, leaving the hysteresis range  $\rightarrow$  output is reset
- 3 Comparison condition met  $\rightarrow$  output is set and hysteresis activated
- 4 Leaving the hysteresis range, the output remains set because the comparison condition is still met
- 5 Comparison condition no longer met but hysteresis still active  $\rightarrow$  output remains set
- 6 Comparison condition met, hysteresis still active  $\rightarrow$  output remains set
- 7 Leaving the hysteresis range and comparison condition met  $\rightarrow$  output remains set



**Operating Principle of the Hysteresis when Counter Value = Comparison Value, Pulse Duration 0**


- 1 Comparison condition met  $\rightarrow$  output is set and hysteresis activated
- 2 Comparison condition not met, leaving the hysteresis range  $\rightarrow$  output is reset
- 3 Comparison condition met  $\rightarrow$  output is set and hysteresis activated
- 4 Leaving the hysteresis range and comparison condition not met  $\rightarrow$  output is reset
- 5 Comparison condition met  $\rightarrow$  output is set and hysteresis activated
- 6 Comparison condition met and hysteresis active  $\rightarrow$  output remains set
- 7 Leaving the hysteresis range and comparison condition no longer met  $\rightarrow$  output is reset



**Operating Principle of the Hysteresis when Counter Value = Comparison Value, Pulse Duration 2**

- 1 Comparison condition met → pulse of the parameterised duration is output, hysteresis activated
- 2 Leaving the hysteresis range → hysteresis deactivated
- 3 Comparison condition met → pulse of the parameterised duration is output, hysteresis activated
- 4 Leaving the hysteresis range → hysteresis deactivated
- 5 Comparison condition met → pulse of the parameterised duration is output, hysteresis activated
- 6 Comparison condition met and hysteresis active → no pulse
- 7 Comparison condition not met, leaving the hysteresis range → hysteresis deactivated


EP-5111 Counter operation through parameter\signal evaluation\rotary transducer xxx



\* see overview of the editable parameter



EP-5111 Counter operation through parameter\signal evaluation\pulse/direction (A/B)




\* see overview of the editable parameter

## 5.15 Digital Counter Module EP- 5112



**Digital Counter Module EP-5112**




**Connection Diagram EP-5112**

The digital counter module EP-5112 can read square-wave signals (for example, from an incremental encoder) with a maximum input frequency of 100 kHz. Depending on the operating mode, both 32-bit counters can count up or down independent of each other in a preset range of values. The counters can be controlled via software by setting the appropriate control word.

In mode Pulse and Direction, channel CH0 A and CH1 A respectively is used as the input, channel CH0 B and CH1 B respectively is used as a direction-determining input. In incremental mode, an incremental encoder with track A and B can be connected. A status LED is assigned to each channel. The module electronics supply the connected sensors with power from the input current path ( $I_{IN}$ ).

- Two 32-bit counters (AB), invertible, 24 V DC
- Counting frequency 100 kHz max (AB 1/2/4-times sampling or pulse and direction)
- Comparison value, setting value, input filter (parametrizable)
- Alarm and diagnostic function with  $\mu$ s time stamp
- $\mu$ s time stamp for value counting (for example, for speed measurements)

	<b>Module Status</b>	<b>Green:</b> Communication over the system bus <b>Red:</b> Module System Fault or Diagnostic Fault
	1.1	<b>Yellow:</b> CH0 A pulse controlled
	1.2	--
	1.3	--
	1.4	<b>Yellow:</b> CH0 B direction controlled
	2.1	
	2.2	
	2.3	
	2.4	
	3.1	<b>Yellow:</b> CH1 A pulse controlled
	3.2	--
	3.3	--
	3.4	<b>Yellow:</b> CH1 B direction controlled
	4.1	
	4.2	
	4.3	
	4.4	



**Specifications EP-5112**

<b>System data</b>	
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in the section, <i>Order and Arrangement of the Modules</i> ).
Interface	RSTi-EP I/O communication bus
System bus transfer rate	48 Mbps
Galvanic isolation	500 V DC between the current paths
<b>Inputs</b>	
Number of counter inputs	2
Type	Incremental encoder
Input filter	Filter time adjustable from 0,01 to 1 ms
Low input voltage	< 5 V
High input voltage	> 11 V
Max. input current per channel	3.5 mA
Sensor supply	Yes
Sensor connection	2- and 3-wire
Reverse polarity protection	Yes
Module diagnosis	Yes
Individual channel diagnosis	Yes
Counter width	32 bits
Maximum input frequency	100 kHz
Latch, gate, reset input	Yes
Mode of operation	Pulse and direction / AB mode with 1-, 2-, 4-times sampling
<b>Status, alarm, diagnostics</b>	
Status indicator	Yes
Process alarm	Yes, parametrizable
Diagnostic alarm	Yes
<b>Supply</b>	
Supply voltage	20.4V – 28.8V
Current consumption from system current path $I_{SYS}$	8 mA
Current consumption from input current path $I_{IN}$	35 mA
<b>General data</b>	
Weight	72 g (2.54 oz)
For additional general data, refer to the section <i>General Technical Data for I/O Modules</i> .	

## Overview of the Editable Parameter EP-5112

Channel	Description	Options (!)	Default
	Diagnostic alarm	disabled (0) / enabled (1)	disabled
0 ... 1	Filter time signal A	0,01 ms [100 kHz] (0) / 0,017 ms [50 kHz] (1) / 0,033 ms [30 kHz] (2) / 0,1 ms [10 kHz] (3) / 0,2 ms [5 kHz] (4) / 0,5 ms [2 kHz] (5) / 1 ms [1 kHz] (6)	0,01 ms
0 ... 1	Filter time signal B	0,01 ms [100 kHz] (0) / 0,017 ms [50 kHz] (1) / 0,033 ms [30 kHz] (2) / 0,1 ms [10 kHz] (3) / 0,2 ms [5 kHz] (4) / 0,5 ms [2 kHz] (5) / 1 ms [1 kHz] (6)	0,01 ms
0 ... 1	Process alarm overflow	disabled (0) / enabled (1)	disabled
0 ... 1	Process alarm underflow	disabled (0) / enabled (1)	disabled
0 ... 1	Process alarm comp. value	disabled (0) / enabled (1)	disabled
0 ... 1	Process alarm end value	disabled (0) / enabled (1)	disabled
0 ... 1	Counting mode	count endless (0) / once - forward (1) / once - backwards (2) / once - no main direction (3) / periodic - forward (4) / periodic - backwards (5) / periodic - no main direction (6)	count endless
0 ... 1	Comparison function	disabled (0) / higher equal comparison value (1) / lower equal comparison value (2) / equal comparison value (3)	disabled
0 ... 1	Counter dir. signal B inv.	disabled (0) / enabled (1)	disabled
0 ... 1	Signal mode	Rotary transducer - single (0) / Rotary transducer - double (1) / Rotary transducer - quadruple (2) / Pulse and Direction (3) / disabled (4)	disabled
0 ... 1	Counter behavior internal gate	Interrupt counting (0) / Cancel counting (1)	interrupt counting
0 ... 1	Setting value	-2147483648 to 2147483647	0
0 ... 1	End value	-2147483648 to 2147483647	2147483647
0 ... 1	Load value	-2147483648 to 2147483647	0
0 ... 1	Hysteresis	0 to 255	0

**Note:** The parameter setting in the network adapter for the Behaviour of outputs on fieldbus error affects the control word and thus the behavior of the EP-5112:

- The Hold last value setting - The counter continues to count during the error. Once normal operating conditions have been restored, the counter continues to count starting at the previous value.
- The Enable substitute value setting - The counter value is frozen. Once normal operating conditions have been restored, the counter value is reset to the parameterised load value.
- All outputs off setting - The counter behaves in the same way as for Hold last value.

## Diagnostic Data EP-5112

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	
		4	External auxiliary supply error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x08
		1		
		2		
		3		
		4	Channel information available	1
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	
		4	Reserved	0
		5	Reserved	0
		6	Process alarm lost	
		7	Reserved	0
Channel type	7	0-6	Channel type	0x76
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	8
Number of channels	6		Number of similar channels per module	2
Channel error	7	0	Error at channel 0	
		1	Error at channel group 1	
		2-7	Reserved	0
Channel error	8	8 – 15	Reserved	0
Channel error	9	16 – 23	Reserved	0
Channel error	10	24 – 31	Reserved	0
Channel 0 error	11	0-1	Reserved	0
		2	Overflow/underflow/end value	
		3	Comparison value reached	
		4-7	Reserved	0
Channel 2 error to Channel 31 error	13 to 42	0-7	Reserve,d	0
Time stamp	43-46		Time stamp [ $\mu$ s] (32 bit)	

**Process Data<sup>†</sup> Inputs EP-5112**

Byte	Format	Name	Bit	Function when active	Remark
IB0 ... IB3	Double word	Counter 0: Counter value			Counter 0: current count value
IB4 ... IB7	Double word	Counter 1: Counter value			Counter 1: current count value
IB8	Word	Counter 0: Counter status	IX8.0	Reserved	
			IX8.1	Comparison bit released	
			IX8.2	SW gate active	
			IX8.3-8.4	Reserved	
			IX8.5	Internal gate active	
			IX8.6	Comparison bit active	
			IX8.7	Counter direction down	
IB9			IX9.0	Counter direction up	
			IX9.1	Comparison condition met	
			IX9.2	End value reached	
			IX9.3	Overflow performed	
			IX9.4	Underflow performed	
			IX9.5	Zero crossing performed	
			IX9.6-9.7	Reserved	
IB10	Word	Counter 1: Counter status	IX10.0	Reserved	
			IX10.1	Comparison bit released	
			IX10.2	SW gate active	
			IX10.3 - 10.4	Reserved	
			IX10.5	Internal gate active	
			IX10.6	Comparison bit active	
			IX10.7	Counter direction down	
IB11			IX11.0	Counter direction up	
			IX11.1	Comparison condition met	
			IX11.2	End value reached	
			IX11.3	Overflow performed	
			IX11.4	Underflow performed	
			IX11.5	Zero crossing performed	
			IX11.6 - 11.7	Reserved	

<sup>†</sup> Internal process data mapping with data format *Standard*. Depending on the fieldbus specification and the data format of the communicating fieldbus components the bytes and/or words can be reversed during data transfer.

**Process Data<sup>†</sup> Outputs EP-5112**

Byte	Format	Name	Bit	Function when edge 0-1	Remark
QB0 ... QB3	Double word	Counter 0: Comparison value			
QB4 ... QB7	Double word	Counter 1: Comparison value			
QB8	Word	Counter 0: Control word	QX8.0	Reserved	
			QX8.1	Release comparison bit	
			QX8.2	Set SW gate	
			QX8.3-8.4	Reserved	
			QX8.5	Load set value	Loads set value into counter value
			QX8.6	Reset status bits	Counter 0: status bits 9.1 - 9.5
			QX8.7-9.0	Reserved	
QB9			QX9.1	Deactivate comparison bit	
			QX9.2	Reset SW gate	
			QX9.3-Q9.7	Reserved	
QB10	Word	Counter 1: Control word	QX10.0	Reserved	
			QX10.1	Release comparison bit	
			QX10.2	Set SW gate	
			QX10.3 - 10.4	Reserved	
			QX10.5	Load set value	loads set value into counter value
			QX10.6	Reset status bits	Counter 1: status bits 11.1 - 11.5
QB11			QX10.7 - 11.0	Reserved	
			QX11.1	Deactivate comparison bit	
			QX11.2	Reset SW gate	
			QX11.3 - 11.7	Reserved	

<sup>†</sup> Internal process data mapping with data format "Standard". Depending on the fieldbus specification and the data format of the communicating fieldbus components the bytes and/or words can be reversed during data transfer.



### 5.15.1 Setting Up the Counter

To start a counting process at least the signal mode needs to be parameterized and a rising flank at the bit QX8.2 or QX10.2 respectively (*Set SW gate*) of the control word is required.

You can define the counter functions by parameterizing: the counting mode, a primary direction (counting up or down), and the counting behaviour. In addition you can parameterize options for setting a comparison bit (conditions, hysteresis) as well as producing a process alarm (refer to the section section, *Additional Counter Features*).

#### Counting Range, count Limits

The maximum count limits are predetermined by the register size and cannot be changed.

**Counting Range**

Limits	Valid range of values
Lower count limit	-2 147 483 648 ( $-2^{31}$ )
Upper count limit	+2 147 483 647 ( $2^{31} - 1$ )

### 5.15.2 Counter Functions

#### Counting Mode

Depending on the application you can chose the counting mode:

- Endless counting, e.g. for detecting the position with a rotary encoder
- 1-time counting with or without primary direction, e.g. for counting products up to a maximum limit
- Periodic counting with or without primary direction, e.g. repeated identical pick-and-place operations

For both counting modes *1-time counting* and *periodic counting* you can parameterize the counting range with load value and end value.

Via bit QX8.5 or QX10.5 respectively of the control word you can load a set value into the counting value. You can define the set value in the module parameters.

#### Counting Direction

##### No Primary Direction

The entire counting range is available when using a counting mode without primary direction.

##### Primary Direction Up

The counting range is limited at the top by a parameterized end value. Starting from 0, a set value or a parameterized load value, the counter counts until the end value -1 and is reset to the load value with the next encoder pulse.

##### Primary Direction Down

The counting range is limited at the bottom by a parameterized end value. Starting from 0, a set value or a parameterized load value, the counter counts until the end value +1 and is reset to the load value with the next encoder pulse.


#### Gate Function Activate / deactivate Counter

The counter is activated and deactivated using an internal gate. The internal gate is identical to the software gate (*SW gate*), it is activated using a 0-1 edge at the bit *Set SW gate* in the control word and deactivated with a 0-1 edge at the bit *Reset SW gate* in the control word (see table *Process data outputs*).

### Counting Behavior: Interrupt/ Cancel Counting

You can parameterise the counting behaviour after a new gate start: Using “Interrupt counting”, the counter continues from the last counting value. Using “Cancel counting”, counting starts again from the load value.


### Endless Counting




Continuous Counting

- Counting starts at the load value, the entire counting range is used.
- If the upper count limit is reached during up-counting, an additional counting pulse in the positive direction leads to a jump to the lower count limit. Counting continues from there.
- If the lower count limit is reached during down-counting, an additional counting pulse in the negative direction leads to a jump to the upper count limit. Counting continues from there.
- Upon exceeding the upper or lower counting limit, the status bit *Overflow performed* or *Underflow performed* is set and a process alarm is triggered if it is parameterized. The status bits remain set until they are reset with the bit *Reset status bits* in the control word.

### One-time Counting/ No Primary Direction




### 1-time Counting, Interrupted Counting



### 1-time Counting, Cancelled Counting

- Counting (up and down) starts at the load value, the entire counting range is used.
- Upon exceeding the upper or lower count limit, the counter jumps to the other count limit respectively. The internal gate is automatically closed, the status bit *Overflow performed* or *Underflow performed* is set and a process alarm will be triggered if it is parameterized.
- To restart counting, the internal gate must be reopened. Depending on the parameters set, counting continues from the current counting value (*Interrupt counting*) or it starts again from the load value (*Cancel counting*).

### One-time Counting/ Primary Direction Up



### 1-time Counting, Primary Direction Up


- Up-counting starts at the load value.
- If the parametrised end value -1 is reached during counting in the positive direction, the counter jumps back to the load value at the next positive count pulse. The internal gate is automatically closed, the status bit *End value reached* is set and a process alarm will be triggered if it is parameterized.

- To restart counting, the internal gate must be reopened. Counting starts again at the load value.
- Upon reaching the lower count limit the counter jumps to the upper count limit to continue counting from there. The status bit *Underflow performed* is set and a process alarm will be triggered if it is parameterized. All status bits remain set until they are reset with the bit *Reset status bits* in the control word. After a cancelled gate control, the counting process starts with the load value

#### Counting Range

Limits	Valid range of values
End value	$-2\,147\,483\,647 (-2^{31} + 1)$ to $+2\,147\,483\,647 (2^{31} - 1)$
Lower count limit	$+2\,147\,483\,648 (2^{31})$

### 1-time Counting/ Primary Direction Down




1-time Counting, Primary Count Down

- If the parametrized end value +1 is reached during counting in the negative direction, the counter jumps back to the load value at the next count pulse. The internal gate is automatically closed, the status bit *End value reached* is set and a process alarm will be triggered if it is parameterized.
- To restart counting, the internal gate must be reopened. Counting starts again at the load value.
- Upon reaching the upper count limit the counter jumps to the lower count limit to continue counting from there. The status bit *Overflow performed* is set and a process alarm will be triggered if it is parameterized. All status bits remain set until they are reset with the bit *Reset status bits* in the control word.

#### Counting Range

Limits	Valid range of values
End value	$-2\,147\,483\,648 (-2^{31})$ to $+2\,147\,483\,647 (2^{31} - 1)$
Upper count limit	$+2\,147\,483\,647 (2^{31} - 1)$


### Periodic Counting/ No Primary Direction



*Periodic Counting, No Primary Direction*

- Counting (up or down) starts at the load value, the entire counting range is used.
- Upon reaching a count limit, the counter jumps back to the load value and starts counting again from there. The status bit *Overflow performed* or *Underflow performed* is set and a process alarm will be triggered if it is parameterized. All status bits remain set until they are reset with the bit *Reset status bits* in the control word.

### Periodic Counting/ Primary Direction Up




*Periodic Counting, Primary Direction Up*

- Up-counting starts at the load value.
- If the parameterised end value -1 is reached during counting in the positive direction, the counter jumps back to the load value at the next positive count pulse and continues counting from there. The status bit "End value reached" is set and a process alarm will be triggered if it is parameterised.
- Upon reaching the lower count limit the counter jumps to the upper count limit to continue counting from there. The status bit "Underflow performed" is set and a process alarm will be triggered if it is parameterised. All status bits remain set until they are reset with the bit "Reset status bits" in the control word.

**Counting Range**

Limits	Valid range of values
End value	$-2\,147\,483\,647 (-2^{31} + 1)$ to $+2\,147\,483\,647 (2^{31} - 1)$
Lower count limit	$+2\,147\,483\,648 (-2^{31})$

**Periodic Counting/ Primary Direction Down****Periodic Counting, Primary Direction Down**

- Down-counting starts at the load value.
- If the parameterised end value +1 is reached during counting in the negative direction, the counter jumps back to the load value at the next count pulse and continues counting from there. The status bit *End value reached* is set and a process alarm will be triggered if it is parameterized.
- Upon reaching the upper count limit the counter jumps to the lower count limit to continue counting from there. The status bit *Overflow performed* is set and a process alarm will be triggered if it is parameterised. All status bits remain set until they are reset with the bit *Reset status bits* in the control word.


**Counting Range**

Limits	Valid range of values
End value	$-2\,147\,483\,647 (-2^{31})$ to $+2\,147\,483\,647 (2^{31} - 1)$
Upper count limit	$+2\,147\,483\,647 (-2^{31} - 1)$

**5.15.3 Additional Counter Features**

You can define the additional features for the counter listed below by parametrising or via the process data outputs:

- Reset: resets the counting value to the load value during counting.
- Comparator: Upon meeting the comparison condition, the comparison bit is activated or a process alarm is triggered.
- Hysteresis: reduces frequent toggling of the comparison bit and/or excessive triggering of a process alarm, e.g. when the value of a sensor signal fluctuates around the comparison value. It is possible to count beyond the lower count limit.



Additional Counter Functions

### Comparison Function

Via the parameter *Comparison function* you can deactivate the comparison function or define a comparison condition:

- Counter value higher or equal comparison value
- Counter value lower or equal comparison value
- Counter value equal comparison value

To use the comparison function, you have to preset the comparison values for both counting channels in the respective first double word of the process data outputs and to set the bit QX8.1 and QX10.1 respectively (*Comparison bit released*) in each control word.

As soon as the counting value meets the corresponding comparison condition, the bits *Comparison bit active* and *Comparison condition met* are activated. The bit *Comparison bit active* remains set as long as the comparison condition is being met (respectively the parameterised hysteresis). The bit *Comparison condition met* remains active until it will be reset with the bit *Reset of the status bits* in the control word.

When using a counting mode with primary direction, the comparison bit will be set only upon reaching the comparison value from the primary direction.


### Hysteresis

It is possible to reduce frequent triggering of a process alarm and toggling of the comparison bit (e.g. if the value of a sensor signal fluctuates around the comparison value), by setting the hysteresis. You thereby define a range above and below a reference value (zero crossing, overflow/underflow and comparison value), within which the status bit will not be reset.

A limit value between 0 and 255 can be parameterized for the hysteresis. With hysteresis = 3 for example, all values differing less than 3 from the reference value are smoothed. Hysteresis is deactivated with the values 0 and 1. The hysteresis is activated upon reaching the comparison condition. The comparison result remains unchanged during active hysteresis until the counting value reaches the predetermined hysteresis limit. After leaving the hysteresis range, hysteresis is reactivated only upon reaching the comparison condition again.

After changing the hysteresis value, an active hysteresis remains active. The new hysteresis value is activated during the next hysteresis event.


The behaviour of the status bit for hysteresis = 0 (hysteresis deactivated) and hysteresis = 3 is shown in the following diagrams (legends describe the behaviour for hysteresis = 3):



**Operating principle of the Hysteresis with Counter Value  $\geq$  Comparison Value**


- 1 Comparison condition met  $\rightarrow$  status bit is set and hysteresis activated
- 2 Comparison condition not met, leaving the hysteresis range  $\rightarrow$  status bit is reset
- 3 Comparison condition met  $\rightarrow$  status bit is set and hysteresis activated
- 4 Leaving the hysteresis range, the status bit remains set because the comparison condition is still met
- 5 Comparison condition no longer met but hysteresis still active  $\rightarrow$  status bit remains set
- 6 Comparison condition met, hysteresis still active  $\rightarrow$  status bit remains set
- 7 Leaving the hysteresis range and comparison condition met  $\rightarrow$  status bit remains set






**Operating Principle of the Hysteresis with Counter Value = Comparison Value**

- 1 Comparison condition met → status bit is set and hysteresis activated
- 2 Comparison condition not met, leaving the hysteresis range → status bit is reset
- 3 Comparison condition met → status bit is set and hysteresis activated
- 4 Leaving the hysteresis range and comparison condition not met → status bit is reset
- 5 Comparison condition met → status bit is set and hysteresis activated
- 6 Comparison condition met and hysteresis active → status bit remains set
- 7 Leaving the hysteresis range and comparison condition no longer met → status bit is reset



### EP-5112 Counter Operation through Parameter\Signal Evaluation\Rotary Transducer xxx




### EP-5112 Counter Operation through Parameter\Signal Evaluation\ Pulse/Direction (A/B)

## 5.16 Digital Frequency Counter Module EP- 5212



**Digital Counter Module EP-5212**



**Connection Diagram EP-5212**


The digital counter module EP-5212 can read frequency of one square-wave signal (1 channel) from one or two external sensors with a maximum input frequency of 100 kHz. Frequencies to be counted are applied to channel CH0 and/or channel CH1, the measurement will be started via control word 1 and 2 respectively. Measuring cycles can be defined in  $\mu\text{s}$ . The longer the measuring cycle the more exactly the measurement.

A status LED is assigned to each channel. The module electronics supply the connected sensors with power from the input voltage path ( $I_{IN}$ ).


The EP-5212 has:

- Two counter inputs 24 V DC
- Counting frequency 100 kHz max
- Digitally adjustable input filter to suppress interferences (17 filter frequencies gradually adjustable between 3 Hz and 187 kHz)

LED Indicators EP-5212

	Module Status	Green: Communication over the system bus Red: Module System Fault or Diagnostic Fault
1.1	--	
1.2	--	
1.3	--	
1.4	Yellow: CH0 active (1-level)	
2.1		
2.2		
2.3		
2.4		
3.1	--	
3.2	--	
3.3	--	
3.4	Yellow: CH1 active (1-level)	
4.1		
4.2		
4.3		
4.4		

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



Block Diagram EP-5212

**Specifications EP-5212**

<b>System data</b>	
Data	Process, parameter and diagnostic data depend on the network Adapter used (refer to the table in the section, <i>Order and Arrangement of the Modules</i> )
Interface	RSTi-EP I/O communication bus
System bus transfer rate	48 Mbps
Galvanic isolation	500 V DC between the current paths
<b>Inputs</b>	
Number of counter inputs	2
Input filter	adjustable between 3 Hz and 187 kHz (333 ms and 5 $\mu$ s)
Low input voltage	< 5 V
High input voltage	> 11 V
Max. input current per channel	3.5 mA
Sensor supply	Yes
Sensor connection	2- and 3-wire
Reverse polarity protection	Yes
Module diagnosis	Yes
Individual channel diagnosis	No
Counter width	32 bits
Maximum input frequency	100 kHz
Mode of operation	Pulse and direction / AB mode with 1-, 2-, 4-times sampling
<b>Supply</b>	
Supply voltage	20.4V – 28.8V
Current consumption from system current path $I_{SYS}$ , typ.	8 mA
Current consumption from input current path $I_{IN}$	35 mA + sensor supply current
<b>General data</b>	
Weight	87 g (3.07 oz)
For additional general data, refer to the section, <i>General Technical Data for I/O Modules</i> .	

## Overview of the Editable Parameter EP-5212

Channel	Description	Options (Value)	Default
0 - 1	Input filter	5 $\mu$ s [187 kHz] (0) / 11 $\mu$ s [94 kHz] (1) / 21 $\mu$ s [47 kHz] (2) / 43 $\mu$ s [23 kHz] (3) / 83 $\mu$ s [12 kHz] (4) / 167 $\mu$ s [6 kHz] (5) / 333 $\mu$ s [3 kHz] (6) / 667 $\mu$ s [1,5 kHz] (7) / 1 ms [732 Hz] (8) / 3 ms [366 Hz] (9) / 5 ms [183 Hz] (10) / 11 ms [92 Hz] (11) / 22 ms [46 Hz] (12) / 43 ms [23 Hz] (13) / 91 ms [11 Hz] (14) / 167 ms [6 Hz] (15) / 333 ms [3 Hz] (16)	5 $\mu$ s [187 kHz]

## Input Filter EP-5212

Limiting frequency	Filter time, real value	Filter time
187 kHz	5.35 $\mu$ s	5 $\mu$ s
94 kHz	10.64 $\mu$ s	11 $\mu$ s
47 kHz	21.28 $\mu$ s	21 $\mu$ s
23 kHz	43.47 $\mu$ s	43 $\mu$ s
12 kHz	83.33 $\mu$ s	83 $\mu$ s
6 kHz	166.67 $\mu$ s	167 $\mu$ s
3 kHz	333.33 $\mu$ s	333 $\mu$ s
1,5 kHz	666.67 $\mu$ s	667 $\mu$ s
732 Hz	1.36 ms	1 ms
366 Hz	2.73 ms	3 ms
183 Hz	5.46 ms	5 ms
92 Hz	10.87 ms	11 ms
46 Hz	21.74 ms	22 ms
23 Hz	43.47 ms	43 ms
11 Hz	90.90 ms	91 ms
6 Hz	166.67 ms	167 ms
3 Hz	333.33 ms	333 ms

Diagnostic Data EP-5212

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x08
		1		
		2		
		3		
		4	Reserved	1
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	2-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	0
		4-7	Reserved	0
Channel type	4	0-6	Channel type	0x76
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	0
Number of channels	6		Number of similar channels per module	2
Channel error	7-10	0-31	Reserved	0
Channel 0 error to Channel 31 error	11 to 42	0-7	Reserved	0
Time stamp	43-46		Time stamp [ $\mu$ s] (32 bit)	



**Process Data<sup>†</sup> Inputs EP-5212**

Byte	Format	Name	Bit	Function when active	Remark
IB0 ... IB3	Double word	Counter 0: Counter value			Channel 0: Currently measured value of period duration multiplied by 125 ns results in the current period duration in $\mu$ s
IB4 ... IB7	Double word	Counter 1: Counter value			Channel 0: Number of rising edges within the current measurement cycle
IB8 ... IB11	Double word	Counter 0: Counter status			Channel 1: Currently measured value of period duration multiplied by 125 ns results in the current period duration in $\mu$ s
IB12 ... IB15	Double word	Counter 1: Counter status			Channel 1: Number of rising edges within the current measurement cycle
IB16	Word	Channel 0: Status	IX16.0 ... 16.7	reserved	
IB17			IX17.0	Measurement active	
			IX17.1 ... 17.7	reserved	
IB18	Word	Channel 1: Status	IX18.0 ... 18.7	reserved	
IB19			IX19.0	Measurement active	
			IX19.1 ... 19.7	reserved	

<sup>†</sup> Internal process data mapping with data format *Standard*. Depending on the fieldbus specification and the data format of the communicating fieldbus components the bytes and/or words can be reversed during data transfer.

**Process Data<sup>†</sup> Outputs EP-5212**

Byte	Format	Name	Bit	Function when edge 0-1	Remark
QB0 ... QB3	Double word	Channel 0: Measurement cycle period			Channel 0: Preset value of the measurement cycle period (23 Bit)
QB4 ... QB7	Double word	Channel 1: Measurement cycle period			Channel 1: Preset value of the measurement cycle period (23 Bit)
QB8	Word	Channel 0: Control word	QX8.0 - QX8.7	reserved	
QB9			QX9.0	Measurement start	
			QX9.1	Measurement stop	
			QX9.2 - 9.7	reserved	
QB10	Word	Channel 1: Control word	QX10.0 - X10.7	reserved	
QB11			QX11.0	Measurement start	
			QX11.1	Measurement stop	
			QX11.2 - 11.7	reserved	

<sup>†</sup> Internal process data mapping with data format *Standard*. Depending on the fieldbus specification and the data format of the communicating fieldbus components the bytes and/or words can be reversed during data transfer.

### 5.16.1 Function Frequency Counting

#### Defining the Measurement Cycle Period

The length of measurement cycle period has to be defined for each channel within the output process data. As the 23 bit value has a resolution of 1 µs, values between 1 µs and 8.388.607 µs can be defined. The measurement cycle period must be long enough to detect at least one rising edge.

#### Setting of Input Filter

In order to suppress any disturbances a digital input filter can be set for each channel via the Parameter Input filter (Filter frequencies and respective pulse width see Overview of editable parameter).

#### Start Measurement

Setting of Bit 8 in the control word of each channel starts the cyclic measurement.

#### Calculation of Results

The input process data Rising edges register the amount of rising edges for each channel within the referring measurement cycle period. Counting starts with the last rising edge of the previous measurement cycle and ends with the last but one edge of the current measurement cycle. The time between first and last counted edge is defined as measured period. This is a 27 bit value with a resolution of 125 ns and an precision of 1 µs (valid value range between 0x00000008 and 0x7FFFFFF8).

Due to its resolution the value has to be divided by 8 within the control programm in order to get the current period duration in microseconds. This value can be between 1 µs and 16.777.215 µs.

The frequency is being calculated programmwise as follows:

$$\text{Frequency } F = \frac{\text{Rising edges in current period}}{\text{Current measured period}}$$

In case there is no rising edge registred within a measurement cycle the current period duration will be set to the maximum value of 16.777.215,875 µs.


If the current period duration as well as the rising edges are registred as zero, the current measured period was too short to register a rising edge.

#### Modifying the Measurement Cycle Period


The measurement cycle period can be modified during a running measurement. In this case the new value is not valid until the following measurement cycle, during the current measurement cycle the old value will be kept.

#### Stop measurement

Setting of Bit 9 in the control word of each channel stops the cyclic measurement. If the last measurement cycle has not been run through completely, the current measured period will be set to the maximum value of 0x7FFFFFFF, the rising edges will be set to zero.



Functional Principle Frequency Counting




Frequency Counter EP-5212

## 5.17 Serial Communication Module EP-5261



**Digital Interface Module 5261**




**Connection Diagram EP-5261**

Serial data can be exchanged between the PLC and a data terminal device using the EP-5261 communication module. The device (such as a barcode scanner, printer) can be connected through an interface type RS232, RS485 or RS422.

The data transfer rate can be parameterized between 300 and 115200 bps. The process data length can be parameterized to be 8 byte or 16 byte. A terminating resistor can be parameterized for the RS485 and RS422 interface respectively.



The communication status is indicated by two LEDs on the respective plug.

The module electronics supply the connected data terminal device with power from the input current path ( $I_{in}$ ) either with 5VDC or 24VDC (parameterizable). Both supply voltage outputs are protected against overcurrent.



Connection Variants for the Voltage Supply

Pin Assignment of the Sub-D Plug (RS232 only)

 					
	Name	Signal	Direction	Cable Color	RS232 Pin
Assignment of the 9-pole plug (male)					
1.1	RXD	Receive data	In	Brown	2
1.2	TXD	Transmit data	Out	Green	3
1.3	RTS	Request to send	Out	Blue	7
1.4	CTS	Clear to send	In	Red	8
4.2	GND	Signal ground		Grey	5
Assignment of the 25-pole plug (male)					
1.1	RXD	Receive data	In	Green	3
1.2	TXD	Transmit data	Out	Brown	2
1.3	RTS	Request to send	Out	Yellow	4
1.4	CTS	Clear to send	In	Grey	5
4.2	GND	Signal ground		Blue	7

### Connection Cables for the Serial Device

Use shielded cables, because electromagnetic interferences from the surroundings have to be assumed. The maximum permissible cable length depends on the cable capacitance and the baud rate.

#### Connecting a RS232 Device

*Maximum Cable Length RS232*

Cable Capacitance	Maximum Cable Length
$\leq 2500$ pF	15 m (49 ft), shielded
55 pF/m	45 m (147 ft)

#### Connecting a RS485 or RS 422 Device

The serial device has to be connected using a twisted pair cable (U/UTP, Type Cat- 3 or J-2YY-2x2x0,6).

*Maximum Cable Length RS422/485*


Baud Rate in kbps	Maximum Cable Length
$\leq 19200$	1200 m (3937 ft), shielded
38400	500 m (1640 ft)
57600	250 m (820 ft)
115200	200 m (656 ft)

- RS485: Use one core pair for Data+/Data-. You can use any wire for the ground signal GND COM. The remaining free wires should be connected to ground.
- RS422: Connect the wires for transmitting signals TXD+/TXD- and those for receiving signals RXD+/RXD- in pairs respectively. You can use any wire for the ground signal GND COM. The remaining free wires should be connected to ground.

LED Indicators EP-5261

Module Status		Green: Communication over the system bus Red: Module System Fault or Diagnostic Fault
1.1	Yellow: RS232 parameterised Yellow flashing: Data are being recieved	
1.2	Yellow: RS232 parameterised Yellow flashing: Data are being transmitted	
1.3	--	
1.4	--	
3.1	3.1 ... 3.4 Yellow: RS422 parameterized	
3.2	3.1 + 3.2 Off, 3.3 + 3.4 Yellow: RS485 parameterized	
3.3	3.3 Yellow flashing: Data are being recieved	
3.4	3.4 Yellow flashing: Data are being transmitted	
4.1	Green: Supply voltage +5VDC	
4.2	--	
4.3	Green: Supply voltage +24VDC	
4.4	--	

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



Block Diagram EP-5261



**Specifications EP-5261**

<b>System data</b>	
Data	Process, parameter and diagnostic data depend on the network Adapter used (refer to the table in the section, <i>Order and Arrangement of the Modules</i> )
Interface	RSTi-EP I/O communication bus
System bus transfer rate	48 Mbps
<b>Serial Interface</b>	
Number	1
Type	RS232, RS485, RS422, parameterizable
Transfer rate	300 ... 115200 Bps, parameterizable
Supply voltage	5VDC or 24VDC
Current of power supply output	max. 500 mA
Standards RS232	DIN 66020, DIN 66259, EIA-RS232C, CCITT V.24/V.28
Standards RS485/RS422	120 Ω, parameterisable
Short-circuit proof	Yes
Module diagnosis	Yes
Individual channel diagnosis	Yes
<b>Supply</b>	
Supply voltage	20.4V – 28.8V
Current consumption from system current path $I_{SYS}$	8 mA
Current consumption from input current path $I_{IN}$	16 mA + load
<b>General data</b>	
Weight	92 g (3.25 oz)
For additional general data, refer to the section, <i>General Technical Data for I/O Modules</i> .	

**Overview of the Editable Parameter EP-5261**

<b>Description</b>	<b>Options<sup>1</sup></b>	<b>Default</b>
Operating mode	Disabled (0) / RS232 (1) / RS485 (2) / RS422 (3)	Disabled
Data bits <sup>2</sup>	7 Bit (0) / 8 Bit (1)	8 Bit
Baud rate	300 (0) / 600 (1) / 1200 (2) / 2400 (3) / 4800 (4) / 9600 (5) / 14400 (6) / 19200 (7) / 28800 (8) / 38400 (9) / 57600 (10) / 115200 (11)	9600
Stop bit	1 Bit (0) / 2 Bit (1)	1 Bit
Parity	None (0) / Even (1) / Odd (2)	None
Flow control	None (0) / CTS/RTS (1) / XON/XOFF (2)	None
XON character	0 ... 255	17
XOFF character	0 ... 255	19
Terminating resistor RS485/422	Off (0) / On (1)	Off
Process data length	16 Byte (1)	16 Byte
1) Values in brackets for EtherCAT and Modbus-TCP		
2) The option "7 Bit" works only in combination with a parity ("even" or "odd")		

Diagnostic Data EP-5261

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type 0x05	1
		1		0
		2		1
		3		0
		4	Reserved	0
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	0
		4-7	Reserved	0
Channel type	4	0	Channel type 0x79	1
		1		0
		2		0
		3		1
		4		1
		5		1
		6		1
		7		0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	0
Number of channels	6		Number of similar channels per module	1
Channel error	7-10	0-31	Reserved	0
Time stamp	43-46		Time stamp [μs] (32 bit)	

## Data Transfer

The process data length can be parameterized to be 8 or 16 Bytes. Byte 0 is used for status and diagnosis, Byte 1 for the data segment length, and the remaining 6 or 14 Bytes are user data.

**Process input data:** The data sent from the serial device are written into the receive memory of the UR20 module. As soon as the SPS request results in that RX\_CNT is not equal RX\_CNT\_ACK, the data will be sent in segments via the fieldbus coupler to the PLC. The successfully data transfer will be acknowledged to the module.

The receive memory can save a maximum of 255 Bytes. A software handshake (XON/XOFF) or a hardware handshake (RTS/CTS) can be parameterised using the flow control, so that an alarm will warn against a buffer overflow.

**Process output data:** The data sent from the PLC via the fieldbus coupler are written into the transmission memory of the UR20 module. The module is continuously checking whether data are ready to be sent or a data transfer to the device has been finished successfully. Not till then the next data will be transferred.

**Process Input Data EP-5261**

Byte	Format	Name	Bit	Description	Remarks
IB0	Word	Status and Diagnosis	IX0.0	Data in the receive memory	RX = 0: Receive memory is empty RX = 1: A telegram or telegram segment in the receive memory is ready for transmission.
			IX0.1	Receive memory nearly full	Only 10 characters are left in the receive memory. XOFF will be set if parametrised.
			IX0.2	Not used	
			IX0.3	RX_CNT	The RX_CNT value is assigned to each data segment of the process input data while transmission. The sequence or the RX_CNT values is: Binary: 00, 01, 10, 11, 00, ... Decimal: 0, 1, 2, 3, 0, ... A faulty data sequence indicates missing data segments.
			IX0.4	RX_CNT	
			IX0.5	TX_CNT_ACK	The TX_CNT_ACK value is a copy of the TX_CNT value, which has been transferred together with the last data segment of the process output data. TX_CNT_ACK acknowledges that the data has been taken over successfully.
			IX0.6	TX_CNT_ACK	
			IX0.7	STAT	STAT = 1: Communication with the device is without fault. STAT = 0: Faulty communication with the device.
IB1	Word	Length of the data segment / of the subsequent diagnosis data		RX	Length of the data / diagnosis data in this frame
IB 2 ... IB 7 or IB 2 ... IB 15		Received data		User data of the transferred telegram segment	


## Process Output Data EP-5261

Byte	Format	Name	Bit	Description	Remarks
QB0	Word	Status and Diagnosis	IX0.0	RXBUF FLUSH	Bit 0: RXBUF FLUSH The receive memory can be scrubbed using this bit. STATRES = 1: A requirement with RXBUF FLUSH = 1 will be ignored. STATRES = 0: The receive memory will be scrubbed with RXBUF FLUSH = 1.
			IX0.1	TXBUF FLUSH	Bit 1: TXBUF FLUSH The emission memory can be scrubbed using this bit. STATRES = 1: A requirement with TXBUF FLUSH = 1 will be ignored. STATRES = 0: The emission memory will be scrubbed with TXBUF FLUSH = 1.
			IX0.2	RX_HWBUFFER	Bit 2: DisableSend_TX_HWBUFFER This bit controls the hardware emission memory: DisableSend_TX_HWBUFFER = 0: The hardware emission memory is released. A character (Byte) will be sent as soon as it reaches the buffer. DisableSend_TX_HWBUFFER = 1: The hardware emission memory is locked. Characters (Bytes) will only be sent, when DisableSend_TX_HWBUFFER is set to 0 again.
			IX0.3	TX_CNT	The TX_CNT value is assigned to each data segment of the process output data. The sequence or the TX_CNT values is: Binary: 00->01->10->11->00... Decimal: 0->1->2->3->0... A faulty data sequence indicates missing data segments.
			IX0.4	TX_CNT	
			IX0.5	RX_CNT_ACK	RX_CNT_ACK must include a copy of the RX_CNT value. The RX_CNT value has been transferred together with the last data segment of the process input data. RX_CNT_ACK must be set in analogy with RX_CNT (in the status byte). It indicates that the data segment has been transferred successfully by using RX_CNT and enables to receive new data.
			IX0.6	RX_CNT_ACK	
			IX0.7	Communication Status	The input data status bit STAT will be reset using this bit. When changing from 1 to 0 (falling edge) STAT will be reset from 0 to 1. STAT = 0: All changes in the data fields TX_BYTE_CNT, TX_CNT and RX_CNT_ACK will be ignored. The receive or emission memory can be scrubbed using RXBUF FLUSH or TXBUF FLUSH respectively. STAT = 1 or changing from 0 to 1: The buffers cannot be scrubbed.
QB1	Word	Length of the data segment			
QB 2 ... QB 7 or QB 2 ... QB 15		Transmission data		User data of the transferred telegram segment	


### Enabling the Data Transfer

There are different ways to announce the communication module to the control. Using the test mode copy the input data into the output data of the module so that the received data will be sent again. Or select one of the function blocks provided by the engineering tool.

For programming, regard the following schemes showing the sequences for receiving and transmission.



Scheme of the Receiving Sequence




Scheme of the Transmission Sequence


The status and control word values during various states of communication are provided in the following table.

Action	Input Byte 0 (Status) of Module								Input Byte 1 (length of RX byte seg.)	Output byte 0 (control) off the module								Output byte 1 (length of TX byte seg.)	Notes
	7	6	5	4	3	2	1	0		7	6	5	4	3	2	1	0		
	Stat	TX_CNT_ACK		RX_CNT						STATRES	RX_CNT_ACK		TX_CNT						
Init/Startup	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	After powerup, module is ready for communication
Activate communication	1	0	0	0	0	0	0	0	0	1	0	0	0	0	0	0	0	0	PLC is ready for communication (response)
Receive data	1	0	0	0	1	0	0	0	N (1..14)	1	0	0	0	0	0	0	0	0	Module has received bytes
	1	0	0	0	1	0	0	0	N	1	0	1	0	0	0	0	0	0	RX acknowledge after data taken over
Send data	1	0	0	0	1	0	0	0	X	1	0	1	0	1	0	0	0	N (1..14)	Before changing TX-CNT, set TX bytes
	1	0	1	0	1	0	0	0	X	1	0	1	0	1	0	0	0	N	TX acknowledge after module sent data

## 5.18 SSI Encoder Interface Module EP- 5311



SSI Encoder Interface Module 5311



Connection Diagram EP-5311

The EP-5311 SSI Encoder Interface module can read differential signals (RS422) from a SSI encoder. It can be connected as a master directly to the encoder providing the clock. To synchronise two SSI encoders a second SSI module running in *Listening* mode can be placed between the encoder and a master module from which it receives the clock.

The data transfer rate can be between 125 kHz and 2 MHz, the data format can be chosen between binary or Gray-Code.

Connected sensors can be delivered either with 5VDC or 24VDC. Both supply outputs are protected against overcurrent, and must not be used simultaneously.


The communication status is indicated by three LEDs. The module electronics supply the connected sensor with power from the input current path ( $I_{IN}$ ).

**Note:** The SSI encoder must be connected using a shielded wire (maximum length 320 m with 125 kHz). The shielding has to be designed as described in the sections, *Earthing (functional earth FE)* and *Shielding*.

LED Indicators EP-5311

	Module Status	<b>Green:</b> Communication over the system bus <b>Red:</b> Module System Fault or Diagnostic Fault
	1.1	<b>Yellow:</b> Data In active
	1.2	--
	1.3	--
	1.4	--
	2.1	<b>Yellow:</b> Data In active
	2.2	--
	2.3	--
	2.4	--
	3.1	<b>Yellow:</b> Data In active
	3.2	--
	3.3	--
	3.4	--
	4.1	<b>Green:</b> Power supply sensor +5VDC
	4.2	--
	4.3	<b>Green:</b> Power supply sensor +24VDC
	4.4	--

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



Block Diagram EP-5311



**Specifications EP-5311**

<b>System data</b>	
Data	Process, parameter and diagnostic data depend on the network Adapter used (refer to the table in the section, <i>Order and Arrangement of the Modules</i> )
Interface	RSTi-EP I/O communication bus
System bus transfer rate	48 Mbps
Number of channels	1
Type	SSI (Differential RS422)
SSI transfer rate	125 kHz ... 2 MHz
Delay time	1 µs ... 64 µs
Data width	8 ... 32 Bit
Data format	Binary / Gray-Code
SSI mode	Listening / Master
Sensor supply	500 mA (24 V DC) / 400 mA (5 V DC)
Reverse polarity protection	Yes
Module diagnosis	Yes
Individual channel diagnosis	No
Cable length	max. 320 m (1049.1 ft) at 125 kHz; shielded
<b>Supply</b>	
Supply voltage	20.4V – 28.8V
Current consumption from system current path $I_{SYS}$	8 mA
Current consumption from input current path $I_{IN}$	25 mA + sensor supply current
<b>General data</b>	
Weight	87 g (3.07 oz)
For additional general data, refer to the section, <i>General Technical Data for I/O Modules</i> .	

## Overview of the Editable Parameter EP-5311

Channel	Description	Options <sup>†</sup>	Default
0	Delay time	1 µs (0) / 2 µs (1) / 4 µs (2) / 8 µs (3) / 16 µs (4) / 32 µs (5) / 48 µs (6) / 64 µs (7)	64 µs
0	SSI transfer rate	125 kHz (0) / 250 kHz (1) / 500 kHz (2) / 1 MHz (3) / 1,5 MHz (4) / 2 MHz (5)	125 kHz
0	Number of indicator bits	0 ... 15	0
0	Number of frame data bits	8 Bit (0) / 9 Bit (1) / 10 Bit (2) / ... / 31 Bit (23) / 32 Bit (24)	25 Bit
0	SSI mode	Listening (0) / Master (1)	Master
0	Bit order	MSB first (0) / LSB first (1)	MSB first
0	Data evaluation at edge	1 to 0 (0) / 0 to 1 (1)	1 to 0
0	Data format	Binary (0) / Gray-Code (1)	Gray-Code
0	SSI interface	Disabled (0) / enabled (1)	Disabled
<sup>†</sup> Values in brackets for Modbus-TCP and EtherCAT			


## Diagnostic Data EP-5311

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type 0x05	1
		1		0
		2		1
		3		0
		4	Reserved	0
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	1
		4-7	Reserved	0
Channel type	4	0	Channel type 0x79	1
		1		0
		2		0
		3		1
		4		1
		5		1
		6		1
		7		0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	0
Number of channels	6		Number of similar channels per module	1
Channel error	7-10	0-31	Reserved	0
Channel 0 error to Channel 31 error	11 to 42	0-7	Reserved	0
Time stamp	43-46		Time stamp [ $\mu$ s] (32 bit)	

## 5.19 Digital Pulse Width Modulation Output Module EP- 5422



**Digital Pulse Width Modulation  
Output Module EP-5422**



**Connection Diagram EP-5422**


The digital pulse width modulation module EP-5422 is used for the control of small motors with current requirements of up to 0.5 A. The period duration for each channel can be parameterised from 25  $\mu$ s to approx. 175 ms (input values from 1202 to 8388607 based on a factor 0.02083  $\mu$ s).

Via an output double word in the process data the pulse duration is defined from 0  $\mu$ s to approx. 175 ms for each channel (input values from 0 to 8388607 based on a factor 0.02083  $\mu$ s). If the pulse duration is equal or exceeds the duration of the period, the output is set permanently.


In another output word the output mode is switched and the output is being started and stopped. Deactivated outputs are set to GND.

For each channel the current status can be read in an status word. A status LED is assigned to each channel. The outputs are supplied with power from the output current path (IOUT). The module is protected against external voltages between 0 V and the operating voltage.

LED Indicators EP-5422

	Module Status	<b>Green:</b> Communication over the system bus <b>Red:</b> Module System Fault or Diagnostic Fault
	1.1	<b>Yellow:</b> PWM output 0 – 100%, P-switching <b>Yellow flashing at 2 Hz:</b> PWM output 0 is > 0 and < 100%, PN-switching or P-switching
	1.2	--
	1.3	--
	1.4	--
	2.1	--
	2.2	--
	2.3	--
	2.4	--
	3.1	<b>Yellow:</b> PWM output 1 – 100%, P-switching <b>Yellow flashing at 2 Hz:</b> PWM output 0 is > 0 and < 100%, PN-switching or P-switching
	3.2	--
	3.3	--
	3.4	--
	4.1	--
	4.2	--
	4.3	--
	4.4	--

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



Block Diagram EP-5422

**Specifications EP-5422**

System data		
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in the section, <i>Order and Arrangement of the Modules</i> )	
Interface	RSTi-EP I/O communication bus	
System bus transfer rate	48 Mbps	
Outputs		
Number	2	
Type	PN output stage	
Response time	< 0.1 μs	
Period duration	25 μs t o 175 ms ( 40 kHz to 6 Hz)	
Max. output current	per channel	0.5 A
	per module	1 A
Switching frequency	Resistive load (min. 47 Ω)	static, 6 Hz to 40 kHz
	Inductive load (DC 13)	static, 6 Hz to 40 kHz
	Lamp load (12 W)	static, 6 Hz to 40 kHz
Actuator connection	2-wire, 3-wire, 3-wire + FE	
Actuator supply	max. 2 A per plug, total max. 4 A	
Pulse/period ratio	0–100 % PN-switching or P-switching, adjustable	
Short-circuit-proof	Yes	
Response time of the protective circuit	< 100 μs	
Module diagnosis	Yes	
Individual channel diagnosis	No	
Reactionless	Yes	
Supply		
Supply voltage	20.4V – 28.8V	
Current consumption from system current path I <sub>sys</sub> , typ.	8 mA	
Current consumption from output current path I <sub>out</sub>	40 mA	
General data		
Weight	77 g (2.72 oz)	
For additional general data, refer to thw section, <i>General Technical Data for I/O Modules</i> .		

**Overview of the Editable Parameter EP-5422**

Channel	Description	Options	Default
0 – 1	Period duration = $n \cdot 0.02083 \mu$ s	1202 ... 8388607	1202

Diagnostic Data EP-5422

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x0F
		1		
		2		
		3		
		4	Reserved	0
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	
		4-7	Reserved	0
Channel type	4	0-6	Channel type	0x72
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	0
Number of channels	6		Number of similar channels per module	2
Channel error	7-10	0-31	Reserved	0
Channel 0 error to Channel 31 error	11 to 42	0-7	Reserved	0
Time stamp	43-46		Time stamp [ $\mu$ s] (32 bit)	

**Process<sup>†</sup> Data Inputs EP-5422**

Byte	Format	Name	Bit	Function, if active	Remarks
IB0	Word	Channel 0: Status word	IX0.0	reserved	
			IX0.1	Status PWM output	0: disabled, 1: enabled
			IX0.2	reserved	
			IX0.3	Output mode	0: PN-switching 1: P-switching
			IX0.4 ... 0.7	reserved	
IB1			IX1.0 ... 1.7	reserved	
IB2	Word	Channel 1: Status word	IX2.0	reserved	
			IX2.1	Status PWM output	0: disabled, 1: enabled
			IX2.2	reserved	
			IX2.3	Output mode	0: PN-switching 1: P-switching
			IX02.4 ... 2.7	reserved	
IB3			IX3.0 ... 3.7	reserved	

<sup>†</sup> Internal process data mapping with data format *Standard*. Depending on the fieldbus specification and the data format of the communicating fieldbus components the bytes and/or words can be reversed during data transfer.

**Process Data<sup>†</sup> Outputs EP-5422**

Byte	Format	Name	Bit	Function, if set	Remarks
QB0	Double Word	Channel 0: Pulse duration			Input value * 0.02083 μs Input range: 1 ... 8388607
QB1					
QB2					
QB3					
QB4	Double Word	Channel 1: Pulse duration			Input value * 0.02083 μs Input range: 1 ... 8388607
QB5					
QB6					
QB7					
QB8	Word	Channel 0: Control word	QX8.0 ... QX8.1	reserved	
			QX8.2	Output mode	0: PN-switching 1: P-switching
			QX8.3 ... QX8.7	reserved	
QB9			QX9.0	starts output	Setting with edge 0-1, dominates stop bit
			QX9.1	stops output	Setting with edge 0-1, start bit must be reset
			QX9.2 ... QX9.7	reserved	
QB10	Word	Channel 1: Control word	QX10.0 ... QX10.1	reserved	
			QX10.2	Output mode	0: PN-switching 1: P-switching
			QX10.3 ... QX10.7	reserved	
QB11			QX11.0	starts output	Setting with edge 0-1, dominates stop bit
			QX11.1	stops output	Setting with edge 0-1, start bit must be reset
			QX11.2 ... QX11.7	reserved	


<sup>†</sup> Internal process data mapping with data format *Standard*. Depending on the fieldbus specification and the data format of the communicating fieldbus components the bytes and/or words can be reversed during data transfer.



## 5.20 Digital Pulse Width Modulation Output Module EP- 5442



**Digital Pulse Width Modulation  
Output Module EP-5442**



**Connection Diagram EP-5442**


The digital pulse width modulation modules EP-5442 is used for the control of small motors with current requirements of up to 2 A. The period duration for each channel can be parameterized from 25  $\mu$ s to approx. 175 ms (input values from 1202 to 8388607 based on a factor 0.02083  $\mu$ s).

Via an output double word in the process data the pulse duration is defined from 0  $\mu$ s to approx. 175 ms for each channel (input values from 0 to 8388607 based on a factor 0.02083  $\mu$ s).


If the pulse duration exceeds the duration of the period, the output is set permanently. In another output word the output mode is switched and the output is being started and stopped. Deactivated outputs are set to GND.

For each channel the current status can be read in an status word. A status LED is assigned to each channel. The outputs are supplied with power from the output current path (IOUT). The module is protected against external voltages between 0 V and the operating voltage.

LED Indicators EP-5442

	Module Status	<b>Green:</b> Communication over the system bus <b>Red:</b> Module System Fault or Diagnostic Fault
	1.1	<b>Yellow:</b> PWM output 0 – 100%, P-switching <b>Yellow flashing at 2 Hz:</b> PWM output 0 is > 0 and < 100%, PN-switching or P-switching
	1.2	
	1.3	
	1.4	
	2.1	
	2.2	
	2.3	
	2.4	
	3.1	<b>Yellow:</b> PWM output 1 – 100%, P-switching <b>Yellow flashing at 2 Hz:</b> PWM output 0 is > 0 and < 100%, PN-switching or P-switching
	3.2	
	3.3	
	3.4	
	4.1	
	4.2	
	4.3	
	4.4	

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



Block Diagram EP-5442

**Specifications EP-5442**

System data		
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in the section, <i>Order and Arrangement of the Modules</i> )	
Interface	RSTi-EP I/O communication bus	
System bus transfer rate	48 Mbps	
Inputs		
Number of counter inputs	2	
Type	PN output stage	
Response time	< 0.1 μs	
Period duration	25 μs t o 175 ms (40 kHz to 6 Hz)	
Max. output current	per channel	2 A
	per module	4 A
Switching frequency	Resistive load (min. 12 Ω)	6 Hz to 40 kHz
	Inductive load (DC 13)	6 Hz to 40 kHz
	Lamp load (48 W)	6 Hz to 40 kHz
Actuator connection	2-wire, 3-wire, 3-wire + FE	
Actuator supply	max. 2 A per plug, total max. 8 A	
Pulse/period ratio	0–100 % PN-switching or P-switching, adjustable	
Short-circuit-proof	Yes	
Response time of the protective circuit	< 100 μs	
Module diagnosis	Yes	
Individual channel diagnosis	No	
Reactionless	Yes	
Supply		
Supply voltage	20.4V – 28.8V	
Current consumption from system current path I <sub>sys</sub> , typ.	8 mA	
Current consumption from output current path I <sub>out</sub>	40 mA	
General data		
Weight	82 g (2.89 oz)	
For additional general data, refer to the section, <i>General Technical Data for I/O Modules</i> .		

**Overview of the Editable Parameter EP-5442**

Channel	Description	Options	Default
0 – 1	Period duration = $n \cdot 0.02083 \mu$ s	1202 ... 8388607	1202

## Diagnostic Data EP-5442

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x0F
		1		
		2		
		3		
		4	Reserved	0
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	
		4-7	Reserved	0
Channel type	4	0-6	Channel type	0x72
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	0
Number of channels	6		Number of similar channels per module	2
Channel error	7-10	0-31	Reserved	0
Channel 0 error to Channel 31 error	11 to 42	0-7	Reserved	0
Time stamp	43-46		Time stamp [ $\mu$ s] (32 bit)	

Process<sup>†</sup> Data Inputs EP-5442

Byte	Format	Name	Bit	Function, if active	Remarks
IB0	Word	Channel 0: Status word	IX0.0	reserved	
			IX0.1	Status PWM output	0: disabled, 1: enabled
			IX0.2	reserved	
			IX0.3	Output mode	0: PN-switching 1: P-switching
			IX0.4 ... 0.7	reserved	
IB1			IX1.0 ... 1.7	reserved	
IB2	Word	Channel 1: Status word	IX2.0	reserved	
			IX2.1	Status PWM output	0: disabled, 1: enabled
			IX2.2	reserved	
			IX2.3	Output mode	0: PN-switching 1: P-switching
			IX02.4 ... 2.7	reserved	
IB3			IX3.0 ... 3.7	reserved	

<sup>†</sup> Internal process data mapping with data format *Standard*. Depending on the fieldbus specification and the data format of the communicating fieldbus components the bytes and/or words can be reversed during data transfer

Process Data<sup>†</sup> Outputs EP-5442


Byte	Format	Name	Bit	Function, if set	Remarks
QB0	Double Word	Channel 0: Pulse duration			Input value * 0.02083 μs Input range: 1 ... 8388607
QB1					
QB2					
QB3					
QB4	Double Word	Channel 1: Pulse duration			Input value * 0.02083 μs Input range: 1 ... 8388607
QB5					
QB6					
QB7					
QB8	Word	Channel 0: Control word	QX8.0 ... QX8.1	reserved	
			QX8.2	Output mode	0: PN-switching 1: P-switching
			QX8.3 ... QX8.7	reserved	
QB9			QX9.0	starts output	Setting with edge 0-1, dominates stop bit
			QX9.1	stops output	Setting with edge 0-1, start bit must be reset
			QX9.2 ... QX9.7	reserved	
QB10	Word	Channel 1: Control word	QX10.0 ... QX10.1	reserved	
			QX10.2	Output mode	0: PN-switching 1: P-switching
			QX10.3 ... QX10.7	reserved	
QB11			QX11.0	starts output	Setting with edge 0-1, dominates stop bit
			QX11.1	stops output	Setting with edge 0-1, start bit must be reset
			QX11.2 ... QX11.7	reserved	

<sup>†</sup> Internal process data mapping with data format *Standard*. Depending on the fieldbus specification and the data format of the communicating fieldbus components the bytes and/or words can be reversed during data transfer.

## 5.21 Analog Input Module EP- 3164



**Analog Input Module EP-3164**




**Connection Diagram EP-3164**

(left: 3/4-wire sensor with sensor wiring via electronics,  
right: 2-wire sensor with sensor wiring via electronics)


The EP-3164 analog input module can record up to 4 analog sensors with  $\pm 10\text{ V}$ ,  $\pm 5\text{ V}$ ,  $0\text{--}10\text{ V}$ ,  $0\text{--}5\text{ V}$ ,  $2\text{--}10\text{ V}$ ,  $1\text{--}5\text{ V}$ ,  $0\text{--}20\text{ mA}$  or  $4\text{--}20\text{ mA}$ . The resolution is 16 bit per channel. Sensors can be connected to each connector in a 2-wire, 3-wire or 3-wire connection + FE. The measurement range is defined using parameterization. A status LED is assigned to each channel. The module electronics supply the connected sensors with power from the input current path ( $I_{IN}$ ).

The inputs are protected against voltage surges and overcurrent. Voltages that exceed  $\pm 30\text{ V}$  may cause the destruction of the module. As a protection against overcurrent, the module temporarily switches to voltage mode.

LED Indicators EP-3164

	Module Status	<b>Green:</b> Communication over the system bus <b>Red:</b> Module System Fault or Diagnostic Fault
	1.1	<b>Red:</b> channel error
	1.2	--
	1.3	--
	1.4	--
	2.1	<b>Red:</b> channel error
	2.2	--
	2.3	--
	2.4	--
	3.1	<b>Red:</b> channel error
	3.2	--
	3.3	--
	3.4	--
	4.1	<b>Red:</b> channel error
	4.2	--
	4.3	--
	4.4	--

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



Block Diagram EP-3164

**Specifications EP-3164**

System data		
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in the section <i>Order and Arrangement of the Modules</i> )	
Interface	RSTi-EP I/O communication bus	
System bus transfer rate	48 Mbps	
Inputs		
Number	4	
Input values	1. Voltage (0 ... 5 V, ±5 V, 0 ... 10 V, ±10 V, 1 ... 5 V, 2 ... 10 V) 2. Current (0 ... 20 mA, 4 ... 20 mA)	
Resolution	16 bits	
Accuracy	0.1 % max. 50 ppm/K max. max. -10 mV/A	at 25 °C (77 °F) Temperature coefficient additional inaccuracy in the voltage mode due to sensor power supply current
Sensor supply	max. 2 A per plug, total max. 8 A	
Sensor connection	2-wire, 3-wire, 3-wire + FE	
Conversion time	1 ms	
Internal resistance	U: 100 kΩ; I: 41.2 Ω	
Reverse polarity protection	Yes	
Short-circuit-proof	Yes	
Response time of the protective circuit	< 50 ms	
Module diagnosis	Yes	
Individual channel diagnosis	No	
Supply		
Supply voltage	20.4V – 28.8V	
Current consumption from system current path I <sub>sys</sub> ,	8 mA	
Current consumption from input current path I <sub>IN</sub>	25 mA + sensor supply current	
General data		
Weight	89 g (3.14 oz)	
For additional general data, refer to the section, <i>General Technical Data for I/O Modules</i> .		

**Overview of the Editable Parameter EP-3164**

Channel	Description	Options	Default
	Frequency suppression	disabled (0) / 50 Hz (1) / 60 Hz (2) / Average over 16 values (3)	disabled
0 ... 3	Measurement range	0 to 20 mA (0) / 4 to 20 mA (1) / 0 V to 10 V (2) / -10 to 10 V (3) / 0 to 5 V (4) / -5 to 5 V (5) / 1 to 5 V (6) / 2 to 10 V (7) / disabled (8)	disabled



## Diagnostic Data EP-3164

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x05
		1		
		2		
		3		
		4	Reserved	0
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	
		4	Power supply fault	
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Channel type	4	0-6	Channel type	0x74
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	0
Number of channels	6		Number of similar channels per module	4
Channel error	7-10	0-31	Reserved	0
Channel 0 error to Channel 31 error	11 to 42	0-7	Reserved	0
Time stamp	43-46		Time stamp [ $\mu$ s] (32 bit)	

Process Data<sup>†</sup> Inputs EP-3164

Byte	Format	Description	Remarks
IB0	Word	AI0	
IB1			
IB2	Word	AI1	
IB3			
IB4	Word	AI2	
IB5			
IB6	Word	AI3	
IB7			

<sup>†</sup> Internal process data mapping with data format "Standard". Depending on the fieldbus specification and the data format of the communicating fieldbus components the bytes and/or words can be reversed during data transfer

Measurement Range EP-3164

Measurement range	Current (I) / Voltage (U)	Decimal (D)	Hexadecimal	Range	Conversion
0 – 20 mA	23.52 mA	32511	0x7EFF	Overloading	D = 27648 × I / 20 I = D × 20 / 27648
	20 mA	27648	0x6C00	Nominal range	
	10 mA	13824	0x3600		
	0 mA	0	0x0000		
4 – 20 mA	22.81 mA	32511	0x7EFF	Overloading	D = 27648 × (I – 4) / 16 I = D × 16 / 27648 + 4
	20 mA	27648	0x6C00	Nominal range	
	12 mA	13824	0x3600		
	4 mA	0	0x0000		
	1.19 mA	-4864	0xED00	Underloading	
0 – 10 V	11.76 V	32511	0x7EFFh	Overloading	D = 27648 × U/10 I = D × 10 / 27648
	10 V	27648	0x6C00	Nominal range	
	5 V	13824	0x3600		
	0 V	0	0x0000		
±10 V	11.76 V	32511	0x7EFF	Overloading	D = 27648 × U / 10 U = D × 10 / 27648
	10 V	27648	0x6C00	Nominal range	
	5 V	13824	0x3600		
	0 V	0	0x0000		
	-5 V	-13824	0xCA00		
	-10 V	-27648	0x9400		
	-11.76 V	-32511	0x8100	Underloading	
2 - 10 V	11.41 V	32511	0x7EFF	Overloading	D = 27648 × (U – 2) / 8 U = D × 8 / 27648 + 2
	10 V	27648	0x6C00	Nominal range	
	6 V	13824	0x3600		
	2 V	0	0x0000		
	0.59 V	-4864	0xED00	Underloading	
1 - 5 V	5.7 V	32511	0x7EFF	Overloading	D = 27648 × (U – 1) / 4 U = D × 4 / 27648 + 1
	5 V	27648	0x6C00	Nominal range	
	3 V	13824	0x3600		
	1 V	0	0x0000		
	0.30 V	-4864	0xED00	Underloading	


Measurement Range EP-3164

Measurement range	Current (I) / Voltage (U)	Decimal (D)	Hexadecimal	Range	Conversion
0 – 5 V	5.88 V	32511	0x7EFF	Overloading	D = 27648 × U/5 I = D × 5 / 27648
	5 V	27648	0x6C00	Nominal range	
	2.5 V	13824	0x3600		
	0 V	0	0x0000		
±5 V	5.88 V	32511	0x7EFF	Overloading	D = 27648 × (U – 1) / 4 U = D × 4 / 27648 + 1
	5 V	27648	0x6C00	Nominal range	
	2.5 V	13824	0x3600		
	0 V	0	0x0000		
	-2.5 V	-13824	0xCA00		
	-5 V	-27648	0x9400		
	-5.88 V	-32511	0x8100	Underloading	
The following applies for all ranges: input value > overload range = 0x7FFF input value < underload range = 0x8000					

## 5.22 Analog Input Module EP- 3264



**Analog Input Module EP-3264**



**Connection Diagram EP-3264**


(left 3-wire sensor with sensor wiring via electronics,  
right: 2-wire sensor with sensor wiring via electronics)

The EP-3264 analog input module can record up to 4 analog sensors with  $\pm 10\text{ V}$ ,  $\pm 5\text{ V}$ ,  $0-10\text{ V}$ ,  $0-5\text{ V}$ ,  $2-10\text{ V}$ ,  $1-5\text{ V}$ ,  $0-20\text{ mA}$  or  $4-20\text{ mA}$ . The resolution is 16 bit per channel. Sensors can be connected to each connector in a 2-wire, 3-wire or 3-wire connection + FE. The measurement range is defined using parameterization. Two status LED are assigned to each channel. The module electronics supply the connected sensors with power from the input current path ( $I_{IN}$ ).


Each sensor output is loadable with 500 mA and protected against overcurrent. The inputs are protected against voltage surges and overcurrent. Voltages that exceed  $\pm 30\text{ V}$  may cause the destruction of the module. As a protection against overcurrent, the module temporarily switches to voltage mode.

The module provides individual channel diagnosis with channel related error messages.

LED Indicators EP-3264

	Module Status	<b>Green:</b> Communication over the system bus <b>Red:</b> Module System Fault or Diagnostic Fault
	1.1	<b>Red:</b> channel error
	1.2	--
	1.3	<b>Red:</b> +24 V short circuit or line break (with current < 1 mA)
	1.4	--
	2.1	<b>Red:</b> channel error
	2.2	--
	2.3	<b>Red:</b> +24 V short circuit or line break (with current < 1 mA)
	2.4	--
	3.1	<b>Red:</b> channel error
	3.2	--
	3.3	<b>Red:</b> +24 V short circuit or line break (with current < 1 mA)
	3.4	--
	4.1	<b>Red:</b> channel error
	4.2	--
	4.3	<b>Red:</b> +24 V short circuit or line break (with current < 1 mA)
	4.4	--

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



Block Diagram EP-3264

**Specifications EP-3264**

System data		
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in the section, <i>Order and Arrangement of the Modules</i> )	
Interface	RSTi-EP I/O communication bus	
System bus transfer rate	48 Mbps	
Inputs		
Number	4	
Input values	1. Voltage (0 ... 5 V, ±5 V, 0 ... 10 V, ±10 V, 1 ... 5 V, 2 ... 10 V) 2. Current (0 ... 20 mA, 4 ... 20 mA)	
Resolution	16 bits	
Accuracy	0.1 % max. 50 ppm/K max. max. –10 mV/A	at 25 °C (77 °F) Temperature coefficient additional inaccuracy in the voltage mode due to sensor power supply current
Sensor supply	max. 0.5 A per plug	
Sensor connection	2-wire, 3-wire, 3-wire + FE	
Conversion time	1 ms	
Internal resistance	U: 100 kΩ; I: 41.2 Ω	
Reverse polarity protection	Yes	
Short-circuit-proof	Yes	
Response time of the protective circuit	< 50 ms	
Module diagnosis	Yes	
Individual channel diagnosis	No	
Supply		
Supply voltage	20.4V – 28.8V	
Current consumption from system current path I <sub>SVS</sub> ,	8 mA	
Current consumption from input current path I <sub>IN</sub>	25 mA + sensor supply current	
General data		
Weight	89 g (3.14 oz)	
For additional general data, refer to the section <i>General Technical Data for I/O Modules</i> .		

**Overview of the Editable Parameter EP-3164**

Channel	Description	Options	Default
	Frequency suppression	disabled (0) / 50 Hz (1) / 60 Hz (2) / Average over 16 values (3)	disabled
0 ... 3	Channel diagnosis	disabled (0) / enabled (1)	disabled
0 ... 3	Diag short circuit 24 V	disabled (0) / enabled (1)	disabled
0 ... 3	Diag line break 24 V	disabled (0) / enabled (1)	disabled
0 ... 3	Measurement range	0 to 20 mA (0) / 4 to 20 mA (1) / 0 V to 10 V (2) / -10 to 10 V (3) / 0 to 5 V (4) / -5 to 5 V (5) / 1 to 5 V (6) / 2 to 10 V (7) / disabled (8)	disabled

**Diagnostic Data EP-3264**

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	
		4	Error	
		5	Power supply fault	
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x05
		1		
		2		
		3		
		4	Channel information available	1
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	
		4	Power supply fault	
		5-7	Reserved	0
Channel type	4	0-6	Channel type	0x74
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	8
Number of channels	6		Number of similar channels per module	4
Channel error	7	0	Error at channel 0	
		1	Error at channel 1	
		2	Error at channel 2	
		3	Error at channel 3	
		4-7	Reserved	0
Channel error	8	8-15	Reserved	0
Channel error	9	16-23	Reserved	0
Channel error	10	24-31	Reserved	0

**Diagnostic Data EP-3264**

Name	Bytes	Bit	Description	Default
Channel 0 error	11	0	Parameter error	
		1	Overload	
		2	Line break sensor supply	
		3	Fuse blown	
		4	Line break signal	
		5	Reserved	0
		6	Lower limit exceeded	
		7	Upper limit exceeded	
Channel 1 error	12	0	Parameter Error	
		1	Overload	
		2	Line break sensor supply	
		3	Fuse blown	
		4	Line break signal	
		5	Reserved	0
		6	Lower limit exceeded	
		7	Upper limit exceeded	
Channel 2 error	13	0	Parameter Error	
		1	Overload	
		2	Line break sensor supply	
		3	Fuse blown	
		4	Line break signal	
		5	Reserved	0
		6	Lower limit exceeded	
		7	Upper limit exceeded	
Channel 2 error	14	0	Parameter Error	
		1	Overload	
		2	Line break sensor supply	
		3	Fuse blown	
		4	Line break signal	
		5	Reserved	0
		6	Lower limit exceeded	
		7	Upper limit exceeded	
Channel 4 error to Channel 31 error	15 - 42	0 - 7	Reserved	0
Time stamp	43-46		Time stamp [ $\mu$ s] (32 bit)	



Process Data<sup>†</sup> Inputs EP-3264

Byte	Format	Description	Remarks
IB0	Word	AI0	
IB1			
IB2	Word	AI1	
IB3			
IB4	Word	AI2	
IB5			
IB6	Word	AI3	
IB7			

<sup>†</sup> Internal process data mapping with data format "Standard". Depending on the fieldbus specification and the data format of the communicating fieldbus components the bytes and/or words can be reversed during data transfer

Measurement Range EP-3264

Measurement range	Current (I) / Voltage (U)	Decimal (D)	Hexadecimal	Range	Conversion
0 – 20 mA	23.52 mA	32511	0x7EFF	Overloading	D = 27648 × I / 20 I = D × 20 / 27648
	20 mA	27648	0x6C00	Nominal range	
	10 mA	13824	0x3600		
	0 mA	0	0x0000		
4 – 20 mA	22.81 mA	32511	0x7EFF	Overloading	D = 27648 × (I – 4) / 16 I = D × 16 / 27648 + 4
	20 mA	27648	0x6C00	Nominal range	
	12 mA	13824	0x3600		
	4 mA	0	0x0000		
	1.19 mA	-4864	0xED00	Underloading	
0 – 10 V	11.76 V	32511	0x7EFFh	Overloading	D = 27648 × U/10 I = D × 10 / 27648
	10 V	27648	0x6C00	Nominal range	
	5 V	13824	0x3600		
	0 V	0	0x0000		
±10 V	11.76 V	32511	0x7EFF	Overloading	D = 27648 × U / 10 U = D × 10 / 27648
	10 V	27648	0x6C00	Nominal range	
	5 V	13824	0x3600		
	0 V	0	0x0000		
	-5 V	-13824	0xCA00		
	-10 V	-27648	0x9400		
	-11.76 V	-32511	0x8100	Underloading	
2 - 10 V	11.41 V	32511	0x7EFF	Overloading	D = 27648 × (U – 2) / 8 U = D × 8 / 27648 + 2
	10 V	27648	0x6C00	Nominal range	
	6 V	13824	0x3600		
	2 V	0	0x0000		
	0.59 V	-4864	0xED00	Underloading	
1 - 5 V	5.7 V	32511	0x7EFF	Overloading	D = 27648 × (U – 1) / 4 U = D × 4 / 27648 + 1
	5 V	27648	0x6C00	Nominal range	
	3 V	13824	0x3600		
	1 V	0	0x0000		
	0.30 V	-4864	0xED00	Underloading	


Measurement Range EP-3264

Measurement range	Current (I) / Voltage (U)	Decimal (D)	Hexadecimal	Range	Conversion
0 – 5 V	5.88 V	32511	0x7EFF	Overloading	D = 27648 x U/5 I = D x 5 / 27648
	5 V	27648	0x6C00	Nominal range	
	2.5 V	13824	0x3600		
	0 V	0	0x0000		
±5 V	5.88 V	32511	0x7EFF	Overloading	D = 27648 x (U – 1) / 4 U = D x 4 / 27648 + 1
	5 V	27648	0x6C00	Nominal range	
	2.5 V	13824	0x3600		
	0 V	0	0x0000		
	-2.5 V	-13824	0xCA00		
	-5 V	-27648	0x9400		
	-5.88 V	-32511	0x8100	Underloading	
The following applies for all ranges: input value > overload range = 0x7FFF input value < underload range = 0x8000					

## 5.23 Analog Input Module EP- 3124



**Analog Input Module EP-3124**




**Connection Diagram EP-3124**

(left: 3/4-wire sensor with sensor wiring via electronics,  
right: 2-wire sensor with sensor wiring via electronics)


The analog input module EP-3124 can record up to 4 analog sensors with  $\pm 10\text{ V}$ ,  $\pm 5\text{ V}$ ,  $0\text{--}10\text{ V}$ ,  $0\text{--}5\text{ V}$ ,  $2\text{--}10\text{ V}$ ,  $1\text{--}5\text{ V}$ ,  $0\text{--}20\text{ mA}$  or  $4\text{--}20\text{ mA}$ . The resolution is 12 bit per channel. Sensors can be connected to each connector in a 2-wire, 3-wire or 3-wire connection + FE. The measurement range is defined using parameterization. A status LED is assigned to each channel. The module electronics supply the connected sensors with power from the input current path ( $I_{IN}$ ).

The inputs are protected against voltage surges and overcurrent. Voltages that exceed  $\pm 30\text{ V}$  may cause the destruction of the module. As a protection against overcurrent, the module temporarily switches to voltage mode.

## LED Indicators EP-3124

	Module Status	<b>Green:</b> Communication over the system bus <b>Red:</b> Module System Fault or Diagnostic Fault
	1.1	<b>Red:</b> channel error
	1.2	--
	1.3	--
	1.4	--
	2.1	<b>Red:</b> channel error
	2.2	--
	2.3	--
	2.4	--
	3.1	<b>Red:</b> channel error
	3.2	--
	3.3	--
	3.4	--
	4.1	<b>Red:</b> channel error
	4.2	--
	4.3	--
	4.4	--

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



Block Diagram EP-3124

**Specifications EP-3124**

System data		
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in the section, <i>Order and Arrangement of the Modules</i> )	
Interface	RSTi-EP I/O communication bus	
System bus transfer rate	48 Mbps	
Inputs		
Number	4	
Input values	1. Voltage (0 ... 5 V, ±5 V, 0 ... 10 V, ±10 V, 1 ... 5 V, 2 ... 10 V) 2. Current (0 ... 20 mA, 4 ... 20 mA)	
Resolution	12 bits	
Accuracy	0.25 % max. 50 ppm/K max. max. –10 mV/A	at 25 °C (77 °F) Temperature coefficient additional inaccuracy in the voltage mode due to sensor power supply current
Sensor supply	max. 2 A per plug, total max. 8 A	
Sensor connection	2-wire, 3-wire, 3-wire + FE	
Conversion time	1 ms	
Internal resistance	U: 100 kΩ; I: 41.2 Ω	
Reverse polarity protection	Yes	
Short-circuit-proof	Yes	
Response time of the protective circuit	< 50 ms	
Module diagnosis	Yes	
Individual channel diagnosis	No	
Supply		
Supply voltage	20.4V – 28.8V	
Current consumption from system current path I <sub>sys</sub> ,	8 mA	
Current consumption from input current path I <sub>in</sub>	25 mA + sensor supply current	
General data		
Weight	87 g (3.07 oz)	
For additional general data, refer to the section <i>General Technical Data for I/O Modules</i> .		

**Overview of the Editable Parameter EP-3124**

Channel	Description	Options	Default
	Frequency suppression	disabled (0) / 50 Hz (1) / 60 Hz (2) / Average over 16 values (3)	disabled
0 ... 3	Measurement range	0 to 20 mA (0) / 4 to 20 mA (1) / 0 V to 10 V (2) / -10 to 10 V (3) / 0 to 5 V (4) / -5 to 5 V (5) / 1 to 5 V (6) / 2 to 10 V (7) / disabled (8)	disabled

Diagnostic Data EP-3124

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x05
		1		
		2		
		3		
		4	Reserved	0
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	
		4	Power supply fault	
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Channel type	4	0-6	Channel type	0x74
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	0
Number of channels	6		Number of similar channels per module	4
Channel error	7-10	0-31	Reserved	0
Channel 0 error to Channel 31 error	11 to 42	0-7	Reserved	0
Time stamp	43-46		Time stamp [ $\mu$ s] (32 bit)	

Process Data<sup>†</sup> Inputs EP-3124

Byte	Format	Description	Remarks
IB0	Word	AI0	
IB1			
IB2	Word	AI1	
IB3			
IB4	Word	AI2	
IB5			
IB6	Word	AI3	
IB7			

<sup>†</sup> Internal process data mapping with data format "Standard". Depending on the fieldbus specification and the data format of the communicating fieldbus components the bytes and/or words can be reversed during data transfer.

Measurement Range EP-3124


Measurement range	Current (I) / Voltage (U)	Decimal (D)	Hexadecimal	Range	Conversion
0 – 20 mA	23.52 mA	32511	0x7EFF	Overloading	D = 27648 × I / 20 I = D × 20 / 27648
	20 mA	27648	0x6C00	Nominal range	
	10 mA	13824	0x3600		
	0 mA	0	0x0000		
4 – 20 mA	22.81 mA	32511	0x7EFF	Overloading	D = 27648 × (I – 4) / 16 I = D × 16 / 27648 + 4
	20 mA	27648	0x6C00	Nominal range	
	12 mA	13824	0x3600		
	4 mA	0	0x0000		
	1.19 mA	-4864	0xED00	Underloading	
0 – 10 V	11.76 V	32511	0x7EFFh	Overloading	D = 27648 × U/10 I = D × 10 / 27648
	10 V	27648	0x6C00	Nominal range	
	5 V	13824	0x3600		
	0 V	0	0x0000		
±10 V	11.76 V	32511	0x7EFF	Overloading	D = 27648 × U / 10 U = D × 10 / 27648
	10 V	27648	0x6C00	Nominal range	
	5 V	13824	0x3600		
	0 V	0	0x0000		
	-5 V	-13824	0xCA00		
	-10 V	-27648	0x9400		
	-11.76 V	-32511	0x8100	Underloading	
2 - 10 V	11.41 V	32511	0x7EFF	Overloading	D = 27648 × (U – 2) / 8 U = D × 8 / 27648 + 2
	10 V	27648	0x6C00	Nominal range	
	6 V	13824	0x3600		
	2 V	0	0x0000		
	0.59 V	-4864	0xED00	Underloading	
1 - 5 V	5.7 V	32511	0x7EFF	Overloading	D = 27648 × (U – 1) / 4 U = D × 4 / 27648 + 1
	5 V	27648	0x6C00	Nominal range	
	3 V	13824	0x3600		
	1 V	0	0x0000		
	0.30 V	-4864	0xED00	Underloading	

Measurement Range EP-3124


Measurement range	Current (I) / Voltage (U)	Decimal (D)	Hexadecimal	Range	Conversion
0 – 5 V	5.88 V	32511	0x7EFF	Overloading	D = 27648 x U/5 I = D x 5 / 27648
	5 V	27648	0x6C00	Nominal range	
	2.5 V	13824	0x3600		
	0 V	0	0x0000		
±5 V	5.88 V	32511	0x7EFF	Overloading	D = 27648 x (U – 1) / 4 U = D x 4 / 27648 + 1
	5 V	27648	0x6C00	Nominal range	
	2.5 V	13824	0x3600		
	0 V	0	0x0000		
	-2.5 V	-13824	0xCA00		
	-5 V	-27648	0x9400		
	-5.88 V	-32511	0x8100	Underloading	
The following applies for all ranges: input value > overload range = 0x7FFF input value < underload range = 0x8000					



## 5.24 Analog Input Module EP-3368



**Analog Input Module EP-3368**



**Connection Diagram EP-3368**

The analog input module EP-3368 can detect up to 8 analog sensors with 0-20 mA or 4-20 mA. The resolution is 16 bit per channel. Sensors can be connected to each connector in a 2-wire, 3-wire or 3-wire connection + FE (IDC). The measurement range is defined using parameterization. A status LED is assigned to each channel. The module electronics supply the connected sensors with power from the input current path ( $I_{IN}$ ).


The inputs are protected against voltage surges and overcurrent. Voltages that exceed  $\pm 30$  V may cause the destruction of the module. The inputs are protected against overcurrent by a self-resetting fuse.

**Note:** This module is released with UL Ordinary Locations certification. The class 1 Division 2 certification for this module is in process.

LED Indicators EP-3368

Module Status		Green: Communication over the system bus Red: Module System Fault or Diagnostic Fault
1.1		Red: channel error
2.1		Red: channel error
3.1		Red: channel error
4.1		Red: channel error
5.1		Red: channel error
6.1		Red: channel error
7.1		Red: channel error
8.1		Red: channel error

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



Block Diagram EP-3368

**Specifications EP-3368**

System data		
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in the section, <i>Order and Arrangement of the Modules</i> )	
Interface	RSTi-EP I/O communication bus	
System bus transfer rate	48 Mbps	
Inputs		
Number	8	
Input values	Current input (0 - 20 mA, 4 - 20 mA)	
Resolution	16 bits	
Accuracy	max. 0.1 % FSR ±50 ppm/K max.	at 25 °C (77 °F) Temperature coefficient
Sensor supply	max. 125 mA per channel; channel 0 - 3 and 4 - 7 respectively are fused in combination	
Sensor connection	2-wire, 3-wire, 3-wire + FE	
Conversion time	1 ms	
Internal resistance	approx. 45 Ω	
Reverse polarity protection	Yes	
Short-circuit-proof	Yes	
Response time of the protective circuit	< 0.1 s with short-circuit to +24 V	
Reset time	Temperature-dependent: < 30 s at 20°C (-4 °F)	
Module diagnosis	Yes	
Individual channel diagnosis	No	
Supply		
Supply voltage	20.4V – 28.8V	
Current consumption from system current path I <sub>sys</sub> ,	8 mA	
Current consumption from input current path I <sub>in</sub>	20 mA + load	
Connection data		
Type of connection	Insulation Displacement Connection (IDC)	
Line connection cross-section	Single-wired, Fine-wired	0.14 - 0.35 mm² (26 – 22 guage)
General data		
Weight	90 g (3.17 oz)	
For additional general data, refer to the section <i>General Technical Data for I/O Modules</i> .		

**Overview of the Editable Parameter EP-3368**

Channel	Description	Options	Default
	Frequency suppression	disabled (0) / 50 Hz (1) / 60 Hz (2) / Average over 16 values (3)	disabled
0 - 7	Measurement range	0 to 20 mA (0) / 4 to 20 mA (1) / disabled (3)	disabled

Diagnostic Data EP-3368

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x05
		1		
		2		
		3		
		4	Reserved	0
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	0
		4	Power supply fault	0
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Channel type	4	0-6	Channel type	0x74
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	0
Number of channels	6		Number of similar channels per module	8
Channel error	7-10	0-31	Reserved	0
Channel 0 error to Channel 31 error	11 to 42	0-7	Reserved	0
Time stamp	43-46		Time stamp [ $\mu$ s] (32 bit)	

**Process Data<sup>†</sup> Inputs EP-3368**


Byte	Format	Description	Remarks
IB0	Word	AI0	
IB1			
IB2	Word	AI1	
IB3			
IB4	Word	AI2	
IB5			
IB6	Word	AI3	
IB7			
IB8	Word	AI4	
IB9			
IB10	Word	AI5	
IB11			
IB12	Word	AI6	
IB13			
IB14	Word	AI7	
IB15			

<sup>†</sup> Internal process data mapping with data format *Standard*. Depending on the fieldbus specification and the data format of the communicating fieldbus components the bytes and/or words can be reversed during data transfer.


**Measurement Range EP-3368**

Measurement range	Current (I) / Voltage (U)	Decimal (D)	Hexadecimal	Range	Conversion
0 – 20 mA	23.52 mA	32511	0x7EFF	Overloading	D = 27648 × I / 20 I = D × 20 / 27648
	20 mA	27648	0x6C00	Nominal range	
	10 mA	13824	0x3600		
	0 mA	0	0x0000		
4 – 20 mA	22.81 mA	32511	0x7EFF	Overloading	D = 27648 × (I – 4) / 16 I = D × 16 / 27648 + 4
	20 mA	27648	0x6C00	Nominal range	
	12 mA	13824	0x3600		
	4 mA	0	0x0000		
	1.19 mA	-4864	0xED00	Underloading	
The following applies for all ranges: input value > overload range = 0x7FFF input value < underload range = 0x8000					

## 5.25 Analog Input Module EP-3468



Analog Input Module EP-3468



Connection Diagram EP-3468

The analog input module EP-3468 can detect up to 8 analog sensors with 0-20 mA or 4-20 mA. The resolution is 16 bit per channel. Sensors can be connected to each connector in a 2-wire, 3-wire or 3-wire connection + FE (IDC). The measurement range is defined using parameterization. A status LED is assigned to each channel. The module electronics supply the connected sensors with power from the input current path ( $I_{IN}$ ).

The inputs are protected against voltage surges and overcurrent. Voltages that exceed  $\pm 30$  V may cause the destruction of the module. The inputs are protected against overcurrent by a self-resetting fuse.


The module provides individual channel diagnosis with channel related error messages.

**Note:** This module is released with UL Ordinary Locations certification. The class 1 Division 2 certification for this module is in process.

LED Indicators EP-3468

Module Status		Green: Communication over the system bus Red: Module System Fault or Diagnostic Fault
1.1		Red: channel error
2.1		Red: channel error
3.1		Red: channel error
4.1		Red: channel error
5.1		Red: channel error
6.1		Red: channel error
7.1		Red: channel error
8.1		Red: channel error

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



Block Diagram EP-3468

**Specifications EP-3468**

System data		
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in the section, <i>Order and Arrangement of the Modules</i> )	
Interface	RSTi-EP I/O communication bus	
System bus transfer rate	48 Mbps	
Inputs		
Number	8	
Input values	Current input (0 - 20 mA, 4 - 20 mA)	
Resolution	16 bits	
Accuracy	max. 0.1 % FSR ±50 ppm/K max.	at 25 °C (77 °F) Temperature coefficient
Sensor supply	max. 125 mA per channel; channel 0 - 3 and 4 - 7 respectively are fused in combination	
Sensor connection	2-wire, 3-wire, 3-wire + FE	
Conversion time	1 ms	
Internal resistance	approx. 45 Ω	
Reverse polarity protection	Yes	
Short-circuit-proof	Yes	
Response time of the protective circuit	< 0.1 s with short-circuit to +24 V	
Reset time	Temperature-dependent: < 30 s at 20°C (-4 °F)	
Module diagnosis	Yes	
Individual channel diagnosis	No	
Supply		
Supply voltage	20.4V – 28.8V	
Current consumption from system current path I <sub>sys</sub> ,	8 mA	
Current consumption from input current path I <sub>in</sub>	20 mA + load	
Connection data		
Type of connection	Insulation Displacement Connection (IDC)	
Line connection cross-section	Single-wired, Fine-wired	0.14 - 0.35 mm² (26 – 22 guage)
General data		
Weight	90 g (3.17 oz)	
For additional general data, refer to the section <i>General Technical Data for I/O Modules</i> .		



Overview of the Editable Parameter EP-3468

Channel	Description	Options	Default
	Frequency suppression	disabled (0) / 50 Hz (1) / 60 Hz (2) / Average over 16 values (3)	disabled
0 - 7	Channel diagnostics	disabled (0) / enabled (1)	disabled
0 - 7	Diag short circuit 24 V	disabled (0) / enabled (1)	Disabled
0 - 7	Measurement range	0 to 20 mA (0) / 4 to 20 mA (1) / disabled (3)	disabled

Process Data<sup>†</sup> Inputs EP-3468

Byte	Format	Description	Remarks
IB0	Word	AI0	
IB1			
IB2	Word	AI1	
IB3			
IB4	Word	AI2	
IB5			
IB6	Word	AI3	
IB7			
IB8	Word	AI4	
IB9			
IB10	Word	AI5	
IB11			
IB12	Word	AI6	
IB13			
IB14	Word	AI7	
IB15			

<sup>†</sup> Internal process data mapping with data format *Standard*. Depending on the fieldbus specification and the data format of the communicating fieldbus components the bytes and/or words can be reversed during data transfer.

Diagnostic Data EP-3468

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x05
		1		
		2		
		3		
		4	Channel information available	1
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	
		4	Power supply fault	
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Channel type	4	0-6	Channel type	0x74
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	8
Number of channels	6		Number of similar channels per module	8
Channel error	7	0	Error at channel 0	0
			Error at channel 1	0
			Error at channel 2	0
			Error at channel 3	0
			Error at channel 4	0
			Error at channel 5	0
			Error at channel 6	0
			Error at channel 7	0
			Reserved	0

**Diagnostic Data EP-3468**

Name	Bytes	Bit	Description	Default
Channel 0 error to Channel 7 error	0	0	Parameter Error	0
		1	Overload	0
		2	Reserved	0
		3	Fuse blown	0
		4	Line break	0
		5	Reserved	0
		6	Lower limit exceeded	0
		7	Upper limit exceeded	0
Channel 8 error to Channel 31 error	19 - 42	0 - 7	Reserved	0
Time stamp	43-46		Time stamp [μs] (32 bit)	


**Measurement Range EP-3468**

Measurement range	Current (I) / Voltage (U)	Decimal (D)	Hexadecimal	Range	Conversion
0 – 20 mA	23.52 mA	32511	0x7EFF	Overloading	D = 27648 x I / 20 I = D x 20 / 27648
	20 mA	27648	0x6C00	Nominal range	
	10 mA	13824	0x3600		
	0 mA	0	0x0000		
4 – 20 mA	22.81 mA	32511	0x7EFF	Overloading	D = 27648 x (I – 4) / 16 I = D x 16 / 27648 + 4
	20 mA	27648	0x6C00	Nominal range	
	12 mA	13824	0x3600		
	4 mA	0	0x0000		
	1.19 mA	-4864	0xED00	Underloading	
The following applies for all ranges: input value > overload range = 0x7FFF input value < underload range = 0x8000					

## 5.26 Analog Output Module EP-4164



Analog Output Module EP-4164



Connection Diagram EP-4164


The analog output module EP-4164 can control up to four analog actuators with  $\pm 10$  V,  $\pm 5$  V, 0-10 V, 0-5 V, 2-10 V, 1-5 V, 0-20 mA or 4-20 mA. The resolution is 16 bit per channel. An output can be connected to each connector, the internal switching is carried out automatically. The output range is defined using parameterization. A status LED is assigned to each channel. The outputs are supplied with power from the output current path ( $I_{OUT}$ ).




### Caution

The outputs as well as the sense-lines of the AO modules must not be used as power outputs.

LED Indicators EP-4164

	Module Status	<b>Green:</b> Communication over the system bus <b>Red:</b> Module System Fault or Diagnostic Fault
	1.1	<b>Red:</b> Channel 0 at voltage output: overload short-circuit, at current output: shunt resistance too high or line break detected
	2.1	<b>Red:</b> Channel 1 at voltage output: overload short-circuit, at current output: shunt resistance too high or line break detected
	3.1	<b>Red:</b> Channel 2 at voltage output: overload short-circuit, at current output: shunt resistance too high or line break detected
	4.1	<b>Red:</b> Channel 3 at voltage output: overload short-circuit, at current output: shunt resistance too high or line break detected

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



Block Diagram EP-4164

**Specifications EP-4164**

<b>System data</b>	
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in the section, <i>Order and Arrangement of the Modules</i> )
Interface	RSTi-EP I/O communication bus
System bus transfer rate	48 Mbps
<b>Inputs</b>	
Number	4
Output levels	1. Voltage (0 – 5 V, $\pm 5$ V, 0 – 10 V, $\pm 10$ V, 1 – 5 V, 2 – 10 V) 2. Current (0 – 20 mA, 4 – 20 mA)
Response time	1 ms for 4 channels
Resolution	16 bits
Accuracy	0.1 % FSR max., 0.05 % FSR typ.
Temperature coefficient	20 ppm voltage / 31 ppm current measurement / K
Max. error between $T_{\min}$ and $T_{\max}$	$\pm 220$ ppm FSR
Monotony	Yes
Crosstalk between the channels	$\pm 0.001$ % FSR max.
Repeat accuracy	$< \pm 1$ mV eff.
Output ripple	max. 0.001 %
Voltage load resistance	$\geq 1$ k $\Omega$ (at $> 50^{\circ}\text{C}$ (122 $^{\circ}\text{F}$ ) max ambient temperature, total sensor current of 10 mA per channel but 25 mA per module)
Current load resistance	$\leq 600$ $\Omega$
Actuator connection	2-wire (current and voltage; automatic detection), 4-wire (voltage)
Short-circuit-proof	Yes
Module diagnosis	Yes
Individual channel diagnosis	No
Substitute value	Yes
<b>Supply</b>	
Supply voltage	20.4V – 28.8V
Current consumption from system current path $I_{\text{SYS}}$	8 mA
Current consumption from output current path $I_{\text{OUT}}$	85 mA
<b>General data</b>	
Weight	83 g (2.93 oz)
For additional general data, refer to the section, <i>General Technical Data for I/O Modules</i> .	

**Overview of the Editable Parameter EP-4164**

Channel	Description	Options	Default
0 - 3	Output range	0 to 20 mA (0) / 4 to 20 mA (1) / 0 V to 10 V (2) / -10 to 10 V (3) / 0 to 5 V (4) / -5 to 5 V (5) / 1 to 5 V (6) / 2 to 10 V (7) / disabled (8)	disabled
0 - 3	Substitute value	Depending on the channels data format (S5/S7	0

**Diagnostic Data EP-4164**

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x05
		1		
		2		
		3		
		4	Reserved	0
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	
		4	Power supply fault	
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Channel type	4	0-6	Channel type	0x73
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	0
Number of channels	6		Number of similar channels per module	4
Channel error	7-10	0-31	Reserved	0
Channel 0 error to Channel 31 error	11 to 42	0-7	Reserved	0
Time stamp	43-46		Time stamp [ $\mu$ s] (32 bit)	

Process Data<sup>†</sup> Inputs EP-4164

Byte	Format	Description	Remarks
QB0	Word	AO0	
QB1			
QB2	Word	AO1	
QB3			
QB4	Word	AO2	
QB5			
QB6	Word	AO3	
QB7			

<sup>†</sup> Internal process data mapping with data format "Standard". Depending on the fieldbus specification and the data format of the communicating fieldbus components the bytes and/or words can be reversed during data transfer.

Value Range<sup>†</sup> EP-4164


Measurement range	Current (I) / Voltage (U)	Decimal (D)	Hexadecimal	Range	Conversion
0 – 20 mA	23.52 mA	32511	0x7EFF	Overloading	D = 27648 × I / 20 I = D × 20 / 27648
	20 mA	27648	0x6C00	Nominal range	
	10 mA	13824	0x3600		
	0 mA	0	0x0000		
4 – 20 mA	22.81 mA	32511	0x7EFF	Overloading	D = 27648 × (I – 4) / 16 I = D × 16 / 27648 + 4
	20 mA	27648	0x6C00	Nominal range	
	12 mA	13824	0x3600		
	4 mA	0	0x0000		
	1.19 mA	-4864	0xED00	Underloading	
0 – 10 V	11.76 V	32511	0x7EFFh	Overloading	D = 27648 × U/10 I = D × 10 / 27648
	10 V	27648	0x6C00	Nominal range	
	5 V	13824	0x3600		
	0 V	0	0x0000		
	0 V	0	0x0000		
±10 V	11.76 V	32511	0x7EFF	Overloading	D = 27648 × U / 10 U = D × 10 / 27648
	10 V	27648	0x6C00	Nominal range	
	5 V	13824	0x3600		
	0 V	0	0x0000		
	-5 V	-13824	0xCA00		
	-10 V	-27648	0x9400		
	-11.76 V	-32511	0x8100	Underloading	
2 - 10 V	11.41 V	32511	0x7EFF	Overloading	D = 27648 × (U – 2) / 8 U = D × 8 / 27648 + 2
	10 V	27648	0x6C00	Nominal range	
	6 V	13824	0x3600		
	2 V	0	0x0000		
	0.59 V	-4864	0xED00	Underloading	




Value Range<sup>†</sup> EP-4164

Measurement range	Current (I) / Voltage (U)	Decimal (D)	Hexadecimal	Range	Conversion
1 - 5 V	5.7 V	32511	0x7EFF	Overloading	$D = 27648 \times (U - 1) / 4$ $U = D \times 4 / 27648 + 1$
	5 V	27648	0x6C00	Nominal range	
	3 V	13824	0x3600		
	1 V	0	0x0000		
	0.30 V	-4864	0xED00	Underloading	
0 - 5 V	5.88 V	32511	0x7EFF	Overloading	$D = 27648 \times U / 5$ $I = D \times 5 / 27648$
	5 V	27648	0x6C00	Nominal range	
	2.5 V	13824	0x3600		
	0 V	0	0x0000		
±5 V	5.88 V	32511	0x7EFF	Overloading	$D = 27648 \times (U - 1) / 4$ $U = D \times 4 / 27648 + 1$
	5 V	27648	0x6C00	Nominal range	
	2.5 V	13824	0x3600		
	0 V	0	0x0000		
	-2.5 V	-13824	0xCA00		
	-5 V	-27648	0x9400		
	-5.88 V	-32511	0x8100	Underloading	
† If the process value is beyond the valid value range, the corresponding channel releases 0 V and 0 mA respectively The following applies for all ranges: value > overload range = output deactivated value < underload range = output deactivated					

## 5.27 Analog Output Module EP-4264



Analog Output Module EP-4264



Connection Diagram EP-4264

The analog output module EP-4264 can control up to four analog actuators with  $\pm 10$  V,  $\pm 5$  V, 0-10 V, 0-5 V, 2-10 V, 1-5 V, 0-20 mA or 4-20 mA. The resolution is 16 bit per channel. An output can be connected to each connector, the internal switching is carried out automatically. The output range is defined using parameterization. A status LED is assigned to each channel. The outputs are supplied with power from the output current path ( $I_{OUT}$ ).


The module provides individual channel diagnosis with channel related error messages.




### Caution

The outputs as well as the sense-lines of the AO modules must not be used as power outputs.

LED Indicators EP-4264

	Module Status	<b>Green:</b> Communication over the system bus <b>Red:</b> Module System Fault or Diagnostic Fault
	1.1	<b>Red:</b> Channel 0 at voltage output: overload short-circuit, at current output: shunt resistance too high or line break detected
	2.1	<b>Red:</b> Channel 1 at voltage output: overload short-circuit, at current output: shunt resistance too high or line break detected
	3.1	<b>Red:</b> Channel 2 at voltage output: overload short-circuit, at current output: shunt resistance too high or line break detected
	4.1	<b>Red:</b> Channel 3 at voltage output: overload short-circuit, at current output: shunt resistance too high or line break detected

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



Block Diagram EP-4264

**Specifications EP-4264**

<b>System data</b>	
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in the section, <i>Order and Arrangement of the Modules</i> )
Interface	RSTi-EP I/O communication bus
System bus transfer rate	48 Mbps
<b>Inputs</b>	
Number	4
Output levels	1. Voltage (0 – 5 V, $\pm 5$ V, 0 – 10 V, $\pm 10$ V, 1 – 5 V, 2 – 10 V) 2. Current (0 – 20 mA, 4 – 20 mA)
Response time	1 ms for 4 channels
Resolution	16 bits
Accuracy	0.1 % FSR max., 0.05 % FSR typ.
Temperature coefficient	20 ppm voltage / 31 ppm current measurement / K
Max. error between $T_{\min}$ and $T_{\max}$	$\pm 220$ ppm FSR
Monotony	Yes
Crosstalk between the channels	$\pm 0.001$ % FSR max.
Repeat accuracy	$< \pm 1$ mV eff.
Output ripple	max. 0.001 %
Voltage load resistance	$\geq 1$ k $\Omega$ (at $> 50^{\circ}\text{C}$ (122 $^{\circ}\text{F}$ ) max ambient temperature, total sensor current of 10 mA per channel but 25 mA per module)
Current load resistance	$\leq 600$ $\Omega$
Actuator connection	2-wire (current and voltage; automatic detection), 4-wire (voltage)
Short-circuit-proof	Yes
Module diagnosis	Yes
Individual channel diagnosis	Yes
Substitute value	Yes
<b>Supply</b>	
Supply voltage	20.4V – 28.8V
Current consumption from system current path $I_{\text{SYS}}$	8 mA
Current consumption from output current path $I_{\text{OUT}}$	85 mA
<b>General data</b>	
Weight	98 g (3.47 oz)
For additional general data, refer to the section, <i>General Technical Data for I/O Modules</i> .	

## Overview of the Editable Parameter EP-4264

Channel	Description	Options	Default
0 - 3	Output range	0 to 20 mA (0) / 4 to 20 mA (1) / 0 V to 10 V (2) / -10 to 10 V (3) / 0 to 5 V (4) / -5 to 5 V (5) / 1 to 5 V (6) / 2 to 10 V (7) / disabled (8)	disabled
0 - 3	Substitute value	Depending on the channels data format (S5/S7)	0
0 - 3	Channel diagnosis	disabled (0) / enabled (1)	disabled

## Diagnostic Data EP-4264

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	0
		4	Error	
		5	Reserved	0
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x05
		1		
		2		
		3		
		4	Channel information available	1
		5-7	Reserved	0
Error byte 2	2	0-7	Reserved	0
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	
		4	Power supply fault	
		5	Reserved	0
		6	Process alarm lost	
		7	Reserved	0
Channel type	4	0-6	Channel type	0x73
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	8
Number of channels	6		Number of similar channels per module	4
Channel error	7	0	Error at channel 0	
		1	Error at channel 1	
		2	Error at channel 2	
		3	Error at channel 3	
		4-7	Reserved	0
	8-10	0-31	Reserved	0

**Diagnostic Data EP-4264**

Name	Bytes	Bit	Description	Default
Error Channel 0	11	0	Parameter Error	
		1	Overtemperature	
		2	Overload	
		3	Error	
		4	Line break	
		5-7	Reserved	0
Error channel 1	12	0	Parameter Error	
		1	Overtemperature	
		2	Overload	
		3	Error	
		4	Line break	
		5-7	Reserved	0
Error channel 2	13	0	Parameter Error	
		1	Overtemperature	
		2	Overload	
		3	Error	
		4	Line break	
		5-7	Reserved	0
Error channel 3	14	0	Parameter Error	
		1	Overtemperature	
		2	Overload	
		3	Error	
		4	Line break	
		5-7	Reserved	0
Channel 4 error to Channel 31 error	15-42	0-7	Reserved	0
Time stamp	43-46		Time stamp [μs] (32 bit)	

**Process Data† Inputs EP-4264**

Byte	Format	Description	Remarks
QB0	Word	AO0	
QB1			
QB2	Word	AO1	
QB3			
QB4	Word	AO2	
QB5			
QB6	Word	AO3	
QB7			
† Internal process data mapping with data format <i>Standard</i> . Depending on the fieldbus specification and the data format of the communicating fieldbus components the bytes and/or words can be reversed during data transfer			

Value Range† EP-4264


Measurement range	Current (I) / Voltage (U)	Decimal (D)	Hexadecimal	Range	Conversion
0 – 20 mA	23.52 mA	32511	0x7EFF	Overloading	D = 27648 × I / 20 I = D × 20 / 27648
	20 mA	27648	0x6C00	Nominal range	
	10 mA	13824	0x3600		
	0 mA	0	0x0000		
4 – 20 mA	22.81 mA	32511	0x7EFF	Overloading	D = 27648 × (I – 4) / 16 I = D × 16 / 27648 + 4
	20 mA	27648	0x6C00	Nominal range	
	12 mA	13824	0x3600		
	4 mA	0	0x0000		
	1.19 mA	-4864	0xED00	Underloading	
0 – 10 V	11.76 V	32511	0x7EFFh	Overloading	D = 27648 × U/10 I = D × 10 / 27648
	10 V	27648	0x6C00	Nominal range	
	5 V	13824	0x3600		
	0 V	0	0x0000		
±10 V	11.76 V	32511	0x7EFF	Overloading	D = 27648 × U / 10 U = D × 10 / 27648
	10 V	27648	0x6C00	Nominal range	
	5 V	13824	0x3600		
	0 V	0	0x0000		
	-5 V	-13824	0xCA00		
	-10 V	-27648	0x9400		
	-11.76 V	-32511	0x8100	Underloading	
2 - 10 V	11.41 V	32511	0x7EFF	Overloading	D = 27648 × (U – 2) / 8 U = D × 8 / 27648 + 2
	10 V	27648	0x6C00	Nominal range	
	6 V	13824	0x3600		
	2 V	0	0x0000		
	0.59 V	-4864	0xED00	Underloading	
1 - 5 V	5.7 V	32511	0x7EFF	Overloading	D = 27648 × (U – 1) / 4 U = D × 4 / 27648 + 1
	5 V	27648	0x6C00	Nominal range	
	3 V	13824	0x3600		
	1 V	0	0x0000		
	0.30 V	-4864	0xED00	Underloading	
0 – 5 V	5.88 V	32511	0x7EFF	Overloading	D = 27648 × U/5 I = D × 5 / 27648
	5 V	27648	0x6C00	Nominal range	
	2.5 V	13824	0x3600		
	0 V	0	0x0000		
2 - 10 V	11.41 V	32511	0x7EFF	Overloading	D = 27648 × (U – 2) / 8 U = D × 8 / 27648 + 2
	10 V	27648	0x6C00	Nominal range	
	6 V	13824	0x3600		
	2 V	0	0x0000		
	0.59 V	-4864	0xED00	Underloading	
1 - 5 V	5.7 V	32511	0x7EFF	Overloading	D = 27648 × (U – 1) / 4 U = D × 4 / 27648 + 1
	5 V	27648	0x6C00	Nominal range	
	3 V	13824	0x3600		
	1 V	0	0x0000		
	0.30 V	-4864	0xED00	Underloading	

Value Range<sup>†</sup> EP-4264


Measurement range	Current (I) / Voltage (U)	Decimal (D)	Hexadecimal	Range	Conversion
0 – 5 V	5.88 V	32511	0x7EFF	Overloading	D = 27648 × U/5 I = D × 5 / 27648
	5 V	27648	0x6C00	Nominal range	
	2.5 V	13824	0x3600		
	0 V	0	0x0000		
2 - 10 V	11.41 V	32511	0x7EFF	Overloading	D = 27648 × (U – 2) / 8 U = D × 8 / 27648 + 2
	10 V	27648	0x6C00	Nominal range	
	6 V	13824	0x3600		
	2 V	0	0x0000		
	0.59 V	-4864	0xED00	Underloading	
1 - 5 V	5.7 V	32511	0x7EFF	Overloading	D = 27648 × (U – 1) / 4 U = D × 4 / 27648 + 1
	5 V	27648	0x6C00	Nominal range	
	3 V	13824	0x3600		
	1 V	0	0x0000		
	0.30 V	-4864	0xED00	Underloading	
0 – 5 V	5.88 V	32511	0x7EFF	Overloading	D = 27648 × U/5 I = D × 5 / 27648
	5 V	27648	0x6C00	Nominal range	
	2.5 V	13824	0x3600		
	0 V	0	0x0000		
±5 V	5.88 V	32511	0x7EFF	Overloading	D = 27648 × (U – 1) / 4 U = D × 4 / 27648 + 1
	5 V	27648	0x6C00	Nominal range	
	2.5 V	13824	0x3600		
	0 V	0	0x0000		
	-2.5 V	-13824	0xCA00		
	-5 V	-27648	0x9400		
	-5.88 V	-32511	0x8100	Underloading	
† If the process value is beyond the valid value range, the corresponding channel releases 0 V and 0 mA respectively The following applies for all ranges: value > overload range = output deactivated value < underload range = output deactivated					



## 5.28 Analog Input Module EP-3704



**Analog Input Module EP-3704**




**Connection Diagram EP-3704**

The analog input module EP-3704 can detect up to 4 analog resistance thermometers. The resolution is 16 bit per channel. A sensor can be connected to each connector in a 2-wire, 3-wire or 4-wire connection. Mixed operation using different sensors as well as different connection methods is possible. Sensor type and temperature range are set using parameterization. A status LED is assigned to each channel.


The inputs are protected against voltage surges and overcurrent. Voltages that exceed  $\pm 30$  V may cause the destruction of the module.

The module provides individual channel diagnosis with channel related error messages.

LED Indicators EP-3704

	Module Status	Green: Communication over the system bus Red: Module System Fault or Diagnostic Fault
	1.1	Red: channel error
	2.1	Red: channel error
	3.1	Red: channel error
	4.1	Red: channel error

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



Block Diagram EP-3704

**Specifications EP-3704**

<b>System data</b>	
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in the section, <i>Order and Arrangement of the Modules</i> )
Interface	RSTi-EP I/O communication bus
System bus transfer rate	48 Mbps
<b>Inputs</b>	
Number	4
Sensor types	Pt100, Pt200, Pt500, Pt1000, Ni100, Ni120, Ni 200, Ni500, Ni1000, Cu10, 40 $\Omega$ , 80 $\Omega$ , 150 $\Omega$ , 300 $\Omega$ , 500 $\Omega$ , 1 k $\Omega$ , 2 k $\Omega$ , 4 k $\Omega$
Resolution	16 bits
Accuracy	max. 0.2 % FSR / 0.3 % FSR for Ni sensors / 0.6 % FSR for Cu10
Sensor connection	2-wire, 3-wire, 4-wire
Sensor current	depending on the sensor type 0,75 mA (Pt100, Ni100, Ni120, Cu10, 40 $\Omega$ , 80 $\Omega$ , 150 $\Omega$ , 300 $\Omega$ ) or 0,25 mA (Pt200, Pt500, Pt1000, Ni200, Ni500, Ni1000, 500 $\Omega$ , 1 k $\Omega$ , 2 k $\Omega$ , 4 k $\Omega$ )
Max. wire resistance / measurement range	2.5 $\Omega$ / 40 $\Omega$ , 5 $\Omega$ / 80 $\Omega$ , 10 $\Omega$ / 150 $\Omega$ and Cu10, 25 $\Omega$ in all other measuring ranges
Temperature coefficient	$\pm 50$ ppm/K max.
Temperature range	-200 to +850°C (-328 to 1562 °F)
Conversion time	36 to 240 ms, adjustable
Common mode input voltage range	Channel to channel: max. $\pm 2$ V
	Channel to voltage supply: max. $\pm 50$ V
Reverse polarity protection	Yes
Module diagnosis	Yes
Individual channel diagnosis	Yes
<b>Supply</b>	
Supply voltage	20.4V – 28.8V
Current consumption from system current path $I_{SYS}$	8 mA
Current consumption from input current path $I_{IN}$	20 mA
<b>General data</b>	
Weight	91 g (3.21 oz)
For additional general data, refer to the section, <i>General Technical Data for I/O Modules</i> .	

Overview of the Editable Parameter EP-3704

Channel	Description	Options	Default
	Temperature unit	Degree Celsius (0) / Degree Fahrenheit (1) / Kelvin (2)	Degree Celsius
0 - 3	Measurement range	PT100 -200 ... 850 Degree Celsius (0) / PT200 -200 ... 850 Degree Celsius (1) / PT500 -200 ... 850 Degree Celsius (2) / PT1000 -200 ... 850 Degree Celsius (3) / NI100 -60 ... 250 Degree Celsius (4) / NI120 -80 ... 260 Degree Celsius (5) / NI200 -60 ... 250 Degree Celsius (6) / NI500 -60 ... 250 Degree Celsius (7) / NI1000 -60 ... 250 Degree (8) / Cu10 -100 ... 260 Degree Celsius (9) / Resistance 40 Ω (10) / Resistance 80 Ω (11) / Resistance 150 Ω (12) / Resistance 300 Ω (13) / Resistance 500 Ω (14) / Resistance 1000 Ω (15) / Resistance 2000 Ω (16) / Resistance 4000 Ω (17) / disabled (18)	disabled
0 - 3	Connection type	2-wire (0) / 3-wire (1) / 4-wire (2)	2-wire
0 - 3	Conversion time	240 ms (0) / 130 ms (1) / 80 ms (2) / 55 ms (3) / 43 ms (4) / 36 ms (5)	80 ms
0 - 3	Channel diagnostics	disabled (0) / enabled (1)	disabled
0 - 3	Limit value monitoring	disabled (0) / enabled (1)	disabled
0 - 3	High limit value	-32768 ... 32767	0
0 - 3	Low limit value	-32768 ... 32767	0

Diagnostic Data EP-3704

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	
		4	Error	
		5	Power supply fault	
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x05
		1		
		2		
		3		
		4	Channel information available	1
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0

**Diagnostic Data EP-3704**

Name	Bytes	Bit	Description	Default
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	
		4	Power supply fault	
		5	Reserved	0
		6	Process alarm lost	
		7	Reserved	0
Channel type	4	0-6	Channel type	0x71
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	8
Number of channels	6		Number of similar channels per module	4
Channel error	7	0	Error at channel 0	
		1	Error at channel 1	
		2	Error at channel 2	
		3	Error at channel 3	
		4-7	Reserved	0
Channel error	8	8-15	Reserved	0
Channel error	9	16-23	Reserved	0
Channel error	10	24-31	Reserved	0
Channel 0 error	11	0	Parameter Error	
		1	Reserved	0
		2	Reserved	0
		3	Reserved	0
		4	Line break	
		5	Process alarm lost	
		6	Lower limit exceeded	
		7	Upper limit exceeded	
Channel 1 error	12	0	Parameter Error	
		1	Reserved	0
		2	Reserved	0
		3	Reserved	0
		4	Line break	
		5	Process alarm lost	
		6	Lower limit exceeded	
		7	Upper limit exceeded	
Channel 2 error	13	0	Parameter Error	
		1	Reserved	0
		2	Reserved	0
		3	Reserved	0
		4	Line break	
		5	Process alarm lost	
		6	Lower limit exceeded	
		7	Upper limit exceeded	

**Diagnostic Data EP-3704**

Name	Bytes	Bit	Description	Default
Error in channel 3	14	0	Parameter Error	
		1	Reserved	0
		2	Reserved	0
		3	Reserved	0
		4	Line break	
		5	Process alarm lost	
		6	Lower limit exceeded	
		7	Upper limit exceeded	
Channel 4 error to Channel 31 error	15-42	0-7	Reserved	0
Time stamp	43-46		Time stamp [μs] (32 bit)	

**Process Data<sup>†</sup> Inputs EP-3704**

Byte	Format	Description	Remarks
IB0	Word	RTD0	
IB1			
IB2	Word	RTD1	
IB3			
IB4	Word	RTD2	
IB5			
IB6	Word	RTD3	
IB7			
† Internal process data mapping with data format “Standard”. Depending on the fieldbus specification and the data format of the communicating fieldbus components the bytes and/or words can be reversed during data transfer.			

**Resistance Measurement Range EP-3704**

Measurement range	Resistance	Decimal	Hexadecimal	Range
40 $\Omega$	> 47.04 $\Omega$	32767	0x7FFF	Overloading or line break
	47.04 $\Omega$	32511	0x7EFF	Overloading
	40 $\Omega$	27648	0x6C00	Nominal range
	0	0	0x0000	
80 $\Omega$	> 94.07 $\Omega$	32767	0x7FFF	Overloading or line break
	94.07 $\Omega$	32511	0x7EFF	Overloading
	80 $\Omega$	27648	0x6C00	Nominal range
	0	0	0x0000	
150 $\Omega$	> 176.4 $\Omega$	32767	0x7FFF	Overloading or line break
	176.4 $\Omega$	32511	0x7FFF	Overloading
	150 $\Omega$	27648	0x6C00	Nominal range
	0	0	0x0000	
300 $\Omega$	> 352.77 $\Omega$	32767	0x7FFF	Overloading or line break
	352.77 $\Omega$	32511	0x7FFF	Overloading
	300 $\Omega$	27648	0x6C00	Nominal range
	0	0	0x0000	
500 $\Omega$	> 587.9 $\Omega$	32767	0x7FFF	Overloading or line break
	587.9 $\Omega$	32511	0x7FFF	Overloading
	500 $\Omega$	27648	0x6C00	Nominal range
	0	0	0x0000	
1 k $\Omega$	> 1.177 k $\Omega$	32767	0x7FFF	Overloading or line break
	1.177 k $\Omega$	32511	0x7FFF	Overloading
	1.0 k $\Omega$	27648	0x6C00	Nominal range
	0	0	0x0000	
2 k $\Omega$	2.352 k $\Omega$	32767	0x7FFF	Overloading or line break
	2.352 k $\Omega$	32511	0x7FFF	Overloading
	2.0 k $\Omega$	27648	0x6C00	Nominal range
	0	0	0x0000	
4 k $\Omega$	> 4.703 k $\Omega$	32767	0x7FFF	Overloading or line break
	4.703 k $\Omega$	32511	0x7FFF	Overloading
	4.0 k $\Omega$	27648	0x6C00	Nominal range
	0	0	0x0000	

## Temperature Measurement Range EP-3704


Measurement range	Value in °C 0.1 ° resolution	Value in °F 0.1 °/digit	Value in K 0.1 K/digit	Range
Pt100	-2000 to 8500	-3280 to 15620	732 to 11232	-200 °C to +850 °C
	-2040	-3352	692	Underloading
	8540	15692	11272	Overloading
	32767	32767	32767	Line break
Pt200	-2000 to 8500	-3280 to 15620	732 to 11232	-200 °C to +850 °C
	-2040	-3352	692	Underloading
	8540	15692	11272	Overloading
	32767	32767	32767	Line break
Pt500	-2000 to 8500	-3280 to 15620	732 to 11232	-200 °C to +850 °C
	-2040	-3352	692	Underloading
	8540	15692	11272	Overloading
	32767	32767	32767	Line break
Pt1000	-2000 to 8500	-3280 to 15620	732 to 11232	-200 °C to +850 °C
	-2040	-3352	692	Underloading
	8540	15692	11272	Overloading
	32767	32767	32767	Line break
Ni100	-600 to +2500	-760 to 4820	2132 to 5232	-60 °C to 250 °C
	-640	-832	2092	Underloading
	2540	4892	5272	Overloading
	32767	32767	32767	Line break
Ni120	-800 to +2600	-1120 to +5000	1932 to 5332	-80 °C to 260 °C
	-840	-1192	1892	Underloading
	2640	5072	5372	Overloading
	32767	32767	32767	Line break
Ni200	-600 to +2500	-760 to 4820	2132 to 5232	-60 °C to 250 °C
	-640	-832	2092	Underloading
	2540	4892	5272	Overloading
	32767	32767	32767	Line break
Ni500	-600 to +2500	-760 to 4820	2132 to 5232	-60 °C to 250 °C
	-640	-832	2092	Underloading
	2540	4892	5272	Overloading
	32767	32767	32767	Line break
Ni1000	-600 to +2500	-760 to 4820	2132 to 5232	-60 °C to 250 °C
	-640	-832	2092	Underloading
	2540	4892	5272	Overloading
	32767	32767	32767	Line break
Cu10	-1000 to +2600	-1480 to 5000	1732 to 5332	-100 °C to 260 °C
	-1040	-1552	1692	Underloading
	2640	5072	5372	Overloading
	32767	32767	32767	Line break




**Process Alarm EP-3704**

Name	Number of bytes	Function
High alarm	1	Bit 0: Upper limit exceeded channel 0
		Bit 1: Upper limit exceeded channel 1
		Bit 2: Upper limit exceeded channel 2
		Bit 3: Upper limit exceeded channel 3
		Bit 4 – 7: Reserved
Low alarm	1	Bit 0: Lower limit exceeded channel 0
		Bit 1: Lower limit exceeded channel 1
		Bit 2: Lower limit exceeded channel 2
		Bit 3: Lower limit exceeded channel 3
		Bit 4 – 7: Reserved
Timestamp	2	The two least significant bytes of the internal 32-bit timer

## 5.29 Analog Input Module EP-3804



**Analog Input Module EP-3804**




**Connection Diagram EP-3804**

The analog input module EP-3804 can detect up to 4 analog thermocouple sensors or voltages between  $\pm 15$  mV and  $\pm 2$  V. The resolution is 16 bit per channel. Sensor type and temperature range are set using parameterisation. Mixed operation using different sensors is possible. For each channel, an internal or external cold-junction compensation (CJC) can be parameterized. A status LED is assigned to each channel.


The inputs are protected against voltage surges and overcurrent. Voltages that exceed  $\pm 30$  V may cause the destruction of the module.

The module provides individual channel diagnosis with channel related error messages.

LED Indicators EP-3804

	Module Status	Green: Communication over the system bus Red: Module System Fault or Diagnostic Fault
	1.1	Red: channel error
	2.1	Red: channel error
	3.1	Red: channel error
	4.1	Red: channel error

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



Block Diagram EP-3804

**Specifications EP-3804**

<b>System data</b>	
Data	Process, parameter and diagnostic data depend on the network adapter used (refer to the table in the section, <i>Order and Arrangement of the Modules</i> )
Interface	RSTi-EP I/O communication bus
System bus transfer rate	48 Mbps
<b>Inputs</b>	
Number	4
Sensor types	J, K, T, B, N, E, R, S, L, U, C, mV
Resolution	16 bits
Accuracy	Conversion time $\geq 80$ ms: $10 \mu\text{V} + 0.1\%$ of voltage measurement range (without cold-junction measurement error)
Sensor connection	2-wire
Sensor current	0,25 mA for the cold-junction compensation with a Pt1000
Cold junction compensation	Internal and external (Pt1000), int. accuracy $\leq 3$ K
Temperature coefficient	50 ppm/K max.
Temperature range	-200 to +2315°C (-328 to 4199 °F)
Conversion time	36 to 240 ms, adjustable
Internal resistance	$> 1 \text{ M}\Omega$
Reverse polarity protection	Yes
Module diagnosis	Yes
Individual channel diagnosis	Yes
<b>Supply</b>	
Supply voltage	20.4V – 28.8V
Current consumption from system current path $I_{\text{SYS}}$	8 mA
Current consumption from input current path $I_{\text{IN}}$	20 mA
<b>General data</b>	
Weight	86 g (3.03 oz)
For additional general data, refer to the section, <i>General Technical Data for I/O Modules</i> .	

## Overview of the Editable Parameter EP-3804

Channel	Description	Options	Default
	Temperature unit	Degree Celsius (0) / Degree Fahrenheit (1) / Kelvin (2)	Degree Celsius
0 - 3	Measurement range	TC Type J (0) / TC Type K (1) / TC Type N (2) / TC Type R (3) / TC Type S (4) / TC Type T (5) / TC Type B (6) / TC Type C (7) / TC Type E (8) / TC Type L (9) / TC Type U (10) / ± 15,625 mV (11) / ± 31,25 mV (12) / ± 62,5 mV (13) / ± 125 mV (14) / ± 250 mV (15) / ± 500 mV (16) / ± 1000 mV (17) / ± 2000 mV (18) / disabled (19)	disabled
0 - 3	Cold junction compensation	internal (0) / external Channel 0 (1) / external Channel 1 (2) / external Channel 2 (3) / external Channel 3 (4)	internal
0 - 3	Conversion time	240 ms (0) / 130 ms (1) / 80 ms (2) / 55 ms (3) / 43 ms (4) / 36 ms (5)	80 ms
0 - 3	Channel diagnostics	disabled (0) / enabled (1)	disabled
0 - 3	Limit value monitoring	disabled (0) / enabled (1)	disabled
0 - 3	High limit value	-32768 ... 32767	0
0 - 3	Low limit value	-32768 ... 32767	0

## Diagnostic Data EP-3804

Name	Bytes	Bit	Description	Default
Error indicator	0	0	Module error	
		1	Internal error	
		2	External error	
		3	Channel error	
		4	Error	
		5	Power supply fault	
		6	Reserved	0
		7	Parameter error	
Module type	1	0	Module Type	0x05
		1		
		2		
		3		
		4	Channel information available	1
		5	Reserved	0
		6	Reserved	0
		7	Reserved	0
Error byte 2	2	0-7	Reserved	0

Diagnostic Data EP-3804

Name	Bytes	Bit	Description	Default
Error byte 3	3	0-2	Reserved	0
		3	Internal diagnostic FIFO full	
		4	Power supply fault	
		5	Reserved	0
		6	Process alarm lost	
		7	Reserved	0
Channel type	4	0-6	Channel type	0x71
		7	Reserved	0
Diagnostic bits per channel	5		Number of diagnostic bit per channel	8
Number of channels	6		Number of similar channels per module	4
Channel error	7	0	Error at channel 0	
		1	Error at channel 1	
		2	Error at channel 2	
		3	Error at channel 3	
		4-7	Reserved	0
Channel error	8	8-15	Reserved	0
Channel error	9	16-23	Reserved	0
Channel error	10	24-31	Reserved	0
Channel 0 error	11	0	Parameter Error	
		1	Reserved	0
		2	Reserved	0
		3	CJC error	
		4	Line break	
		5	Process alarm lost	
		6	Lower limit exceeded	
		7	Upper limit exceeded	
Channel 1 error	12	0	Parameter Error	
		1	Reserved	0
		2	Reserved	0
		3	CJC error	
		4	Line break	
		5	Process alarm lost	
		6	Lower limit exceeded	
		7	Upper limit exceeded	
Channel 2 error	13	0	Parameter Error	
		1	Reserved	0
		2	Reserved	0
		3	CJC error	
		4	Line break	
		5	Process alarm lost	
		6	Lower limit exceeded	
		7	Upper limit exceeded	

**Diagnostic Data EP-3804**

Name	Bytes	Bit	Description	Default
Error in channel 3	14	0	Parameter Error	
		1	Reserved	0
		2	Reserved	0
		3	CJC error	
		4	Line break	
		5	Process alarm lost	
		6	Lower limit exceeded	
		7	Upper limit exceeded	
Channel 4 error to Channel 31 error	15-42	0-7	Reserved	0
Time stamp	43-46		Time stamp [μs] (32 bit)	

**Process Data† Inputs EP-3804**

Byte	Format	Description	Remarks
IB0	Word	TC0	
IB1			
IB2	Word	TC1	
IB3			
IB4	Word	TC2	
IB5			
IB6	Word	TC3	
IB7			

† Internal process data mapping with data format *Standard*. Depending on the fieldbus specification and the data format of the communicating fieldbus components the bytes and/or words can be reversed during data transfer

**Voltage Measurement Ranges EP-3804**

Measurement range	Voltage	Decimal signal range	Hexadecimal signal range
±15.625 mV	15.625 mV	32767	0x7FFF
	-15.625 mV	-32768	0x8000
±31.25 mV	31.25 mV	32767	0x7FFF
	-31.25 mV	-32768	0x8000
±62.5 mV	62.5 mV	32767	0x7FFF
	-62.5 mV	-32768	0x8000
±125 mV	125 mV	32767	0x7FFF
	-125 mV	-32768	0x8000
±250 mV	250 mV	32767	0x7FFF
	-250 mV	-32768	0x8000
±500 mV	500 mV	32767	0x7FFF
	-500 mV	-32768	0x8000
±1 V	+1 V	32767	0x7FFF
	-1 V	-32768	0x8000
±2 V	+2 V	32767	0x7FFF
	-2 V	-32768	0x8000

## Temperature Measurement Ranges EP-3804

Measurement range	Value in °C 0.1 ° resolution Bit significance	Value in °F 0.1 °/digit Bit significance	Value in K 0.1 K/digit Bit significance	Range
Type K	-2000 to 13720	-3280 to 25016	732 to 16452	-200 °C to +1372 °C
	-2040	-3352	692	Underloading
	13760	25088	16492	Overloading
	32767	32767	32767	Line break, cold compensation error
Type J	-2100 to 12000	-3460 to 21920	632 to 14732	-210 °C to +1200 °C
	-2140	-3532	592	Underloading
	12040	21992	14772	Overloading
	32767	32767	32767	Line break, cold compensation error
Type B	500 to 8500	1220 to 32767 (limited range) 3276.7 °F = 1802.6 °C	3232 to 20932	+50 °C to +1820 °C
	460	1148	3192	Underloading
	18240	33152	20972	Overloading
	32767	32767	32767	Line break, cold compensation error
Type N	-2000 to 13000	-3280 to 23720	4732 to 15732	-200 °C to +1300 °C
	-2040	-3352	692	Underloading
	13040	23792	15772	Overloading
	32767	32767	32767	Line break, cold compensation error
Type E	-2000 to +10000	-3280 to 18320	4732 to 12732	-200 °C to 1000 °C
	-2040	-3352	692	Underloading
	10040	18392	12772	Overloading
	32767	32767	32767	Line break, cold compensation error
Type R	-500 to +17680	-580 to +32144	3232 to 20412	-50 °C to +1768 °C
	-540	-652	2192	Underloading
	17720	32216	20452	Overloading
	32767	32767	32767	Line break, cold compensation error
Type S	-500 to +17680	-580 to +32144	3232 to 20412	-50 °C to +1768 °C
	-540	-652	2192	Underloading
	17720	32216	20452	Overloading
	32767	32767	32767	Line break, cold compensation error
Type T	-2000 to +4000	-3280 to 7520	732 to 6732	-200 °C to +400 °C
	-2040	-3352	692	Underloading
	4040	7592	6772	Overloading
	32767	32767	32767	Line break, cold compensation error
Type L	-2000 to +9000	-3280 to 16520	732 to 11732	-200 °C to +900 °C
	-2040	-3352	692	Underloading
	9040	16592	11772	Overloading
	32767	32767	32767	Line break, cold compensation error
Type U	-2000 to +6000	-3280 to 11120	732 to 8732	-200 °C to +600 °C
	-2040	-3352	692	Underloading
	6040	11192	8772	Overloading
	32767	32767	32767	Line break, cold compensation error
Type C	0 to 23150	320 to 32767 (limited range) 3276.7 °F = 1802.6 °C	2732 to 25882	0 °C to +2315 °C
	-40	248	2692	Underloading
	23190	32767	25922	Overloading
	32767	32767	32767	Line break, cold compensation error




**Process Alarm EP-3804**

Name	Number of bytes	Function
High alarm	1	Bit 0: Upper limit exceeded channel 0
		Bit 1: Upper limit exceeded channel 1
		Bit 2: Upper limit exceeded channel 2
		Bit 3: Upper limit exceeded channel 3
		Bit 4 – 7: Reserved
Low alarm	1	Bit 0: Lower limit exceeded channel 0
		Bit 1: Lower limit exceeded channel 1
		Bit 2: Lower limit exceeded channel 2
		Bit 3: Lower limit exceeded channel 3
		Bit 4 – 7: Reserved
Timestamp	2	The two least significant bytes of the internal 32-bit timer

### 5.30 Power-feed Module for Input Current Path EP-7631



**Power-feed Module for Input Current Path EP-7631**



**Connection Diagram EP-7631**

Power-feed modules are used to refresh the current paths and isolate the power supply. The RSTi-EP station's main power supply is always fed in via the network adapter. A power-feed module EP-7631 must be connected if the current demand of the series of input modules is too large.

The maximum feed-in current in the input current path via the 4-pole connector is 10 A. Details required to calculate current demand and power supply refer to the section, *Current Demand and Power Supply*. Power-feed modules are passive modules without fieldbus communication, therefore they are not considered during configuration.


**Note:** A maximum of three passive modules (powerfeed module, potential distribution module, empty slot module) may be installed in succession, however the next module to be installed must be an active module.




#### **Caution**

In the case of a maximum power supply of >8 A and a maximum temperature of > +55°C (131 °F), all four contacts must be connected with 1.5 mm<sup>2</sup> wiring.

### LED Indicators EP-7631

	Module Status	
		<b>Green:</b> Voltage applied and is > 18 V DC
	3.1	<b>Green:</b> Supply voltage for input current path > 18 V DC
	3.2	<b>Red:</b> Supply voltage for input current path < 18 V DC
	3.3	--
	3.4	<b>Red:</b> Internal fuse defective, replace module

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.




**Specifications EP-7631**

<b>Supply</b>	
Supply voltage	20.4V – 28.8V
Maximum feed current for input modules	10 A
Current consumption from input current path $I_{IN}$	10 mA
<b>General data</b>	
Weight	76 g (6.21 oz)
For additional general data, refer to the section, <i>General Technical Data for I/O Modules</i> .	

### 5.31 Power-feed Module for Output Current Path EP-7641



**Power-feed Module for Output Current Path EP-7641**



**Connection Diagram EP-7641**

Power-feed modules are used to refresh the current paths and isolate the power supply. The RSTi-EP station's main power supply is always fed in via the network adapter. A power-feed module EP-7641 must be connected if the current demand of the series of output modules is too large.

The maximum feed-in current in the output current path via the 4-pole connector is 10 A. Details required to calculate current demand and power supply refer to the section, Current Demand and Power Supply.

Power-feed modules are passive modules without fieldbus communication, therefore they are not considered during configuration.


**Note:** A maximum of three passive modules (powerfeed module, potential distribution module, empty slot module) may be installed in succession, however the next module to be installed must be an active module.




#### **Caution**

In the case of a maximum power supply of >8 A and a maximum temperature of > +55°C (131 °F), all four contacts must be connected with 1.5 mm<sup>2</sup> wiring.

## LED Indicators EP-7641

	Module Status	<b>Green:</b> Voltage applied and is > 18 V DC
	4.1	<b>Green:</b> Supply voltage for input current path > 18 V DC
	4.2	<b>Red:</b> Supply voltage for input current path < 18 V DC
	4.3	--
	4.4	<b>Red:</b> Internal fuse defective, replace module

For error messages refer to the chapter, *LED Indicators and Troubleshooting*.



**Specifications EP-7641**

<b>Supply</b>	
Supply voltage	20.4V – 28.8V
Maximum feed current for input modules	10 A
Current consumption from output current path $I_{OUT}$	10 mA
<b>General data</b>	
Weight	76 g (2.68 oz)
For additional general data, refer to the section, <i>General Technical Data for the Fieldbus Network Adapter</i> .	

### 5.32 Safe Feed-in Modules EP-1901, EP-1902, and EP-1922



Safe Feed-in Module EP-1901

Safe Feed-in Module EP-1901

Safe Feed-in Module EP-1922

GE provides 3 variants of RSTi-EP safe feed modules EP 1901: one safe input, EP 1902: two safe inputs and EP 1922: two safe inputs, with delayed disconnection, which are intended for connecting safety-related equipment. The RSTi-EP safe feed-input modules are controlled using contact-based safety transducers and/or safety transducers with OSSD (Output Signal Switching Device) inputs. The safety function consists of the safe disconnection of 24 V outputs, the safe state of which is 24 V *switched off* (current path for outputs and the OSSD output is switched off).

All input sensors are independently supplied via separate voltage paths and report the current machine status to the control unit.

Each RSTi-EP safe feed-input module safely switches off all following modules that are supplied by the output current path (until the next EP-7641 power module) and thus creates a safety segment. To switch the 24 V OSSD voltage back on, either an automatic or a manual start can be selected.

- Automatic start: the safe output current path is switched on immediately after resetting the safety circuit(s).
- Manual start: the output current path is only switched on again if the start button has been held down for a preset length of time.




With the delay module (EP-1922), switching off can be delayed by a defined time so that, for example, a machine can be shut down in a controlled manner. The delay time can be set in four steps between 0 and 60 seconds (corresponds to stop category 1 as per EN 60204).

**Note:** All product-specific information and notes on the use of EP-19xx modules can be found in the *Modules for Functional Safety Manual* (GFK-2956).

### 5.33 Potential Distribution Module for Input Current Path EP-711F




Power-feed Module for Output Current Path EP-711F



Connection Diagram EP-711F

The potential distribution module EP-711F provides 16 connections for +24 V from the input current path. Potential distribution modules are passive modules without fieldbus communication, therefore they are not considered during configuration.

**Note:** A maximum of three passive modules (power-feed module, potential distribution module, and empty slot module) may be installed in succession, however the next module to be installed must be an active module.




Block Diagram EP-711F


#### Specifications EP-711F

Supply	
Supply voltage	20.4V – 28.8V
General data	
Weight	84 g (2.96 oz)
For additional general data, refer to the section, <i>General Technical Data for I/O Modules</i> .	

### 5.34 Potential Distribution Module for Output Current Path EP-751F




*Potential Distribution Module for  
Output Current path EP-751F*



*Connection Diagram EP-751F*

The potential distribution module EP-751F provides 16 connections for +24 V from the output current path. Potential distribution modules are passive modules without fieldbus communication, therefore they are not considered during configuration.

**Note:** A maximum of three passive modules (power-feed module, potential distribution module, and empty slot module) may be installed in succession, however the next module to be installed must be an active module.




Block Diagram EP-751F


Specifications EP-751F

Supply	
Supply voltage	20.4V – 28.8V
General data	
Weight	84 g (2.96 oz)
For additional general data, refer to the section, <i>General Technical Data for I/O Modules</i> .	

### 5.35 Potential Distribution Module for Functional Earth EP-700F




*Potential Distribution Module for  
Output Current Path EP-700F*



*Connection Diagram EP-700F*

The potential distribution module EP-700F provides 16 connections for the functional earth. Potential distribution modules are passive modules without fieldbus communication, therefore they are not considered during configuration.

**Note:** A maximum of three passive modules (power-feed module, potential distribution module, and empty slot module) may be installed in succession, however the next module to be installed must be an active module.




Block Diagram EP-700F


Specifications EP-700F

Supply	
Supply voltage	20.4V – 28.8V
General data	
Weight	84 g (2.96 oz)
For additional general data, refer to the section, <i>General Technical Data for I/O Modules</i> .	

### 5.36 0-V Potential Distribution Module for Input Current Path EP-710F




*0-V Potential Distribution Module for  
the Input Current path EP-710F*



*Connection Diagram EP-710F*

The potential distribution module EP-710F provides 16 connections for ground from the input current path. Potential distribution modules are passive modules without fieldbus communication, therefore they are not considered during configuration.

**Note:** A maximum of three passive modules (power-feed module, potential distribution module, and empty slot module) may be installed in succession, however the next module to be installed must be an active module.



**Block Diagram EP-710F**

**Specifications EP-710F**


Supply	
Supply voltage	0 V (from input current path)
General data	
Weight	84 g (2.96 oz)
For additional general data, refer to the section, <i>General Technical Data for I/O Modules</i> .	



### 5.37 0-V Potential Distribution Module for Output Current Path EP-750F




*0-V Potential Distribution Module for  
the Output Current Path EP-750F*



*Connection Diagram EP-750F*

The potential distribution module EP-750F provides 16 connections for ground from the output current path. Potential distribution modules are passive modules without fieldbus communication, therefore they are not considered during configuration.

**Note:** A maximum of three passive modules (power-feed module, potential distribution module, and empty slot module) may be installed in succession, however the next module to be installed must be an active module.



Block Diagram EP-750

#### Specifications EP-750F

Supply	
Supply voltage	0 V (from output current path)
General data	
Weight	84 g (2.96 oz)
For additional general data, refer to the section, <i>General Technical Data for I/O Modules</i> .	

### 5.38 Empty Slot Module EP-8310



**Empty Slot Module EP-8310**


Empty slot modules can be integrated as reserve modules in a station. They bridge all contacts in the basic module 1:1 and otherwise have no function. Empty slot modules are passive modules without fieldbus communication, therefore they are not considered during configuration.

**Note:** A maximum of three passive modules (power-feed module, potential distribution module, and empty slot module) may be installed in succession, however the next module to be installed must be an active module.

#### **Specifications EP-8310**

General data	
Weight	70 g (2.47 oz)
For additional general data, refer to the section, <i>General Technical Data for I/O Modules</i> .	

### 5.39 Termination Kit EP-8301



**Termination Kit EP-8301**

Each RSTI-EP fieldbus network adapter is delivered together with a termination kit EP-8301. This comprises two end brackets and an end plate. The end plate protects the contacts on the last module at the end of the RSTI-EP station. The station is fixed to the DIN rail on both sides via the end brackets.

#### **Technical Data EP-8301**

General data	
Weight	51 g (1.8 oz)

## Notes

# Chapter 6 Installation



## Warning

Explosion risk - During assembly work, sparks can form and surfaces may become excessively hot.

- Before assembly, make sure that there is not a potentially explosive atmosphere.
- For applications in potentially explosive atmospheres, observe the installation and construction requirements of EN 60079- 15 and/or country-specific regulations.



## Warning

Dangerous contact voltage:

- Carry out assembly and wiring work on the RSTi-EP station only when the power supply is disconnected.
- Make sure that the place of installation (switch cabinet etc.) has been disconnected from the power supply.

## 6.1 Preparations for Assembly

The RSTi-EP station is designed for installation in switch cabinets, terminals or switch boxes in decentralised systems. The field-bus network adapter and I/O modules conform to protection class IP20.

### 6.1.1 Environmental Conditions

Make sure that the permitted environmental conditions for installation and operation are observed (refer to the General Technical Data in the sections, *General Technical Data for the Fieldbus Network Adapter* and *General Technical Data for I/O Modules*).

### 6.1.2 DIN Rail

The RSTi-EP system products are intended for installation on a DIN rail in accordance with EN 60715 [35 × 7.5 mm (1.4" × 0.3")], steel strip in accordance with Annex A of EN 60715, or tinned steel strip. The DIN rail must be mounted prior to the installation of the RSTi-EP station.

The DIN rail must be attached to the surface at least every 20 cm (7.9 in) to protect it from vibration and impact.

If the DIN rail is installed on earthed mounting plates, it does not have to be separately earthed.

### 6.1.3 Stripping Lengths

The required stripping length for every RSTi-EP product is specified in mm (in). These lengths, such as 6 mm (0.24 in) ± 0.5 mm (0.02 in), ≥ 10 mm (0.39 in) ± 1 mm (0.04 in), must be observed. This also applies to the use of wire-end ferrules. The external dimensions of the crimped wire-end ferrules must conform with IEC-60947-1. For detailed information refer to the section, *Wiring*.

### 6.1.4 Unpacking and Delivery

All of the elements that make up the RSTi-EP station are packaged individually for delivery.

- Check the delivery for completeness and transport damage.
- Report any transport damage immediately to the respective transport company.



**The product can be destroyed by electrostatic discharge.**

**The components in the RSTi-EP series can be destroyed by electrostatic discharge.**


#### **Caution**

- Ensure that personnel and work equipment are adequately grounded.

- Unpack all parts and sort the modules into the installation sequence as per the instructions.
- Dispose of all packaging in accordance with the local disposal guidelines. The cardboard packaging from the modules and fieldbus network adapters can be sent for paper recycling.

### 6.1.5 Use in a Potentially Explosive Atmosphere


If the RSTi-EP station is used in a potentially explosive atmosphere rated as Zone 2, the housing must meet the requirements of explosion protection type Ex n or Ex e and protection class IP54. Sensors and actuators that are located in Zone 2 or in a safe zone can be connected. All cable glands on the housing must be approved for Ex e.



*Use in Potentially Explosive Atmosphere*

### 6.1.6 Installation Position

The RSTi-EP station is usually installed on a horizontally positioned DIN rail.



*Installation Position of the RSTi-EP Station on the DIN Rail (Horizontal Installation)*

Installation on vertically positioned DIN rails is also possible. In this case however, the heat dissipation is reduced such that the derating values change (refer to the section, *Current Demand and Power Supply*).

In the case of vertical mounting, the field-bus network adapter must always be arranged as the first module at the bottom and secured with a reinforced end bracket for vertical mounting.


### 6.1.7 Installation Distances

**Note:** Depending on how the station shielding is implemented, the specified distances may have to be larger than those given below.


**Note:** Ensure compliance with the minimum permissible cable bending radius.

In order to carry out the installation and further maintenance work and to ensure sufficient ventilation, the RSTi-EP station must be installed while observing the following minimum distances. Earth terminals already installed can be ignored when calculating the distance.






*Minimum Distances with Horizontal Installation*



*Minimum Distances with Vertical Installation*



*Minimum Distance to Switch Cabinet Door (with/without Swivel Marker)*

### 6.1.8 Calculation of Space Requirements

The space requirements for a RSTi-EP station with  $n$  modules (**horizontal installation**) is calculated as follows:

**Height:** 120 mm (4.72")  
           + 2 × 40 mm (1.57")           distances at top and bottom  
           = **200 mm (7.87")**

**Width:** 8 mm (1.57")           end bracket  
           + 52 mm (2.05")           bus network adapter  
           +  $n \times 11.5$  mm (0.45")     $n$  modules  
           + 11.5 mm (0.45")           end plate and end bracket  
           + 2 × 20 mm (0.79")       distances to the sides  
           = **111.5 mm (4.39") +  $n \times 11.5$  mm (0.45")**

For vertical installation interchange height and width. When calculating the width for vertical installation, 4.5 mm (0.18") must be added for the end bracket.

### 6.1.9 Installation Sequence

A RSTi-EP station may only be installed in this sequence (starting from the left/bottom):

- End bracket
- Bus network adapter
- Up to 64 active modules
- End plate and end bracket

If the station has already been configured, proceed to the corresponding installation drawing. If you are configuring the station yourself, observe the following instructions:

- Observe the maximum current carrying capacity (refer to the section, *Current Demand and Power Supply*).
- Furthermore, the modules may be arranged in any sequence. In order to configure the station as clearly as possible, it is recommended to arrange the modules according to their function.

### 6.1.10 Arrangement of SIL Modules

An EP-19xx module can be positioned anywhere in the RSTi-EP station. All of the following output modules up to the next EP-7641 module are safely disconnected (safety segment). Multiple EP-19xx modules / safety segments can be set up in a single station.

**Note:** When using RSTi-EP EP-19xx modules, also refer to the *Modules for Functional Safety Manual* (GFK-2956).

### 6.1.11 Preparation and the required tool

The DIN rail must already be installed. To mechanically install the RSTi-EP station, you will need a 3-mm screwdriver.

- Lay out the modules in the intended sequence.
- Check whether the DIN rail feet can be moved on both end brackets. If necessary, loosen the mounting screw until the DIN rail feet can be moved freely.
- If not done yet, fit an earth terminal to the DIN rail.

## 6.2 Assembling the RSTi-EP Station



#### Warning

Explosion risk - During assembly work, sparks can form and surfaces may become excessively hot.

- Before assembly, make sure that there is not a potentially explosive atmosphere.
- For applications in potentially explosive atmospheres, observe the installation and construction requirements of EN 60079- 15 and/or country-specific regulations.



#### Warning

Dangerous contact voltage:

- Carry out assembly and wiring work on the RSTi-EP station only when the power supply is disconnected.
- Make sure that the place of installation (switch cabinet etc.) has been disconnected from the power supply.



#### Caution


The product can be destroyed by electrostatic discharge.

The components in the RSTi-EP series can be destroyed by electrostatic discharge.

- Ensure that personnel and work equipment are adequately grounded.

**Note:** For failure-free operation, the end brackets delivered with the network adapter have to be installed to achieve a permanent set of the RSTi-EP station.

1. On the left side of the installation site, place an end bracket on the DIN rail with the exterior of the bracket facing left and screw it down tightly (using a 3-mm (0.1") screwdriver).



*Attaching the End Bracket*

**Note:** When installing the RSTi-EP products, make sure that you listen for the double click:

- a) When snapping onto the DIN rail
- b) When pushing together with the neighboring module.

The modules are in the correct position and the connection is made only when both snapping noises are heard.




**Caution**

**Improper installation may prevent grounding.**


The grounding of the modules and network adapters is only ensured if the FE spring at the bottom is in contact with the DIN rail.

During installation, make sure that both release levers on the bus network adapter and all release levers on the modules are closed before snapping onto the DIN rail.




*Release Lever Closed*

2. Place the field bus network adapter (module side to the right) on the DIN rail so that it audibly clicks into place.



***Attaching the Bus Network adapter to the DIN Rail***


3. Slide the bus network adapter to the left until it completely connects with the end bracket. At the same time, press the bus network adapter as close as possible to the DIN rail so that the network adapter is not tilted.



***Sliding the Bus network adapter into Position***


4. Place the first module on the DIN rail and press it down firmly. It must audibly click into place.

5. Slide the module to the left until it audibly clicks into place on the bus network adapter. At the same time, press the module as close as possible to the DIN rail so that the module is not tilted.



***Sliding the Module into Position***

6. Attach all of the other modules as described above.
7. Connect the second end bracket to the end plate as specified by the alignment pins.
8. Place both parts on the DIN rail on the right-hand side of the station so that the end bracket faces outwards.
9. Slide the end bracket and end plate to the left until it completely connects with the last module.



***Sliding the End Plate with End Bracket into Position***


10. Screw down the end bracket tightly (using a 3-mm screwdriver).
11. Make sure that all release levers are in the locking position as standard. If this is not the case, click the open release lever into place.

## 6.3 Attaching the Marker

### 6.3.1 Attaching the Swivel Marker

A swivel marker, available as an accessory (EP-8100), is best suited for making detailed markings on the connector frame.

1. Snap the swivel marker into place on top of the module connector frame.



*Attaching the Swivel Marker*

2. Insert the labelled marker into the swivel marker from below.

## 6.4 Wiring



### Warning

Explosion risk - During assembly work, sparks can form and surfaces may become excessively hot.

- Before assembly, make sure that there is not a potentially explosive atmosphere.
- For applications in potentially explosive atmospheres, observe the installation and construction requirements of EN 60079- 15 and/or country-specific regulations.



### Warning

Dangerous contact voltage:

- Carry out assembly and wiring work on the RSTi-EP station only when the power supply is disconnected.
- Make sure that the place of installation (switch cabinet etc.) has been disconnected from the power supply.



### Warning

Safety functions of EP-19xx modules can be impaired. When EP-19xx modules are installed in the RSTi-EP station, observe the following points:

- Use wire-end ferrules in combination with flexible/multi-conductor cables.
- Ensure that for safety inputs in the configuration without test pulses the cabling prevents external short circuits (refer to DIN EN ISO 13849-2 Table D.4).

### 6.4.1 Wiring of Modules with Standard Connectors

Wires with a cross section between 0.14 mm<sup>2</sup> and 1.5 mm<sup>2</sup> (AWG 26 – 16) can be connected.

The external dimensions of the crimped wire-end ferrules must conform with IEC-60947-1.

RSTi-EP modules (except HD modules) and bus network adapters are equipped with the *spring-style* connector system. Singlestrand and fine-strand lines with wire-end ferrules can be inserted without the need for a tool.

- Each cable must be the optimal length so the bending radii observe the manufacturer's specifications.
- Strip the insulation from the lines to a length of approx. 10 mm ± 1 mm (0.4 in ± 0.04 in), even if you are using wire-end ferrules. If you use wire-end ferrules with plastic collars, strip the wires to 12 mm ± 1 mm (0.5 in ± 0.04 in).
- Connect all lines according to wiring diagram.

For the usage and handling of the *spring-style* system, refer to the section, *Removing/Replacing Cables*.




### 6.4.2 Wiring of Modules with HD Connectors EP-8360

When using HD-connectors EP-8360 qualified wires with a cross section between 0.14 mm<sup>2</sup> and 0.35 mm<sup>2</sup> (AWG 22 – 26) and an outer wire diameter between 1.0 and 1.6 mm (0.04 to 0.06 in) can be connected by insulation displacement connectors (IDC). A list of SAI cables approved for the use with HD-connectors (Document-No. GFK-2971) is available to download from the GE website.

Required tools:

- Multi-stripax 6-16 (9202210000)
- Pressing tool PWZ-UR20-HD

**Note:** When using HD-connectors EP-8360 two HD connectors must always be applied into one slot of the connector frame.



**Application of HD Connectors**

- Each cable must be the optimal length so the bending radii observe the manufacturer's specifications.
- Strip the insulation from the cable to a length of approx. 20 mm (0.8 in) using the multi-stripax 6-16.
- Insert all wires according to wiring diagram as far as they will go into the clamping unit of the connector. Regard the marking (pin 1 to 4) on the transparent presorter.
- Apply the pressing tool and check whether all wires are inserted as far as they will go.
- Press the HD connector using the pressing tool.
- Insert the wired connector into the module's connector frame.

## 6.5 Insulation Test

Insulation tests on the RSTi-EP station have to be done according to regulations, in any case, they are necessary before each commissioning.

---

**The product can be destroyed by too high test voltage.**

**Note during insulation test:**



**Caution**

- Within one channel the test voltage between 24 V and GND must not exceed 28,8 V<sup>†</sup>
  - A maximum test voltage of 500 V can be applied to all other connection points.
  - Up to 4000 V can be applied to the modules EP-2814 and
  - EP-2714:
    - between the four channels
    - between one channel and the system voltage.
- 

<sup>†</sup> GE recommends to short-circuit 24 V and GND on all power supply connectors (fieldbus network adapter, power-feed modules, and EP-19xx).

## Notes

## Chapter 7 Earthing and Shielding

The terms *earths* and *shields* are classified according to their relation to human safety or system safety. An earth is installed primarily to protect human life, and for this reason it is referred to as the protective earth (PE) conductor. A shield, on the other hand, serves to ensure the trouble-free operation of an electrotechnical system as well as electromagnetic compatibility.

The main differences between the two terms are therefore the electrical design and installation. A shield is not designed to transfer power, even though leakage currents can flow on it – something which must be avoided. In contrast, a PE conductor must be capable, at least in the short term, of discharging high residual currents (IEC 60947-7-2). The corresponding short-term current resistance of the PE connection must be  $120 \text{ A/mm}^2$  ( $77419.2 \text{ A/in}^2$ ) of the connected cross-section. To make sure a shielding concept is able to work properly, the shield impedance must be 10 times larger than the impedance of the earth potential.


The following figure shows how these two topics relate to each other in application. As shown in the figure below, the cable's shielding is connected to the earth potential so that the shield's current can be discharged. Depending on the sensitivity of the system, an attempt is made to create separate potential areas for this. However, it is still typical to mix the areas, i.e. the shielding has a common equipotential bonding (earth). This figure shows how the number of shields and PE conductors that need to be connected can increase quite rapidly (in this case only one component is used). The shielding and earthing systems must be planned carefully to provide adequate safeguards for personnel and equipment. The following sections describe the complexity and special characteristics in more detail.



Shielding



Earthing



Connection Diagram of a Frequency Converter

## 7.1 Earthing of Shielded Cables

Electrical and electronic systems must be designed such that they are largely safeguarded against electrical interference, thus enabling them to operate securely even in the case of transient interference voltages.

Electrical interference can be introduced into electric circuits in a variety of ways. The most frequent causes are due to inductive interference. In addition, galvanic and capacitive coupling as well as electrical fields and other processes are causes for interference voltages. Here, high-frequency voltage fluctuations – known as transients – are the cause of interference with a high level of effectiveness.

### 7.1.1 Shielded Cables Increase Interference Resistance

The sources of interference voltages can rarely be eliminated and even then not always completely. Thus, it is necessary to take measures to combat their effect. In general, the more effectively interference voltages can be kept away from circuit elements or can be discharged, the less electrical circuits are affected. This can be accomplished in a variety of ways with varying levels of effectiveness. A very effective measure, in particular for safeguarding against inductive effects, that is, ensuring *electromagnetic compatibility* (EMC), is the shielding of electrically functional components to earth potential. In doing so, for instance, components are installed in metallic, earthed housings and the connecting lines are equipped with shielding.

In general, it can be said that interference from cables can be combated by routing cables as far away as possible from each other, keeping the common return as short as possible and using twisted-pair wire. Far better protection, however, is provided by completely shielding of all cables. This is the most effective measure that can be taken against the coupling of interference signals.

The best type of shielding consists of a braided mesh sleeve that uses individual wires made of non-magnetic materials (copper, aluminium). The braided mesh should be sufficiently large and also be as thick as possible. For cables that are equipped with foil shields, it is necessary to be aware of the low mechanical strength and the low current-carrying capacity of the shielding.

### 7.1.2 Proper Use of Shielded Cables

The shielding of cables will only result in the desired effect if this is implemented properly. Incorrect earthing or the use of improper components that perform their task inadequately reduces or even totally eliminates the effect. Placing the shielding at any spot on the earth potential will not suffice, as this earth connection may have no effect on high frequencies. In addition, ground loops must also be taken into consideration. Furthermore, the shielding should be earthed over a large surface area. Beyond that, the quality of the shield conductor and earthing accessories is also important.

In practice, the shield is still often twisted and connected to a terminal point. There is very high attenuation (voltage drop) on these connections, especially for high-frequency interference. Therefore, this type of shielding should not be used, even for short cable lengths. The shielding of the cable is practically negated and can, at best, be helpful for low-frequency interference. We recommend that there is a large amount of surface contact with the braided shield of the cable.


There are generally four distinct types of coupling:

- Galvanic coupling
- Capacitive coupling
- Inductive coupling
- Radiation coupling

These types of interference usually occur mixed together, but they can be categorised as follows:

- Electromagnetic fields
- Ripple voltage (50 Hz)
- Lightning
- Interference pulses (current, voltage)
- Transient surge voltages
- Radio interference
- ESD (electrostatic discharge)
- Burst
- Mains feedback

Note: Another area of concern as regards shield contact is the *flow* within the conductor. Temperature changes caused by the current lead to changes in the conductor cross-section. A rigid contact can therefore only be partially effective. A self-adjusting contact is what is really required.



*Use of a Clamping Bracket*


### 7.1.3 Effective shielding

It is important that the shielding is not positioned on the earth of the connected component, but on the protective earth. In the case of components that are installed in a metal housing, the shielding must be positioned to this housing. If no earthed housing is available, the shielding is positioned on a separate earth.


When installing ground connections on shielding, it is generally also important that no earth loops are created. The smaller the earth loop, the less the danger of the induction of interference voltages. It is therefore most suitable to have a purely neutral-point installation.

The following sketches show the possible shielding connections to protective earth.


A one-sided connection of the shielding protects against capacitive coupling of interference voltages.



If you use a two-sided shielding connection, make sure that compensating current (different earth potentials) does not flow through the cable shield.



If you wish to avoid the disadvantages associated with creating an earth loop with two-sided shields, it is recommended you connect one side of the shield through a high impedance.




For longer lengths of shielded cables, such as if a sensor must be added to a control panel, a potential difference between both end points must not be ignored.

However, such shield conductors are relatively expensive and also require more time in working with them. Another possibility would be to place an additional voltage equalizing cable between the measurement location and the control panel. The shield can then be hooked up on both sides.

A high-impedance earth connection is also another option. In the control panel, the shield is then connected to the earth potential, and the shield has a high-impedance connection to earth at the measurement location via a gas discharge tube. This solves the problem of a potential transfer and 50-Hz humming.

For non-isolated measurement locations, two gas discharge tubes must be installed. One connects the shield to earth, and the other connects it to the non-isolated measurement location. This method prevents a galvanic coupling between the measurement circuit and the earthed measurement location.






## 7.2 Potential Ratios

### 7.2.1 Basic aspects

As regards the potential ratios of a RSTi-EPsystem, the following aspects must be kept in mind:

- The power supply of the network adapter and I/O modules as well as field power is provided via the power supply at the power-feed module (PF)
- A potential-free design is made possible through the use of an isolated power supply at the system power supply and the field power supply

The block diagram shows the typical design of a RSTi-EP system. The power supply concept here makes sure that, starting with a certain capacity utilisation, power refresh is implemented using power-feed modules.



*RSTi-EP Power Supply Concept*

### 7.2.2 Potential-free Design


In a potential-free design, the reference potentials of control and load circuits are galvanically isolated from each other. A potential-free design is necessary for the following:

- Use of the power-feed module (EP-19xx), i.e. in all AC load circuits
- DC load circuits that cannot be coupled

Potential-free installation depends on the type of earthing.

### 7.2.3 Non-isolated Design

In a non-isolated design, the reference potentials of control and load circuits are galvanically connected to each other.



#### RSTi-EP Earthing Concept:

The spring contacts underneath the module and the network adapter snap into the DIN rail to make a connection.

## 7.3 Electromagnetic Compatibility (EMC)

RDTi-EP products completely meet EMC requirements. EMC planning, however, is necessary prior to installation.

Aspects to consider include all potential interference sources such as galvanic, inductive and capacitive couplings, as well as radiation couplings.

### 7.3.1 Ensuring EMC

To ensure EMC, the following basic principles must be observed during installation of the RSTi-EP modules:

- Proper, extensive earthing of inactive metal parts
- Correct shielding of cables and equipment
- Proper layout of wires – cabling
- Creation of a uniform reference potential and earthing of all electrical equipment
- Special EMC measures for special applications (e.g. frequency converters, servo drives)
- Contactors and relay coils must be equipped with the corresponding interference suppressors

### 7.3.2 Earthing of Inactive Metal Parts

The earthing of all inactive metal parts reduces the influence of coupled interference. For this purpose, all inactive metal parts (such as switch cabinets, cabinet doors, support beams, mounting plates, DIN rails, etc.) must be connected to each other over a large surface area with low impedance, whereby a uniform reference potential is ensured for all control unit elements.

Required measures:

- Removal of the insulating layer around screw connections. Protection of connection points against corrosion
- Connection of moving earthed components (cabinet doors, separated mounting plates, etc.) through short earthing straps with large surfaces
- When possible, avoid using aluminium parts, because aluminium oxidises easily and in this respect is unsuited for earthing

### 7.3.3 PE connection

The connection from earth to the PE (protective earth) connection must be done centrally.



In the event of a fault, the earth must never take on a dangerous contact voltage, which is why it must be connected to a PE conductor.

---

### **7.3.4 Unearthed Operation**


In the event of unearthed operation, the corresponding safety regulations must be observed.

### **7.3.5 DIN Rails**

Notes concerning the use of DIN rails:

- Large-surface, low-impedance attachment on the mounting plate and corresponding contact with the carrier system using screws or rivets
- Proper earthing
- Use corrosion-proof DIN rails
- Remove the insulating layer on painted, anodised or insulated metal components in the area around the connection point
- Protect the connection point against corrosion (e.g. using grease; Attention: only use grease suitable for the purpose)

### 7.3.6 Cabinet Design According to EMC Guidelines



	<p>The cable must be connected to a large part of the protective conductor system.</p> <p>Refer to EMC Directive 2004/108/EC</p>
--	--

## 7.4 Shielding of Cables

To prevent the coupling of interference voltages and the decoupling of interference fields in cables, only shielded cables made from well-conducting material (copper or aluminium) with braided shielding and a coverage of at least 80 % should be used in the design of a cable shield.

Only when a cable shield is connected to the local reference potential on both sides is it possible to achieve optimal shielding against electric and magnetic fields. Exceptions are possible, for example, with high-impedance, symmetrical or analogue signal cables. If a shield is attached on only one side, this merely achieves an isolation against electric fields.



### Caution


#### Requirements for effective shielding design:

- The shield connection to the shield bus should be low impedance
  - The shield must be connected directly at its entrance into the system
  - Keep cable ends as short as possible
  - Do not use cable shields for equipotential bonding
- 

When connecting a data cable using a sub-D connector, the connection must be made through the connector's shield collar and never through pin 1.

The data cable's shield must be attached to the shield bus with the insulation stripped away. The shield is to be connected and attached with clamping brackets or similar metal fixing devices. The shield bus must be connected to the reference potential surface through a low impedance [e.g. fastening point with a separation of 10 to 20 cm (3.94" x 7.87")]. The brackets must surround and make contact with a large part of the shield.

Isolation of the cable shield should be avoided. Instead, it should be routed into the system (for example, the switch cabinet) up to the interface connection.



### Attention

When shielding field-bus cables, the installation guidelines for the respective field buses must be observed. (Refer the websites of the field bus organizations.)

---



### Caution

If it is only possible to have a one-sided shield connection for reasons specific to the circuit or equipment, the second side of the cable shield can be routed to the local reference potential via a capacitor (with short connections). To prevent disruptive discharges when interference pulses occur, a varistor or a resistor can also be wired in parallel to the capacitor.

As an alternative, a doubled version (galvanically isolated) can be used, whereby the inner shield is connected on one side and the outside shield is connected on both sides.

---

### 7.4.1 Equipotential Bonding

If system components are positioned separately from each other, potential differences may arise, provided that:

- Power is provided from different sources
- The earthing is implemented at different system parts, despite the cable shields being connected at both sides

A voltage equalizing cable must be used for equipotential bonding.



#### **Warning**

**The shield must not be used for equipotential bonding.**

---

The following features are essential for a voltage equalizing cable:

- In the case of cable shields on both ends, the impedance of the equalising cable must be considerably smaller than that of the shield connection (maximum 10 % of its impedance)
- When the length of the equalising cable is less than 200 m (656.2 ft), its cross-section must be at least 16 mm<sup>2</sup> (0.025 in<sup>2</sup>). If the cable is greater than 200 m (656.2 ft) in length, a cross-section of at least 25 mm<sup>2</sup> (0.039 in<sup>2</sup>) is necessary.
- Large-surface connection with the PE conductor or the earthing and corrosion protection are requirements for long-term safe operation
- They must be made of copper or galvanised steel
- In order to keep the enclosed area as small as possible, the equalising cable and signal cable must be routed as close to each other as possible

### 7.4.2 Inductance wiring

For inductive loads, it is recommended that protective circuits be placed directly on the load. The earth (PE/FE) must be connected in a neutral-point configuration according to regulations for switch cabinets.




#### **Caution**

**When disassembled, RSTi-EP modules and network adapters are at risk of electrostatic discharge (ESD). Therefore, avoid touching bus connections with bare hands, as this can lead to damage due to electrostatic discharges.**

---





## Notes

## Chapter 8 Commissioning



### **Warning**

Explosion risk - Prior to starting work, make sure that there is not a potentially explosive atmosphere.



### **Warning**

During commissioning, the system may be manipulated to such an extent that can result in risks to life and material damage.  
Ensure that system components cannot start up unintentionally.



### **Caution**

Conduct an insulation test before each commissioning (refer to the section, *General Contact Information*).

---

The procedures applied during commissioning depend on which control unit is being used on site. The descriptions in this chapter use commissioning with a PROFINET network adapter and the GE Proficy Machine Edition as an example.

### 8.1 Requirements

Before you start the commissioning work, the following requirements must be fulfilled.

- The control unit must be in operation.
- The RSTi-EP station must be completely assembled and wired up.
- The control unit and RSTi-EP station must be connected via fieldbus, and a PC/laptop must also be connected.
- The power supply must be turned on.


If these requirements are fulfilled, the following LEDs light up:

- On the bus network adapter
  - The PWR LED lights up green.
  - For the port to which the control unit is connected, the LINK LED lights up green and the ACT LED lights up yellow.
- On the modules, the Status LED lights up green.


## 8.2 Configuring EPXPNS001

- To add an EPXPNS001 to a LAN


From the **Navigator** right-click on the **EPXPNS001** module and select **Add I/O Device**. The **PROFINET Device Catalog** displays.




From the **PROFINET Device Catalog**, expand the **EPXPNS001** line and select the module type:



Select the **EPXPNS001** type and click **OK**. The **EPXPNS001** displays in the **Navigator** window:



The device name, IP address of the EPXPNS001 can be changed by right-clicking on the scanner and selecting properties.




IO-Device	
Device Number	1
Update Rate (ms)	128
Reference Variable	<None>
<input type="checkbox"/> Network Identification	
IO LAN	LAN01
Device Name	rsti-ep-pns
Device Description	
IP Address	192.168.0.2
<input type="checkbox"/> General	
GSDML	GSDML-V2.3-GE-EPXPNS001-20151028.xml
Device Type	EPXPNS001
Device Access Point	DAP 1
Group IO References	True

**Note:** When firmware is updated, the IP address is not retained when configured using the master module. But when configured in web server and the same IP is used in the master, it is retained during profinet NA firmware update.

### 8.2.1 Configuring EPXPNS001 Parameters

After adding a EPXPNS001 to the LAN, its parameters can be configured by either double-clicking on the scanner in the Navigator, or right-clicking and selecting Configure from the menu.

#### PROFINET Scanner Parameters IO-device Access Point



**Inputs Default:** Choose whether the RX3i CPU will set inputs from any modules in the EPXPNS001 module's remote node to Off or Hold Last State in the following cases:

- The EPXPNS001 is not operational or is removed.
- The EPXPNS001 cannot reach the scanner due to cable or network configuration issues.
- The EPXPNS001 is not able to scan the VersaMax module in its remote node.

**I/O Scan Set:** Specifies the I/O scan set to be assigned to the EPXPNS001. Scan sets are defined in the CPU's Scan Sets tab. The valid range is 1 through 32; the default value is 1.

#### PROFINET Scanner Parameters (Media Redundancy Tab)

By default, the EPXPNS001 is not set up for Media Redundancy. If the system will use Media Redundancy, open the Media Redundancy Tab and select Client.

Parameters	
Media Redundancy	Client
Ring Port 1	1
Ring Port 2	2
Domain Name	mrpdomain-1

#### PROFINET Scanner Parameters (General Parameters Tab)

The EPXPNS001 has seven module parameters:

Parameters	
Process Alarm:	enabled
Diagnostic Alarm:	enabled
Type of diagnostic:	Extended Channel diagnostic
Behaviour of outputs on field bus error:	All outputs off
Module behaviour on hot swap:	Continue data exchange
Data format:	Motorola
Lock force mode:	Force mode unlocked

**Process Alarm, Diagnostic Alarm:**

User can select the process alarm, diagnostic alarm to be enabled or disabled. By default they are disabled.

**Type of Diagnostic:**

The Type of diagnostic can be selected either “Extended Channel diagnostic” or “Vendor Specific diagnostic”.

Type of diagnostic:	Extended Channel diagnostic
Behaviour of outputs on field bus error:	Extended Channel diagnostic Vendor specific diagnostic

**Behavior of Outputs on Filed Bus Error:**

The behavior of the outputs can be set to all outputs to go off, set to substitute value or Hold last state.

Behaviour of outputs on field bus error:	All outputs off
Module behaviour on hot swap:	All outputs off Enable substitute value Hold last value

**Module Behavior on Hot Swap:**

When the user performs hot swap, user can either continue data exchange or can behavior like field bus error.

Module behaviour on hot swap:	Continue data exchange
Data format:	Continue data exchange Behaviour like field bus error

**Data Format:**

User can select either Motorola or Intel data format. By default it is Motorola.

Data format:	Motorola
Lock force mode:	Motorola Intel

**Lock Force Mode:**

User can enable the force of outputs while the slave is communicating with the master or can lock the force mode so that the outputs can not be forced.

Lock force mode:	Force mode unlocked Force mode unlocked Force mode locked
------------------	---

**PROFINET Scanner Parameters (GSDML Tab)**

The EPXPNS001 module's GSDML tab displays the information from its GSDML file.

IO-Device Access Point   Media Redundancy   General Parameters   <b>GSDML Details</b>	
Device Access Point: EPXPNS001	
Name:	EPXPNS001
ID:	DAP 1
DNS Compatible Name:	rsti-ep-pns
Physical Slots:	0..64
Supports System Redundancy:	False
Description:	PROFINET IRT NETWORK ADAPTER, 2 CU PORTS
Vendor:	GE Intelligent Platforms, Inc.
Order Number:	EPXPNS001
Hardware Release:	256
Software Release:	V01.00.00
Graphic: GSDML-015A-000C-EPXPNS001	
	

This information cannot be edited.

Double-clicking on the EPXPNS001 module's Interface 1 icon in the Navigator displays additional GSDML parameters:


GSDML Details	
Interface: EPXPNS001	
Interface:	EPXPNS001
Supported RT Classes:	RT_CLASS_1:RT_CLASS_3
Supported Protocols:	SNMP;LLDP
Supported Management Info Bases:	MIB2
Network Component Diagnosis Supported:	True
DCP Hello Supported:	True
PTP/LLDP Boundary Supported:	False
DCP Boundary Supported:	False

Double-clicking on the EPXPNS001 module's Port 1 and Port 2 icons in the Navigator also displays Settings and additional GSDML parameters for the scanner:

Settings: GSDML Details	
Port: Port 1	
Port:	Port 1
MAU Types:	16
Maximum Tx Delay:	108
Maximum Rx Delay:	302
Deactivation Supported:	True
Link State Diagnosis Capability:	UpDown
Power Budget Control Supported:	False
Is Default Ring Port:	True
Check MAUtypes	True


## 8.2.2 Adding EPXPNS001 Modules to a Remote Node

To add a module to the remote node, right click on the EPXPNS001 icon in the Navigator and select Change Module List. In the right pane of the Change Module List window, expand the list of VersaMax module types.





Select modules from the list and drag them to their slot locations in the remote node.



(If you need to delete a module on the left, select it and press the keyboard Delete key). When the modules on the left are correct, click OK to add them to the configuration.

### 8.2.3 Configuring EPXPNS001 Module Parameters

After adding RSTi-EP modules to the remote node, their parameters must be configured. For all EPXPNS001 modules, this includes configuring a set of basic parameters (such as: reference address, length, general parameters).


## 8.3 Configuring EPXPBS001

The number and types of slave devices that can exchange data with the master are constrained by memory resources within the master module. The amount of memory available for the PROFIBUS configuration is affected by the number and types of slave modules in the network configuration. The total slave configuration data size is limited to approximately 9KB.

### 8.3.1 Adding Slaves and Modules


➤ **To add slaves and modules**

1. Start GE Proficy Machine Edition.
2. In the Navigator window, right-click the EPXPNS001 and select **Add Slave**. The **Slave Catalog** dialog box displays. This dialog box lists the slave devices that are available to configure in the PROFIBUS network.



3. Select a slave device and click **OK**. The **Slave Properties** dialog box displays.


**Note:** If the slave module is not in the list but you have a GSD file for it, click **Have Disk**.



<b>Name</b>	The name assigned to the slave. You can edit the name or use the default name. The name appears in the title bar of the dialog box (in the figure above, the default name is Station 1).
<b>Station</b>	The address of the slave on a PROFIBUS DP network. The slave is defaulted to the next highest available address.
<b>Description</b>	An optional description for the slave device. The Inspector displays a maximum of 254 characters. However, more than 254 characters can be entered in the dialog box.
<b>Vendor</b>	The manufacturer of the slave device, from the GSD file. This is a read-only field.
<b>Device ID</b>	The ID of the PROFIBUS device. This is a read-only field.
<b>Model</b>	The model of the slave device. This is a read-only field.
<b>Hardware Rev.</b>	The hardware revision of the device, from the GSD file. This is a read-only field.
<b>Class</b>	The class of the slave device. This is a read-only field.
<b>Software Rev.</b>	The software revision of the device, from the GSD file. This is a read-only field.


4. Enter **Name**, **Description** and **Station** if desired.
5. To add modules to the slave, select the **Modules** tab and click **Add**. The **Select New Module** dialog box displays.

**Note:** To add the slave to the configuration, you must configure at least one module.



**Note:** The Select New Module list of modules is determined by the .GSD for the slave type. Each type of slave may have a different list of modules.


6. Select a module and click **OK**. The module is added to the **Modules** list in the **Slave Properties** dialog box. Add additional modules as required for your system. The following figure shows the **Modules** tab after several modules have been added.




To change the order (position) of a module, select it and click **Properties**. The **Module Properties** dialog box displays. Enter the numerical value of the new position the module is to have. The position numbering starts at 0.

The other information in this dialog box is generated by the GSD file associated with the Slave module.

**Note:** The Data field corresponds to the module's configuration identifier as defined in the PROFIBUS specification.



7. When finished adding modules, click **OK**. The modules display under the **Slave** node in the **Hardware Configuration**.



**Note:** To add, remove, or change the order of modules associated with an existing slave, right-click the Slave node in the Hardware Configuration and select **Configure**. The Properties dialog box for the selected slave opens.

### 8.3.2 Configuring Module Data Areas

- **To configure module data areas:** Right-click the **Module** node in the **Hardware Configuration**, and select **Configure**. The **Parameter Editor** window for the module displays.

The values for read-only parameters are supplied from the GSD text file that defines the PROFIBUS module's characteristics. Most devices have one data area with inputs, outputs or both. Some devices have multiple data areas that are shown as additional rows.

#### Data Area Parameters

<b>Area</b>	This value is an index beginning at 1. Read-only.
<b>Type</b>	Specifies whether the data is input or output as well as type, digital or analog. Value can be Digital In, Analog In, Digital Out, or Analog Out.
<b>Ref Address</b>	Specifies the memory area that is used to map the data area. Regardless of the reference type used, input areas are considered as consumed and cannot overlap, while output areas are considered as produced and may overlap. Allowable Ranges: %AI, %AQ, %I, %Q, %G, %R, %W, %T, %M. If the number of bytes is odd, analog memories are not allowed and selections are limited to: %I, %Q, %G, %M
<b>Length</b>	Specifies the length of the reference. Includes the entire data area by default. If set to 0, the data area is not mapped. For discrete memories, the allowable range is [0, 8, 16, ..., X] For analog memories, the allowable range is [0, 1, 2, ..., X]
<b>Swap Bytes</b>	The swap bytes field is used to manipulate the byte order. Because PROFIBUS devices often do not follow the standard, the ability to change byte ordering is provided. The analog areas travel in MSB and should be swapped if LSB is required. <ul style="list-style-type: none"> <li>■ If Type is Digital and the module has an odd number of bytes, Swap Bytes is set to False (no swapping) and read-only.</li> <li>■ If Type is Digital and the module has an even number of bytes, default is set to False. Setting Swap Bytes to True causes the LSB and MSB to be swapped before the data is mapped into PLC memory.</li> <li>■ If Type is Analog, default is set to False. Setting Swap Bytes to True causes the LSB and MSB to be swapped before the data is mapped into PLC memory.</li> <li>■ For EP-5111, EP-5112, EP-5212, EP-5442 and EP-5422 modules, user should set Swap Bytes to true. In application if the user want to access the DWORD for these modules, use SWAP_DWORD function block.</li> </ul>

### 8.3.3 Configuring DP-V1 Settings for a Slave


Whether or not a slave device supports DP-V1 functions is indicated in the GSD file provided by the vendor of that device. For devices that do provide DP-V1 functions, support is disabled by default.

➤ **To enable DP-V1:**

1. From the **Project Navigator**, right-click the **Slave** and select **Properties**.



2. In the **Properties** window, click the ellipsis (...) in the **DPV1 Settings** field. The **PROFIBUS DPV1 Setup** dialog box displays.



## PROFIBUS DPV1 Setup Parameters

The default values in this dialog box are populated by the GSD file associated with the device.

<b>Enable DPV1 Support</b>	Check this box to enable DPV1 settings for the selected PROFIBUS device. The device's GSD file determines which settings are editable and which are read-only. Clear this check box to disable DPV1 settings. The values of all parameters are retained until the DPV1 settings are enabled again for the selected device.
<b>Maximum Channel Data Length</b>	The maximum length in bytes of the DPV1 telegrams. The slave adapts its buffer size for the respective data count. Valid range: 4 through n bytes, where n is the value specified in the GS? file.
<b>Maximum Alarm PDU Length</b>	The maximum length in bytes of the DPV1-Alarm telegrams. Valid range: 4 through n, where n is calculated by the following formulas $m = \text{Max\_Diag\_Data\_Len} - 6$ $n = \text{Max}(\text{Min}(m, 64), 4)$ Max_Diag_Data_Len is a value specified in the GS? file. If m is greater than 64, n is set to 64. If m is less than 4, then n is set to 4. Otherwise, n is set to m. If n is set to 4, the only valid Maximum Alarm PDU Length is 4. Default: The value n calculated by the above formulas.
<b>Diagnostic Update Delay</b>	The maximum number of extra diagnosis cycles that the master waits to obtain from a slave the release for a DATA_EXCHANGE. If the Diagnostic Update Delay is set to 0, the master waits for one diagnosis cycle before reporting an error. If the Diagnostic Update Delay is set to 15, the master waits for 16 diagnosis cycles before reporting an error. The master waits for one diagnosis cycle more than the value of the Diagnostic Update Delay. Some newer slave devices require more time for the consistency testing for the processing of the SET_PRM parameterizing telegrams. Therefore a simple diagnosis cycle may be insufficient until the participant can inform the Master of the release for the DATA_EXCHANGE. Valid range: 0 through 15.
<b>Maximum Active Alarms</b>	The maximum number of possible active alarms. Choices: 1 alarm of each type 2, 4, 8, 12, 16, 24 or 32 alarms in total

## Slave Functions

<b>Extra Alarm Service Access Point</b>	The service access point (SAP) through which the master quits alarms. Choices: Master Alarmacknowledge SAP51: Master quits alarms via SAP51. Master Alarmacknowledge SAP50: Master quits alarms via SAP50.
<b>Configuration Data Convention</b>	The DPV1 data types. Choices: Configuration Data of EN 50170 Configuration Data of DPV1


## Enabled Alarms

<b>Pull Plug Alarm</b>	Editable or read-only, depending on the GSD file. When this box is checked, a slot signals the withdrawal of a module or the insertion of a module.
<b>Process Alarm</b>	Editable or read-only, depending on the GSD file. When this check box is checked, a process alarm signals the occurrence of an event in the connected process. For example, the event may be "upper limit value exceeded."
<b>Diagnostic Alarm</b>	Editable or read-only, depending on the GSD file. When this check box is checked, a diagnostic alarm signals an event within a slot. For example, events may be over temperature or short circuit.
<b>Manufacture Alarm</b>	Editable or read-only, depending on the GSD file. When this box is checked, manufacturer-specific alarms are enabled.
<b>Status Alarm</b>	Editable or read-only, depending on the GSD file. When this check box is checked, a status alarm signals a change in the state (such as run, stop, or ready) of a module.
<b>Update Alarm</b>	Editable or read-only, depending on the GSD file. When this check box is checked, an update alarm signals the change of a parameter in a slot, for example, by a local operation or remote access.

## 8.4 Configuring EPXECT001


### ➤ To configure EPXECT001

1. Open CoDeSys software, right-click **CoDeSys** and select **Add Device**.




2. From the **Add Device** dialog box, click to select **Append device**, then double-click **EtherCAT Master**.







- From the CoDeSys software **Tree View**, select **EtherCAT\_Master** and from the **Tools** menu, select **Install device**.




- From the **Install Device Description** dialog box, select the **GE\_EPXETC001\_TwinCAT.xml** file and click **Open**.



5. From the **Add Device** dialog box, click to select **Append device**, select the **EPXETC001** device, and click **Add Device**.




6. From the **Add Device** dialog box, select the **I/O devices** from the list and click **Add device**.



➤ **To change the module parameters**

1. From the CodeSys software **Tree View**, select the **Network Adapter** and the **Startup parameters** tab.
2. Right-click the **Name** column, select **Add** from the drop-down menu, select the parameter details to add, and click **OK**.



### 8.5 Configuring EPXMBE001

The Modbus/TCP Network Adapter, EPXMBE001, Modbus/TCP register mapping is automatically determined by the I/O modules included in the physical configuration. Network Adapter and I/O Module parameters are configured using the Network Adapter Web Server interface. Refer to the section, *Modbus® TCP Network Adapter EPXMBE001* of this manual for more information on the automatic Modbus/TCP register mapping information. Refer to the Chapter, *Web Server* for more information on editing the Network Adapter and I/O Module parameters Web Server interface.

## Chapter 9 Web Server

With the web server, the RSTi-EP station is displayed on a connected PC. This allows you to carry out the following tasks prior to the complete commissioning of a system:

- Simulate the operation of the RSTi-EP station
- Query the status of each network adapter and module
- Display the parameters of network adapters and modules, and change them for testing purposes
- Access diagnostic information
- Operate the station in Force mode for testing purposes

With default settings each network adapter type offers web server access only via USB port. For that multiple IP addresses can be parametrized. Please note that this is a virtual DHCP server. To avoid network disruption no other network device with the same subnet ID should be connected to the PC.

Using network adapters for Ethernet-based fieldbus systems – recognizable by the RJ45 socket – web server access can be realized alternatively via Ethernet. This function must be enabled in the web server in the network adapters parameter setup. Any changes of the IP settings on either USB port or Ethernet port will not be effective until restarting the network adapter.



### **Warning**

**Explosion Risk - Prior to starting work, make sure that there is not a potentially explosive atmosphere.**



### **Warning**

**In Force mode, the system may be manipulated to such an extent that can result in life-threatening personal injury and damage to materials. Only use Force mode if you are very familiar with the connected system and know at all times the consequences that your actions will have.**



### **Caution**

**Prior to connecting a PC, make sure that the RSTi-EP station has been grounded properly.**

---

## 9.1 Requirements

The RSTi-EP station must be completely assembled and supplied with voltage.

### 9.1.1 Operating System

The RSTi-EP web server is designed for operation with the Windows® XP, Windows 7 and Windows Vista operating systems.

### 9.1.2 Browser

The RSTi-EP web server can be used with the following browsers:

- Microsoft® Internet Explorer® 9, 10, 11
- Mozilla® Firefox 4.0 or higher
- Opera 10.61 or higher
- Google® Chrome 9.0 or higher

### 9.1.3 Device Drivers


You need the driver files **usb8023.inf** and **rndis.inf**, which you can download from the <http://support.ge-ip.com> website.

## 9.2 Installing the USB Driver


**Note:** The USB port acts as a virtual DHCP Server. Please do not assign any IP addresses to other devices within the same subnet of the USB port (default 192.168.1.0), otherwise network failure might occur.

### ➤ To install the USB driver

1. Start up your PC.
2. Connect the PC to the network adapter using a USB cable (Type USB-A to USB Micro-B). The USB socket at the network adapter can be found behind the service flap.  
**Note:** The USB cable can be a maximum of 2 m in length. Extension cables must not be used.
3. You receive the message that Windows cannot install the driver.
4. To install the driver manually, open the **Device Manager**. Under **Other devices** the interface **RSTi-EP NA** displays.



5. Right-click on the interface and select **Update driver software**. You will be asked if you would like to search for the driver software.
6. Select **Search for driver software on this computer**.



7. Click **Browse** and select the folder in which you have stored both **.inf** files and click **Next**.  
**Note:** There could be a security inquiry because the driver software does not have a signature. Nonetheless, continue with the installation.
8. Follow the rest of the steps in the installation routine until the successful installation is confirmed. The driver displays in the **Device Manager** under **Network adapters**.



9. Close the **Device Manager**.

### 9.3 Starting the Web Server

**Note:** Simultaneous access via both interfaces to the webserver is not possible. Make sure that there is no USB connection before you start the access via Ethernet.

#### ➤ To start the web server

1. Open an internet browser.
2. In the address line, enter the **IP address** of the network adapter (default: **192.168.1.202**).


### 9.3.1 Activating the Ethernet Socket

➤ **To activate the Ethernet socket**

1. In the station view, click on the **Network Adapter** and then **Parameters**.
2. Scroll down the list of parameters until you see the entry **Web server via Ethernet**.
3. Change the setting to **enabled**.


Parameter	
Connected to fieldbus	Off
IP address	0   0   0   0
Subnet mask	0   0   0   0
Gateway	0   0   0   0
Webserver via Ethernet	enabled
IP address USB port	192.168.1.202
Station name	node3
Process alarm	disabled
Diagnostic alarm	disabled
Type of diagnostic alarm	Vendor-specific diagnostic
Output behaviour on fieldbus error	All outputs off
Module behaviour on hot swap	Continue data exchange
Data format	Motorola

4. Enter the required **IP address** and **Subnet mask**.
5. Click **Apply Changes** to confirm.
6. Close the network adapter window and restart the network adapter. You can review the **IP address** in **Windows Control Panel**, in the **Network and Sharing Center**.
7. Under **Unidentified network**, click on **LAN connection**. The **LAN Connection Status** window displays.



8. Click **Details**. The **Network Connection Details** window opens.





The IP address of the virtual LAN port (the USB connection) displays under **IPv4 DHCP server**. The standard IP address is **192.168.1.202**. The web server is started.

## 9.4 Setting up Registration Data and Password Protection

If you do not set up a user, all web server functions are accessible to every user at all times. As soon as you set up a user with password protection, users without a user ID will only have read-only rights. Write access is blocked for them, which means that they cannot do the following:

- Change parameters
- Operate the station in Force mode
- Load firmware updates

### ➤ To set up registration data and password protection

1. When you start up the web server for the first time, you are prompted to enter the registration data. The Change login data window opens automatically. You can access this window later via the Network Adapter status dialog box (refer to the section, 9.6):

The 'Change login data' window contains the following fields and buttons:

- Current login**
  - User name:
  - Password:
- New login**
  - New user name:
  - New password:
  - Repeat new password:


At the bottom, there are three buttons: 'Change login', 'No login data', and 'Cancel'.

2. Enter the **User name** and **Password**.
3. To change the login data, enter the **new user** name and the **new password** twice, click on **change login**.
4. To deactivate password protection, do not enter any new data, but instead, click on **No login information**.
5. If you have changed the login data, you must log back in again afterwards.

**Note:** A forgotten password can be overwritten if the network adapter gets restarted with no modules connected.

**Note:** The status data can be displayed at all time, regardless of the state of the field bus connection. Setup changes can only be stored while the field bus is not active.

After registration, the connected station is displayed with all of its active modules.



**Note:** The web server only registers modules that can communicate on the system bus. Empty slot modules and other passive modules (for example, AUX modules) are not registered by the web server and therefore are not displayed in the screen view. Because of this, the numbering of the modules in the web server view may deviate from the count in the actual station.


## 9.5 Navigation and Operating Instructions

### 9.5.1 Setting the Language

When the program is started, the web server attempts to start with the language set in your web browser. If this language is not supported by the web server, the program starts with the *English* setting.

New language versions are continually being developed and can be later installed by the user with separate language files.

- **To change the language:** Click **Language** and select the desired setting.




### 9.5.2 Zooming the View In/Out

- **To zoom the view in/out:** Click on the magnifying glass symbol to zoom in or out on the station's display.



### 9.5.3 Quick View (Tooltip) of Detailed Values

- **To display detailed channel values:** Move the cursor slowly over the station without clicking. The detailed values of the channel on top of which the cursor is presently situated display.




## 9.6 Displaying and Editing the Network Adapter Status

**Note:** These functions are only accessible when *Force* mode is *not* activated.

**Note:** The status data can be displayed at all times, regardless of the state of the field bus connection. Setup changes can only be stored while the field bus is not active.

- **To display and edit the network adapter status:** Click on the **network adapter**. The **Network Adapter Status** dialog box displays.



Parameter	
Connected to fieldbus	Off
IP address	0 0 0 0
Subnet mask	0 0 0 0
Gateway	0 0 0 0
Webserver via Ethernet	disabled
IP address USB port	192.168.1.202
Station name	node3
Process alarm	disabled
Diagnostic alarm	disabled
Type of diagnostic alarm	Vendor-specific diagnostic
Output behaviour on fieldbus error	All outputs off

From here you can:

- Reset the network adapter to factory default settings
- Change the registration data and set up password protection to limit access to the web server
- Reset any changes that have been made
- Access the network adapter parameters
- Access the network adapter's datasheet (link to product designation)


### 9.6.1 Resetting the Web Server

You can undo all the changes that have been made since the last time that the web server was started.

**Note:** After a reset, the network adapter is restarted. All data not protected against power failure is reset.

➤ **To reset the web server**

1. Click on the **network adapter**.
2. From the **Network Adapter Status** dialog box, click **Reset**.




3. To reset changes that have been made, respond to the prompt by clicking **Yes**.

### 9.6.2 Resetting the Network Adapter to Factory Settings

This function allows you to set up the web server in its original state as at delivery. This also includes registration data and password protection.

➤ **To reset the network adapter to factory settings**

1. Click on the **network adapter**.
2. From the **Network Adapter Status** dialog box, click **Factory settings**.



3. Click **Yes** to confirm that you would like to reset the network adapter to the factory settings.

### 9.6.3 Accessing Network Adapter Parameters

- **To access network adapter parameters:** Navigate to the **Network Adapter Status** dialog box and click **Parameters**. All the parameters are then listed in a new window.

no connection

Parameter

Connected to fieldbus: Off

IP address: 192.168.0.200

Subnet mask: 255.255.255.0

Gateway: 192.168.0.1

Webserver via Ethernet: enabled

IP address USB port: 192.168.1.202

Station name: node10

Process alarm: disabled

Diagnostic alarm: disabled

Type of diagnostic alarm: Vendor-specific diagnostic

Output behaviour on fieldbus error: All outputs off

Module behaviour on hot swap: Continue data exchange

Data format: Motorola

Lock force mode: Force mode unlocked

+ General information

Apply changes Restore

For parameters that can be edited, enter the changes in the entry fields or select alternative settings from a dropdown menu.

## 9.7 Displaying Module Data and Editing Parameters

**Note:** These functions are only accessible when Force mode is not activated.

**Note:** Parameters can only be written when the field bus is not active.

- **To display module data and edit parameters**

1. Click on a **module** to view its properties. A window with all status values displays.

Module 1: EP-2218 (Ordering data)

+ General information

Channel 0 Value 0

Parameter

Substitute value Off

Channel 1 Value 0

Parameter

Substitute value Off

Channel 2 Value 0

+ Parameter

Channel 3 Value 0

+ Parameter

Channel 4 Value 0

+ Parameter

Channel 5 Value 0

+ Parameter


Channel 6 Value 0

+ Parameter

Channel 7 Value 0

+ Parameter

2. To open the datasheet for the module, click on the link next to **Name**.
3. To change individual parameters, click **Parameters**.




For parameters that can be edited, alternative settings are offered in a dropdown menu:

1. Select the **parameter** you would like to change.
2. Select the desired setting from the dropdown menu.
3. Click **Apply Changes** to save all changes and close the window.
4. Click **Close** to close the **Module Status** window.

## 9.8 Displaying Node Information

You can use this menu to display all of the Process data and Diagnostic data.





## 9.8.1 Displaying Process Data

### ➤ To display process data

1. From the menu bar, click **Node Info** and then **Process Data**. The overview displays all modules and channels along with their current values; these values are continuously updated.

Process data

Channels	1 EP-2218	2 EP-3704	3 EP-3804	4 EP-225F	5 EP-4164	6 EP-3124
0	1	0	0	1	7.000 V	5.926 V
1	0	0	0	0	0.000	0.000
2	0	0	0	0	0.000	0.000
3	0	0	0	0	0.000	0.000
4	0			0		
5	0			1		
6	1			0		
7	0			0		
8				0		
9				0		
10				1		
11				0		
12				0		
13				0		
14				1		
15				0		

2. Click **Close** to leave this view.

## 9.8.2 Displaying Diagnostic Data

### ➤ To display diagnostic data

1. From the menu bar, click **Node Info** and then **Diagnostic data**. In the overview, all of the modules that have diagnostic messages.

Diagnostic data

0	Diagnosis message
EPXPNS001	Forcing active
	No connection
6	Error
EP-3124	

2. Click **Diagnostic message** to view the message.
3. Click **Close** to leave this view,.

## 9.9 Web Server in Force Mode



### Warning

In Force mode, the system may be manipulated to such an extent that can result in life-threatening personal injury and damage to materials.

Only use Force mode if you are very familiar with the connected system and know at all times the consequences that your actions will have.


**Note:** If the force mode is activated during an established field bus connection a diagnose alarm is generated. Depending on parametrized alarm behaviour the PLC can continue to transmit process data and the RSTi-EP station will process them for all unforced channels. However, forced channels will ignore any process data and behave according to forced values.

**Note:** Safety related modules (EP-19xx) can not be forced.

The force mode allows you to carry out functional tests or preconfigure the station prior to commissioning, even if sensors have not yet been connected.

To do so, you must change the operating mode of the web server.


- **To enable force mode:** From the menu bar, click on **Force** and **enable**.



The web server is now in force mode.

**Note:** When force mode is activated, the screen display changes.

**Note:** If the USB connection is interrupted, force mode is stopped immediately.




- **To force a module:** Click on the respective channel.

- To accept an individual change: Click **Apply changes**.
- To accept all changes: Click **OK**.

9.9.1 Open the Detail View of the Station in Force Mode

For a better survey we recommend changing to the detail view. In this view modules can be fade out and in, which is helpful, especially when working with larger stations.


- To open the detail view in force mode: From the menu bar, click **Force** and **Node**.



All active modules are displayed in the overview. The switchable channels are provided with a changeover switch.

9.9.2 Filtering the Module View

- To view only the modules that you would like to force: Click the Filter bar.



Displayed modules are highlighted in color in the filter bar, while hidden modules are displayed in white.

Overview Node Info **Force** ⚠ Force mode

**Node**

Filter

Choose modules ▶ All ▶ None

1  
EP-2218

2  
EP-3704

3  
EP-3804

4  
EP-225F

5  
EP-4164

6  
EP-3124

Channels	1 EP-2218	3 EP-3804	5 EP-4164	6 EP-3124
0	<input type="checkbox"/> ×	0	0.000 V	0.000 V
1	<input type="checkbox"/> ×	0	0.000	0.000
2	<input type="checkbox"/> ×	0	0.000	0.000
3	<input type="checkbox"/> ×	0	0.000	0.000
4	<input type="checkbox"/> ×			
5	<input type="checkbox"/> ×			
6	<input type="checkbox"/> ×			
7	<input type="checkbox"/> ×			
8				
9				

- **To display or hide modules:** From the filter bar, click on the module you would like to display or hide.

### 9.9.3 Resetting Filters

- **To display all modules again:** Click **Display all**.
- **To hide all modules:** Click **Hide all**.

### 9.9.4 Manually Switching Outputs (Forcing)

- **To switch a channel:** Click on the corresponding **module** in the Node display.

**Node**

Filter

Choose modules ▶ All ▶ None

1  
EP-2218

2  
EP-3704

3  
EP-3804

Channels	1 EP-2218	2 EP-3704	3 EP-3804
0	<input checked="" type="checkbox"/> ×	200.700 °C	3276.700 °C
1	<input checked="" type="checkbox"/> ×	3276.700 °C	0
2	<input type="checkbox"/> ×	0	0
3	<input type="checkbox"/> ×	0	0
4	<input type="checkbox"/> ×		
5	<input type="checkbox"/> ×		
6	<input type="checkbox"/> ×		
7	<input type="checkbox"/> ×		

- **To accept an individual change:** Click on **Apply changes**.
- **To accept all changes:** Click **OK**.

9.9.5 Modules with Registers

Modules with registers (for example, counter modules and PWM modules) can be forced individually.

- **To force individual modules with registers**
  1. Click on the **channel** that needs to be forced, enter the required value, and click **Apply Changes**.

Node  
Filter  
Choose modules All None

1  
EP-2218

2  
EP-3704

3  
EP-3804

Channels	1 EP-2218	2 EP-3704	3 EP-3804
0	<div><input checked="" type="checkbox"/> <input type="checkbox"/></div>	<div>200.700 °C </div>	<div>57.700 °C </div>
1	<div><input checked="" type="checkbox"/> <input type="checkbox"/> </div>	<div>3.700 °C </div>	<div>0</div>
2	<div><input type="checkbox"/> <input checked="" type="checkbox"/> </div>	<div>0</div>	<div>0</div>
3	<div><input type="checkbox"/> <input checked="" type="checkbox"/> </div>	<div>0</div>	<div>0</div>
4	<div><input type="checkbox"/> <input checked="" type="checkbox"/> </div>		
5	<div><input type="checkbox"/> <input checked="" type="checkbox"/> </div>		
6	<div><input type="checkbox"/> <input checked="" type="checkbox"/> </div>		
7	<div><input type="checkbox"/> <input checked="" type="checkbox"/> </div>		

Apply changes Restore

9.9.6 Ending/Deactivating Forced Operations

- **To cancel a forced operation:** Click **Restore**. All of the changes you made will not have any effect.
- **To deactivate Force mode:** Click **Disable**.

## 9.10 Updating Firmware

Before you can update the firmware, you must download the latest firmware file for each network adapter and each module from the GE website to your local PC.

Firmware files for the network adapter have the extension .bsc. For PROFINET network adapters, for instance, the file might be named EPXPNS001\_.....xyz.bsc.

Firmware files for IO modules have the extension .bsm. For Analog input modules, for instance, the file might be named EP-3\_.....xyz.bsm.

The language files will be in the format NA-....xyz.lng.


**Note:** You can determine for each module separately whether an update shall be proceed.

**Note:** A firmware update cannot be undone. The old firmware in the network adapter/module is overwritten.


**Note:** Make sure that the power supply is not interrupted while the firmware files are being loaded

### ➤ To update firmware


1. Navigate to the web server and click **Firmware**. The **Firmware** window displays.




2. Click **Select firmware**, to select a firmware file for the required module.
3. Select the firmware file from the storage location on your computer and click **Open**.



- Click **Update now** to carry out a firmware update for individual modules in the RSTi-EP station.
- You can also update multiple modules by clicking **For Multi update Click here**. Use the relevant firmware file for this purpose. Once the firmware file has been loaded, the **Options** area displays which modules can be updated with this file.



- Click to check or uncheck the boxes so that only those modules that are to be updated are selected.
- Once you have called up all the required firmware files and you have selected the required modules, click **Update now**.
- Once the firmware is updated, a Firmware update message box recommending a restart of the network adapter displays.




9. Click **Reset** and restart the network adapter (power reset) to complete the firmware update



## 9.11 Web Server About Help

- To access web server help: Click **About**.



The program version of the web server is displayed in the help dialog box.

- To open the manual for the RSTi-EP station: Click on the link.

### 9.11.1 Exporting Log Data, Saving a Service File

In the event of problems and service cases, it may be helpful to save the current log data for the RSTi-EP station. This data can provide the service technician with valuable information about the malfunction.

- To save a service file
1. Click on **Save service file**.
  2. Select a storage location on your PC for the service file (**logdata.wmi**) and click **Save**.
  3. Click **Close** to close the window.

## Notes

# Chapter 10 Replacing Components

## 10.1 Removing/Replacing the Plug-in Unit



**Warning**

Explosion Risk - Prior to starting work, ensure that there is not a potentially explosive atmosphere.

---



**Warning**

All work on the RSTi-EP station must be carried out with the power supply disconnected. Ensure that the place of installation (switch cabinet and such) has been disconnected from the power supply.

---




**Caution**

The components in the RSTi-EP series can be destroyed by electrostatic discharge. Ensure that personnel and work equipment are adequately earthed!

---

➤ To remove/replace the plug-in unit


1. Unlock the connector frame.



2. Swivel the plug-in unit with the cabling towards the front by 90°.

**Note:** The plug-in unit can only be removed in this 90° position.

3. Remove the plug-in unit by pulling it out in a straight, downward motion.



## 10.2 Replacing the Electronic Unit



**Explosion Risk** - Prior to starting work, ensure that there is not a potentially explosive atmosphere.

### Warning



### Caution

Pulling or inserting of an electronic unit might bring the inputs and outputs of all other modules temporarily into an undefined condition.

If the machine/system might be put into a dangerous state as a result of the removal of an electronic unit, a replacement can only be made once the machine/system is disconnected from the power.

Only one electronic unit may be removed from the station at any one time. If multiple electronic units have to be replaced, this must be done consecutively.



### Caution

The components in the RSTi-EP series can be destroyed by electrostatic discharge. Ensure that personnel and work equipment are adequately grounded.

**Note:** Once an electronic unit is removed from a power-feed module, the inputs and outputs of the subsequent modules are no longer supplied with power. For EP-19xx modules, this is equivalent to triggering the connected safety equipment.

An electronic unit can be replaced while the system is powered up (no load) and in operation without having to disassemble the module. The station remains functional, and there is no need to disconnect and restart it. When replacing the electronic unit, the wiring remains intact.

**Operation and Behavior of I/O Module During Hot-swap**

<b>Behavior of Outputs on Field Bus Error</b>	<b>Module behavior on hot swap: Continue data exchange</b>	<b>Module behavior on hot swap: Behavior like field bus error</b>
All outputs off	The I/O modules continue data exchange on hot swap of the module.	All of the outputs will be OFF until the module is replaced as per the original configuration.
Enable substitute value	The I/O modules continue data exchange on hot swap of the module.	All of the outputs will be replaced by the substitute value as per the configuration until the module is replaced as per the original configuration.
Hold last value	The I/O modules continue data exchange on hot swap of the module.	All the outputs will be retained prior to hot removal of the module until the module is replaced as per the original configuration.



**Caution**

During hot insertion or removal of IO modules, a transient Loss of Power up-to 500 ms may occur on the network adapter and IO modules, during which all of the outputs may drop to zero. This system behavior should be verified against the application requirements before hot insertion or removal of the IO module is done.





**Caution**


Data shift occurs when a module is pulled out from a node where similar modules are sequentially configured. For example, when there are 6 RTD modules EP-3704 configured sequentially in the node, on hot-removing the module from the slot 4 would case the data from the module 5 and 6 to be reflected on variables configured for slot 4 and 5 with 'Loss of Module' reported for slot 6.

➤ **To replace the electronic unit**


1. Unlock the connector frame and open it as far as possible (at least to an angle of 90°).



2. Lift the electronic unit removal lever and swivel it forwards by 90°.




3. Using the removal lever, pull the electronic unit forwards and out.



4. If the existing electronic unit was coded, insert the new coding pins into the coding seats located in the base module.
5. Hold the new electronic unit by the top and the bottom, and carefully slide it into the base module.

**Note:** The electronic units are functionally coded so that they can only be inserted into the appropriate base module. If it is not possible to insert a new electronic unit into the base module, check if the combination is correct and if there is a possible mix-up.





6. Fold the connector frame back so that it closes and clicks into place.
7. In case of replacement during operation: Pay attention to the **collective error LED (SF)** on the field-bus network adapter. Only when this doesn't light up any more, the new electronic unit has been recognised and the next electronic unit is able to be pulled out.

## 10.3 Replacing an I/O Module



### Warning

Explosion Risk - Prior to starting work, ensure that there is not a potentially explosive atmosphere.



### Warning

Dangerous contact voltage - Prior to removing modules, the RSTi-EP station must be completely de-energised (supply of the field bus network adapter and all external feed-in). Ensure that the place of installation (switch cabinet and so forth) has been disconnected from the power supply.




### Caution

The components in the RSTi-EP series can be destroyed by electrostatic discharge. Ensure that personnel and work equipment are adequately grounded.


To remove an individual module from the station, all modules to the right of it and the termination kit must be moved by approximately 5 cm (2 in).

#### ➤ To replace an I/O module

1. Unfasten the mounting screw on the right-hand end bracket.
2. Slide the end bracket and end plate approximately 5 cm (2 in) to the right or remove both parts from the DIN rail.
3. Open the release lever on the module furthest to the right.



4. Slide the module on the DIN rail approximately 5 cm (2 in) to the right, push it onto the DIN rail and click the release lever into place.
5. Repeat the previous step for all other modules which are located to the right of the module being replaced: release, slide to the right, and click in once again.
6. Remove the plug-in unit of the module to be replaced as described in the section *Removing/Replacing the Plug-in Unit*.
7. Open the release lever for the module to be removed.




8. Slide the module to the right and remove it from the DIN rail.
9. Position the new module with its closed release lever on the DIN rail so that it clicks audibly into place.
10. Slide the module to the left until it audibly clicks into place against the neighbouring module.
11. Return the modules that were slid away back into their original position: slide the modules to the left so that they audibly click into place on the new module.

**Note:** After all the modules have been moved, make sure that they have all been clicked securely into place on the DIN rail.

12. Reassemble the end plate and end bracket.
13. Place the plug-in unit in a 90° position from below into the guideway of the base module on the new module.

**Note:** The plug-in unit can only be inserted in this 90° position.



14. Swivel the plug-in unit upwards until the connector frame clicks into place.

## 10.4 Removing/Replacing Connectors



Explosion Risk - Prior to starting work, ensure that there is not a potentially explosive atmosphere.

### **Warning**

---



In the event of the machine/system being put into a dangerous state as a result of the removal of a connector, a replacement can only be made once the machine/system is disconnected from the power.

### **Caution**

---



Risk of contact fire - Remove connectors only while they are load current free.

### **Caution**

---




The components in the RSTi-EP series can be destroyed by electrostatic discharge. Ensure that personnel and work equipment are adequately grounded.

### **Caution**


---

➤ **To remove/replace connectors**

1. Open the connector frame and flip the plug-in unit open so far that you can reach the connector.



2. Press both sides of the connector together so that it can be slid off the frame.



3. Remove the connector by pulling it off.
4. Insert the new connector in the frame so that it audibly clicks into place.
5. Swivel the plug-in unit upwards until the connector frame clicks into place.

## 10.5 Removing/Replacing Cables



### Warning

Explosion Risk - Prior to starting work, ensure that there is not a potentially explosive atmosphere.

---



### Warning

Dangerous contact voltage - Prior to removing modules, the RSTi-EP station must be completely de-energised (supply of the field bus network adapter and all external feed-in). Ensure that the place of installation (switch cabinet and so forth) has been disconnected from the power supply.

---



### Caution

In the event of the machine/system being put into a dangerous state as a result of the removal of cables, a replacement can only be made once the machine/system is disconnected from the power.

---



### Caution

The components in the RSTi-EP series can be destroyed by electrostatic discharge. Ensure that personnel and work equipment are adequately grounded.

---




### Caution

The components in the RSTi-EP series can be destroyed by overcurrent. Potentials may only be disconnected either simultaneously or in the correct order. At the fieldbus network adapter as well as at power-feed modules, always disconnect the 24 V supply (red pusher) first, before you disconnect the GND potential (blue pusher).

---

➤ **To remove/replace cables**

1. Using a 3-mm (1/8<sup>th</sup> in) screwdriver, push in the pusher adjacent to the cable to be removed and pull the wire out.



2. Release the pusher.
3. Insert the new wire into the opening. To do so, you do not need to push in the pusher.

# Chapter 11 Disassembly and Disposal

## 11.1 Disassembling the RSTi-EP Station



Explosion Risk - Prior to starting work, ensure that there is not a potentially explosive atmosphere.

### **Warning**

---



Dangerous contact voltage - Carry out all disassembly work on the RSTi-EP station only when the power supply is disconnected. Ensure that the place of installation (switch cabinet and such) has been disconnected from the power supply.

### **Caution**

---

#### ➤ To disassemble the RSTi-EP station

1. Remove all cables and lines.
2. Remove the end bracket marker (if present).
3. Unfasten the mounting screw on the right-hand end bracket.
4. Slide the end bracket with the end plate to the right and remove both from the DIN rail.  
You can now disassemble the modules and the field-bus network adapter either individually or in groups of three to four modules.
5. Press all the release levers of a module group towards the mounting plate so that they click into place.
6. Slide the module group to the right and remove it from the DIN rail.
7. Repeat the above procedure for all remaining modules/ module groups.
8. To disassemble the field-bus network adapter, open both release levers and remove it from the DIN rail.
9. Unfasten the mounting screw on the left-hand end bracket and remove it.
10. Observe the instructions for proper disposal.



## 11.2 Disposing of the RSTi-EP Station

---



### **Attention**

Products in the RSTi-EP series are subject to WEEE (EU Directive 2002/96 EC), which regulates the collection and recycling of electrical and electronic equipment. Ensure that disassembled products are properly disposed of.

---


When all RSTi-EP products reach the end of their life cycle, you can return them to GE, and we will arrange for their proper disposal. This also applies to countries outside the European Union.

- **To dispose of the RSTi-EP station:** Pack the products properly and send them to your responsible distributor.

You can find the address of your respective country representative in the annex and at the GE website.

## Notes

## Chapter 12 LED Indicators and Troubleshooting



### Attention

In the event of a malfunction occurring on a RSTi-EP station, carry out the following recommended measures. If the malfunction cannot be fixed, send the affected product to GE (refer to the section, *General Contact Information*).

GE does not assume any liability If the base or electronic module has been tampered with.

### 12.1 Fieldbus Network Adapters

#### EPXPBS001

Indicator	LED	Status	Recommended action
Power LED	PWR	<b>Green:</b> Supply voltage applied	
		<b>Off,</b> and the status LED of the module is <b>green:</b> Defective network adapter	Have the network adapter repaired or replaced The internal fuse was triggered due to an overload
		<b>Off,</b> and the module status LED is <b>off:</b> Improper supply voltage	Check the supply voltage
System Fault	SF	<b>Red:</b> Configuration error, or error in the network adapter, or error in a module, or there is a new diagnostic message	Check that the GSD file is up-to-date Check if the configured station setup matches the actual setup Read the diagnostic message with the web server or an engineering tool and determine which further actions to take
		<b>Red flashing:</b> Station in Force mode	
Bus Fault	BF	<b>Red:</b> No connection to the fieldbus	Check the fieldbus cable and the PLC configuration
		<b>Red flashing:</b> Configuration error, no connection to the control unit, or error in the parameter set or slave address error or firmware update is running	Check the fieldbus parameters and the PLC configuration Check that the GSD file is up-to-date Check if the configured station setup matches the actual setup
Maintenance Required	MT	<b>Yellow:</b> Error on the system bus or the fieldbus	Check that the modules have been snapped into place properly Check fieldbus wiring Check the fieldbus connection parameters

Indicator	LED	Status	Recommended action
Input supply voltage	3.1	<b>Green:</b> Supply voltage for input current path > 18 V DC	
	3.2	<b>Red:</b> Supply voltage for input current path < 18 V DC	Check the supply voltage
	3.4	<b>Red:</b> Internal fuse defective	Replace the network adapter
Output supply voltage	4.1	<b>Green:</b> Supply voltage for output current path > 18 V DC	
	4.2	<b>Red:</b> Supply voltage for output current path < 18 V DC	Check the supply voltage
	4.4	<b>Red:</b> Internal fuse defective	Replace the network adapter

## EPXPNS001

Indicator	LED	Status	Recommended action
Power LED	PWR	<b>Green:</b> Supply voltage	
		<b>Off,</b> and the status LED of the module is <b>green:</b> Defective network adapter	Have the network adapter repaired or replaced The internal fuse was triggered due to an overload
		<b>Off,</b> and the module status LED is <b>off:</b> Improper supply voltage	Check the supply voltage
System Fault	SF	<b>Red:</b> Configuration error, or error in the network adapter, or error in a module, or there is a new diagnostic message	Check that the GSDML file is up-to-date Check if the configured station setup matches the actual setup Read the diagnostic message with the web server or an engineering tool and determine which further actions to take
		<b>Red flashing:</b> Station in Force mode	
Bus Fault	BF	<b>Red:</b> No connection to the fieldbus	Check the fieldbus cable and the PLC configuration
		<b>Red flashing:</b> Configuration error, no connection to the control unit, or error in the parameter set	Check the fieldbus parameters and the PLC configuration Check that the GSD file is up-to-date Check if the configured station setup matches the actual setup
Maintenance Required	MT	<b>Yellow:</b> Error on the system bus	Check that the modules have been snapped into place properly
Connection	Link 1	<b>Green:</b> Connection established between port 1 of the network adapter and another field device	
		<b>Off:</b> No connection	Check the connection to the next participant and the fieldbus cable
Active	ACT 1	<b>Yellow flashing:</b> Data being exchanged on port 1	
Connection	Link 2	<b>Green:</b> Connection established between port 2 of the network adapter and another field device	
		<b>Off:</b> No connection	Check the connection to the next participant and the fieldbus cable

Indicator	LED	Status	Recommended action
Active	ACT 2	<b>Yellow flashing:</b> Data being exchanged on port 2	
Input supply voltage	3.1	<b>Green:</b> Supply voltage for input current path > 18 V DC	
	3.2	<b>Red:</b> Supply voltage for input current path < 18 V DC	Check the supply voltage
	3.4	<b>Red:</b> Internal fuse defective	Replace the network adapter
Output supply voltage	4.1	<b>Green:</b> Supply voltage for output current path > 18 V DC	
	4.2	<b>Red:</b> Supply voltage for output current path < 18 V DC	Check the supply voltage
	4.4	<b>Red:</b> Internal fuse defective	Replace the network adapter

**EPXETC001**

Indicator	LED	Status	Recommended action
Power LED	PWR	<b>Green:</b> Supply voltage	
		<b>Off,</b> and the status LED of the module is <b>green:</b> Defective network adapter	Have the network adapter repaired or replaced The internal fuse was triggered due to an overload
		<b>Off,</b> and the module status LED is <b>off:</b> Improper supply voltage	Check the supply voltage
System Fault	SF	<b>Red:</b> Configuration error, or error in the network adapter, or error in a module, or there is a new diagnostic message	Check that the ESI configuration file is up-to-date Check if the configured station setup matches the actual setup
		<b>Red flashing:</b> Station in Force mode	Read the diagnostic message with the web server or an engineering tool and determine which further actions to take
Bus Fault	BF	<b>Red:</b> No connection to the fieldbus	Check the fieldbus cable and the PLC configuration
		<b>Red flashing:</b> Configuration error, no connection to the control unit, or error in the parameter set	Check the fieldbus parameters and the PLC configuration Check that the ESI file is up-to-date Check if the configured station setup matches the actual setup
Maintenance Required	MT	<b>Yellow:</b> Error on the system bus	Check that the modules have been snapped into place properly
Connection/Active	L/A IN	<b>Off:</b> No connection	Check the fieldbus cable
		<b>Green:</b> Connection established between port 1 of the network adapter and another field device	
		<b>Green flashing:</b> Data being exchanged on port 1	

Indicator	LED	Status	Recommended action
Connection/Active	L/A OUT	<b>Off:</b> No connection	Check the fieldbus cable
		<b>Green:</b> Connection established between port 2 of the network adapter and another field device	
		<b>Green flashing:</b> Data being exchanged on port 2	
Network Adapter State	RUN	<b>Off:</b> Network adapter in INIT state	
		<b>Green flashing:</b> Network adapter in PRE-OPERATIONAL state	
		<b>Green lights up briefly:</b> Network adapter in SAFE OPERATIONAL state	
		<b>Green:</b> Network adapter in OPERATIONAL state	
Internal Fault	ERROR	<b>Red:</b> Critical error in the network adapter	<p>Check that the ESI file is up-to-date. Check if the configured station setup matches the actual setup</p> <p>Check that the network adapter firmware is up-to-date. Compare the master cycle time with the time set up on watchdog timer</p>
		<b>Red lights up briefly:</b> Error in the network adapter application	
		<b>Red lights up briefly twice:</b> Output of the sync manager watchdog out-of-date	
		<b>Red flashing:</b> Configuration error	
Input Supply Voltage	3.1	<b>Green:</b> Supply voltage for input current path > 18 V DC	
	3.2	<b>Red:</b> Supply voltage for input current path < 18 V DC	Check the supply voltage
	3.4	<b>Red:</b> Internal fuse defective	Replace the network adapter
Output Supply Voltage	4.1	<b>Green:</b> Supply voltage for output current path > 18 V DC	
	4.2	<b>Red:</b> Supply voltage for output current path < 18 V DC	Check the supply voltage
	4.4	<b>Red:</b> Internal fuse defective	Replace the network adapter

## EPXMBE001

Indicator	LED	Status	Recommended action
Power LED	PWR	<b>Green:</b> Supply voltage	
		<b>Off</b> , and the status LED of the module is <b>green</b> : Defective network adapter	Have the network adapter repaired or replaced The internal fuse was triggered due to an overload
		<b>Off</b> , and the module status LED is <b>off</b> : Improper supply voltage	Check the supply voltage
System Fault	SF	<b>Red:</b> Configuration error, or error in the network adapter, or error in a module, or there is a new diagnostic message	Check if the configured station setup matches the actual setup Read the diagnostic message with the web server or an engineering tool and determine which further actions to take
		<b>Red flashing:</b> Station in Force mode	
Bus Fault	BF	<b>Red:</b> No connection to the fieldbus	Check the fieldbus cable and the PLC configuration
		<b>Red flashing:</b> Configuration error, no connection to the control unit, or error in the parameter set	Check if the configured station setup matches the actual setup Check the master configuration and try again to establish connection
Maintenance Required	MT	<b>Yellow:</b> Error on the system bus or the fieldbus	Check that the modules have been snapped into place properly Check the fieldbus cabling Check the fieldbus connection parameters
Connection/Active	L/A X1	<b>Green:</b> Connection established between port 1 of the network adapter and another field device	
		<b>Green flashing:</b> Data being exchanged on port 1	
		<b>Off:</b> No connection	Check the connection to the next participant and the fieldbus cable
Connection/Active	L/A X2	<b>Green:</b> Connection established between port 2 of the network adapter and another field device	
		<b>Green flashing:</b> Data being exchanged on port 2	
		<b>Off:</b> No connection	Check the connection to the next participant and the fieldbus cable
Input Supply Voltage	3.1	<b>Green:</b> Supply voltage for input current path > 18 V DC	
	3.2	<b>Red:</b> Supply voltage for input current path < 18 V DC	Check the supply voltage
	3.4	<b>Red:</b> Internal fuse defective	Replace the network adapter
Output Supply Voltage	4.1	<b>Green:</b> Supply voltage for output current path > 18 V DC	

	4.2	<b>Red:</b> Supply voltage for output current path < 18 V DC	Check the supply voltage
	4.4	<b>Red:</b> Internal fuse defective	Replace the network adapter

## 12.2 I/O Modules

Module	LED	Status	Recommended action
<b>Digital Input Modules</b>			
EP-1214, EP-1218, EP-1318, EP-125F, EP-12F4, EP-1804	Status LED	<b>Red:</b> <ul style="list-style-type: none"> <li>Error in supply voltage at input current path</li> <li>Communication error on the system bus</li> <li>There is a new diagnostic message</li> </ul>	<ul style="list-style-type: none"> <li>Check that the module has been snapped into place properly</li> <li>Check the supply voltage</li> </ul>
<b>Digital Output Modules</b>			
EP-2214, EP-2614, EP-2634, EP-2218, EP-225F	Status LED	<b>Red:</b> <ul style="list-style-type: none"> <li>Error in supply voltage at output current path</li> <li>Communication error on the system bus</li> <li>There is a new diagnostic message</li> <li>At least one output overloaded</li> </ul>	<ul style="list-style-type: none"> <li>Check that the module has been snapped into place properly</li> <li>Check the supply voltage</li> <li>Eliminate the overload/short-circuit</li> </ul>
<b>Digital Relay Output Modules</b>			
EP-2714, EP-2814	Status LED	<b>Red:</b> <ul style="list-style-type: none"> <li>Error in supply voltage at output current path</li> <li>Communication error on the system bus</li> <li>There is a new diagnostic message</li> </ul>	<ul style="list-style-type: none"> <li>Check that the module has been snapped into place properly</li> <li>Check the supply voltage</li> </ul>
<b>Digital Counter, SSI and Serial Communication Modules</b>			
EP-5111, EP-5112, EP-5212, EP-5261, EP-5311	Status LED	<b>Red:</b> <ul style="list-style-type: none"> <li>Error in supply voltage at input current path</li> <li>Communication error on the system bus</li> <li>There is a new diagnostic message</li> </ul>	<ul style="list-style-type: none"> <li>Check that the module has been snapped into place properly</li> <li>Check the supply voltage</li> </ul>
<b>Pulse-width Modulation Modules</b>			
EP-5422, EP-5442	Status LED	<b>Red:</b> <ul style="list-style-type: none"> <li>Error in supply voltage at output current path</li> <li>Communication error on the system bus</li> <li>There is a new diagnostic message</li> </ul>	<ul style="list-style-type: none"> <li>Check that the module has been snapped into place properly</li> <li>Check the supply voltage</li> <li>Eliminate the overload/short-circuit</li> </ul>



		- At least one output overloaded	
--	--	----------------------------------	--

Module	LED	Status	Recommended action
<b>Analog Input Modules</b>			
<b>EP-3124, EP-3164, EP-3264</b>	Status LED	<b>Red:</b> <ul style="list-style-type: none"> <li>- Error in supply voltage at input current path</li> <li>- Communication error on the system bus</li> <li>- There is a new diagnostic message</li> <li>- Channel error</li> <li>- Firmware error</li> </ul>	<ul style="list-style-type: none"> <li>- Check that the module has been snapped into place properly</li> <li>- Check the supply voltage</li> <li>- Check channel error</li> <li>- Check firmware, update firmware as necessary</li> </ul>
		Status LED <b>off</b> and all other LEDs <b>red</b> : Error in the bus network adapter power supply	<ul style="list-style-type: none"> <li>- Check the bus network adapter supply voltage</li> </ul>
	Channel LED 1.1-4.1	<b>Red:</b> <ul style="list-style-type: none"> <li>- Input signal outside permissible range</li> <li>- System bus cannot be accessed (for example, caused by interruption of the bus network adapter power supply)</li> </ul>	<ul style="list-style-type: none"> <li>- Check the input signal</li> <li>- Check the bus network adapter supply voltage</li> </ul>
<b>EP-3368, EP-3468</b>	Status LED	<b>Red:</b> <ul style="list-style-type: none"> <li>- Error in supply voltage at output current path</li> <li>- Communication error on the system bus</li> <li>- There is a new diagnostic message</li> <li>- At least one output overloaded</li> </ul>	<ul style="list-style-type: none"> <li>- Check that the module has been snapped into place properly</li> <li>- Check the supply voltage</li> <li>- Eliminate the overload/short-circuit</li> </ul>
	Channel LED 1.1-8.1	<b>Red:</b> Channel error	<ul style="list-style-type: none"> <li>- Check channel error</li> </ul>

Module	LED	Status	Recommended action
EP-3804, EP-3704	Status LED	<b>Red:</b> <ul style="list-style-type: none"> <li>– Error in supply voltage at input current path</li> <li>– Communication error on the system bus</li> <li>– There is a new diagnostic message</li> <li>– Channel error</li> <li>– Firmware error</li> </ul>	<ul style="list-style-type: none"> <li>– Check that the module has been snapped into place properly</li> <li>– Check the supply voltage</li> <li>– Check channel error</li> <li>– Check firmware, update firmware as necessary</li> </ul>
		Status LED <b>off</b> and all other LEDs <b>red</b> : Error in the bus network adapter power supply	<ul style="list-style-type: none"> <li>– Check the bus network adapter supply voltage</li> </ul>
	Channel LED 1.1-4.1	<b>Red:</b> <ul style="list-style-type: none"> <li>– Input signal outside permissible range</li> <li>– Line break</li> <li>– Cold-junction compensation error (EP-3804 only)</li> <li>– System bus cannot be accessed (for example, caused by interruption of the bus network adapter power supply)</li> </ul>	<ul style="list-style-type: none"> <li>– Check the input signal, the cabling and, if necessary, the sensor for external cold-junction compensation.</li> <li>– Check the bus network adapter supply voltage</li> </ul>
Analog output modules			
EP-4164, EP-4264	Status LED	<b>Red:</b> <ul style="list-style-type: none"> <li>– Error in supply voltage</li> <li>– Communication error</li> <li>– Channel error</li> </ul>	<ul style="list-style-type: none"> <li>– Check that the module has been snapped into place properly</li> <li>– Check the supply voltage</li> <li>– Check the channel error</li> </ul>
		Status LED <b>off</b> and all other LEDs <b>red</b> : Error in the bus network adapter power supply	<ul style="list-style-type: none"> <li>– Check the bus network adapter supply voltage</li> </ul>
	Channel LED 1.1-4.1	<b>Red:</b> <ul style="list-style-type: none"> <li>– Overload in voltage mode</li> <li>– Broken line in current mode</li> <li>– System bus cannot be accessed (for example, caused by interruption of the bus network adapter power supply)</li> </ul>	<ul style="list-style-type: none"> <li>– Check the connected load, check the cabling,</li> <li>– Check the bus network adapter supply voltage</li> </ul>

Power modules			
EP-7631	Status LED	<b>Red:</b> – Channel error or communication error on the system bus, or there is an error in the supply voltage	– Check that the module has been snapped into place properly – Check the channel error, check the supply voltage
	3.2	<b>Red:</b> – Supply voltage of the feed in plug < 18 V DC	– Check supply voltage of feed in plug
	3.4	<b>Red:</b> – Damage of internal fuse	– Replace module
EP-7641	Status LED	<b>Red:</b> – Channel error or communication error on the system bus, or there is an error in the supply voltage	– Check that the module has been snapped into place properly – Check the channel error, check the supply voltage
	3.2	<b>Red:</b> – Supply voltage of the feed in plug < 18 V DC	– Check supply voltage of feed in plug
	3.4	<b>Red:</b> – Damage of internal fuse	– Replace module
Potential distribution modules			
EP-711F, EP-710F	Status LED	<b>Red:</b> – Error in supply voltage of the input path	– Check that the module has been snapped into place properly – Check the supply voltage
EP-751F, EP-750F	Status LED	<b>Red:</b> – Error in supply voltage of the input path	– Check that the module has been snapped into place properly – Check the supply voltage
EP-700F	Status LED	<b>Off:</b> No supply voltage	– Check that the module has been snapped into place properly

Safety modules			
EP-1901	Status LED	<b>Red:</b> <ul style="list-style-type: none"> <li>– Module has not been snapped properly</li> <li>– Error in the supply voltage</li> <li>– Channel error</li> </ul>	<ul style="list-style-type: none"> <li>– Check that the module has been snapped into place properly</li> <li>– Check the supply voltage                             <ol style="list-style-type: none"> <li>1. check +24 V input current path</li> <li>2. Check voltage on plug 4.3; in case of cascading 0 V might be properly, therefore this is not an error</li> </ol> </li> <li>– Check channel error</li> </ul>
		– Overload at the OSSD output level	– Remove cross connection at OSSD
		– External feed-in recognised from field side	– Measure voltage at OSSD pin (4.3) vs. GND (4.4). If a voltage is present, check the wiring. <b>Attention:</b> safety hazard! Shut down the system and prevent it from switching on again.
		– Internal error detected	– Module might have switched off caused by overtemperature; check the temperature inside the switch cabinet – Perform a cold start within 24 hours If the error has not been fixed, send the module to GE for a technical examination.
		– Interruption in one of the two safety loops of a safety circuit for at least 3 seconds.	– Check safety circuit for interruptions if an interruption of the safety channel is not part of the application.
		– Cross connection between the safety loops for at least 3 seconds.	– Check safety circuit for cross connections.
	1.1	<b>Off:</b> Safety circuit 1 interrupted <b>Yellow:</b> Safety circuit 1 OK	– Check safety circuit 1
	4.2	<b>Off:</b> OSSD not active <b>Yellow:</b> OSSD active, 24 V DC at output	
	4.3	<b>Green:</b> Feed-in voltage in valid range	

Safety modules			
EP-1902, EP-1922	Status LED	<b>Red:</b> <ul style="list-style-type: none"> <li>Module has not been snapped properly</li> <li>Error in the supply voltage</li> <li>Channel error</li> </ul>	<ul style="list-style-type: none"> <li>Check that the module has been snapped into place properly</li> <li>Check the supply voltage                             <ol style="list-style-type: none"> <li>check +24 V input current path</li> <li>Check voltage on plug 4.3; in case of cascading 0 V might be properly, therefore this is not an error</li> </ol> </li> <li>Check channel error</li> </ul>
		<ul style="list-style-type: none"> <li>Overload at the OSSD output level</li> </ul>	<ul style="list-style-type: none"> <li>Remove cross connection at OSSD</li> </ul>
		<ul style="list-style-type: none"> <li>External feed-in recognised from field side</li> </ul>	<ul style="list-style-type: none"> <li>Measure voltage at OSSD pin (4.3) vs. GND (4.4).</li> </ul> <p>If a voltage is present, check the wiring.</p> <p><b>Attention:</b> safety hazard! Shut down the system and prevent it from switching on again.</p>
		<ul style="list-style-type: none"> <li>Internal error detected</li> </ul>	<ul style="list-style-type: none"> <li>Module might have switched off caused by overtemperature; check the temperature inside the switch cabinet</li> <li>Perform a cold start within 24 hours</li> </ul> <p>If the error has not been fixed, send the module to GE for a technical examination.</p>
		<ul style="list-style-type: none"> <li>Interruption in one of the two safety loops of a safety circuit for at least 3 seconds.</li> </ul>	<ul style="list-style-type: none"> <li>Check safety circuit for interruptions if an interruption of the safety channel is not part of the application.</li> </ul>
		<ul style="list-style-type: none"> <li>Cross connection between the safety loops for at least 3 seconds.</li> </ul>	<ul style="list-style-type: none"> <li>Check safety circuit for cross connections.</li> </ul>
	1.1	<b>Off:</b> Safety circuit 1 interrupted <b>Yellow:</b> Safety circuit 1 OK	<ul style="list-style-type: none"> <li>Check safety circuit 1</li> </ul>
	1.2	<b>Off:</b> Safety circuit 2 interrupted <b>Yellow:</b> Safety circuit 2 OK	<ul style="list-style-type: none"> <li>Check safety circuit 2</li> </ul>
	4.1 (DELAY only)	<b>Off:</b> SS1 not active <b>Yellow:</b> SS1 active, 24 V DC at output	
	4.2	<b>Off:</b> OSSD not active <b>Yellow:</b> OSSD active, 24 V DC at output	
	4.3	<b>Green:</b> Feed-in voltage in valid range	


**Notes**

## Chapter 13 Accessories and Replacement Parts

### 13.1 Accessories

Order No.	Designation	Purpose
EP-8100	Swivel marker	Pivoting holder for module markers
EP-8101	Paper labels for swivel markers	Can be printed with laser printers
EP-8301	Termination kit	Set with two end brackets and one end plate
EP-8360	HD-Plug	Plug for HD-modules (8 pieces per package)

### 13.2 Replacement Parts



#### Replacement Parts for Network Adapters

Network Adapter/ Order No.
EPXPBS001
EPXPNS001
EPXMBE001
EPXETC001


**Replacement Parts for Modules**

Module/Order No.	Base Module
EP-1214	EP-8300
EP-1218	EP-8300
EP-1318	EP-8300
EP-125F	EP-8300
EP-12F4	EP-8300
EP-1804	EP-8300
EP-2214	EP-8300
EP-2614	EP-8300
EP-2634	EP-8300
EP-2218	EP-8300
EP-225F	EP-8300
EP-2814	EP-8300
EP-2714	EP-8300
EP-5111	EP-8300
EP-5112	EP-8300
EP-5212	EP-8300
EP-5261	EP-8300
EP-5311	EP-8300
EP-5422	EP-8300
EP-5422	EP-8300
EP-3164	EP-8300
EP-3264	EP-8300
EP-3124	EP-8300
EP-3368	EP-8300
EP-3468	EP-8300
EP-4164	EP-8300
EP-4264	EP-8300
EP-3704	EP-8300
EP-3804	EP-8300
EP-7631	EP-8300
EP-7641	EP-8300
EP-1901	EP-8300
EP-1902	EP-8300
EP-1922	EP-8300
EP-711F	EP-8300
EP-751F	EP-8300
EP-700F	EP-8300
EP-710F	EP-8300
EP-750F	EP-8300
EP-8310	EP-8300



## Notes

## Chapter 14 Standalone controller for RSTi-EP



The PACSystems\* RSTi-EP EPSCPE100, is an enhanced performance standalone 1GHz programmable controller equipped with 1MB of user memory and four Ethernet ports to run real time deterministic control applications. LAN1 is dedicated to highspeed Ethernet and LAN2 comprised of 3 switched ports configurable as either an embedded Ethernet controller or an embedded PROFINET controller, which provides the PROFINET functionality and supports only simplex mode of operation. It is a standalone PLC that supports distributed I/O. From now on in rest of the document this controller will be referred to as CPE100.

Highlights include:

- A built-in PACSystems RSTi-EP PLC CPU
  - User may program in Ladder Diagram, Structured Text, Function Block Diagram.
  - Contains 1Mbytes of configurable data and program memory.
  - Supports auto-located Symbolic Variables that can use any amount of user memory.
  - Reference table sizes include 2k bits for discrete %I and %Q and up to 2k words each for analog %AI and %AQ. Bulk memory (%W) also supported for data exchanges.
  - Supports up to 512 program blocks. Maximum block size is 128KB
  - Supports two independent 10/100 Ethernet LANs. LAN1 has only one port and is dedicated to highspeed Ethernet and whereas LAN2 comprises of 3 switched ports configurable as either an embedded Ethernet controller or an embedded PROFINET controller. All four ports are located on the front panel, as shown aside.
- The embedded communications interface has dedicated processing capability, which permits the CPU to independently support LAN1 and LAN2 with:
    - up to 16 combined SRTP Server and Modbus TCP Server connections out of which Modbus TCP cannot exceed more than 8 connections (or) up to 16 simultaneous SRTP Server connections (or) up to 8 simultaneous Modbus TCP Server connections.
    - 8 Clients are permitted; each may be SRTP or Modbus TCP or a Combination of both.
    - up to 8 simultaneous Class 1 Ethernet Global Data (EGD) exchanges.
    - When used in combination for optimal performance, user must not exceed 4 Channels for Server (Modbus/SRTP) & 4 Channels for client (Modbus/SRTP), 8 PROFINET nodes and 8 EGD data exchanges.
  - Ability to display serial number and date code in PME Device Information Details.
  - Operating temperature range -40°C to 70°C (-40°F to 158°F).

## Membrane Run/Stop push button



Pressing Membrane Run/Stop push button briefly, will change the state of CPU from the state it is in to the next state. Switch operation state as given in the following state diagram:




The **Run/Stop** switch is enabled by default; it can be disabled in PME Hardware Configuration (HWC) settings.

## LED Indicators (LEDs)

### Ethernet Status Indicators

There are two LEDs (Yellow/Green) for each Ethernet ports of LAN1 and LAN2, which are embedded in the RJ-45 connectors. The green LED indicates an Ethernet connection has been established. The yellow LED indicates packet traffic.

### Module status Indicators



There are three LEDs and one Membrane Push Button on the front panel (The one in blue color) as shown in the figure. The below table describes the behavior of each module LED:

Push Button: Toggles the current mode of the PLC.

LED	LED State	Operating State
OK	● On Green	PLC has passed its power-up diagnostics and is functioning properly
	○ Off	Power is not applied or PLC has a problem.
	✖ Blinking; All other LEDs off	PLC in STOP/Halt state; possible watchdog timer fault. If the programmer cannot connect, cycle power and refer to the fault tables.
RUN	● On Green	PLC is in RUN mode.
	○ Off	PLC is in STOP mode.
	✖ Blinking; All other LEDs off	Indicates that PLC has encountered a fatal error and is blinking the error code.
Fault	● On Green	PLC is in STOP/Faulted mode: a fatal fault has occurred.

	<input type="radio"/> Off	No fatal faults detected.
--	---------------------------	---------------------------

## Ethernet Ports

LAN 1 connects to the uppermost RJ-45 connector. It is not switched. LAN2 connects to the three lower RJ-45 connectors. They are switched internally.

The embedded Ethernet interfaces automatically senses the link data rate (10 Mbps or 100 Mbps), communications mode (half-duplex or full-duplex), and cabling arrangement (straight-through or crossover).

The embedded Ethernet LAN 1 port may be used to communicate with PME programming software using the Service Request Transport Protocol (SRTTP, a proprietary GE protocol, used primarily for communication with the programmer).

To establish Ethernet communications between the PME programming package and the CPU, you first need to set an IP address.

EPSCPE100	LAN1	LAN2
<b>Default IP Address:</b>	192.168.0.100	0.0.0.0
<b>Subnet Mask:</b>	255.255.255.0	0.0.0.0
<b>Gateway:</b>	0.0.0.0	0.0.0.0

Note: LAN2 will not be operational unless it is configured from the programmer with a valid IP address.

A typical application will take advantage of the two independent LANs. The dedicated LAN 1 port will be used for communications with plant-level or supervisory layers. The switched LAN 2 will be used to communicate with devices over PROFINET within the manufacturing cell or process.




Figure 1: Typical Multi-Tier LAN Application (supports only Star/Bus network topology)

## 14.1 Hardware Installation

### 14.1.1 Initial Checks

Upon receiving your equipment, carefully inspect all shipping containers for damage. If any part of the system is damaged, notify the carrier immediately. The damaged shipping container should be saved as evidence for inspection by carrier.

As the consignee, it is your responsibility to register a claim with the carrier for damage incurred during shipment. GE Automation & Controls will fully cooperate with you, however, should such action be necessary.

After unpacking the equipment, record all serial numbers. Serial numbers are required if you should need to contact Customer Care during the warranty period. All shipping containers and all packing material should be saved should it be necessary to transport or ship any part of the system.

Verify that all components of the system have been received and that they agree with your order. If the system received does not agree with your order, contact Customer Care.

### 14.1.2 Installation Location

As shipped, the CPE100 is intended for mounting on a DIN rail. An optional panel-mount adaptor is also available with part number (ICMFAACC001-AA). If panel-mounting is required, replace the DIN-rail adaptor with the panel-mount adaptor using the screws supplied with that adaptor. Both adaptors attach to the rear of the CPE100 chassis using four Torx M3 screws. Torque newly-installed screws to 5.3 in-lbs (0.6 Nm) if installing a new adaptor plate.

#### **Thermal Requirements:**

When mounting the CPE100, allow a minimum clearance of 50mm on the left & right side of the unit and a minimum clearance of 100mm on the top & bottom sides.

#### **Instructions to mount the CPE100 on a DIN Rail:**

The CPE100 snaps easily onto the DIN rail. No additional tools are required.

(1) Incline the unit so that the upper hooks of the DIN rail adaptor engage with the upper edge of the DIN rail.

(2) Press on the lower part of the unit until you hear a click. The click indicates that the lower hooks of the DIN rail adaptor have engaged with the lower edge of the DIN rail.

If you need any technical help, please contact Technical Support. For phone numbers and email addresses, refer to the back cover of this Guide.



Figure xx: Mounting positions of the EPSCPE100 on DIN rail

### Instructions to mount the CPE100 on a Panel

- (1) Attach the panel mount plate to the rear side of CPE100 using the four M3 screws supplied with the adapter.
- (2) Fasten the tabs of panel mount adapter in the appropriate location of panel with the four screws. The screw size used for each panel mount tab should not exceed M5.




Figure xx: Mounting position of the EPSCPE100 in panel

## 14.2 Grounding

Proper grounding of the CPE100 is essential using the provided ground terminal as shown in the below figure. Use a 16-22 AWG braided wire with lugs to connect the ground terminal of CPE100 to DIN Rail. The DIN rail into which this product will be mounted must be grounded as per the instructions provided in *RSTi-EP System Manual*, GFK-2958.




Figure xx: Ground Terminal of EPSCPE100

## 14.3 Replacement of internal Super Capacitor (EPSACC001)

EPSCPE100 have internal supercap circuitry, which is replaceable with a new one EPSACC001. The replacement procedure is given below.

1. Power off the unit (EPSCPE100) and wait for 5 minutes to allow the internal Super Capacitors to discharge completely.
2. Detach the side panel cover by removing the (M3) screws with a screw driver as shown below.



3. Detach the Super Capacitor card from the carrier board using a screw driver (M2.5) as shown below.



4. Install the new Super Capacitor card (Cat. No.: EPSACC001) as shown below check if the mounting holes are aligned properly before tightening both the M2.5 screws (Recommended Torque= 3 in/lb) and check if the card was installed properly by verifying the mating connectors.
5. Mount the side panel cover and tighten all the M3 Screws (Recommended Torque = 5 in/lb) as shown below. Now the unit is ready for use.



## 14.4 Replacement of RTC Battery

The EPSCPE100 module is shipped with a battery pre-installed. The battery holder (BT1) is located near the supercapacitor daughter card, and can be replaced by opening the top cover.

### ➤ To replace the battery

1. Power OFF the MFA Module.
2. Wait for 1 minute.
3. Open the top cover by loosening the four screws on the edges.
4. Use a small flat-head screw driver to gently pry out the old battery.
5. Insert the new battery.



# Appendix A Decimal/Hexadecimal Conversion Table

## Decimal/Hexidecimal Conversion

Decimal	Hexadecimal	Decimal	Hexadecimal	Decimal	Hexadecimal	Decimal	Hexadecimal	Decimal	Hexadecimal	Decimal	Hexadecimal	Decimal	Hexadecimal
001	1	034	22	067	43	100	64	133	85	166	A6	199	C7
002	2	035	23	068	44	101	65	134	86	167	A7	200	C8
003	3	036	24	069	45	102	66	135	87	168	A8	201	C9
004	4	037	25	070	46	103	67	136	88	169	A9	202	CA
005	5	038	26	071	47	104	68	137	89	170	AA	203	CB
006	6	039	27	072	48	105	69	138	8A	171	AB	204	CC
007	7	040	28	073	49	106	6A	139	8B	172	AC	205	CD
008	8	041	29	074	4A	107	6B	140	8C	173	AD	206	CE
009	9	042	2A	075	4B	108	6C	141	8D	174	AE	207	CF
010	A	043	2B	076	4C	109	6D	142	8E	175	AF	208	D0
001	B	044	2C	077	4D	110	6E	143	8F	176	B0	209	D1
012	C	045	2D	078	4E	111	6F	144	90	177	B1	210	D2
013	D	046	2E	079	4F	112	70	145	91	178	B2	211	D3
014	E	047	2F	080	50	113	71	146	92	179	B3	212	D4
015	F	048	30	081	51	114	72	147	93	180	B4	213	D5
016	10	049	31	082	52	115	73	148	94	181	B5	214	D6
017	11	050	32	083	53	116	74	149	95	182	B6	215	D7
018	12	051	33	084	54	117	75	150	96	183	B7	216	D8
019	13	052	34	085	55	118	76	151	97	184	B8	217	D9
020	14	053	35	086	56	119	77	152	98	185	B9	218	DA
021	15	054	36	087	57	120	78	153	99	186	BA	219	DB
022	16	055	37	088	58	121	79	154	9A	187	BB	220	DC
023	17	056	38	089	59	122	7A	155	9B	188	BC	221	DD
024	18	057	39	090	5A	123	7B	156	9C	189	BD	222	DE
025	19	058	3A	091	5B	124	7C	157	9D	190	BE	223	DF
026	1A	059	3B	092	5C	125	7D	158	9E	191	BF	224	E0
027	1B	060	3C	093	5D	126	7E	159	9F	192	C0	225	E1
028	1C	061	3D	094	5E	127	7F	160	A0	193	C1	226	E2
029	1D	062	3E	095	5F	128	80	161	A1	194	C2	227	E3
030	1E	063	3F	096	60	129	81	162	A2	195	C3	228	E4
031	1F	064	40	097	61	130	82	163	A3	196	C4	229	E5
032	20	065	41	098	62	131	83	164	A4	197	C5	230	E6
033	21	066	42	099	63	132	84	165	A5	198	C6	231	E7
												232	E8
												233	E9
												234	EA
												235	EB
												236	EC
												237	ED
												238	EE
												239	EF
												240	F0
												241	F1
												242	F2
												243	F3
												244	F4
												245	F5
												246	F6
												247	F7
												248	F8
												249	F9
												250	FA
												251	FB
												252	FC
												253	FD
												254	FE
												255	FF
												256	100
												257	101
												258	102
												259	103
												260	104
												261	105
												262	106
												263	107
												264	108



### **GE Information Centers**

**Headquarters:**

1-800-433-2682 or 1-434-978-5100

Global regional phone numbers  
are available on our web site  
[www.geautomation.com](http://www.geautomation.com)

© 2015-2017 General Electric Company.

\*Trademark of GE Electric Company.

All other brands or names are property of their respective holders.

### **Additional Resources**

For more information, visit the

GE web site:

[www.geautomation.com](http://www.geautomation.com)

GFK-2958D