

A

B

C

D

A

B

C

D



Thank you for choosing this vertical mouse. Please read the user manual carefully before you use this product.

Package content

Mouse-----x1
Manual-----x1
CD (optional)-----x1
Type-C braided cable-----x1
USB receiver-----x1

Compatibility
Compatible with Windows XP, Windows Vista, Windows 7, Windows 8, Windows 10, mac OS (Only basic function, no software available)

Keys Function



*MAX 20 degree adjustment for the shaft, from 53 degrees to 73 degrees
*When charging, indicator light will be always on, when fully charged, the light is off, which only needs 2.5 hours.

1.

Combo keys

Press DPI and scroll wheel together to shift between 3 light modes: single color breathing, 7-color cycling and off. Do not release DPI key before rolling up or rolling down the wheel.

Mouse Usage

Connect the mouse with your computer by USB port, it can work normally after detecting finished. If needed, you can set the button functions as following.

Rechargeable

Designed especially with a rechargeable Li-ion battery. If with light on, the mouse can last 2 weeks or so. With light off, the mouse can last 2 months or so.
(Theoretical condition: continuous use for 2 hours every day, 5 working days per week)

3 connection options

The mouse can connect to up-to-4 devices (not at the same time). And there are 3 wireless connection options: 2.4G USB, Bluetooth 3.0, and Bluetooth 4.0.
There is a magnetic latch at the bottom for the dongle, it is sturdy and secured.

LED indicator light

For 2.4G mode, no indicator light. For Bluetooth mode, there are 3 channels, each with 1 indicator light and support Bluetooth 3.0 and Bluetooth 4.0.

DPI indication

Press DPI button the green LED light will flash once for the first level of DPI, twice for the second, etc.

The mouse will automatically enter into deep mode and turn off light if there is no operation after 3 minutes.

Programming

Press the program button to shift device, the light will flash and be off after 5 seconds.
Long press the program button for 3 seconds to enter Bluetooth programming mode, the light will flash for 120 seconds, if no device is programmed within 120 seconds, the light will be off.

2.




Driver Setting

1. Installation
Download the driver from www.deluxind.com or the CD in the package, install the driver.
Note: Please make sure this mouse is already connected to computer when setting the functions in the driver.


2. Settings
Please remember to click "Apply" to activate your settings, and you can click "Reset" to restore factory default settings.

Key settings



These functions can be customized as below: Click, Menu, Scroll, Forward, Backward, Scroll up, Scroll down, Scroll left, Scroll right, Double click, Assign a shortcut, Select macro, Function off, Multimedia, Basic function, Advanced function.

3.



There are multiple choices under Multimedia, Windows, Basic function, Advanced function menu.

Windows Pointer Speed

Windows pointer speed is adjustable from slow to fast, and you can enhance pointer precision.

4.


Macro Settings



Click "Record" and type the name under "Macro Name" to create a macro command.
Click "Record" button and all your keystrokes and button presses will automatically register on the macro screen. When you finish recording your macro commands, click "STOP" button to finish.

The Macro session allows you to input the delay in-between commands.
In "Record delay" the delay in-between commands are registered as how it is entered.
The "Record delay" uses a predefined time (expressed in seconds) as the delay.
And "No delay" omits all the pauses in-between keystrokes and button presses.

5.



The "Insert" button allows you to put in additional keystrokes, button presses or time delays either before or after the selected command. A new display window will appear beside the list of macro commands. You may add in a new set of macro commands by clicking the button on the keystroke menu, or input time delays on the duration time field using the delay menu.

CAUTION

RISK OF EXPLOSION IF BATTERY IS REPLACED BY AN INCORRECT TYPE.
DISPOSE OF USED BATTERIES ACCORDING TO THE INSTRUCTIONS.

The statements should be displayed in the user manual.
This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.
changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.
If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
-- Reorient or relocate the receiving antenna.
-- Increase the separation between the equipment and receiver.
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/TV technician for help.

7.

分 发

☐ 研发部 ☒ 产品部 ☒ 资材部 ☒ 品保部 ☒ 生产部 ☒ 工程部 ☐ 海外营销部 ☒ 国内营销部 ☒ 文控中心

批 准

审 核



名 称
料 号

M618X 海外说明书

设 计

李锦峰20190115