

4120EC PROGRAMMING FORM

DEFAULT VALUES, WHERE APPLICABLE, ARE SHOWN IN BRACKETS []

*00 INSTALLER CODE

(ENTER 0-9) [4120]

*01 MASTER CODE

(ENTER 0-9) [1234]

*02 RESPONSE TYPE

(00-10)
 1 2 3 4 Zones

 [0]9 [0]1 [0]3 [0]4
 5 6 7 8 Zones

 [0]5 [0]6 [0]7 [0]8

*05 MULTIPLE ALARMS & RESPONSE TYPES FOR KEYPAD PANICS

Multiple Alarms 3 & # (or C) * & # (or B)
 [0]0 [0]7 [0]6

1st location: 00 = one alarm/per zone/per armed period; 01 = multiple alarms/per zone/per armed period.
 2nd & 3rd locations: enter response types for keypad panics.

RESPONSE TYPES

00 = Unused Zone 05 = Trouble by day/ Alarm by night
 01 = E/E #1 06 = 24-hour Silent
 02 = Not used 07 = 24-hour Audible
 03 = Perimeter 08 = 24-hour Auxiliary
 04 = Interior Follower 09 = Fire

*08 N.O. or N.C. SENSOR LOOP (ZONES 1-8)

1 2 3 4 5 6 7 8

 [1] [1] [1] [1] [1] [1] [1] [1]

0 = N.O. Sensor Loop; 1 = N.C. Sensor Loop.

*09 ENTRY DELAY

X 15 secs (00-15)
 [0]2

*10 EXIT DELAY

X 15 secs (00-15)
 [0]3

*13 ALARM SOUNDER TIME DURATION

X 2 mins. (01-15) [0]4

*14 ZONE 8 RESPONSE TIME

0 = Slow, 1 = Fast [0]

*21 NO FIRE TIME-OUT

1 = Yes, 0 = No [0]

*25 DISABLE DURESS IN ADEMCO EXPRESS FORMAT

1 = Yes, 0 = No [0]

*27 TEST REPORT INTERVAL

0 = No report; 1 = 12 hrs.; 2 = 24 hrs.; 3 = 168 hrs.
 [2]

*29 QUICK ARM

1 = Yes, 0 = No
 [1]

*30 TOUCH-TONE DIAL

1 = Yes, 0 = Rotary
 [0]

*31 PABX CODE

00-09; B-F

*32 SUBSCRIBER

00-09; B-F

*33 PRIMARY PHONE

0-9

*34 SECONDARY PHONE

0-9

*35 CS DOWNLOAD PHONE

0-9

*36 CS ID# 00-09; A-F

[1]5 [1]5 [1]5 [1]5 [1]5 [1]5 [1]5 [1]5

*40 PROGRAM TAMPER CODE

00-09; B-F [0]0

*41 DISABLE USAGE OF EOLR SUPERV. ON ZONE 1

1 = No EOLR; 0 = EOLR supervision [0]

*44 RING DETECT COUNT

[0]0

00 = no ring detect; 01-14 for ring counts of 1-14; 15 when telephone answering machine is connected to the same phone line.

*46 PRIMARY TRANSMISSION FORMAT

0 = ADEMCO LO SPEED; 1 = RADIONICS; 2 = ADEMCO EXPRESS
 [0]

*48 SECONDARY TRANSMISSION FORMAT

0 = ADEMCO LO SPEED; 1 = RADIONICS; 2 = ADEMCO EXPRESS
 [0]

*49 CHECKSUM VERIFY

1 = Yes, 0 = No [0]

*54 4+2 ZONE FORMAT SELECTION

1 = 4+2 Format, 0 = 3+1/4+1 [0]

*55 ALARM REPORT

0 = Standard, 1 = Expanded
 [0]

*56 RESTORE REPORT

0 = Standard, 1 = Expanded
 [1]

*57 BYPASS REPORT

0 = Standard, 1 = Expanded
 [0]

*58 TROUBLE REPORT

0 = Standard, 1 = Expanded
 [0]

*59 OPEN/CLOSE REPORT

0 = Standard, 1 = Expanded
 [1]

*60 LOW BAT, AC LOSS & TEST REPORT

0 = Standard, 1 = Expanded

*65 ALARM REPORTING CODES ASSIGNED

Z1 Z2 Z3 Z4 Z5 Z6 Z7 Z8
 [0]0 [0]0 [0]0 [0]0 [0]0 [0]0 [0]0 [0]0

Enter 01-15; 00 = no code reporting

(NOTE: When reporting 4+2 format, 2nd digit is always zone number)

***66 ALARM REPORTING CODES ASSIGNED (CONT'D)**

<input type="text"/>	<input type="text"/>	<input type="text"/> (01-15); 00=no channel reporting
Duress	3 & # Panic (or C)	* & # Panic (or B)
[010]	[010]	[010]

See Note in *65

NON-ALARM CODES

(01-15)	AC Loss	<input type="text"/>	Open	<input type="text"/>
(00 for no code reporting)	AC Loss 2nd Digit	<input type="text"/>	Close	<input type="text"/>
	Trbl	<input type="text"/>	Lo Bat	<input type="text"/>
	Trbl Restr	<input type="text"/>	L. Bat 2 nd Digit	<input type="text"/>
	Bypass	<input type="text"/>	Test	<input type="text"/>
	Bypass Restr	<input type="text"/>	Cancel	<input type="text"/>
	Rstr code for Alarm, AC Loss, Lo Bat	<input type="text"/>		

Defaults for above are all 010

HEXADECIMAL TO NUMERIC ENTRY CONVERSION

0 = 10 (REPORT CODES)
 0 = 00 (SUBS ID, PABX OR CS ID)
 1=01, 2=02, 3 =03 , 4=04, 5=05, 6=06 , 7=07, 8=08, 9=09, B=11, C=12, D=13, E=14 , F=15

- **To Enter Program Mode:** a) Press [*] and [#] at the same time within 30 seconds after power is applied to the control, or
 b) Enter installer code + [8] + [0] + [0]. Enter first field address to begin programming (e.g., *01).
- **To Set Standard Defaults:** Press *96
- **To Exit Program Mode:** Press *99 or *98: *99 allows re-entry to the programming mode by installer code. *98 prevents re-entry to programming mode by installer code.



A DIVISION OF PITTHWAY CORPORATION