NetApp®

2013

NETAPP HARDWARE UNIVERSE

SHELF ENCLOSURES

NetApp Disk Shelves							
Model	DS14mk4 FC	DS14mk2 AT	DS4243	DS4246	DS2246	DS4486	FibreBridge 6500N
Front View							
Maximum Drive Quantity	14	14	24	24	24	48	-
Environmental Specifications: Rack Height	3U	3U	4U	4U	2U	4U	1U
Environmental Specifications: Weight (Empty / Loaded)	77 lb. (35 kg) 50.06 lb. (23 kg)	77 lb. (35 kg) 50.06 lb. (23 kg)	110 lb. (49.9 kg) 53.7 lb. (24.4 kg)	110 lb. (49.9 kg) 53.7 lb. (24.4 kg)	56 lb. (25.4 kg) 34.6 lb. (15.7 kg)	150 lb. (68 kg) 82 lb. (33 kg)	8.78 lb. (3.97 kg)
Environmental Specifications: AC Power[1]	300GB 15K FC 4.43A 450GB 15K FC 4.43A 600GB 15K FC 3.44A	750GB SATA 2.72A 1.0TB SATA 2.51A 2.0TB SATA 2.50A	100GB SSD 1.96A 450GB SAS 6.00A 600GB SAS 5.96A 1.0TB SATA 4.41A 2.0TB SATA 4.72A 3.0TB SATA 4.95A (mixed SSD / SATA support)	900GB SAS 3.30A 1.0TB SATA 4.41A 2.0TB SATA 4.72A 3.0TB SATA 4.95A (mixed SSD / SATA support)	450GB SAS 4.41A 600GB SAS 4.22A 900GB SAS 4.22A	3.0TB SATA 8.71A	1.0A @100V 0.5A @200V
Environmental Specifications: BTU/hr[1]	300GB 15K FC 1,512 450GB 15K FC 1,512 600GB 15K FC 1,166	750GB SATA 924 1.0TB SATA 853 2.0TB SATA 849	100GB SSD 899 450GB SAS 2,047 600GB SAS 2,028 1.0TB SATA 1,499 2.0TB SATA 1,599 3.0TB SATA 1,690 (mixed SSD / SATA support)	900GB SAS 1,127 1.0TB SATA 1,499 2.0TB SATA 1,599 3.0TB SATA 1,690 (mixed SSD / SATA support)	450GB SAS 1,461 600GB SAS 1,441 900GB SAS 1,441	3.0TB SATA 2,970	342 @100V 342 @200V
Data Shelf Part Numbers: Empty Shelf (with AC PSU)	X353A-R5	X561-R5	X356A-R6 (2x PSU) X357A-R6 (4x PSU)	X356A-R6 (2x PSU) X357A-R6 (4x PSU)	X550A-R6	-	The FibreBridge 6500N provides bridging between FC and SAS connectivity for NetApp and Fabric MetroCluster configurations enabling backend connectivity to DS224X and DS42xx SAS storage. Two FB Bridges are required to support a single shelf. Dual-path SAS is the minimum per MetroCluster. Each FibreBridge provides 2x 8Gb FC ports and 1x 6Gb SAS port beyond SAS ports unused.
Data Shelf Part Numbers: Empty Shelf (without PSUs)	X554A-R5	X562-R5	X558A-R6	X558A-R5	X567A-R6	X568A-R6	
Data Shelf Part Numbers: AC Power Supply	X511A-R5	X511A-R5	X518A-R6	X518A-R6	X519A-R6	X521A-R6	
Data Shelf Part Numbers: Quickship Half Populated			DS4243: 150x 450 GB FC (X5529A) DS4243: 150x 600 GB FC (X5530A) DS4243: 150x 1 TB SATA (X5531A) DS4243: 150x 2 TB SATA (X5532A) DS4243: 150x 3 TB SATA (X5533A)	DS4246: 150x 450 GB SAS (X5529A) DS4246: 150x 600 GB SAS (X5530A) DS4246: 150x 1 TB SATA (X5531A) DS4246: 150x 2 TB SATA (X5532A) DS4246: 150x 3 TB SATA (X5533A)	DS2246: 150x 450 GB SAS (X5529A) DS2246: 150x 600 GB SAS (X5530A) DS2246: 150x 900 GB SAS (X5534A) DS2246: 150x 1.2 TB SAS (X5535A) DS2246: 150x 1.6TB GB SAS (X5536A)		
Data Shelf Part Numbers: Quickship Fully Populated	X5497A-E24=(QS-R5 (X5529) X5497A-E24=(QS-R5 (X5530)	DS6=1x 0TB QS-R5 (1.0TB) DS6=3x 0TB QS-R5 (3.0TB)	DS4243: 24x 450 GB FC (X5529) DS4243: 24x 600 GB FC (X5530) DS4243: 24x 1 TB SATA (X5531) DS4243: 24x 2 TB SATA (X5532) DS4243: 24x 3 TB SATA (X5533)	DS4246: 24x 450 GB SAS (X5529) DS4246: 24x 600 GB SAS (X5530) DS4246: 24x 1 TB SATA (X5531) DS4246: 24x 2 TB SATA (X5532) DS4246: 24x 3 TB SATA (X5533)	DS2246: 24x 450 GB SAS (X5529) DS2246: 24x 600 GB SAS (X5530) DS2246: 24x 900 GB SAS (X5534) DS2246: 24x 1.2TB GB SAS (X5535) DS2246: 24x 1.6TB GB SAS (X5536)	DS4486: 24x 4TB GB SAS (X5538)	
Data Shelf Modules: IOM3 X5511A-R5	Supported	-	-	-	-	-	-
Data Shelf Modules: IOM6 X5512A-R5	Supported	-	-	-	-	-	-
Data Shelf Modules: AT-FCX X5612A-R5	-	Supported	-	-	-	-	-
Data Shelf Modules: IOM12 X5713A-R5	-	-	Supported	-	-	-	-
Data Shelf Modules: IOM12 X5713A-R6	-	-	-	Supported	Supported	Supported	-
Minimum Data ONTAP® Release	7.2.1, 7.3, 8.0, 8.1	7.0, 7.1, 7.2, 7.3, 8.0, 8.1	7.3.2, 8.0, 8.1	8.1.1	7.3.4, 8.0.1, 8.1.1	8.1.1	8.1



TERMS AND ABBREVIATIONS

ACP – Alternate Control Path
BTU – British Thermal Unit
Cu – Copper Connector
EOA – End of Availability
EOS – End of Support
ESH – Electronically Switched Hub
FAS – Fabric-Attached Storage
FCP – Fibre Channel Protocol
FC – Ferrule Connector
FC – Fibre Channel
FRU – Field Replacement Unit
GbE – Gibabit Ethernet
IIA – High Availability
HSSDC – High-Speed Serial Data Connector
HT – Hyper-Threading
IB4X – InfiniBand 4X
IEC – International Electrotechnical Commission
IOM3 – I/O Module 3Gbit per second
IOM6 – I/O Module 6Gbit per second
LC – Lucent Connector
LRC – Loop Resiliency Circuit
LUN – Logical Unit Number
MTP – Mechanical Transfer Pull-Off
NEMA – National Electrical Mfg. Association
NIC – Network Interface Card
NVRAM – Nonvolatile RAM
Op – Optical Connector
PAM – Performance Acceleration Module
PSU – Power Supply Unit
QSFP – Quad Small Form-Factor Pluggable
RLM – Remote LAN Module
RPM – Revolutions Per Minute
SAS – Serial-Attached SCSI
SATA – Serial ATA
SC – Subscriber Connector
SFP – Small Form-Factor Pluggable
SSD – Solid State Drives
ST – Straight Tip Connector
TOE –TCP/IP Offload Engine

ADAPTER CARDS

	Card Type	Part Number / Description	Media	Optical Module FRU (Mfr Part Number)	Min Data ONTAP®	Fabric-Attached Storage & V-Series: 6280	6240	6210	3270	3240	3210	2240
FIBRE CHANNEL	PCIe	X1128A-R6 FCP TARGET 2-Port 4Gb	Op - LC	Fixed Optics Non-removable	7.3, 8.0, 8.1				6	6	2	
	PCIe	X1130A-R6 FCP TARGET 4-Port 4Gb	Op - LC	Fixed Optics Non-removable	7.3, 8.0, 8.1	4	4	4	4	6	2	
	PCIe	X1131A-R6 FCP TARGET 2-Port 8Gb	Op - LC	SFP module pre-installed (FTLF8528P2BCV-QL) No optical FRU available	7.3, 8.0, 8.1	12	12	4	6	6	2	
	PCIe	X1132A-R6 TARGET/DISK/TAPE 4-Port 8Gb	Op - LC	SFP module pre-installed (FTLF8528P3BCV-QL) No optical FRU available	8.1.1	12	12	4	6	6	2	
	PCIe	X2053A-R6 TAPE 2-Port 4Gb	Op - LC	Fixed Optics Non-removable	7.3, 8.0, 8.1	8	8	4	6	6	2	
	PCIe	X2054A-R6 DISK/TAPE 4-Port 4Gb	Op - LC	Fixed Optics Non-removable	7.3, 8.0	12	12	4	6	6	2	
	PCIe	X2055A-R6 DISK 2-Port 4Gb	Op - LC	Fixed Optics Non-removable	7.3, 8.0, 8.1	12	12	4	6	6	2	
	PCIe	X2056-R6 TARGET/DISK/TAPE 4-Port 8Gb	Op - LC	X6588-R6 (AFBR-57D7APZ or FTLF8528P2BNV)	8.0.1, 8.1	3	3	1				
	Mezzanine	X1150A-R6 TARGET/DISK/TAPE 2-Port 8Gb	Op - LC	X6588-R6 (AFBR-57D7APZ or FTLF8528P2BNV)	8.1							1
ETHERNET	PCIe	X1038A-R6 NIC 2-Port GbE	Op - LC	Fixed Optics Non-removable	7.3, 8.0, 8.1	12	12[13]	4	6	6	2	
	PCIe	X1046A-R6 NIC 4-Port GbE	Op - LC	Fixed Optics Non-removable	8.1.1	8	8[13]	4	6	6	2	
	PCIe	X1049B-R6 NIC 4-Port GbE	Cu - RJ45	-	7.3.5, 8.0.2, 8.1	8	8[13]	4	6	6	2	
	PCIe	X1107A-R6 NIC 2-Port 10GbE	Op - LC	X6563-R6 (FTLRXPL-SC-S43-42B or FTLX8571D3BCL)	7.3.2, 8.0, 8.1				6	6	2	
	PCIe	X1117A-R6 NIC 2-Port 10GbE	Op - LC	X6569-R6 (FTLX8571D3BCV-IT)	8.0.1, 8.1	8	8[13]	4	6[14]	6[14]	2[14]	
	PCIe	X1139A-R6 Unified Target 2-Port 10Gb	Op - LC	SFP module pre-installed (PLRXPL-VC-S43-21-N) No optical FRU available	7.3.2, 8.0.1, 8.1	12	12[13]	4	6	6	2	
	PCIe	X1140A-R6 Unified Target 2-Port 10Gb	Cu - SFP+	Approved Twinax Cables	7.3.2, 8.0.1, 8.1	12	12[13]	4	6	6	2	
	Mezzanine	X1160A-R6 NIC 2-Port 10GbE	Cu - SFP+	X6589-R6 (AFBR-703SDZ-NA2 or FTLX8571D3BCL-IN2)	8.1							1
SCSI / SAS	PCIe	X2028A-R6 TAPE 2-Port SCSI-LVD/SE	Cu - 68p VHDCI	-	7.3, 8.0, 8.1	8	8	4	6	6	2	
	PCIe	X2065A-R6 SAS, 4-Port, 6Gb	Cu - QSFP	-	7.3.2, 8.0, 8.1	4	4	4	6	6	2	
	PCIe	X2067-R6 SAS, 4-Port, 6Gb	Cu - QSFP	-	8.0.1, 8.1	3	3	1				
IHA	PCIe	X1927A-R6 MetroCluster™ FC-VI 2-Port 8Gb	Op - LC	SFP module pre-installed (FTLF8528P3BCV-QL) No optical FRU available	8.0.1, 8.1	1	1	1	1	1	1	
	PCIe	X3148-R6 NVRAM8 4GB	Cu-QSFP	X1956-R6 (optional)	8.0.1, 8.1	1	1	1				
OTHER	PCIe	X1142A-R6 SnapMirror® over FC 2-Port 8Gb	Op - LC	SFP module pre-installed (FTLF8528P3BCV-QL) No optical FRU available	8.0.1, 8.1	4	4	3	1	1	1	
	PCIe	X1970A-R5 Flash Cache - 256GB	-	-	7.3.5, 8.0.2, 8.1				2	1[15]		
	PCIe	X1971A-R5 Flash Cache - 512GB	-	-	7.3.5, 8.0.2, 8.1	8	6	3	2	1		
	PCIe	X1972A-R5 Flash Cache - 1TB	-	-	7.3.5, 8.0.2, 8.1	8	3	1	1			

COMMON CABLES

Fibre Channel Cable and Connectors



Part Number	Begin	End	Length	Notes
X6529-R6	SFP	LC	-	Op Module (50p)
X6539-R6	SFP	I/O	-	Op Module (4Gb FIA/HBA) (Both, 50/0, 27/0, and 0/50)
X6588-R6	SFP+	LC	-	FAS/V6200 and FAS/V70 Op Module (8Gb)
X6530-R6	SFP	SFP	0.5m	
X6532-R6	SFP	SFP	3m	24p Shelf-Type only
X6536-R6	SFP	SFP	5m	4Gb-support
X6533-R6	SFP	DB9	3m	
X6531-R6	SFP	HSSDC2	0.5m	
X6533-R6	SFP	HSSDC2	3m	

Part Number	Begin	End	Length	Notes
X6513-R6	HD-68	VHDCI	2m	-
X6557-R6	QSFP	QSFP	0.5m	-
X6558-R6	QSFP	QSFP	2m	-
X6559-R6	QSFP	QSFP	5m	-
X6560-R6	QSFP	QSFP	10m	SAS16
X6591-R6	QSFP	QSFP	20m	SAS16
X6594-R6	QSFP	QSFP	1m	SAS
X6595-R6	QSFP	QSFP	3m	SAS
X6543A-R6	QSFP	miniSAS	2m	-
X6544A-R6	QSFP	miniSAS	3m	-

Optical Cables and Connectors



Part Number	Begin	End	Length	Notes
X6510A-R6	SC	SC	5m	OM3, 50u, 500MHz
X6511A-R6	SC	SC	30m	OM3, 50u, 500MHz
X6524-R6	2 x LC	2 x LC	2m	OM3, 50u, 500MHz
X6553-R6	LC	LC	2m	OM3, 50u, 2000MHz
X6536-R6	LC	LC	5m	OM3, 50u, 2000MHz
X6554-R6	LC	LC	10m	OM3, 50u, 2000MHz
X6537-R6	LC	LC	30m	OM3, 50u, 2000MHz
X6523-R6	2 x LC	2 x SC	2m	OM3, 50u, 500MHz
X6547-R6	LC	SC	5m	OM3, 50u, 2000MHz
X6546-R6	LC	SC	30m	OM3, 50u, 2000MHz

HA Pair, Cluster Interconnect Cables and Connectors



Part Number	Begin	End	Length	Notes
X6558-R6	QSFP	QSFP	2m	FAS/V6000 to/Shelf kit
X6559-R6	QSFP	QSFP	5m	FAS/V6000 to/Shelf kit
X1966-R6	MTP	MTP	0.5m	-
X1945A-R6	MTP	MTP	5m	-
X1946A-R6	MTP	MTP	30m	-
X1951A-R6	MTP	SC	30m	4X to 1X patch
X1952A-R6	MTP	ST	30m	4X to 1X patch
X1953A-R6	MTP	LC	30m	4X to 1X patch
X1954A-R6	MTP	FC	30m	4X to 1X patch
X1955A-R6	MTP	MT-RJ	30m	4X to 1X patch
X-SFP-10GE-CU5M-R6	SFP+	SFP+	1m	FAS/V3250 kit
X-SFP-10GE-CU5M-R6	SFP+	SFP+	3m	FAS/V3250 kit
X-SFP-10GE-CU5M-R6	SFP+	SFP+	5m	FAS/V3250 kit
X6566-2-R6	SFP+	LC	2m	10 Module FAS/V3200 kit
X6566-3-R6	QSFP	QSFP	3m	10GbE
X6566-4-R6	QSFP	QSFP	2m	10GbE
X6566-5-R6	QSFP	QSFP	5m	10GbE
X6566-05-R6	QSFP	QSFP	0.5m	10GbE

Ethernet Cables and Connectors



Part Number	Begin	End	Length	Notes
X6560-R6	RJ45	RJ45	0.5m	CAT6
X6561-R6	RJ45	RJ45	2m	CAT6
X6562-R6	RJ45	RJ45	5m	CAT6
X6577-R6	RJ45	RJ45	30m	CAT6
X6563-R6	SFP+	LC	-	X1117A Op Module
X6569-R6	SFP+	LC	-	X1117A Op Module
X6589-R6	SFP+	LC	-	FAS/V6200 10GbE Op Mod
X6562-R6	RJ45	RJ45	10m	CAT6 - ACP
X6583-R6	RJ45	RJ45	20m	CAT6 - ACP
X-SFP-H10GE-CU1M-R6	SFP+	SFP+	1m	Cisco Twinax
X-SFP-H10GE-CU3M-R6	SFP+	SFP+	3m	Cisco Twinax
X-SFP-H10GE-CU5M-R6	SFP+	SFP+	5m	Cisco Twinax
X-TWX-0101-R6	SFP+	SFP+	1m	Brocade Twinax
X-TWX-0301-R6	SFP+	SFP+	3m	Brocade Twinax
X-TWX-0501-R6	SFP+	SFP+	5m	Brocade Twinax

STORAGE CONTROLLERS

Fabric-Attached Storage (FAS) and V-Series Controllers											
Model	FAS/V6280	FAS/V6240	FAS/V6210	FAS/V3270	FAS/V3250	FAS/V3240[1]	FAS/V3220[1]	FAS/V3210	FAS2240-4	FAS2240-2	FAS2220
Front View											
Max Capacity[2] (7.3.x / 8.0.x / 8.1.x)	- / 4320TB[3] / 4320TB[3]	- / 4320TB[3] / 4320TB[3]	- / 3600TB[3] / 3600TB[3]	960TB / 2880TB[3] / 2880TB[3]	- / - / 2160TB[3]	600TB / 1800TB[3] / 1800TB[3]	- / - / 1440TB[3]	240TB / 720TB[3] / 720TB[3]	- / - / 432TB	- / - / 374TB	- / - / 180TB
Max Aggregate[4] (7.3.x / 8.0.x / 8.1.x)	- / 100TB / 162TB	- / 100TB / 162TB	- / 70TB / 70TB	16TB / 70TB / 105TB	- / - / 105TB	16TB / 50TB / 90TB	- / - / 90TB	16TB / 50TB / 75TB	- / - / 60TB	- / - / 60TB	- / - / 60TB
Max FlexVol Size (7.3.x / 8.0.x / 8.1.x)	- / 100TB / 100TB	- / 100TB / 100TB	- / 70TB / 70TB	16TB / 70TB / 70TB	- / - / 70TB	16TB / 50TB / 50TB	- / - / 60TB	16TB / 50TB / 50TB	- / - / 60TB	- / - / 60TB	- / - / 60TB
Max Shelves (DS4486 / DS2246 / DS4243 / DS14)	30 / 60 / 60 / 84	30 / 60 / 60 / 84	25 / 50 / 50 / 72	20 / 40 / 40 / 68	15 / 30 / 30 / 51	16TB / 50TB / 50TB	12.5 / 25 / 25 / 42	10 / 20 / 20 / 34	- / 10 / 10 / 17	- / 5 / 5 / 6	- / 5 / 5 / 6	- / 2 / 2 / -
Max Drive Quantity	1440	1440	1200	960	720	600	480	480	240	144 (24 Int + 120 Ext)	144 (24 Int + 120 Ext)	60 (12 Int + 48 Ext)
V-Series Specifications: Max Backend LUNs	1440	1440	1200	960	720	600	480	480	100[5]	No V-Series Models		
V-Series Specifications: V-Series Supported Arrays	EMC - VNX - CX3,CX4 - VMAX - DMX4 HP - EVA x400, x100 - P6x00, P9x00 - XP24K, XP20K JPAR - P10000 - T400, T800 - F200, F400 HDS - USP - AMS - USP-V - HUS IBM - DS8700, DS8800 - DS5x00 - DS4700, DS4800 - XIV Gen2 & Gen3 Fujitsu - DX8000 - DX4x0 - DX8700 S2 - DX4x0 S2 Refer to the NetApp Interoperability Matrix at **http://support.netapp.com/matrix** for the latest back-end storage array support information.								No V-Series Models		
Environmental and HA Pair / Single Controller: Height (HA / Single)	12U / 6U	12U / 6U	6U / 6U	6U / 3U	6U / 3U	6U / 3U	6U / 3U	3U / 3U	4U / 4U	2U / 2U	2U / 2U
Environmental and HA Pair / Single Controller: Weight (HA / Single)	251.4 (114 kg) 125.7 lbs (57 kg)	251.4 (114 kg) 125.7 lbs (57 kg)	130.1 lb. (59 kg) 99.2 lb. (45 kg)	149 lb. (67.6 kg) 74.5 lb. (33.8 kg)	149 lb. (67.6 kg) 74.5 lb. (33.8 kg)	149 lb. (67.6 kg) 74.5 lb. (33.8 kg)	149 lb. (67.6 kg) 74.5 lb. (33.8 kg)	79.5 lb. (36.1 kg) 67.3 lb. (30.5 kg)	107.1 lbs (48.7 kg) 102 lbs (46.4 kg)	55.4 lbs (25.2 kg) 50.4 lbs (22.9 kg)	62.4 lbs (28.3 kg) 57.8 lbs (26.2 kg)
Environmental and HA Pair / Single Controller: AC Power[1] (HA / Single)	19.2A / 9.6A @100V 9.4A / 4.7A @200V	18.6A / 9.3A @100V 9A / 4.5A @200V	- / 5A @100V 4.8A / 2.5A @200V	7.28A / 5.47A @100V 3.58A / 2.73A @200V	10.94A / 5.47A @100V 5.46A / 2.73A @200V	6.37A / 5.01A @100V 3.15A / 2.5A @200V	6.37A / 3.71A @100V 3.15A / 1.96A @200V	6.27A / 4.22A @100V 3.11A / 2.11A @200V	5.97A / 5.36A @100V 3.01A / 2.70A @200V	4.45A / 3.92A @100V 2.23A / 1.92A @200V	4.32A / 5.31A @100V 2.59A / 2.14A @200V
Environmental and HA Pair / Single Controller: BTU/hr[1] (HA / Single)	6486 / 3243 @100V 6212 / 3106 @200V	6280 / 3140 @100V 5974 / 2987 @200V	- / 1673 @100V 3174 / 1639 @200V	2485 / 1867 @100V 2413 / 1820 @200V	3734 / 1867 @100V 3640 / 1820 @200V	2168 / 1707 @100V 2116 / 1632 @200V	2168 / 1256 @100V 2116 / 1229 @200V	2137 / 1437 @100V 2089 / 1403 @200V	2031 / 1820 @100V 1775 / 1983 @200V	1536 / 1332 @100V 1434 / 1294 @200V	1806 / 1471 @100V 1751 / 1444 @200V
Platform Specifications HA Pair / Single Controller: Processor (HA / Single)	4 / 2 64-bit six-core	4 / 2 64-bit quad-core	4 / 2 64-bit quad-core	4 / 2 64-bit dual-core	4 / 2 64-bit quad-core	4 / 2 64-bit quad-core	2 / 1 64-bit quad-core	2 / 1 64-bit dual-core	2 / 1 64-bit dual-core	2 / 1 64-bit dual-core HT	2 / 1 64-bit dual-core HT
Platform Specifications HA Pair / Single Controller: Memory (HA / Single)	192GB / 96GB	96GB / 48GB	48GB / 24GB	40GB / 20GB[10]	40GB / 20GB[10]	16GB / 8GB[10]	24GB / 12GB[10]	10GB / 4GB[10]	12GB / 6GB[10]	12GB / 6GB[10]	12GB / 6GB[10]
Platform Specifications HA Pair / Single Controller: NVRAM (HA / Single)	8GB / 4GB	8GB / 4GB	8GB / 4GB	4GB / 2GB NVMEM	4GB / 2GB NVMEM	2GB / 1GB NVMEM	3.2GB / 1.6GB NVMEM	1GB / 512MB NVMEM	1.5GB / 768MB NVMEM	1.5GB / 768MB NVMEM	1.5GB / 768MB NVMEM
Platform Specifications HA Pair / Single Controller: Exp Slots (HA / Single)	24 / 12 PCIe	24 / 12 PCIe	8 / 4 PCIe	12 / 6 PCIe	12 / 6 PCIe	12 / 6 PCIe	12 / 6 PCIe	4 / 2 PCIe	2 / 1 mezzanine	2 / 1 mezzanine	-
Platform Specifications HA Pair / Single Controller: Ethernet (HA / Single)	4 / 2 GbE RJ45 8 / 4 10GbE SFP+	4 / 2 GbE RJ45 8 / 4 10GbE SFP+	4 / 2 GbE RJ45 8 / 4 10GbE SFP+	4 / 2 GbE RJ45 4 / 2 10GbE SFP+	4 / 2 GbE RJ45	4 / 2 GbE RJ45	4 / 2 GbE RJ45	4 / 2 GbE RJ45	8 / 4 GbE RJ45 0-4 / 0-2 10GbE	8 / 4 GbE RJ45 0-4 / 0-2 10GbE	8 / 4 GbE RJ45
Platform Specifications HA Pair / Single Controller: FC Ports (HA / Single)	8-32 / 4-16 8Gb SFP+[11]	8-32 / 4-16 8Gb SFP+[11]	8-16 / 4-8 8Gb SFP+[11]	4 / 2 8Gb SFP	4 / 2 8Gb SFP	4 / 2 8Gb SFP	4 / 2 4Gb SFP	4 / 2 4Gb SFP	0-4 / 0-2 8Gb SFP+	0-4 / 0-2 8Gb SFP+	-
Platform Specifications HA Pair / Single Controller: SAS Ports (HA / Single)	0-24 / 0-12 6Gb QSFP	0-24 / 0-12 6Gb QSFP	0-8 / 0-4 6Gb QSFP	4 / 2 6Gb QSFP	4 / 2 6Gb QSFP	4 / 2 6Gb QSFP	4 / 2 6Gb QSFP	4 / 2 6Gb QSFP	4 / 2 6Gb QSFP	4 / 2 6Gb QSFP	4 / 2 6Gb QSFP
Platform Specifications HA Pair / Single Controller: Data ONTAP® (Min Release)	8.0.1, 8.1	8.0.1, 8.1	8.0.1, 8.1	7.3.5, 8.0.1, 8.1	8.1.2	7.3.5, 8.0.1, 8.1	8.1.2	7.3.5, 8.0.1, 8.1	8.1	8.1	8.1.1



Cluster-Mode Switches

Model	CN1610	CN1601
Supported Modes	Cluster	Cluster Management
Rack Units	1U	1U
Dimensions	H: 1.69 in (4.3 cm) W: 17.5 in (44.5 cm) D: 20 in. (50.8 cm)	H: 1.69 in (4.3 cm) W: 17.5 in (44.5 cm) D: 20 in. (50.8 cm)
Weight	22.5 lbs (10.2 kg)	12 lbs (5.45 kg)
Amps (Worst-case)	1.26A @100-120V .63A @200-240V	0.58A @100-120V 0.31A @200-240V
Watts (Worst-case)	126W @100-120V 126W @200-240V	33W @100-120V 33W @200-240V
BTU/hr (Worst-case)	403 @100-120V 403 @200-240V	113 @100-120V 113 @100-120V
Ethernet	16 10GbE SFP+	16 GbE RJ45
Data ONTAP® (Min. Release)	8.1.1	8.1.1

Optical Module Support for Onboard Ports

Model	FAS/V6280	FAS/V6240	FAS/V6210	FAS/V3270	FAS/V3250	FAS/V3240	FAS/V3220	FAS/V3210	FAS2240-4	FAS2240-2	CN1610
10GbE (Data)	X6569-R6 10Gb SFP+	●	●	●							●	●
8Gb FC (Data)	X6588-R6 8Gb SFP+