

C.B. RADIO SECRET Master Tune Up Manual

Hello! Welcome to the C.B. RADIO SECRET ~ Master Tune Up Manual online sample version. The following pages contain the the tuning adjustment locations and microphone wiring charts for most C.B. and many Ham radios. We have also included the complete set of 29 SECRET CB Manuals to help you with this great hobby. I hope that this information is helpful to you. Please keep in mind that this is only a fraction of the massive amount of information contained on the CD ROM versions. The CD-ROMS contains Information for most of the newer radios including such very useful information as....

** 100's of Owners/Operator and Service Manuals **

** Boat Loads Of Schematic Diagrams **

** Block Diagrams **

** Microphone wiring charts **

** Antenna information (Most Models Covered) **

** Frequency Modifications **

** PLL Mods **

** PLL Data **

** Expo Expander Kits (info) **

** Crystal Cross Reference Charts For Modifying The Older Rigs **

** Channel Chart For Most Export Radios (After Mods) **

** Linear Amplifier Information. Most Models Covered*



(Including Manuals) *

~ MICROPHONE WIRING CHARTS ~

[Click Here For Wiring Instructions](#)

Just Click The Brands Below To Find The Chart You Need.

[ALAN-COBRA](#) [COBRA](#) [CRAIG](#) [CRAIG-GALAXY](#) [GALAXY](#) [MAXON](#) [MIDLAND](#) [RANGER](#) [RANGER-](#)
[REALISTIC](#) [ROBYN](#) [SEARS](#) [SOMMERKAMP](#) [TEABERRY](#) [TEABERRY-TRISTAR](#) [TRS-CHALLENGER-](#)
[UNIDEN/PRESIDENT](#) [UNIDEN](#) [ZODIAC](#)

~ CB RADIO Tune-Up Information ~

[Click Here For Tune-Up Instructions](#)

Just click the letters below to choose a radio brand that you want to tune.

[A](#) [B](#) [C](#) [D](#) [E](#) [F](#) [G](#) [H](#) [I](#) [J](#) [K](#) [L](#) [M](#) [N](#) [O](#) [P](#) [Q](#) [R](#) [S](#) [T](#) [U](#) [V](#) [W](#) [X](#) [Y](#) [Z](#)



[~ CLICK HERE FOR ALL 29 VOLUMES OF SECRET CB RADIO ~](#)



[Ads by Google](#)

[CB Repair](#)

[CB Store](#)

[Base CB Amps](#)

[Texas Ranger CB](#)

[Galaxy CB](#)

[Ham Radio Online Courses](#)

The easiest way to pass the ham radio exams. Results guaranteed!



[Barracuda Wiring Diagram](#)

You can find it on Yahoo! Search for Barracuda Wiring Diagram

[Ads by Google](#)



All Rights Reserved C.B. RADIO SECRET © 2003 - 2008

[Back to Main Menu](#)[Next Page](#)

C.B. RADIO SECRET Master Tune Up Manual

If You Find This Information Helpful Then Please Consider A Small Donation To Help Keep This Site Alive!

[Make A Donation](#)

ACTIONLINE RADIOS

Model	Modulation	AM Power	SSB Power
WCB-10	RV1	N/A	N/A

ALAN RADIOS

Model	Modulation	AM Power	SSB Power
555	VR14 or Cut R249 or Remove TR53	VR13	VR12
560	VR14 or Cut one end of R291	VR15 Low Power VR13 High Power	VR12

ALARON RADIOS

Model	Modulation	AM Power	SSB Power
B-1025	VR7 or Cut D14	L11 L10 L9	
B-1100	VR3 or Remove C72	L15 L16	
B-1150	VR5 or Cut D11 & D12	L15 L16	
B-4075	VR219 or Cut D201 & D204	L307 L308 L309 L306	
B-4085	RV202 or Remove C210	L306 L307 L308	
B-4900	Remove C228 or Cut D208	L401 L403 L406	

B-5050A	VR219 or Cut D201 or D204	L307 L308 L309 L306	
B-5200	VR4	L5 L8 L9	

AMERICAN ELECTRONICS

Model	Modulation	AM Power	SSB Power
76-501	VR4 or Cut D18	L8 L10	
76-551	VR4 or Cut D7	L8 L9	
76-601	VR4 or Cut D18	L8 L10	

ARGO RADIOS

Model	Modulation	AM Power	SSB Power
ARGO 300	VR4 or Remove C135	RV6 (AM) RV7 (FM)	

ARGUS RADIOS

Model	Modulation	AM Power	SSB Power
5000	RV12	RV11	RV6 RV3

AUDIOVOX RADIOS

Model	Modulation	AM Power	SSB Power
100	Cut D12		
MCB-500	R68 or Cut D16	L5	
MCB-750	VR3 or Cut D16	T7 L3 L4	
MCB-1000	VR5 or Cut D11 & D12	L16 L15 L14 VR10	
MCB-2000	R145 or Cut D108 or Remove C173	T114 T115	
MCB-3000	VR5 or Remove C48	T8 T9	
MCB-5000	R268 or Cut D207 or D215	L202 L204	

MCB-6000	R279 or Cut D220 or D215	L202	
WINDSOR	VR5 or Cut D11 & D12	L16 L15 L14 VR10	

AUTOMATIC RADIOS

Model	Modulation	AM Power	SSB Power
CBH-2265	R207 or Cut D201	L205	

[Back to Main Menu](#)

[Next Page](#)

[Want More? Check Out The CD! Over 400MB of VERY Useful Information](#)



[Ham Radio Online Courses](#)

Get your ham radio license. Morse Code no longer required!

[Connex CB Radio Sale](#)

Reduced pricing on all CB Radios plus free shipping over \$200.

Ads by Google

All Rights Reserved C.B. RADIO SECRET © 2003,2004,2005,2006

[Previous Page](#)[Back to Main Menu](#)[Next Page](#)

C.B. RADIO SECRET

Master Tune Up Manual

If You Find This Information Helpful Then Please Consider A Small Donation To Help Keep This Site Alive!

[Make A Donation](#)

BELTEK RADIOS

Model	Modulation	AM Power	SSB Power
ENDURO 5	R142	C142 L115	
ENDURO 23	R191 or Cut CR120 & CR121	L115	

BETA RADIOS

Model	Modulation	AM Power	SSB Power
BETA 23 DELUXE	Cut R78		

BOMAN RADIOS

Model	Modulation	AM Power	SSB Power
CB-515	RV5 or Cut D10	CV1	
CB-555	VR481 or Cut D481 & D482	L451 L463	
CB-720B	Cut CD12	L3	
CB-725	VR481 or Cut D481 & D482	L451 L463	
CB-750	FVR3 or Cut D10	L23 L22	
CB-770	VR206 or Cut D213	VC201 L301	VR205
CB-775	Cut D17	L7 L6	
CB-910	RV2 or Remove C96	L7 L11 L12	
CB-920	RV2 or Remove C96	L7 L11 L12	

CB-930	RV2 or Remove C96	L7 L11 L12	
CB-950	RV12 or Remove Q37 & Q38	VR4	RV11 RV2
CBH-900	RV2 or Remove C96	L7 L11 L12	
CBH-990	RV2 or Remove C96	L7 L11 L12	
CBH-6100	Cut D221	L301 L314	
CBR-9600	RV105	L111 L113	
CBR-9900	VR902	L903 L905	
CBR-9940	VR902 & VR 903	VR901	
CBR9950 AM/FM/CB	VR2	L4 L3 L1	

BRISTOL RADIOS

Model	Modulation	AM Power	SSB Power
CB-2271	Cut D481 & D482	L451 L463	

BROWNING RADIOS

Model	Modulation	AM Power	SSB Power
BARON	R134 or Cut CD36	L5 L7 L3	R130
BROWNIE 23	Cut CD12	L3 L5	
BROWNIE 40	Cut CD12	L3 L5	
LTD	R85 or Remove Q23	L2 L5	R96
MARK 4A	R603	T303 C602	R318
SABRE	Cut D11 & CD12	L5 L3	
SST (early)	Cut D19 & D20	A20 A21	
SST (late)	Cut D18 & D19	L2 L5	
SST 2	Cut D11 & CD12	L5 L3	

[Previous Page](#)

[Back to Main Menu](#)

[Next Page](#)

Want More? Check Out The CD! Over 400MB of VERY Useful Information



[Ham Radio 2010 Special](#)

Entry-level license for \$20 and 10 hours study. No Morse code needed!



[CB Radios & Equipment](#)

Galaxy, Connex, Magnum Radios Sirio, CB, Ham & Marine Antennas

Ads by Google

All Rights Reserved C.B. RADIO SECRET © 2003,2004,2005,2006

[Previous Page](#)[Back to Main Menu](#)[Next Page](#)

C.B. RADIO SECRET Master Tune Up Manual

If You Find This Information Helpful Then Please Consider A Small Donation To Help Keep This Site Alive!

[Make A Donation](#)

C.P.I. RADIOS

Model	Modulation	AM Power	SSB Power
CP 400	R699 or Cut Base Leg of Q410	R205	R274

CALTRON RADIOS

Model	Modulation	AM Power	SSB Power
CB-7500	VR6 or Cut D24 & D25	L18 L20 L21	

CHANNEL MASTER RADIOS

Model	Modulation	AM Power	SSB Power
CB-6830	VR7 or Cut D505	L906 L903	
CB-6832	VR7 or Cut D505	L906 L903	
CB-6834	VR6 or Cut D506 or D505	L903 L905	
CB-6835	VR6 or Cut D506 or D505	L903 L905	

CHEROKEE RADIOS

Model	Modulation	AM Power	SSB Power
AH-100	RV14	RV4	
CBS-1000	VR5 VR14	VR4	

CM-10

VR103

VR502

CLARICON RADIOS

Model	Modulation	AM Power	SSB Power
ACTIVATOR (30800)	R152 or Cut CR107	L11 C162	
PRIVATEER (30600)	R152 or Cut CR107	L11 C162	
RAIDER (30500)	VR4 or Cut D13	L16 L14	
INTRUDER (30200)	R152 or Cut CR107	L11 C162	
PIRATE (30400)	R152	L10 C154	
71200	R152	L111 L110	

CLAIRION RADIOS

Model	Modulation	AM Power	SSB Power
DMA-066	VR201	L201 L204	
JC-201E	Cut D201	L207	
JC-202E	VR201	L201 L204	
JC-203E	VR201 or Cut D205	L201 L204	
PE-672E	VR201	L201 L204	
RCJ-003	VR201	L201 L204	
TC-203C	VR201 or Cut D205	L201 L204	

COBRA RADIOS

Model	Modulation	AM Power	SSB Power
7 PLUS	VR4 or Cut D8	L11 L12 L13	
10 PLUS	VR4 or Cut D8	L11 L12 L13	
18 LTD	Cut D13 or Cut R84	L7 L6 L5	
18 PLUS	Cut D12	L7	
18 RV	RV501 or Cut D502	L304 L305 L306	
19	Cut D11	L5 L8 L9	
19 GTL	VR6 or Cut D9	L15 L16 L17	

19 LTD	VR6 or Cut D9	L15 L16 L17	
19 LTD CLASSIC	VR4 or Cut D7	L7 L8	
19 M	Remove C73	L8 L5 L3	
19 PLUS	RV501 or Cut C511	L305 L306	
19 PLUS (new)	VR4 or Cut D8	L11 L12 L13	
19XS	Cut D105		
20 (B&K)	Cut CD20 & CD21	T11 T10 C60	
20 LTD	Cut D13		
20 PLUS	RV501 or Cut C511	L305 L306	
20 PLUS (new)	VR4 or Cut D8	L11 L12 L13	
21	Remove C105 & C106	L12 L9	
21A (old)	Cut D24	L9 L8	
21 GTL	VR5 or Cut D9	L13 L10 L9 L8	
21 LTD	VR5 or Cut D9	L13 L10 L9 L8	
21 LTD CLASSIC	VR4 or Cut D7	L7 L8	
21 PLUS	Cut 1.5k resister next to TR34	L12 L10	
21X	VR207 or Cut D212	L212 L214	
21 XLR	RT4 or Cut D13	L15 L12 L11	
23 PLUS	RV501 or Cut D502	L304 L306 L307	
25 GTL	VR5 or Cut D9	L13 L10 L9 L8	
25 LTD	VR5 or Cut D9	L13 L10 L9 L8	
25 LTD CLASSIC	VR5 or Cut D9	L10 L9 L8	
25 PLUS	Cut 1.5k resister next T34	L12 L10	
26	Cut D24	L7 L8	
28A	Cut CD28 & CD29	T12 L2 L5	
29A (old)	Cut D24	L7 L8	
29 XLR	VR5 or Cut D14	L15 L12 L11	
29 GTL	VR4 or Cut D11	L14 L13 L12	
29 LTD	VR4 or Cut D11	L14 L13 L12	
29 LTD CLASSIC	VR4 or Cut D11	L14 L13 L12	
29 LTD GOLD	VR4 or Cut D11	L14 L13 L12	
29 PLUS	Cut D20	L12	
31 PLUS	Cut D19	L13 L12 L11	
32 XLR	Cut CD11 & CD12	L5 L3	

33 PLUS	VR4 Or Cut D17	L11 L9	
33 LTD (sos)	RV1		
40 PLUS	RV104 or Cut D203	L305 L306	
40X	RV201 or Cut D203 or C215	L304 L305 L306	
41 PLUS	RV4 or Cut D21	L19 L20 L21	
45 XLR	VR105 or Cut D119	L113 L109	
46 XLR	VR105 or Cut D119	L113 L109	
47 XLR	VR105 or Cut D119	L113 L109	
50 XLR	VR5 or Cut D119	L109	
55 XLR	VR5 or Cut D119	L109	
62 XLR	VR3 or Remove C67	L16 L15 L12	
66 GTL	VR2 or Cut D4	L14 L15 L17	
66 LTD	Cut R54		
67 LTD	RV4 or Cut D212	L306 L307 L308	
77X	VR207 or Cut D212	L211 L212 L214	
78X	VR6 or Cut D9	L11 L12 L15	
85	Remove Q17 from Circuit	L3 T4	
86 XLR	L3 T4	L3	
CAM 89	Add a 1k resister in series with C110	L13 L12 L9	
87 GTL	VR6 or Cut D16	L17 L16 L13	
89 GTL	VR6 or Cut D16	L17 L16 L13	
89 XLR	VR5 or Cut D14	L15 L12 L11	
90 LTD	RV201 or Cut D203		
132 (old)	Cut Q25 from circuit	T14 T15 L3 C116	R136
132A	Cut CD39 & CD 40	R79	R87
132 XLR	R134 or Cut R125	L3	R130
134	Cut D40 & D41	L8 L10	VR15
135 (old)	Cut Cut Q25 from circuit	T14 T15 L3 C116	R136
135 XLR	R134 or Cut R125	L3	R130
138A (old)	Cut D40 & D41	L8 L10	VR15
138 XLR	VR7 & VR6	VR8	CT7
139	VR12 or Cut D63	L12 L10	VR15
139 XLR	VR7 & VR6	VR8	CT7

140 GTL	Cut R104	VR6	VR7
142 GTL	Cut R104	VR6	VR7
146 GTL	VR5 or Remove TR29	VR10	VR6
148 GTL	Cut R131	VR10	VR11
148 GTL-DX (early)	VR5	VR11	VR7
148 GTL-DX (late)	VR14 or Remove TR32	VR13	VR12
148 GTL-B	RV14	RV15	RV13
148 GTL-DX	RV12	RV11	RV6 RV3
1000 GTL	VR6 or Cut D16	L17 L16 L13	
2000 GTL	Cut R131	VR10	VR11
GTL 150	RV14	RV13	RV12 RV4

COLT RADIOS

Model	Modulation	AM Power	SSB Power
SX33	RV2 or Remove C96	L7 L11 L12	
190	R71		
210	RV201 or Cut D203	L305 L306	
222	RV201 or Cut D203	L305 L306	
290	RV2 or Remove C96	L7 L11 L12	
320DX	RV14	RV13	RV12 RV4
320FM	RV14	RV13	RV12 RV4
350	RV121 or Cut D19 & D20	L34 L37	
355	RV201		
357 (new)	VR4	L11 L12 L13	
357 (old)	RV3	L5	
390	RV2 or Remove C96	L7 L11 L12	
444	Remove C99	L12 L15 L16 (HI PWR)	
480	RV12 or Remove Q37 & Q38	VR4	RV11 RV2
485	RV12 or Remove Q37 & Q38	VR4	RV11 RV2
485DX	RV12 or Remove Q37 & Q38	VR4	RV11 RV2
510	RV201 or Cut D203	L304 L305 L306	

800	RV2 or Remove C96	L7 L11 L12	
870	RV2 or Remove C96	L7 L11 L12	
870 (export)	RV2 or Remove C96	L7 L11 L12	
1000	RV12 or Remove Q37 & Q38	VR4	RV11 RV2
1200	RV12	VR9	VR2
1200 DX	RV14	RV13	RV12 RV4
1600 DX	RV12	RV11	RV6 RV3
2000 DX	RV12	RV11	RV6 RV3
2400	RV12	RV11	RV6 RV3
EXCAIBUR (EPT30010Z Board)	VR14 or Cut R249	VR13	VR12
EXCALIBUR (PTBM121D4X Board)	RV14	RV13	RV12 RV4

COMMANDO RADIOS

Model	Modulation	AM Power	SSB Power
2310	Rv5 or Cut D10	CV1	
2320	VR7 or Cut D14	L11 L10	
2325	VR7 or Cut D14	L11 L10	
2340	Cut R82 or Cut D11	L19 L18	

COMMTRON RADIOS

Model	Modulation	AM Power	SSB Power
VIII	RV201 or Cut D203	L304 L305 L306	
XII (export)	RV201 or Cut D203	L304 L305 L306	

CONNEX RADIOS

Model	Modulation	AM Power	SSB Power
3300	Cut R249 & R246	VR13 (L PWR) L32 L33 (HI PWR)	

CONVOY RADIOS

Model	Modulation	AM Power	SSB Power
CON-400	R121 or Cut D19 & D20	L34 L37	
CON-430	VR102 or Cut D112	L113 L116	
CON-450	R85	L25	

COURIER RADIOS

Model	Modulation	AM Power	SSB Power
BLAZER 40D	VR9 or Cut D12	T13 L9	
CADET	Cut D4	L14 L15	
CARAVELLE II	VR6 or Cut D6	L2	
CARAVELLE 40D	R504 or Cut D503	L404 L403	
CENTURIAN 23	VR14 or Cut D46 & D47	VR17 L12 L14	VR12 L15
CENTURIAN 40D	RT601	RT14	RT14
CENTURIAN PLL40	RT9 or Cut D24	RT14	RT14
CLASSIC II	R715	C934 L14 L15	
CLASSIC III	R523 or Cut D506		
CLASSIC IV	RV3 or Cut D9	L11 L13	
CLASSIC PLL40	VR6 or Remove C508 or Cut D505	L903 L906	
CONQUEROR II	VR6 or Cut D6	L2	
CONQUEROR 40D	R504 or Cut D503	L404 L403	
CRUISER	Cut D17 or D18	L7 L8 L9	
GALAXY	VR11 or Cut R104	VR6	VR7
GALAXY IV	RV3	RV7	RV8
GALAXY V	RV14 or Cut R249	VR13	VR12
GALAXY VI	RV14 or Cut R249	VR13	VR12
GLADIATOR	VR14	VR17	VR15

NIGHTRIDER 40DR	VR301	L120 L119	
RANGLER 40D	VR301	L120 L119	
REBEL 23+	Cut D12	L13 L12 L9	
REBEL 40A	VR207 or Cut D212	L211 L212 L214	
REBEL PLL	VR207 or Cut D212	L214	
REDBALL	Cut D17 or D18	L7 L8 L9	
RENEGADE 40	VR9 or Cut D12	T13 L9	
ROGUE 40	VR5 or Cut D12	L9	
SPARTAN SSB	Cut D54 & D53	VR14	VR9
TRAVELLER II	VR6	L16 L18 L20	

CRAIG RADIOS

Model	Modulation	AM Power	SSB Power
4101	VR4 or Cut D18	L6 T9 T10	
4102	VR4 or Cut D18	L6 T9 T10	
4103	R192 or Cut CR118 & CR119	L111 L110	
4104	R192 or Cut CR118 & CR119	L111 L110	
4201	R192 or Cut CR118 & CR119	L111 L110	
L-101	R226 or Cut R224	L305 L308 L309	
L-102	R348 or Cut CR312	L311 L315	
L-103	Cut D8	L16	
L-104	VR5 or Cut D9	L10	
L-131	R605 or Cut CR602	L109 L106	R130
L-132	Cut R104	VR6	VR7
L-150	Cut D4	L14 L15 L17	
L-231	R605 or Cut CR602	L109 L106	R130
L-232	Cut R104	VR6	VR7
L-600	VR402 or Cut R461	T409 T410	

[Previous Page](#)

[Back to Main Menu](#)

[Next Page](#)

[Want More? Check Out The CD! Over 400MB of VERY Useful Information](#)



[Ham Radio 2010 Special](#)

Entry-level license for \$20 and 10 hours study. No Morse code needed!

[Stryker CB Radio Sale](#)

Reduced pricing on all CB radios. Free Shipping on orders over \$200.



Ads by Google

[All Rights Reserved C.B. RADIO SECRET © 2003,2004,2005,2006](#)

[Previous Page](#)[Back to Main Menu](#)[Next Page](#)

C.B. RADIO SECRET Master Tune Up Manual

If You Find This Information Helpful Then Please Consider A Small Donation To Help Keep This Site Alive!

[Make A Donation](#)

DAK RADIOS

Model	Modulation	AM Power	SSB Power
DAK IX (old)	RV202 or Remove Q202	C714	
DAK X	REMOVE Q37 & Q38	RV201	RV2
MARK II	Remove C226	L307 L308 L309	
MARK V	RV202 or Cut D202	L306 L307 L308	

DIRLAND RADIOS

Model	Modulation	AM Power	SSB Power
77-099	RV4 or Cut D8	L11 L12	
SS-3900	VR14 or Remove TR53	VR13	VR12
SS-3900B	VR14 or Remove TR53	VR13	VR12

EAGLE RADIOS

Model	Modulation	AM Power	SSB Power
Eagle 2000	VR14 or Cut R249	VR13(HI PWR) VR16(LO PWR)	VR12
Eagle 5000	VR14	VR13(HI PWR) VR16(LO PWR)	VR12

ECHO RADIOS

Model	Modulation	AM Power	SSB Power
Echo 49er	VR5 or Cut D17	L9 L8 L7	
Echo 99er	R74 or Cut D4	T7 L14 L15	

EMPEROR RADIO

Model	Modulation	AM Power	SSB Power
TS-5010	VR110 or Cut R247	VR111	VR103

FALCON RADIO

Model	Modulation	AM Power	SSB Power
FALCON 2000	RV12	RV11	RV6 RV3

FANON RADIOS

Model	Modulation	AM Power	SSB Power
10-40 (AM/FM/CB)	VR4	L5 L8 L9	
FANFARE 100	Cut D12	L9 L12	
FANFARE 100F1	VR207 or Cut D212	L211 L212 L214	
FANFARE 120	VR5 or Cut D7	L8 L9	
FANFARE 125F	VR5 or Cut D12	T14 T13 L9	
FANFARE 182F	VR9 or Cut D12	T14 T13 L9	
FANFARE 184DF	VR9 or Cut D12	T14 T13 L9	
FANFARE 185DF	VR301	L118 L120 L119	
FANFARE 185PLL	VR301	L118 L120 L119	
FANFARE 190DF	VR301	L118 L120 L119	
FANFARE 350F	VR8 or Cut D33	VR6	VR7
FANFARE 700	R40 or Remove Q8	L3 C6	
FANFARE 880	VR6 or Cut D6	L2	
FANFARE 880DF	R504 or Cut D503	L404 L403	
FANON SFT-400	Cut D10 & D9	A10	

FANON SFT-500	Cut D10 & D9	A10	
FANON SFT-900	VR403 or Cut D204	A16 A17	
FANON T-600	R510 or Cut D503	L901 L902	
FANON T-700	R510 or Cut D503	L901 L902	
FANON T-800	R510 or Cut D503	L901 L902	
FANON T1000C	VR6 or Cut D505	L911	

FIELDMASTER RADIO

Model	Modulation	AM Power	SSB Power
MICRO-MINI 40	RV401	L13 L10	

FORMAC RADIOS

Model	Modulation	AM Power	SSB Power
88 AM/FM Export	RV2	L7 L11 L12	
FORMAC 40	VR2 or Remove C96	L7 L11 L12	
FORMAC 240	VR3(LO MOD) VR4(MED MOD) VR5 (HI PWR MOD)	LT3 LT2 (HI PWR) VR6 (MID PWR) VR7(LO PWR)	
FORMAC 700	VR3(LO MOD) VR4(MED MOD) VR5(HI PWR MOD)	LT6 LT5(HI PWR) VR6(MID PWR) VR7(LO PWR)	

FOX RADIOS

Model	Modulation	AM Power	SSB Power
CB-240	RV4 or Cut R65 or R61	L9 L11 L12	
CB-340	RV201	L304 L305 L306	
CB-440	RV4	L11 L12 L14	
CB-911	RV1		

FULCOMM RADIOS

Model	Modulation	AM Power	SSB Power
2303	VR206 or Cut D214 & D214	L301 VC201	VR104 VR205
2330	VR481 or Cut D481 & D482	L451 L463	

FUZZBUSTER RADIOS

Model	Modulation	AM Power	SSB Power
Z-40	RV201 or Remove C253	L205 L206 L207	
Z-50	VR3 or Cut D7	LX18 LX19 LX20	
Z-80	Cut D203	L305 L306 L304 L303	

[Previous Page](#)
[Back to Main Menu](#)
[Next Page](#)

Want More? Check Out The CD! Over 400MB of VERY Useful Information



<p>Become a ham for \$20 Entry-level ham license for \$20 and 10 hours study. Success guaranteed!</p>	<p>Sony dash Internet Viewer Display Over 1,500 Free Internet Apps At the Touch of Your Finger.</p>
---	---

Ads by **Google**

All Rights Reserved C.B. RADIO SECRET © 2003,2004,2005,2006

[Previous Page](#)[Back to Main Menu](#)[Next Page](#)

C.B. RADIO SECRET Master Tune Up Manual

If You Find This Information Helpful Then Please Consider A Small Donation To Help Keep This Site Alive!

[Make A Donation](#)

GALAXY RADIOS

Model	Modulation	AM Power	SSB Power
2100	VR14 or Cut R249	VR13	VR14
33 PLUS	VR14 or Remove TR53	VR13(LOW) L32 L33 (HI)	
DX 11B	VR14	VR803...AM/FM Low Power VR13...AM/FM High Power	VR12
DX 22B	VR14	VR15...AM Low Power VR13...High Power	VR12
DX 2517	VR16	VR18...AM/FM Low Power VR14...AM/FM High Power	VR17
DX 2527	VR14	VR15...AM Low Power VR13...High Power	VR16
DX33 HML	Cut R249	VR13 (HI PWR)	
DX33 HML (late)	VR14 or Remove TR53	VR13(HI PWR) VR16(LO PWR)	
DX 44V	Cut R249	VR13 (HI PWR)	
DX 55V	VR14 or Remove TR53	VR13(HI PWR) VR16(LO PWR)	
DX 66V	VR14 or Remove TR53	VR13(HI PWR) VR16(LO PWR)	
DX 77HML	VR14 or Remove TR53	VR13(HI PWR) VR16(LO PWR)	VR12

DX 77V	VR14 or Remove TR53	VR13(HI PWR) VR16(LO PWR)	VR12
DX 88HL	VR14 or Cut R249	VR13	VR12
DX 949	VR16	VR18...AM Low Power VR14...AM High Power	VR13 VR17
DX 99V	VR14 or Remove TR53	VR13(HI PWR) VR16(LO PWR)	VR12
DX 959	VR16	VR18...AM Low Power VR14...AM High Power	VR13 VR17
Galaxy II	VR14 or Cut R249	VR13	VR12
Jupiter	VR14 or Cut R249	VR13	VR12
Mars	Cut One End Of R104 & D11	L14 L12 L11 L10 (HI PWR)	
Mirage 44	Cut R249	VR13	VR12
MIRAGE 44 (EPT 360014B Board)	VR14 or Remove TR53	VR13(HI PWR) VR16(LO PWR)	
MIRAGE 66	Cut R249	VR13	VR12
MIRAGE 88	Cut R249	VR13	VR12
PLUS	VR14 or Cut R249	VR13	VR12
PLUTO	VR14 or Cut R249	VR13	VR12
PLUTO (late)	VR14 or Remove TR53	VR13(HI PWR) VR16(LO PWR)	VR12
SATURN	VR14 or Cut R249	VR13	VR12
SATURN II	VR14 or Remove TR53	VR13(HI PWR) VR16(LO PWR)	VR12
SIRIUS	VR4 or Cut R124	L18 L21 L25	
SUPER GALAXY	VR14 or Cut R249	VR13	VR12

GEMTRONICS

Model	Modulation	AM Power	SSB Power
GR-11930	VR481 or Cut D481 & D482	L451 L463	

GT-230	VR5 or Remove C56 or Cut D14	L9 L10	
GT-44	RV2 or Remove C96	L7 L11 L12	
GT-55	RV2 or Remove C96	L7 L11 L12	
GTX-23	VR481 or Cut D481 & D482	L451 L463	
GTX-230	VR5 or Remove C56 or Cut D14	L9 L10	
GTX-2325	VR103 or Cut D214	VC201	VR205
GTX-3000	R94 or Remove C82 or Cut D16	L9 L10	
GTX-3323	VR481 or Cut D481 & D482	L451 L463	
GTX-36	VR481 or Cut D481 & D482	L451 L463	
GTX-4040	VR481 or Cut D481 & D482	L451 L463	
GTX-5000	VR4	L702 (TOP)	
GTX-66	RV2 or Remove C96	L7 L11 L12	
GTX-77	RV12 or Remove Q37 & Q38	VR4	VR2

GENERAL ELECTRIC RADIOS

Model	Modulation	AM Power	SSB Power
3-5800A	VR5 or Cut D507 or D508	L906	
3-5801A	VR7 or Cut D505	L905 L903	
3-5804	RV5 or Cut D12	T4 T5 L3	
3-5804A	VR7 or Cut D505	L905 L903	
3-5804B	VR8 or Remove Q503	L905 L903	
3-5804D	RV2 or Remove C96	L7 L11 L12	
3-5804F	Cut D8 or Change R87 to 1.2k	L9 L12 L16	
3-5804G	RV5 or Cut D12	T4 T5 L3	
3-5805A	Cut D13	L8 L9 L12	
3-5805B	RV201	L304 L305 L306	
3-5806	Cut D9	L9 L11 L12	

3-5806A	VR4	L11 L12	
3-5810A	VR7	Cut D505 or D504	
3-5810B	RV102 or Cut D111	L110 L109	
3-5811B	RV2 or Remove C96	L7 L11 L12	
3-5813A	RV2 or Remove C96	L7 L11 L12	
3-5813B	RV2 or Remove C96	L7 L11 L12	
3-5814A	RV2 or Cut D10	L10 L5 L9	
3-5814B	RV2 or Remove C96	L7 L11 L12	
3-5814D	Remove Q14		
3-5815A	VR504 or Cut D512	L903	
3-5816A	RV4	L5 L6 L7 L8	
3-5817A	RV2 or Cut D11	T3 T4 L3	
3-5818A	VR2 or Remove C98	L5 L9 L10	
3-5819A	RV2 or Remove C96	L7 L11 L12	
3-5819B	VR2 or Remove C98	L5 L9 L10	
3-5821A	VR10 or Cut R554 or Cut D519	L903 L905	
3-5821B	VR10 or Cut R554 or Cut D519	L903 L905	
3-5825A	RV12 or Remove Q37 & Q38	VR5	RV2
3-5825B	RV9	VR1	RV3 RV201
3-5826A	RV6	RV7	RV5 RV2
3-5827A	RV501	L305 L308	
3-5830	VR2	L4 L1 L3	
3-5869A	RV2 or Cut D10	L5 L9 L10	
3-5871A	VR6 or Cut D504 & D505	L905	
3-5871B	VR11 or Cut D504	L905 L903	
3-5875A (SUPERBASE)	RV9 or Remove C71	VR10	RV20
3-5900A	RV3 or Remove V71	VR10	

GENERAL MOTORS RADIOS

Model	Modulation	AM POWER	SSB Power
4120	Cut CR12	L6 L4	

4145	Cut CR12	L6 L4	
4175	Cut CR14	T8	
4230	CR12	L6 L4	
70BFMCE	Remove VR2	L12	
80BCB1	RV2 or Remove C96	L7 L11 L12	
80BCB2	Remove RV2	L4 L9	
80BFTC1	RV2 or Remove C96	L7 L11 L12	
86KFTC1	RV2 or Remove C96	L7 L11 L12	
90BCB1	Remove RV2	L4 L9	
90BFMC1	Cut D9	L44	
90BFPC1	Cut D9	L44	
90BFTC1	Remove RV2	L4 L9	
91YFMC1	Cut D9	L44	
90ECB1	Remove RV2	L4 L9	
CBD-10	RV102 or Cut D111	L110 L109	
CBD-12	Cut CR11	L6 L7	
CBD-203 AM-FM-CB	RV2	L4 L8 L9	
CBD-20U (90BCB2)	RV2	L4 L8 L9	
GM123A	Cut CR11	L6 L7	
GM130	Cut CR11	L6 L7	
GM23B	Cut D9	L8	
GM23C	Cut D9	L8	

GLOBE RADIOS

Model	Modulation	AM Power	SSB Power
9000	VR7 or Cut D14	L9 L10 L11	
9001	VR7 or Cut D14	L9 L10 L11	

GRAN PRIX RADIOS

Model	Modulation	AM Power	SSB Power
1125	VR7 or Cut D14 or D15	L18 L17	

D-1235RF

VR481 or Cut D481 & D482

L451 L463

GRANADA RADIOS

Model	Modulation	AM Power	SSB Power
CB-6	RV5 or Cut D17 & D18	L16 L14	
CB-7	Remove C322 or Cut D11	L15	
FCB-27	Remove C322 or Cut D11	L15	

GREAT RADIOS

Model	Modulation	AM Power	SSB Power
GT-818	VR8	L901 L903 L905	
GT-838	Cut D17	T203 T204 T205	

[Previous Page](#)

[Back to Main Menu](#)

[Next Page](#)

Want More? Check Out The CD! Over 400MB of VERY Useful Information



[Become a ham for \\$20](#)

Entry-level ham license for \$20 and 10 hours study. Success guaranteed!

[CB Radios & Equipment](#)

Galaxy, Connex, Magnum Radios Sirio, CB, Ham & Marine Antennas

Ads by Google

[Previous Page](#)[Back to Main Menu](#)[Next Page](#)

C.B. RADIO SECRET Master Tune Up Manual

If You Find This Information Helpful Then Please Consider A Small Donation To Help Keep This Site Alive!

[Make A Donation](#)

HAM INTERNATIONAL RADIOS

Model	Modulation	AM Power	SSB Power
120-FM	VR13(LO PWR MOD) VR12(MED PWR MOD) VR11(HI PWR MOD)	VR15(LO PWR) VR14(MED PWR) L15 L16(HI PWR)	
CONCORDE II	RV14	RV13	RV12 RV4
CONCORDE III	RV12	RV11	RV9 RV3
JUMBO III	RV12	RV11	RV9 RV3
MAJOR 120 (EXPORT)	RV2 or Remove C96	L7 L11 L12	
MAJOR M-360	RV12 or Remove Q37 & Q38	VR4	RV11 RV3
MULTIMODE III	RV12	RV11	RV9 RV3

HANDIC RADIOS

Model	Modulation	AM Power	SSB Power
199	VR2 or Cut D23 or D12	VR5	
230	R85 or Cut D22	L25	
2305	R51 or Remove C54	L8 L7	
235	R54 or Cut D9 & D10	L6 L5	
240 (AM-FM-CB)	VR102	L113 L116	
305	R54 or Cut D9 & D10	L6 L5	
3605	R51 or Remove C54	VR6 or Cut D14 & D15	
605	R54 or Cut D9 & D10	L6 L5	
605 DL	VR4 or Cut D6	L9 L8	

HITACHI RADIOS

Model	Modulation	AM Power	SSB Power
CM-2375H	Cut D12	T15 T14	
CM-2400C	Cut D17	T17 T18	
CM-2400H	Cut D17	T17 T18	
CM-2425H	Cut D19	T13	
CM-4800 C-H	Cut D17	T17 T18	

HUNTER RADIO

Model	Modulation	AM Power	SSB Power
Hunter 120	RV3 or Cut D9	L11 L12 L13	

HY-GAIN RADIOS

Model	Modulation	AM Power	SSB Power
2679A	RV102 or Cut D111	L110 L109	
2680	RV102 or Cut D111	L110 L109	
2681	RV102 or Cut D111	L110 L109	
2682	RV102 or Cut D111	L110 L109	
2683	RV102 or Cut D111	L110 L109	
2701	RV102 or Cut D111	L110 L109	
2702	RV2 or Remove C96	L7 L11 L12	
2703	RV2 or Remove C96	L7 L11 L12	
2705	Remove Q37 & Q38	VR4	RV2
2710X	RV201 or Cut D111	L106 L109 L110	
2720	RV201 or Cut D111	L106 L109 L110	
2795	RV14	RV13	RV12 RV4
2795-DX	RV14	RV13	RV12 RV4
3077	RV2 or Cut D10	L9 L8	

670B	RV2 or Cut D10	L7 L8 L9	
670B-PR	RV2 or Cut D10	L7 L8 L9	
672B	RV2 or Cut D10	L7 L8 L9	
8795 (V)	RV12	RV11	RV6 RV3
HYGAIN 16 (2716)	RV2 or Remove C209	L109 L110	
HYGAIN 9 (2679)	RV102 or Cut D111	L110 L109	
HYGAIN I	RV102 or Cut D111	L110 L109	
HYGAIN II	RV102 or Cut D111	L110 L109	
HYGAIN VII	RV2 or Remove C96	L7 L11 L12	
HYGAIN VIII (3078)	RV7 or Cut D301	RV608	RV8 RV5
HY-RANGE I	Cut D6	D10 D11	
HY-RANGE IA	RV102 or Cut D111	L110 L109	
HY-RANGE II	Cut D6	D10 D11	
HY-RANGE IIA	RV102 or Cut D111	L110 L109	
HY-RANGE III	RV103	L110 L111 VC2	

INTEK RADIO

Model	Modulation	AM Power	SSB Power
INTEK 2000FM	RV14	RV13	RV12 RV4

ITT RADIOS

Model	Modulation	AM Power	SSB Power
CB-4000FM	R40 or Cut D10	L3 T13	
4000	VR206 or Cut D209	L211 L210 L209	
4400M	VR206 or Cut D209	L211 L210 L209	

[Previous Page](#)
 [Back to Main Menu](#)
 [Next Page](#)

Want More? Check Out The CD! Over 400MB of VERY Useful Information



[HamTestOnline 2010 Promo](#)

Tech license for \$20 and 10 study hours.
Success guaranteed!



[Cb Radio Manufacturers](#)

Suppliers checked by D&B. Free info by HK
Trade Development Council.

Ads by Google

All Rights Reserved C.B. RADIO SECRET © 2003,2004,2005,2006

[Previous Page](#)

[Back to Main Menu](#)

[Next Page](#)

C.B. RADIO SECRET Master Tune Up Manual

If You Find This Information Helpful Then Please Consider A Small Donation To Help Keep This Site Alive!

[Make A Donation](#)

JC PENNY RADIOS

Model	Modulation	AM Power	SSB Power
981-6203	Cut D7		
981-6204 (981-7461)	RV2 or Remove C96	L7 L11 L12	
981-6212A	Cut D10		
981-6213	Cut D1	L5	
981-6216 (981-3130)	RV2 or Remove C98 or Cut D10	L10	
981-6218	RV2 or Remove C96	L7 L11 L12	
981-6221 (981-8345)	Cut D501 or D502	T704 T705	
981-6225	R2 or Remove C2	L406	
981-6235	Cut D15 & D14	L5 L8 L9	
981-6237 (981-8352)	Cut D7 or D12	T14 T15	
981-6240 (981-3445)	R212	L26	R316
981-6241 (981-8360)	Cut D406	RT602	RT701
981-6246	Cut D313		
981-6247 (981-3080)	RV12 or Remove Q37 & Q38	VR4	RV2
981-6248	Cut D302	RT301	RT402
981-6255 (981-7701)	Cut D401 or D402	T704 T705	

JIL RADIOS

Model	Modulation	AM Power	SSB Power

606CB	Cut D208	L208 L209	
615CB	VR101	L203 L202 L201	
825CB	Cut D208	L208 L209	
860CB	VR101	L203 L202 L201	
SSB-M6	RV12 or Remove Q37 & Q38	VR4	RV1 RV2

JOHNSON RADIOS

Model	Modulation	AM Power	SSB Power
110	Cut X6	A13 A14	
120A	Cut CR5	L3 L4	
121A	Cut CR5	L3 L4	
123	Cut D7		
123A	Cut CR11	L6 L7	
123B	Cut CR11	L6 L7	
123SJ	Cut CR11	L6 L7	
125	Cut D5		
130	Cut CR11	L6 L7	
132	Cut CR11	L6 L7	
250	Cut CR11	L6 L7	
320	Cut X11		
323	Cut X11		
323M	Cut D17		
MESSENGER 323A	Remove C93 or Cut CR19	L10 L9	
MESSENGER 351	VR7 or Cut D34	L7 L8	
MESSENGER 40	VR49 or Cut CR62	L84 L85 L86	
MESSENGER 4120	Cut CR12	L3 L4 L6	
MESSENGER 4125	Cut CR12	L3 L4 L6	
MESSENGER 4135	Cut CR12	L3 L4 L6	
MESSENGER 4140	Cut CR12	L3 L4 L6	
MESSENGER 4145	Cut CR12	L3 L4 L6	
MESSENGER 4170	Cut CR12	L3 L4 L6	
MESSENGER 4175	Cut CR12	L3 L4 L6	

MESSENGER 4190	Cut CR12	L3 L4 L6	
MESSENGER 4230	Cut CR12	L3 L4 L6	
MESSENGER 4250	Cut CR12	L3 L4 L6	
MESSENGER 4730	R207 or Cut CR202	T704 T705 T706	R725
MESSENGER 50	VR49 or Cut CR62	L84 L85 L86	
MESSENGER 80	VR49 or Cut CR62	L84 L85 L86	
VIKING 200	Cut CR12	L3 L4 L6	
VIKING 230	R49 or Cut CR64	T83 L84	
VIKING 260	R49 or Cut CR64	T83 L84	
VIKING 270	R49 or Cut CR64	T83 L84	
VIKING 352	R216 or Cut CR203	T702 T703	R727
VIKING 430	R49 or Cut CR64	T83 L84	
VIKING 4330	R227 or Cut CR12	T8	
VIKING 4360	R227 or Cut CR12	T8	
VIKING 4740	R216 or Cut CR203	T704 T705 T706	R726

K-40 RADIOS

Model	Modulation	AM Power	SSB Power
K40 SSB	Cut D301	L15	VR101
K40-1	T401 or Remove C417	TT004 TT005	
K401 (AM)	RT401 or Cut D9	L104 L107 L108	
K40-2	RV201 or Remove C213	L304 L305 L306	
K40-3	VR3 or Remove C94	T9 T10	
K40-6	VR3 or Remove C94	T9 T10	
K40-7	Cut D14	L6 L5 L4	
Trucker Model	VR5 or Cut D9	L10 L9 L8	

KINGHOOD RADIO

Model	Modulation	AM Power	SSB Power
K-195	VR7 or Cut D14		

K-MART RADIOS

Model	Modulation	AM Power	SSB Power
D-40	VR202 or Cut D202	T302 L303	
K-605	VR202		

KRACO RADIOS

Model	Modulation	AM Power	SSB Power
CCB-4007	RV3 or Cut D7	L6 L7	
KB-2355	RV7 or Cut D301	RV607	RV8 RV5
KB-4045	RV2 or Remove C96	L7 L11 L12	
KCB-1300	VR5 or Cut D7	L8 L9	
KCB-1307	VR4 or Cut D9	L16	
KCB-1401	VR7 or Cut D14	L11 L10 L9	
KCB-2310A	VR7 or Cut D14	L11 L10 L9	
KCB-2320	RV2	L7 L8 L9	
KCB-2320A	RV102 or Cut D111	L110 L109	
KCB-2320B	RV102 or Cut D111	L110 L109	
Kcb-2330B	RV102 or Cut D111	L110 L109	
KCB-2340	RV7 or Cut D206	RV605	RV8 RV5
KCB-2370	VR401 or Cut D402	L309	
KCB-2390	Cut D208	L208 L209	
KCB-4000	VR4	L6 L9	
KCB-4001	VR202 or Cut D202	L303	
KCB-4003	VR202 or Cut D205	L204 L205 L206	
KCB-4004	R207 or Cut D201	L205 L202	
KCB-4005	VR201 or Cut D201	L402 L403 L404 VR402	
KCB-4006	RV1 or Remove C47	T3 T4 T6	
KCB-4007	RV3 or Cut D7	L5 L4 L3	
KCB-4009	RV1 or Remove C47	T3 T4 T6	
KCB-4010	RV2 or Remove C96	L7 L11 L12	
KCB-4020	RV2 or Remove C96	L7 L11 L12	
KCB-4030	RV2 or Remove C96	L7 L11 L12	

KCB-4060	VR3	L9 L8	
KCB-4070	VR402 or Cut D402	L317	
KCB-4088	VR104 or Cut D115	L402	
KCB-4090	VR401 or Cut D403 or D405	L613	
KCB-4095	VR401 or Cut D403 or D405	L613	
KCB-5001	RV2 or Remove C96	L7 L11 L12	
KCB-5003	RV2 or Remove C96	L7 L11 L12	

KRIS RADIOS

Model	Modulation	AM Power	SSB Power
KRIS 99'ER	R74 or Cut D4	L14 L15 T7	
VEGA	R74 or Cut D4	L14 L15 T7	
VICTOR	R51 or Cut CR11	L12 L13	
VICTOR II	R51 or Cut CR11	L12 L13	
XL-23A	VR6 or Cut D10 or D11	L12 L13	
XL-25	VR6 or Cut D10 or D11	L12 L13	
XL-45	VR201 or Cut D205 & D206	L309 L308	
XL-50	VR301 or Cut D305 & D304	L13	
XL-70	VR206 or Cut D214 & D213	VC201	VR104

[Previous Page](#)
 [Back to Main Menu](#)
 [Next Page](#)

Want More? Check Out The CD! Over 400MB of VERY Useful Information



<p><u>Why Settle for CB?</u> Talk around the world with ham radio. No Morse Code required!</p>	<p><u>CB Radios & Equipment</u> Galaxy, Connex, Magnum Radios Sirio, CB, Ham & Marine Antennas</p>
---	---

Ads by Google

[Previous Page](#)[Back to Main Menu](#)[Next Page](#)

C.B. RADIO SECRET Master Tune Up Manual

If You Find This Information Helpful Then Please Consider A Small Donation To Help Keep This Site Alive!

[Make A Donation](#)

LAFAYETTE RADIOS

Model	Modulation	AM Power	SSB Power
1800	RV12	RV11	RV6 RV3
2400-FM	RV12	RV11	RV6 RV3
CBH-740	RV2 or Remove C96	L7 L11 L12	
COM-PHONE-23	RV4 or Cut D11	L7 L8	
COM-PHONE-23A	RV102 or Cut D111	L110 L109	
COM-PHONE-Mark II	RV4 or Cut D16	L7 L8	
COMSAT-35	RV4	L6 CV3	
COMSAT-525	RV2 or Remove C96 or Cut D11	L7 L11 L12	
DYNA-COM 40	RV2 or Remove C96 or Cut D11	L7 L11 L12	
DYNA-COM 5A	R4 or Cut X4	A9 A10	
HB-4000	VR2 or Cut D8	L4 L3 L1	
HB-525F	RV4	L13 VC VR6	
HB-550	Remove C217 or Cut D201	L308 L307	
HB-625A	VR4	VC1 L12 L13	
HB-640	RV2 or Remove C96 or Cut D11	L7 L11 L12	
HB-650	RV102 or Cut D111	L110 L109	
HB-700	RV203 or Cut D211	L215 VC1	
HB-740	RV2 or Remove C96 or Cut D11	L7 L11 L12	
HB-750	RV102 or Cut D111	L110 L109	

HB-870 AFS	RV14	RV13	RV12 RV4
HB-940	RV2 or Remove C96 or Cut D11	L7 L11 L12	
HB-950	RV102 or Cut D111	L110 L109	
LM-100	RV2 or Cut d3	L7 L11 L12	
LM-200	VR305 or Cut D312	L402 L405	
LM-300	RV2 or Cut D3	L7 L11 L12	
LM-400	VR201 or Cut D205	L201 L204	
MB-740	Remove Q15		
MICRO-223A	RV102 or Cut D111	L110 L109	
MICRO-66	RV102 or Cut Q118	L103 L102 C001	
MICRO-723	Cut D107	L115	
TELSAT SSB-100	RV7 or Cut D301	RV607	RV8 RV5
TELSAT SSB-140	RV12	VR4	RV11 RV2
TELSAT SSB-25A	RV8 or Cut D22	L18 L19 TC18	RV9 RV7
TELSAT SSB-50A	RV8 or Cut D22	L18 L19 TC18	RV9 RV7
TELSAT SSB-75	RV7 or Cut D206	RV304	RV8 RV5
TELSAT-1000	Cut D201	L308 L307	
TELSAT-1023	RV103	L114 L115	
TELSAT-1050	RV102 or Cut D111	L110 L109	
TELSAT-1140	RV2 or Remove C96 or Cut D11	L7 L11 L12	
TELSAT-1240	VR305 or Cut D312 & D311	L402 L405 L406	
TELSAT-925	VR6 or Cut D13	L8 VC	

LAKE RADIOS

Model	Modulation	AM Power	SSB Power
410	RV202 or Remove C209	L304 L305 L306	
450	VR301 or Remove C313	LC202 LC203 LC204	
5000 (SN-16)	VR402 or Cut D402	L317 L319	
5100 (SN-14)	VR401 or Cut D401	L317 L310	
600	VR2 or Remove C96	LC203 LC204	
650	R218 or Cut CR205 &	T301 T302 T303	

	CR204		
750	R226 or Cut CR39 & CR40	L308 L309	

LINCOLN RADIO

Model	Modulation	AM Power	SSB Power
1500	RV2 or Remove C96	L7 L11 L12	

MEDALLION RADIOS

Model	Modulation	AM Power	SSB Power
63-030	RV2 or Remove C96	L7 L11 L12	
63-200	VR2 or Cut D8	L4 L3 L1	
63-240	VR2 or Cut D8	L4 L3 L1	
63-540	VR501 or Cut D502	L1 L2 L3	

MARKO RADIO

Model	Modulation	AM Power	SSB Power
CB-444	RV2 or Remove C96	L7 L11 L12	

MAXON RADIOS

Model	Modulation	AM Power	SSB Power
LP-27	RV202	L307	
MCB-25	RV2 or Cur one end of D403	L802 RFC705 RFC709	
MCB-30	RV2 or Cur one end of D403	L802 RFC705 RFC709	
MCB-60	RV201 or Remove C215	L304 L305 L306	

METROSOUND RADIO

Model	Modulation	AM Power	SSB Power
CB-1	Cut D7	LX19 LX20 LX16	

MIDLAND RADIOS

Model	Modulation	AM Power	SSB Power
1001	RV201 or Cut D203	L304 L305 L306	
100M	RV201 or Cut D203	L304 L305 L306	
101M	RV201 or Cut D203	L304 L305 L306	
102M	RV201 or Cut D203	L304 L305 L306	
103M	RV201 or Cut D203	L304 L305 L306	
104M	VR4	L14 L13 L12	
105M (77-150)	RV201 or Cut D203	L304 L305 L306	
13-700	VR4	L7 L8 L11	
13-729	Cut D105	L101	
13-779	Cut D8	L5	
13-796	VR4	L5	
13-830	RV102 or Cut D111	L110 L109	
13-845	VR502 or CutD502	L6 L5	
13-852	VR5 or Cut D703 or D702	L914 VC1	
13-853	VR5 or Cut D703 or D702	L914 VC1	
13-854	Cut D6	C4 L2	
13-857	RV2 or Cut D10	L8 L9	
13-857B	RV102 or Cut D111	L110 L109	
13-858	RV102 or Cut D111	L110 L109	
13-862	R58 or Cut D8	T14 L3	
13-862B	R58 or Cut D8	T14 L3	
13-863	RV103 or Cut D111	L113 L114 L115	
13-863B	RV2 or Cut D10	L8 L9	
13-866	Cut D1	L5	
13-867	Cut D14	L12 L13	

13-870D	VR3 or Cut D10	L3 L4	
13-871	VR9 or Cut D14	L12 L13 L15	
13-879	Remove C88	L15	
13-879B	R58	L3 C5	
13-881	VR7 or Cut D26	L2 L21	
13-882	Cut D6	L10 L11 L9	
13-882B	RV2 or Cut D10	L8 L9	
13-882C	Remove Q121	L109 L110	
13-883	Cut D24	L11 L7 L8	
13-883B	VR213 or Cut D216	L212 L215	
13-884	VR7 or Cut D506 or D505	L909 L908	
13-886	RV2 or Cut D10	L8 L9	
13-887	RV103 or Cut D111	L113 L114 L115	
13-888B	RV102 or Cut D111	L110 L109	
13-892	RV7 or Cut D206	RV305	
13-893	VR12 or Cut D41 & D40	L8	VR15
13-894	VR9 or Cut D48	L13 L11	VR11
13-895	VR12 or Cut D41 & D40	L8	VR15
13-896	VR9 or Cut D48	L13 L11	VR11
13-898	RV301 or Cut D302	L1 TC1	RV302 RV106
13-898B	RV302 or Cut D301	L113 L114 L112	L107 RV301
13-955	RV102 or Cut D111	L110 L109	
13-976	RV7 or Cut D206	RV605	RV8 RV5
2001	RV201 or Cut D203	L304 L305 L306	
200M (77-200)	VR4 or Cut D11	L11 L14	
3001	RV201 or Cut D203	L304 L305 L306	
4001	RV201 or Cut D203	L304 L305 L306	
5001 (77-005)	RV2 or Cut D10	T4 L5 L10	
52-100 (CARAVAN)	RV2	L7 L12	
6001 (79-006)	RV9	VR1	RV8 RV10
6001 (79-012 ONLY)	VR5	VR10	VR6
6001(7)	VR5	VR10	VR6
63-445	VR5 or Cut D119	L112 L109	
7001	RV9	VR1	RV8 RV10

7001(7)	VR5	VR10	VR6
7001(8)	RV12	RV11	RV6 RV3
76-300 (BASE AM)	RV201or Cut D203	L304 L305 L306	
76-858	RV2 or Remove C96	L7 L11 L12	
76-860	VR6 or Cut D7	L3 L4 L5 L7	
76-863	RV2 or Remove C96	L7 L11 L12	
76-886	RV2 or Remove C96	L7 L11 L12	
77-094	RV2 or Cut J27	L7 L6	
77-099	RV4 or Cut D8	L10 L11 L13	
77-101B	RV201or Cut D203	L304 L305 L306	
77-101C	RV201or Cut D203	L304 L305 L306	
77-104	RV4	L14 L13 L12	
77-106	RV4 (Located Next To C45)	L11 L12 L13	
77-112	RV4 or Remove C45	L11 L12	
77-116	RV2 or Cut D7	L8 L9 L10	
77-118	RV501 or Cut D502	L304 L305 L306 L307	
77-145A	RV104 or Cut D111	L204 L206 L207 L208	
77-149	Cut D206	L12 L11 L10	
77-151 (77-151M)	RV201or Cut D203	L305 L306	
77-155	VR4 or CutR42 or D16	LX12 LX13 LX14	
77-202A (202M)	VR201 or Cut D203	L305 L306	
77-225A	RV4	L13 L14 L15	
77-250	RV201or Cut D203	L304 L305 L306 L307	
77-808	RV2 or Cut D10	L5 L9 L10	
77-821	RV2 or Cut D10	L5 L9 L10	
77-824	RV201or Cut D203	L304 L305 L306	
77-824B	VR5 or Cur D20 & D19	L15 L16 L12	
77-824C	RV201or Cut D203	L304 L305 L306	
77-825	Remove C38 or Cut D3	T4 T5 L3	
77-830	RV2 or Remove C96	L7 L11 L12	
77-838	RV2 or Remove C96	L7 L11 L12	
77-849	RV2 or Remove C96	L7 L11 L12	
77-853	VR7	L205 L903 L901	
77-856	VR5 or Cut D9	L16 L15 L12	

77-857	RV2 or Remove C96	L7 L11 L12	
77-859	RV2 or Remove C98 or Cut D10	L5 L9 L10	
77-860	VR6 or Cut D7	L3 L4 L5 L7	
77-861	Cut D2	L4 L5 L13	
77-861B	Remove C53	T2 T3 T4	

MIDLAND RADIOS (cont)

Model	Modulation	AM Power	SSB Power
77-865	VR5 or Cut D21	L16 L15 L12	
77-882	VR2 or Cut C96	L7 L11 L12	
77-883	VR401	L215	
77-888	RV2 or Remove C96	L7 L11 L12	
77-889	RV2 or Remove C96	L7 L11 L12	
77-899	RV2 or Remove C96	L7 L11 L12	
77-955	RV2 or Remove C96	L7 L11 L12	
77-963	RV2 or Remove C96	L7 L11 L12	
78-574	RV9 or Remove C71 or Cut D22	VR1	RV3 RV201
78-976	RV12 or Remove Q37 & Q38	VR4	RV11 RV2
78-999	RV9 or Remove C71	VR2	RV3 RV201
79-012 (6001)	VR5	VR10	VR6
79-265	RV3	RV7	RV8
79-891	RV9 or Remove C71	VR2	RV3 RV201
79-892	RV12 or Remove Q37 & Q38	VR4	RV11 RV2
79-893	RT601	VR6	VR7
79-900(4)	VR6 or Cut R104	VR7	CT4
79-900(5)	Cut R104	VR6	VR7

MONGOOSE RADIO

Model	Modulation	AM Power	SSB Power
-------	------------	----------	-----------

2000

RV12

RV11

RV3 RV7

MONTGOMERY WARDS RADIOS

Model	Modulation	AM Power	SSB Power
GEN-680A	VR3 or Cut D8	L6 L7 L9	
GEN-696A	VR3 or Cut D8	L6 L7 L9	
GEN-702A	VR6 or Cut D209	L208 L209 L210 L211	
GEN-716A	VR3 or Cut D8	L6 L7 L9	
GEN-719A	Cut R104	VR6	VR7
GEN-730A	VR6 or Cut D209	L208 L209 L210 L211	
GEN-774A	VR7 or Cut D19	L6 L7 L10	
GEN-775A	VR6 or Cut D209	L208 L209 L210 L211	
GEN-828A	VR6 or Cut D209	L208 L209 L210 L211	

MOPAR RADIOS

Model	Modulation	AM Power	SSB Power
4094173	VR402	L319 L317	
4094176	RV2 or Remove C96	L7 L11 L12	
4094177	RV2 or Remove C96	L7 L11 L12	
4094178	RV2 or Remove C96	L7 L11 L12	
4094179	RV2 or Remove C96	L7 L11 L12	

MORSE ELECTROPHONIC RADIOS

Model	Modulation	AM Power	SSB Power
2001	VR202 or Cut D205	L205 L204	
3005	RV2 or Remove C96	L7 L11 L12	
CB-2000	R83 or Cut D10 & D9	L1 L2	
CB-700	RV5 or Cut D10	CV1 L5	
CB-800	VR481 or Cut D481 & D482	L451 L463	

MOTOROLA RADIOS

Model	Modulation	AM Power	SSB Power
CB550	VR701	L310 L313 L316	
CB555	VR701	L310 L313 L316	
CF925AX	Cut r27 & R33 or D8	L4 L3 L1	
CM-540	VR701	L310 L313 L316	VR303
CM-550	VR701	L310 L313 L316	VR303
CM-555	VR701	L310 L313 L316	VR303
CT950AX	VR501	L3 L1	
T-4002A	Cut CR206 & CR305		
T-4005A	Cut CR206 & CR305		
T-4009A	Cut CR206 & CR305		
T-4010A	Cut CR206 & CR305		
T-4020A	Cut CR206 & CR305		
T-4025A	Cut CR206 & CR305		

[Previous Page](#)

[Back to Main Menu](#)

[Next Page](#)

[Want More? Check Out The CD! Over 400MB of VERY Useful Information](#)



[Ham Radio 2010 Special](#)

Entry-level ham license for \$20 and 10 study hours. Success guaranteed!

[2-Way Radios](#)

ICOM 2-Way Radios Check prices radios & accessories

Ads by Google

[Previous Page](#)[Back to Main Menu](#)[Next Page](#)

C.B. RADIO SECRET Master Tune Up Manual

If You Find This Information Helpful Then Please Consider A Small Donation To Help Keep This Site Alive!

[Make A Donation](#)

N.D.I. RADIOS

Model	Modulation	AM Power	SSB Power
PC101	R203 or Cut CR304	T502 T503	
PC102	R203 or Cut CR304	T502 T503	
PC200	R217 or Cut CR206	R207	R721
PC201	R217 or Cut CR206	R207	R721

NATO RADIO

Model	Modulation	AM Power	SSB Power
2000	RV12	RV11	RV3 RV7

NUVOX RADIOS

Model	Modulation	AM Power	SSB Power
CB-7000	VR7 or Cut D14	L11 L9	
TC-5020	R69 or Cut D16	L5 T14	

OLSON RADIO

Model	Modulation	AM Power	SSB Power
CB-409	VR5 or Cut D11	L16 L15	

OMNIVOX RADIO

Model	Modulation	AM Power	SSB Power
GB-1000	Remove C207	L7 L10	

ORBITSONIC RADIO

Model	Modulation	AM Power	SSB Power
ORBITSONIC 200	VR202	T205 T206	

PACE RADIOS

Model	Modulation	AM Power	SSB Power
1000 MC	R521 or Cut CR508	L109 L107	R134
2300C	R243 or Cut CR9 & CR205	L10 L11 L12	
2376B	Cut CR9	L12	
8003	VR201 or Remove C219 or Cut D201	L303 CT301 L304	
8008	R218 or Cut CR18 or CR19	L7	
8010A	R220 or Cut CR201	L308 L307	
8014	R501 or Cut CR501	L602 L604 L605	
8015A	R220 or Cut CR201	L308 L307	
8016	R168 or Remove C178 or Cut CR115	L109 L106	
8025	R207 or Remove C215 or Cut CR21	L10 L4	
8041	R302 or Remove C68 or Cut CR15	L13 L14	
8046	R302 or Remove C68 or Cut CR15	L13 L14	
8047	R302 or Remove C68 or Cut CR15	L13 L14	
8092	R307 or Cut CR46	L10 L13	C306

8093	VR7 or Cut R52	L12	VR11
8113	R220 or Cut CR201	L308 L307	
8117	R220 or Cut CR201	L308 L307	
8155	R310 or Remove C313 or Cut CR302	L404 L408 C432	
8193	VR7 or Cut R52	L12	VR11
8340	R104	L404 L402	
C123A	Cut D11	L9	
CB-113	VR503 or Cut CR102 & CR103	L10 L11 L9	
CB-144	R92 or Cut CR15 & CR16	L9 L10	
CB-145	R506 or Cut CR301	L103 L102	
CB-161	R218 or Cut CR18 & CR19	L8 L7	
CB-162	R64 or Cut CR7	L5 L6	
CB-166	R207 or Cut CR20 or CR21	L14 L15	
CB-166C	R207 or Remove C215 or Cut CR21	L10 L4	
CB-185	R302 or Remove C68 or Cut CR15	L13 L14	
CB-76	Cut CR9	L11 L12 L13	
CB-8001	RV3	L4 L5	
CB-8001(1)	RV3	LX20	
CB-8002	RV4 or Cut D16	LX12 LX 13 LX14	
CBST-23 (SIDETALK 23)	VR8 or Cut D44	L7	VR7
SIDETALK 1000B	R616 or Cut CR603	L106	
SIDETALK 1000M	R616 or Cut CR603	L106	
SIDETALK CB-1023	VR7	L3	VR3
SIDETALK1000BC	R521 or Cut CR508	L109 L107	R134

PACER RADIO

Model	Modulation	AM Power	SSB Power
XLR 29	Cut D207	L407 (Spreadable Coil)	

PACIFIC RADIO

Model	Modulation	AM Power	SSB Power
160	RV12	RV11	RV3

PAL RADIOS

Model	Modulation	AM Power	SSB Power
COYOTY 23	VR206 or Cut D204	VC201	VR104
ROADRUNNER 23	VR7 or Cut D14	L9 L10 L11	

PALOMAR RADIOS

Model	Modulation	AM Power	SSB Power
1200 (EXPORT)	Remove C99	L15 L16 (HI PWR)	
21	Remove C204 or Cut D30	L9	
2400	RV12	RV11	RV6 RV3
2900	RV12 or Remove Q37 & Q38	VR4	RV11 RV2
4100	RV2 or Remove C96	L7 L11 L12	
49	Cut D207 & D208	L403 L406	
5000	RV12	RV11	RV6 RV3
SSB-500	VR6 & VR7	VR8	CT7

PANASONIC RADIOS

Model	Modulation	AM Power	SSB Power
CQ-B5919EU	VR801	T901 L904	
CR-B1717EU	VR902 & VR903	L903 L905 VR901	
CR-B4737EU	VR902 & VR903	L903 L905 VR901	
CR-B4747EU	VR902 & VR903	L903 L905 VR901	
RJ-3050	R117	L25 L16	

RJ-3100	Cut D21	L17 L18	
RJ-3150	R117	L25 L16	
RJ-3200	R74 & Cut D14	L16 L17 L18	
RJ-3250	R70	L6 FL1 L18	
RJ-3450	R50	L7 FL1 FL2	
RJ-3600	R94	L10 FL1 L11	
RJ-3660	R94	L10 FL1 L11	
RJ-3700	R129	R189	R192

PARADYNAMICS RADIOS

Model	Modulation	AM Power	SSB Power
PDC-19	VR6 or Cut D10	L6 L7	
PDC-25	VR6 or Cut D10	L6 L7	
PDC-29	VR103 or Cut D203	L404 L408	

PEARSE SIMPSON RADIOS

Model	Modulation	AM Power	SSB Power
ALLYCAT 23	Cut D11	L5 L8	
BEARCAT 23C	Cut D16	L15 L16 L19	
BENGAL SSB	Cut R109	L9 VR17	VR16
BOBCAT 23B	Cut D7	L8 L10	
BOBCAT 23C	Cut D9	L8 L10	
BOBCAT 23D	VR4 or Cut D18 or D19	L10	
BOBCAT 23E	Cut D9	L8 L10	
CHEETAH SSB	Cut D53 & D54	L13 L10 VR15	L12 VR17
COURGAR 23 (late)	VR6 or Cut D15	L22	
COURGAR 23B	Cut D16	L15 L16 L19	
JAGUAR 40B	FVR3 or Cut D10 or D11	L26 L25	
LEOPARD B	VR903 or VR902	VR901	
LION 40	RV2 or Cut C96	L7 L11 L12	
LYNX 23	VR9 or Cut D14	L6 L5	

MARK II	RV102 or Cut D111	L106 L110 L109	
PANTHER SSB	Cut D53 & D54	VR4	VR9
PUMA 23B	Remover C50 or Cut R58	L4 L5 L8	
PUMA 23C	Cut D9	L8 L10	
PUSSYCAT 23	R152 or Cut CR107	C162 L111	
SIMBA SSB (late)	VR14 or Cut D47 & D48	L12 L14 VR17	VR12
SUPER LYNX	Remove C103 or Cut D12	L8 L5	
SUPER TIGER 40A	VR13 or Cut D8	L12 L9 L6	
TIGER 23B	Cut D10	L4 L7	
TIGER 23C	Cut D12	L4 L5 L8	
TIGER 23D	Cut D10	L4 L7	
TIGER 40	RV2 or Cut C96	L7 L11 L12	
TIGER 40A	RV102 or Cut D111	L106 L110 L109	
TOMCAT 23B	VR4 or Cut D18	L10 L8	
TOMCAT23C	Change CR56 to 800 OHMS	L9	

PIONEER RADIOS

Model	Modulation	AM Power	SSB Power
GT-1100G	VR2 or Cut D8	L4 L3 L1	
GT-600	Cut D8		
GT-6600	VR2 or Cut D8	L4 L3 L1	

PRESIDENT RADIOS (Also see Uniden radios)

Model	Modulation	AM Power	SSB Power
ADAMS	VR7 & VR6	VR8	CT7
ANDREW JACKSON	VR5 or Cut D9	L13 L10 L9 L8	
AR-14	Cut D9	L15 L12 L11	
AR-144	VR5 or Remove TR29	VR10	VR6
AR-44	VR5 or Cut D9	L13 L10 L9 L8	
AR-7	Cut D8 or Change R87 to 1.2k	L10 L12 L16	

AR-711	VR5 or Cut D9	L13 L10 L9 L8	
AX-11	VR3 or Cut R54	L12 L14	
AX-14	Cut D9	L15 L12 L11	
AX-144	VR5 or Remove TR29	VR10	VR6
AX-24	VR3 or Cut R54	L12 L14	
AX-4	Cut D19 & D13		
AX-43	Cut D12	L8 L9 L12	
AX-44	VR5 or Cut D9	L13 L10 L9 L8	
AX-52	Remove TR13	L9 L12	
AX-55	Remove TR13	L9 L12	
AX-7	Cut D13	L8 L9 L12	
AX-711	VR5 or Cut D9	L13 L10 L9 L8	
CONVOY II	Cut D18	L11 L9 L8	
DWIGHT D (858)	VR5 or Cut D14	L15 L12 L11	
GRANT (858)	VR7 & VR6	VR8	CT7
GRANT-DX	VR14	VR13	VR12
HONEST ABE (858)	VR5 or Cut D14	L15 L12 L11	
JACKSON	VR12 or Remove TR26	VR11	VR8
JACKSON (new)	VR12	VR11	VR8
JAMES K	Cut D4	L15 L17	
JFK	Cut Brown Wire Next To D8	L20 L15 L14 (HI PWR)	
JOHN Q	RT4 or Cut D13	L15 L12 L11	
LINCOLN	VR114	VR103	VR102
MADISON (858)	VR7 & VR6	VR8	CT7
McKINLEY (101001)	Cut R104	VR6	VR7
McKINLEY (EXPORT)	VR5	VR11	VR11
OLD HICKORY	VR5 or Cut R75	L11 L12	
P-200	Cut D14	L6 L5 L4	
P-210	Cut D14	L6 L5 L4	
P-220	VR5 or Cut D9	L10 L9 L8	
P-300	VR5	VR10	VR6
P-400	Cut R104	VR6	VR7
TEDDY R (858)	VR5 or Cut D14	L15 L12 L11	
THOMAS J (1013001)	VR4 or Cut D11	L14 L13 L12	

VEEP	VR6 or Cut D9	L12 L15 L16	
WASHINGTON (858)	VR7 & VR6	VR8	CT7
ZACHARY T (858)	VR5 or Cut D14	L15 L12 L11	

PYRAMID RADIOS

Model	Modulation	AM Power	SSB Power
1300	RV3 or Remove C94	T9 T10	
CB-22	VR3 or Cut D9	L11 L12 L13	
CB-22 (late)	RV4 or Cut D7	L5 L4 L1	
CB-24	VR3 or Cut D9	L11 L12 L13	
CB-25	RV3 or Cut D12	L5 L4 L1	
CB-26	RV7 or Cut D22	L14 L16 L17	
CB-28	RV301 or Cut D302	L5 L4	
CB-29	D11		
GTL-148	RV7 or Remove C120	L16 L17	

[Previous Page](#)
 [Back to Main Menu](#)
 [Next Page](#)

Want More? Check Out The CD! Over 400MB of VERY Useful Information



Ham Radio 2010 Special
 Entry-level ham license for \$20 and 10 study hours. Success guaranteed!
www.hamtestonline.com

Ads by Google

[Previous Page](#)[Back to Main Menu](#)[Next Page](#)

C.B. RADIO SECRET Master Tune Up Manual

If You Find This Information Helpful Then Please Consider A Small Donation To Help Keep This Site Alive!

[Make A Donation](#)

QUESTAR RADIO

Model	Modulation	AM Power	SSB Power
Mark I	Cut D201	L307 L308	

RANGER RADIOS

Model	Modulation	AM Power	SSB Power
HCA-818	Cut R60	T9 L4	
RCI-2900	VR14	VR13	VR12
RCI-2950	VR14	VR13	VR12
RCI-2950DX	VR17	VR15	VR12
Rci-2970	VR14	VR15 (LO PWR) VR13 (HI PWR)	VR12
RCI-2970DX	VR17	VR15	VR12
RCI-2980	VR14	VR15 (LO PWR) VR13 (HI PWR)	VR12
RCI-2980DX	VR17	VR15	VR12
RCI-2990	VR14	VR15 (LO PWR) VR13 (HI PWR)	VR12
RCI-6300	VR16	VR14	
RCI-6900	VR17	VR15	VR14
ST-1000	Cut R60	T9 L4	

RAY JEFFERSON RADIOS

Model	Modulation	AM Power	SSB Power
CB-707	R68 or Cut D16	L5 T14	
CB-740	VR1	L4	
CB-845	VR2 or Cut C96	L7 L11 L12	
CB-905	R53 or Cut D7	L6 L2	

RCA RADIOS

Model	Modulation	AM Power	SSB Power
14T100	VR481 or Cut D481 & D482	L451 L463	
14T200	VR481 or Cut D481 & D482	L451 L463	
14T260	RV2 or Remove C96	L7 L11 L12	
14T270	RV2 or Remove C96	L7 L11 L12	
14T275	RV2 or Remove C96	L7 L11 L12	
14T300	RV201 or Cut D111	L110 L109	
14T301	RV201 or Cut D111	L110 L109	
14T302	RV12 or Remove Q37 & Q38	VR4	RV2
14T303	RV2 or Remove C96	L7 L11 L12	
14T304	RV2 or Remove C96	L7 L11 L12	
14T305	RV2 or Remove C96	L7 L11 L12	
14T400	VR903 VR902	L905 L903	
14T405	VR903 VR902	L905 L903	
14T410	VR903 VR902	L903 VR901	

REALISTIC RADIOS

Model	Modulation	AM Power	SSB Power
TRC-10A	Cut D8 or D10	T10 T11	
TRC-180	R48	L13 L12 L7	
TRC-190	VR4 (LO) VR5 (HI) or Cut D11	L6	

TRC-200	Cut R43 or Remove C52 or Cut D11	T7 L4 L5	
TRC-204	Cut R43 or Remove C52 or Cut D11	T7 L4 L5	
TRC-205	Remove TR306	L302 L303 L100	
TRC-206	Cut R53 or D9	L8 L10	
TRC-208	VR3 or Cut R49		
TRC-209	VR5 or Cut D7	L4 L7 L8	
TRC-210	Cut R77	L12 L8	
TRC-211	Cut R49	L6 L7 VR5	
TRC-212	Remove C76	L11 L12 VR4	
TRC-214	Cut R60		
TRC-215	VR2 (LO PWR MOD) VR3 (HI PWR MOD)	VR4 L6 L7	
TRC-216	VR2 (LO PWR MOD) VR3 (HI PWR MOD)	VR4 L6 L7	
TRC-217	Cut R68	L12 L13	
TRC-218	Cut R70	L4 L3 L6	
TRC-23B	Cut D6	T15 T14	
TRC-23C	Cut D11	T15 T16	
TRC-24B	VR8 or Cut D507	L910 L912 L913	
TRC-24C	VR8 or Cut D507	L910 L912 L913	
TRC-29	Cut D10	L11 L17	
TRC-30	VR8 or Cut D507	L910 L912 L913	
TRC-30A	VR8 or Cut D507	L910 L912 L913	
TRC-35C	R501 or Cut D503 or D504	L902 L901	
TRC-410	Remove Q12	L5 L4 L3	
TRC-411	Cut R61 & R64	T10 L5 L8	
TRC-412	Remove Q6		
TRC-413	Cut R85	L3 L6	
TRC-414	Cut D7 or Remove Q10	L3 L6 L7	
TRC-415	RV4 or Cut R63	L10 L11	
TRC-416	VR2	L21 L22	
TRC-417	Cut D10	L10 L3 L1	
TRC-418	Cut R73 or D10	L3 L10	

Trc-419	VR202	L306 L305 L304	
TRC-420	Cut D105 & D106	L104 L106	
TRC-420-18	Cut D105 & D106	L104 L106	
TRC-420A	Cut D6	L5 L4 L3	
TRC-421	Cut D16	L18 L9 L12	
TRC-421A	Cut D16 & D17	L3 L6	
TRC-422	Cut D16	T18 L9 L12	
TRC-422A	Cut D16 & D17	L3 L6	
TRC-423	Remove Q207	L305 L306 L304	
TRC-424	VR9 or Cut D509 & D508	L909 L910	
TRC-425	VR8 or Cut D508	L901 L902 L905	
TRC-426	VR8 or Cut D507	L901 L903 L905	
TRC-427	VR5 or Cut D19	L15 L12	
TRC-428	R104 or Cut R90	L5 L8	
TRC-429	VR2		
TRC-431	VR7 or Cut D506 & D507	L905 L907 L910	
TRC-432	Remove Q10 or Cut R56	L5 L4 L3	
TRC-433	Remove Q15	L4 L3	
TRC-434	Cut D11	L11 L12	
TRC-435	VR4	L12 L19 L18 L17	
TRC-440	Cut D107 or D108	L102 L104 L106	
TRC-441	Cut D109	L107 L104	
TRC-443	Cut X3		
TRC-446	Cut D110	L106 L104 L102	
TRC-448	VR5 or Cut D27 & D28	VR210	VR204
TRC-449	VR6 & VR7	VR8	CT7
TRC-450	Cut D42	VR6	VR7
TRC-451	VR5	VR10	VR6
TRC-452	VR207 or Cut D213 or D212	L212 L214 L211	
TRC-453	VR5	VR10	VR6
TRC-454	VR702B or Cut D704	L903 L907 L908	
TRC-455	R504 or Cut D503	C430 L404 L403	
TRC-456	VR8 or Cut D507	L903 L905	
TRC-457	VR6 & VR7	VR8	CT7

TRC-458	VR6 & VR7	VR8	CT7
TRC-459	VR13 or Cur D54 & D55	VR14	VR4 VR5
TRC-46	R212	T15 T16	R316 R213
TRC-461	VR2 or Cut D11	VR5	
TRC-462	VR2 or Remove C60	L15 VR3	
TRC-466	Cut D110	L104 L106	
TRC-467	Cut D110	L104 L106	
TRC-468	Cut D116	T14 T15	
TRC-469	VR5 or Cut D17 & D18	L13 L11	
TRC-47	R46 or Cut D10 & D9	R55	R102
TRC-470	VR10 or Cut D513	L901 L903 L905	
TRC-471	VR2 or Remove Q6	L4 L3 L1	
TRC-472	VR204	L212 L210	
TRC-473	VR3 or Remove C80	T11 T13 T14	
TRC-473 (late)	VR4 or Cut D16	L8 L11 L6	
TRC-474	VR4 or Cut D19	L6 L8	
TRC-474 (late)	VR4 or Cut D21	L12 L11	
TRC-477	Cut R216	L10 L11 L12 L13	
TRC-48	R220	L305	R316
TRC-480	VR13 or Cur D54 & D55	VR14	VR4 VR5
TRC-49	Cut D18	T24 T25	
Trc-490	Cut R104	VR6	VR7
TRC-50B	Cut D6 or D7	T15 T16	
TRC-52	VR8 or Cut D11	L4	
TRC-55	Cut D15 & D16	L10 L9	
TRC-56	VR7 or Cut D507 & D508	L909	
TRC-57	VR12 or Cut D33 & D31	VR21	VR25
TRC-61	R68 or Cut D12 & D11	R104	
TRC-67	Cut D7	L3 L1	
TRC-68	Cut D7	T15 T14	

REGENCY RADIOS

Model	Modulation	AM Power	SSB Power
-------	------------	----------	-----------

CB-1 (INFO-1)	RV4 or Cut D9	L11 L12 L13	
CB-2 (INFO 2)	RV201 or Cut D203	L304 L305 L306	
CB-501	Cut CR107	L102 L101	
CB-701	Cut CR107	L102 L101	
CR-123	Cut D54 & D53	VR14	VR9
CR-123B	VR17	L10 L12	VR16
CR-142	Cut D14	L4	
CR-185	Cut R73	L8	
CR-186	Cut D9	L4 L5 L8	
CR-202	Remove C73 or Cut D11	L8 L5	
CR-230	Cut D16	L19 L21	
CR-240	VR213 or Cut D218 & D219	L217	
SPRINT-23	VR4 or Cut D13	A15 A16	

ROADMASTER RADIOS

Model	Modulation	AM Power	SSB Power
RE-4000	RV4	L10 L11 L12	
RE-6000	RV4 or Cut D14	L7 L9 L10	

ROBERTS RADIO

Model	Modulation	AM Power	SSB Power
ROBERTS 40CH	VR202		

ROBYN RADIOS

Model	Modulation	AM Power	SSB Power
007-140	VR6 or Cut D15 & D14	L13 L12 L11 L10	
440	RV202 or Remove C210	L306 L307	
AM-500D	VR5 or Cut D14	L15 L12	
DG-130A	VR6 or Cut D15 & D14	L13 L12 L11 L10	

DG-30	VR4 & VR5 or Cut D17	L9 L10	
GT-410D	VR12 or Cut D16	L20 L21 L15	
GT-V11B	VR8 or Cut D14 & D15	L18	
K-123	VR4 or Cut D13	A16	
LB-120	VR6 or Cut D15 & D14	L13 L12 L11 L10	
LB-23A	VR4	L9 L14	
SB-505D	Cut R104	VR6	VR7
SB-510D	VR7	VR8	CT7
SB-520D	VR7	VR8	CT7
SB-540D	VR311	VR531	VR312
SX-101	VR5	L20 L23	
Sx-401	VR7 or Cut D18 & D19	L16 L17 L18	
SX-402	VR12 & VR13 or Cut D17 & D18	L15 L20 L21	
T-240D	VR4 + Replace 6BQ5 Audio Tube With A 7189 Tube	L702(TOP) VC901 VC902	
TR-123C	Cut D11		
TR-123D	Cut D12	L17 L18 L19	
WV-110	VR6 or Cut D15 & D14	L13 L12 L11 L10	
WV-23	VR6	L13 L17	
WV-23A	VR4	L9 L14	

ROYCE RADIOS

Model	Modulation	AM Power	SSB Power
603	VR201 or Cut D202	L204 CT 201	
604	VR201 or Cut D202	L303 VC1	
607	VR201 or Cut D202	L303 CT301	
608	VR201 or Cut D202	L303 VC1	
609	VR201 or Cut D202	L303 VC1	
611	VR201 or Cut D202	L303 VC1	
613	VR201 or Cut D202	L303 VC1	
619	VR201 or Cut D202	L303 VC1	
639	VR7	L2 L3	CT6

I-580	VR201 or Cut D201	T302 L303 CT301	
I-582	VR201 or Cut D201	T302 L303 CT301	
I-601 (PLL)	VR201 or Cut D202	L204 L203	
I-602	Cut D6		
I-602A	VR5 or Cut D5 & D6	L11 L15	
I-605A	VR5 or Cut D5 & D6	L11 L15	
I-606	VR7 or Cut D16 & D17	L21 L16 L15	
I-610	Cut D202	CT301	
I-611	Remove Q205	VC1	
I-612	VR5 or Cut D7	VR8	
I-613	Cut D202	CT301	
I-617	VR401 or Cut D401	L310	
I-620	VR10 or Cut D43 & D44	L13 L12	VR13
I-621	VR3	VR4	
I-624	VR201 or Cut D202	L204 L203	
I-625	VR1602	T402	
I-630	VR10 or Cut D43 & D44	L13 L12	VR13
I-631	VR10	L2 L4	VR12
I-632	VR7	L6 L4 L1	VR5
I-635	VR10 or Cut D43 & D44	L13 L12	VR13
I-639	VR7 or Remove Q16	L12 T8 T9	VR11
I-640	VR10 or Cut D43 & D44	L13 L12	VR13
I-641	VR7	L6 L1	VR8
I-642	VR7 or Remove Q16	L3 L2	VR11
I-648	VR3	VR4	
I-650	Cut D301	T402	
I-651	VR201 (HI PWR) VR203 (LO PWR)	C317 C319	
I-653	Cut D301	T402	
I-655	Cut D301	T402	
I-658	Cut D301	T402	
I-660	Cut D301	T402	
I-662	Cut D301	T402	
I-673	Cut D301	T402	
I-675	Cut D301	T402	

I-678	Cut D301	T402	
I-680	Cut D301	T402	
I-682	Cut D301	T402	

RYSTAL RADIOS

Model	Modulation	AM Power	SSB Power
CB-523	VR3 or Cut CR9	VC1 L3	
CBR-1700	RV5 or Cut D10	CV1 L5 T5	
CBR-1800	VR481 or Cut D481 & D482	L451 L463	

[Previous Page](#)
 [Back to Main Menu](#)
 [Next Page](#)

[Want More? Check Out The CD! Over 400MB of VERY Useful Information](#)



<p>HamTestOnline 2010 Promo Tech license for \$20 and 10 study hours. Success guaranteed!</p>	<p>HP Desktop Computers HP Official Store: Find Great Deals on the Latest Models. Shop Now!</p>
---	---

Ads by Google

[Previous Page](#)[Back to Main Menu](#)[Next Page](#)

C.B. RADIO SECRET Master Tune Up Manual

If You Find This Information Helpful Then Please Consider A Small Donation To Help Keep This Site Alive!

[Make A Donation](#)

SAGA RADIO

Model	Modulation	AM Power	SSB Power
2530	Cut D310	L15	VR101

SAM RADIO

Model	Modulation	AM Power	SSB Power
SAM 2000	RV201	L304 L305 L306	

SANKYO RADIO

Model	Modulation	AM Power	SSB Power
SCS-555	R62 or Cut R63 or D14	T12 T13 T1	

SANYO RADIOS

Model	Modulation	AM Power	SSB Power
TA-2000	VR7 or Cut D504 & D505	L903 L905	
TA-4000	VR7 or Cut D504 & D505	L903 L905	
TA-6000	VR7 or Cut D504 & D505	L903 L905	

SBE RADIOS

Model	Modulation	AM Power	SSB Power
12CB	VR7	L5 L6 L7 L8	VR1
14CB	VR502 or Cut D502	L6 L5	VR504
16CB (Console II)	VR7	L5 L6 L7 L8	VR1
21CB (Cortez)	VR4 or Remove C87 or Cut D14	L8 L10	
22CB (Catalina II)	R152 or Cut CR107	C162 L110 L111	
23CB (Capri)	VR1	L10	
26CB (Formula D)	VR9 or Cut D17	L8 L9	
26CB-A (Formula 40)	VR9 or Cut D17	L8 L9	
27CB-A	VR803 or Cut D801	L505 L502	VR302
29CB (Malibu)	VR4 or Cut D18	L8 L10	
30CB (Trinidad II)	VR4 or Cut D18	T10 L6	
32CB (Touchcom)	VR9 or Cut D17	L8 L9	
34CB (Brute)	Cut D11 or Cut R82	L14 L18 L19	
39CB (Sidebander V)	VR803 or Cut D801	L505 L502	VR302
40CB	VR803 or Cut D801	L505 L502	VR302
41CB (Aspen)	VR203 or Cut D208 & D209	L304 L306	
42CB (Cortez)	VR203 or Cut D208 & D209	L304 L306	
43CB (Touch-Com 40)	R4 or Cut D17	L9 L8	
44CB (Malibu 40)	R226 or Cut CR33 & CR32	L308 L309	
45CB (Trinidad III)	R226 or Cut CR33 & CR32	L308 L309	
47CB (Stowaway)	VR4 or Cut D17	L14 L15 VR5	
49CB (Tahoe)	R121 or Cut D19 & D20	L34 L37	
54CB (Key-Com 1000)	RV1	L503 L505 L506	
5CB (Cascade)	R52 or Cut V2	L2 L5 L7	
CONSOLE V	Remove C804		
CONSOLE VI	VR601 VR603	L404 L407	VR404
LCB-8	VR6 or Cut D16	VR6 or Cut D16	
Lcm-5	VR6 or Cut C49 or D9	L10 L11 L12 L15	
LCM-8	RV2 or Cut D13	L7 L11 L12	

LCM-8P	R201 or Cut D201	L302 C310	
LCMS	VR7		VR11
TRINIDAD 23CH	R152	L110 C154	

SEARS RADIOS

Model	Modulation	AM Power	SSB Power
242-38160700	VR201	L203	
370-38050700	R218 or Cut CR204	T302 T303 C436	
562-38200700	Cut D11	L5 L3 C301	
663-38000900	Cut D8	L13 L16	
663-38020800	VR6 or Cut D9	L11 L12 L15	
663-38030050	Cut D7	L14 L15 L16	
663-38070700	VR2 or Cut D14	L21 L11	
663-3810500	VR5	VR10	VR6
7531	Cut D7	L7 L8	
934-36710500	Cut D7	T15 T16	
934-36740500	Cut D9	T17 T18	
934-36741600	Cut D8		
934-36770500	Cut D25 & D26	L14	R86 R281
934-36771500	Cut D25 & D27	R405	R281
934-36772600	Cut D25 & D27	R405	R281
934-38060700	Cut D7 or Cut D12	T14 T15	
934-38061700	Cut D7 or Cut D12	T14 T15	
934-38062700	Cut D7 or Cut D12	T14 T15	
934-38080700	Cut D7	T14 T15	
934-38081700	Cut D501 or D502	T704 T705	
934-38110700	Cut D7	T14 T15	
934-38120700	Cut D501 or D502	T704 T705	
934-38260700	D303	RT301	RT402
934-38270700	Cut D405 or D406	RT602	RT701
934-38310700	D303	RT301	RT402

SHAKESPEARE RADIOS

Model	Modulation	AM Power	SSB Power
GBS-1500	VR481 or Cut D481 & D482	L451 L463	
GBS-2000	VR5 or Cut D14 & D15	L13 L16 L18	
Gbs-240	VR481 or Cut D481 & D482	L451 L463	
GBS-2500	VR481 or Cut D481 & D482	L451 L463	

SHARK RADIO

Model	Modulation	AM Power	SSB Power
SHARK 23	VR201	L308 L307 L305	

SHARP RADIOS

Model	Modulation	AM Power	SSB Power
CB-2170	R110 or Cut D101	T304 L302 L301	
CB-2260	R112 or Cut D101	L302 L303	
CB-2460	R112 or Cut D101	L302 L303	
CB-4370	R110 or Cut D101	T304 L302 L301	
CB-4470	R110 or Cut D101	T304 L302 L301	
CB-4670	R110 or Cut D101	T304 L302 L301	
CB-500UB	R74 or Cut D4	L15 L14	
CB-5470	R541	C-31	R542
CB-700	R110 or Cut D101	T304 L302 L301	
CB-750A	R110 or Cut D101	T304 L302 L301	
CB-800	R110 or Cut D101	T304 L302 L301	
CB-800A	R110 or Cut D101	T304 L302 L301	

SILTRONIX RADIOS

Model	Modulation	AM Power	SSB Power
APACHE (AM-1)	VR7 or Cut D14	L9 L10 L11	
CHEROKEE	VR206 or Cut D214 & D213	VC201	VR102 VR205
MOHAWK (AM-2)	VR7 or Cut D14	L9 L10 L11	
SSB-23	VR204 or Cut D207 & D208	VC203	VR110 VR206
SSB-23A (Albatross)	VR206 or Cut D214 & D213	VC201	VR102 VR205

SOMMERKAMP RADIO

Model	Modulation	AM Power	SSB Power
TS-2000DX	VR14 or Cut one end of R291	VR13	VR12

SOUND CREATION RADIO

Model	Modulation	AM Power	SSB Power
SCB-500X	Cut D115	L107 L108	

SPARKOMATIC RADIOS

Model	Modulation	AM Power	SSB Power
CB-1040	Cut D201	L202 L205	
CB-1123	Cut D107	L5 L6	
CB-1140	RV5 or Cut D15		
CB-40	VR (next to D105)		
RA-400	RV3	L4 L5	
SBR-1CBM	Cut D7		

STAG RADIO

Model	Modulation	AM Power	SSB Power

Model	Modulation	AM Power	SSB Power
STAG-357	VR7	VR8	CT7

STANDARD COMMUNICATIONS RADIOS

Model	Modulation	AM Power	SSB Power
HORIZON 29-13 CH	VR213 or Cut D218 & D219	L217 L214	
HORIZON 29A-40 CH	VR213 or Cut D218 & D219	L217 L214	

STARFIRE RADIO

Model	Modulation	AM Power	SSB Power
STARFIRE DX	RV12	RV11	RV6 RV3

STEREOSONIC RADIOS

Model	Modulation	AM Power	SSB Power
2300	VR481 or Cut D481 & D482	L451 L463	
2301	VR481 or Cut D481 & D482	L451 L463	
2302	VR481 or Cut D481 & D482	L451 L463	
2355	VR481 or Cut D481 & D482	L451 L463	
2360	VR481 or Cut D481 & D482	L451 L463	

SUPERSCOPE (AIR COMMAND) RADIOS

Model	Modulation	AM Power	SSB Power
CB-140	R613 or Cut R612 or D602	L407 L409 L410	

CB-340	R613 or Cut R612 or D602	L407 L409 L410	
CB-640	R613 or Cut R612 or D602	L407 L409 L410	
CBB-1040	R508 or Cut Q517 & Q516	L606 L607 L610	
CBR-40 AM-FM-CB	VR2	L3 L4	

SUPERSTAR RADIOS

Model	Modulation	AM Power	SSB Power
120	Remove C99	L15 L16 (HI PWR)	
1700	VR14 or Cut R249	VR13	VR12
1700 B	RV12	L15 L16 (HI PWR)	
1700 S	RV12	L15 L16 (HI PWR)	
2000	RV12	RV11	RV6 RV3
2200	RV12	RV11	RV6 RV3
360	Cut R104	VR6	
3600	VR14 or Cut R249	VR13	VR12
360FM	VR14 or Cut R301	VR13	VR7
3900	VR14 or Cut R249	VR13	VR12
95	Remove C99	L15 L16 (HI PWR)	

SURVEYOR RADIOS

Model	Modulation	AM Power	SSB Power
1500	VT3 or Cut D6	L1 L19 (HI PWR) VR4 (LO PWR)	
2100	VT3 or Cut D6	L15 L16	
2300	Remove C54 or Cut D8 & D9	L19 L20	
2400	VR5 or Cut D12	L15 L16	
2600	VR6 or Cut D12	L115 L116	
2610	R207 or Cut D201	L202 L205	
2620	RV401	L302 L306	

2630

VR104 or Cut D115

L404 L402

[Previous Page](#)

[Back to Main Menu](#)

[Next Page](#)

[Want More? Check Out The CD! Over 400MB of VERY Useful Information](#)



[Ham Radio 2010 Special](#)

Entry-level ham license for \$20 and 10 study hours. Success guaranteed!

[Cb Radio Manufacturers](#)

Connect to suppliers & exporters from China and Hong Kong.

Ads by Google

All Rights Reserved C.B. RADIO SECRET © 2003,2004,2005,2006

[Previous Page](#)[Back to Main Menu](#)[Next Page](#)

C.B. RADIO SECRET Master Tune Up Manual

If You Find This Information Helpful Then Please Consider A Small Donation To Help Keep This Site Alive!

[Make A Donation](#)

TEABERRY RADIOS

Model	Modulation	AM Power	SSB Power
BIG T	VR8		
FIVE BY FIVE (early)	RV5 or Cut X10	A17	
FIVE BY FIVE (late)	Cut D10	L12 L9 L7	
MIGHTY T	VR5 or Cut D702 or D703	VC1 L914	
MODEL T	VR6 or Cut D505	L905 L903	
RACER T (23 CH)	VR7	L906	
RACER T (40 CH)	VR6 or Cut D505	L905 L903	
STALKER 3	Cut D13	L7 L10	
STALKER I	VR13 or Cut D52	VR17	VR16 VR12
STALKER II	VR13 or Cut D28 & D29	VR17	VR6 VR12
STALKER III	VR8 or Cut D504	L901 L903 L905	
STALKER IV	VR6 or Cut D9	L11 L12 L15	
STALKER IX	Cut R104	VR6	VR7
STALKER IX (export)	VR5	VR11	VR7
STALKER V	VR4 or Cut D11	L17 L16 L14	
STALKER VIII	Cut D9	L10 L11 L15	
STALKER XII	VR6 or Cut D16	L17 L16 L13	
STALKER XV	Cut R104	VR6	VR7
STALKER XX	VR11 or Cut R104	VR6	VR7
STALKER XX (export)	Cut R104	VR6	VR7
"T"	RV4 (Change 6BQ5 to 7189)	CV5	

T BEAR	VR5 or Cut D14	L15 L12 L11	
T CHARLIE (40 CH)	VR7 or Cut D505	L905	
T COMMAND	VR5 or Cut D14	L15 L12 L11	
T CONTROL	VR5 or Cut D505	L914	
T DISPATCH	VR3	L13 L15	
T SCOUT	Remove C73 or Cut D11	L8 L5	
TELE T	VR7 or Cut D506 & D507	L909	
TITAN T	VR2 or Cut D14	L11 L12 L15	

TEK RADIO

Model	Modulation	AM Power	SSB Power
HR-3950	RV203 or Cut R270	RV300	RV304

TENNA RADIOS

Model	Modulation	AM Power	SSB Power
10901	R54 or Cut D13	T10 T11 L3 L2 L1	
10902	R71 or Cut D20 & D21	T15 T16 L4	
11302 (AM-FM-CB)	Cut D703 Or Cut D702	L609 L610	
A0902	R77 or Cut D12	T11 L3	

TEXAS RANGER RADIOS

Model	Modulation	AM Power	SSB Power
TR-296DX	VR7	VR10	VR11
TR-396F	VR16	VR14	
TR-696F	VR16	VR14	VR13
TR-696F SSB Base	VR16	VR14	VR13

TEXAS STAR RADIO

Model	Modulation	AM Power	SSB Power
2100	VR14 or Cut R249	VR13	VR12

THUNDER RADIO

Model	Modulation	AM Power	SSB Power
THUNDER 2000	RV12	RV11	RV6 RV3

TRAM RADIOS

Model	Modulation	AM Power	SSB Power
D-12	R61 or Cut CD12	L6 L3	
D-201	R647	C711 C712	R719
D-300	Cut R104	VR6	VR7
D-42	R80 or Cut CD11	L5	
D-64	R217	L704 L706 L709	R721
D-80	Cut R104	VR6	VR7
DIAMOND 40	Change R114 to a 10k	L2 L5	
DIAMOND 60	R98	L2 L5	R112
TITAN II	Cut X9	A18 A19 A24	R112
TITAN IV	R520		C718 C719
XL	Cut CD12	L5 L3	
XL-5	R616 or Remove C611 or Cut CR603	L106 R130	

TRI MAX RADIO

Model	Modulation	AM Power	SSB Power
TRI MAX 220	RV3 or Cut D9	L11 L12 L13	

TRISTAR RADIOS

Model	Modulation	AM Power	SSB Power

Model	Modulation	AM Power	SSB Power
120	RV3 or Cut D9	L10 L11 L12 L13	
240 (early)	VR7 or Cut D22	L14 L16 L17	
240 (late)	RV2 or Cut D12	L7 L11-B LH10 L1	
340 (early)	RV7 or Cut D22	L14 L16 L17	
340 (late)	RV2 or Cut D12	L7 L11-B LH10 L1	
727	Remove C99	L15 L16 (HI PWR)	
747	RV14	RV13	RV12 RV4
777	RV12	RV11	RV6 RV3
797	RV12	RV11	RV6 RV3
848	RV12	RV11	RV6 RV3

TRS CHALLENGER RADIOS

Model	Modulation	AM Power	SSB Power
1200	VR1 or Cut D201 or D202	VR6	
1400	VR1	VR15	VR2 VR8
460	VR3 or Cut D8 & D9	L103 L106 1109	
600	VR1 or Cut D2	VR210	
730	VR1 or Cut D201 or D202	VR6	
850	VR1	VR15	VR2 VR8

TRUETONE RADIOS

Model	Modulation	AM Power	SSB Power
CYJ4732A-77	RV102 or Cut D111	L110 L109	
CYJ4832A-87	RV2 or Remove C96	L7 L11 L12	
CYJ4834A-87	RV2 or Remove C96	L7 L11 L12	
CYJ4837A-87	RV12 or Remove Q37 & Q38	VR4	RV2
CYJ4862A-87	RV2 or Remove C96	L7 L11 L12	
DC4530	Cut D6	L2 C4	

DC4672	RV2 or Cut D10	L7 L8 L9	
MCC4370A-57	R58 or Cut D8	L3 C5	
MCC4434A-57	Remove C39 or Cut D12	L11 L12 L14	
MCC4434A-67	RV2 or Cut D10	L7 L8 L9	
MCC4434B-67	RV102 or Cut d111	L110 L109	
MCC4532A-47	R58	T14 C5	
MCC4630A-67	Cut D7	T2 C4 L2	
MCC4635A-67	Cut D24	L7 L8 L9	
MCC4724A-77	VR4 or Cut D7	L5 L6	
MCC4726A-67	Remove C45 or Cut D1	C29 L6 L9	
MCC4760A-67	VR7 or Cut D507 & D507	L908 L909	
MCC4770	RV2 or Cut D10	L7 L8 L9	
MIC4350A-37	VR4 or Cut D6	L8 VR5	
MIC4434A-67	RV2 or Cut D10	L7 L8 L9	
MIC4622A-67	VR4 or Cut D6	L106	
MIC4726A-67	Cut D1	C29 L6 T5	
MIC4730A-67	RV2 or Cut D10	L7 L8 L9	
MIC4731A-67	VR5 or Cut D703 or D702	L914 VC1	
MIC4733A-67	VR5 or Cut D703 or D702	VC1	
MIC4737A-67	RV7 or Cut D206	RV305	RV8 RV5
MIC4739A-67	RV2 or Cut D10	L7 L8 L9	

[Previous Page](#)
 [Back to Main Menu](#)
 [Next Page](#)

Want More? Check Out The CD! Over 400MB of VERY Useful Information



Ham Radio Online Courses

Don't just memorize the answers. Learn about ham radio!

Motorola VL50 Radio

Small, easy-to-use, affordable Now only \$141.50 ea.

Ads by Google

[Previous Page](#)[Back to Main Menu](#)

C.B. RADIO SECRET Master Tune Up Manual

If You Find This Information Helpful Then Please Consider A Small Donation To Help Keep This Site Alive!

[Make A Donation](#)

UNIC RADIOS

Model	Modulation	AM Power	SSB Power
CB-40	RV4 or Cut R65	T9 T10 T11	
CB-50	Cut D22	T9 T10	
RV-40CB	VR3 or Cut D9	L11 L12 L13	

UNIDEN RADIOS (Also see President Radios)

Model	Modulation	AM Power	SSB Power
DWIGHT D (1003002)	VR6 or Cut D16	L13 L12 L11	T9 T10 T11
GRANT (1005002)	Cut R131	VR10	VR11
HR-2510	VR114	VR103	VR104
MADISON	Cut R131	VR10	VR11
PC-122	VR5	VR10	VR11
PC-22	VR3 or Cut R54	L12 L14	
PC-244	VR5 or Remove TR29	VR10	VR6
PC-3	Cut D13	L7 L10	
PC-33	Cut D13	L15 L12 L11	
PC-33X	Cut D14	L6 L5 L4	
PC-43	Cut D12	L8 L9 L12	
PC-55	Cut D13	L15 L12 L11	
PC-55X	Cut D14	L6 L5 L4	
PC-66	VR5 or Cut D9	L13 L10 L9 L8	
PC-66A	VR5 or Cut D9	L13 L10 L9 L8	

PC-77	Cut D15	L17 L16 L13	
PC-9 (emergency radio)	Cut D11		
PRO-500D	Cut D14	L6 L5	
PRO-510e	Cut D14	L6 L5 L4	
PRO-510XL	Cut D14	L6 L5	
PRO-520e	Cut D14	L6 L5 L4	
PRO-520XL	Cut D14	L6 L5	
PRO-530e	Cut D14	L11	
PRO-540e	Cut D22	L12 L10	
PRO-640e	VR5 or Remove TR29	VR10	VR6
PRO-710e	Cut D11	L8 L7 L6	
PRO-810e	VR5 or Remove TR29	VR10	VR6
PTC-104	Cut D18	L11 L9 L8	
WASHINGTON (1002002)	Cut R104	VR6	VR7
ZACHARY T (1002002)	VR6 or Cut D16	L13 L12 L11	

UNIMETRIC RADIOS

Model	Modulation	AM Power	SSB Power
DOLPHONE	VR4 or Cut D11	L7 L8	
MAKO-1	VR6 or Cut D8	VC2 L14	
MARLIN-1	VR6 or Cut D8	VC2 L13	
PORPOIS-I	VR6	L15 L16 VC2	
SEA-HOURSE I	RV203 or Cut D211	L214 VC1	
STINGRAY-II	RV7	RV304	RV8 RV5

USACO RADIO

Model	Modulation	AM Power	SSB Power
U900CB	VR3 or Remove C80	T11 T13 T14	

UTAC RADIOS

Model	Modulation	AM Power	SSB Power
MICRO-MINI 23	R69 or Cut D16	T14 L5	
STUDIO 4000	R70 or Remove TR14	L21 L19	
SUPER TINY 23	R69 or Cut D16	T14 L5	
TR-18M	R71 or Cut D10	L15 L17	
TRX-2000	Cut D2 or D1	L5 T9	R41
TRX-30	R69 or Cut D10 or D16	L17	
TRX-400	VR7 or Cut D10	L15 L17	
TRX-500	VR7 or Cut D10	L15 L17	

VECTOR RADIOS

Model	Modulation	AM Power	SSB Power
770	FVR3 or Remove C35 or Cut D14	L26 L25	
790	FVR3 or Cut D10	L26 L25	
VECTOR IV	VR7 or Cut D14	L10 L11 L9	
VECTOR IX	VR9 or Cut D11 & D12	L12 L11	
VECTOR VI	VR7 or Cut D8 & D15	L12	
VECTOR VII	R71 or Cut D23	L22	
VECTOR X	VR260 or Cut D260 & D261	L53 L55 L57	

WELLS RADIO

Model	Modulation	AM Power	SSB Power
W 705	R207 or Cut D9	L11 L12 L13	

WESTPOINT RADIO

Model	Modulation	AM Power	SSB Power

CB-9000

Cut D17 & D16

L14 L17

WHISTLER RADIO

Model

Modulation

AM Power

SSB Power

900

RV301 or Cut R351

L410 L411 L412

XTAL RADIOS

Model

Modulation

AM Power

SSB Power

XCB-11

Cut D13 & D14

L15 L13

XCB-12

Cut D13 & D14

L15 L13

XCB-23A

Cut D9 or Remove C226

L25 TC7

XCB-28

Cut D24 or Remove C211

C228 L207

XCB-4

VR7 or Cut D7

L15 L13

XCB-5

Cut D11 or D14

L15 L13

XCB-6

RV5 or Cut D17 & D18

L16 L15

XCB-7

R75 or Cut D17 & D18

L16 L15

XCB-71

VR202 or Cut D202

XCB-88

TR4 or Cut D14

L22

XSSB-10

Cut D2 & D1 or Remove C8

T8 T9 L5

R41

XSSB-4

Jumper Cathode side of D2 to Ground

YOSAN RADIO

Model

Modulation

AM Power

SSB Power

JC-2204

VR604

L204 L206

ZODIAC RADIOS

Model

Modulation

AM Power

SSB Power

M-5023	VR4 or Cut D14 & D13	L16 L14	
M-5026	R89 & R35 or Cut D12 & D11	L14 L15 L17	

[Previous Page](#) [Back to Main Menu](#)

[Want More? Check Out The CD! Over 400MB of VERY Useful Information](#)



<p>Become a ham for \$20 Entry-level ham license for \$20 and 10 hours study. Success guaranteed!</p>	<p>Not a Toy R/C Helicopter Falcon 40-100% Built RC Helicopter Top quality parts and electronics</p>
--	---

Ads by Google

All Rights Reserved C.B. RADIO SECRET © 2003,2004,2005,2006