



**B5CH114AA**

---

# **B5CH114AA Product Manual DRU 5 GHz WLAN Radio Module**

---

Document Date:	Nov 10, 2010
Document Number:	B5CH114AA
Document Version Number:	1
Document Status:	Release

© Copyright 2010 by BelAir Networks.  
All rights reserved.

## Contents

About this Document.....	2
Introduction .....	3
Conditions of Use .....	4
Module Installation and Service.....	5
Final Product Requirements .....	6
Regulatory Statements .....	11

## About this Document

This document is a product manual for the DRU 5 GHz WLAN Radio Module, including its limitations on use in any product marketed or offered for sale. It is intended as a supplement to training and documentation by BelAir Networks Inc. or its authorized agents.

## Introduction

The B5CH114AA (hereafter referred to as “the module”) is a 5 GHz radio module compatible with the IEEE 802.11 standard for Wireless LAN operation. It is designed to be interoperable with WLAN products which are based on Orthogonal Frequency Division Multiplexing (OFDM) radio technology.

The module contains a complete IEEE 802.11a/n radio and Medium Access Control (MAC) protocol engine which allows implementation of an IEEE 802.11a/n access point (AP).

The module is not intended for stand-alone operation. It will only be marketed as a complete product, in conjunction with a package, DC power supply and antennas (hereafter referred to as “the product” or the “final product”).

The module can be used in the 5 GHz ISM unlicensed bands.

Since the module has a BelAir networks proprietary digital interface, it cannot be directly connected to any standard telecommunications or computer devices. It can only be used with final products designed and authorized specifically for that purpose.

## Conditions of Use

### General Conditions of Use

This manual is intended to supplement training provided by BelAir Networks or authorized parties. The module B5CH114AA is only intended for use in BelAir Networks products and is not for sale to the general public as a stand-alone module.

Please read this entire document, including the Regulatory Statements section before attempting to install or operate the module.

**Warning:** Any use of B5CH114AA in any manner which is not expressly specified within this manual or specifically approved by BelAir Networks or its authorized agents will void the user's right to operate this module, and is expressly forbidden by BelAir Networks. This includes any modification of the module, installation of the module in a configuration or used with antennas which are not expressly listed in this document or approved by BelAir Networks.

## Country of Use

B5CH114AA is certified with limited modular approval for use as an Intentional Radiator in the United States as device: FCC ID: RAR30005002 and in Canada as IC: 4674A-30005002. Please read all regulatory statements at the end of this document before any attempt to install or operate this module.

The module is only certified for operation in the United States and Canada. Before attempting to install and operate this module in any other country, contact BelAir Networks for approval.

## Module Labeling

One or more labels are applied to the module during manufacture, including a label which identifies the FCC and Industry Canada identification numbers. Do not attempt to remove any labels from the module.

## Module Installation and Service

### Installation into a Product

The module shall only be installed by a technician trained by BelAir Networks or its authorized agents. It should only be installed into an approved product (see above) following all manufacturing and service procedures for that product. The module should only be installed into a final product in a manufacturing or service depot site.

**Caution:** B5CH114AA is an electro-static discharge (ESD) sensitive device. All appropriate ESD measures must be taken when handling the module. Failure to employ appropriate ESD protection may damage the module.

### Module Service

The module is not intended as a field-serviceable unit. It contains no field-replaceable or field-serviceable parts, or any external adjustable mechanisms. The module should only be serviced in a manufacturing or service depot site approved by BelAir Networks or its authorized agents.

## Final Product Requirements

The requirements below apply to any final product in which the B5CH114AA module is installed.

### Antenna Usage and Module Transmit Power

The DRU 5GHz radio module supports MIMO 2x2 configuration with two transmit chains and two receive chains. The B5CH114AA module shall only be used at the following output power levels in conjunction with the following antenna types as outlined in the tables that follow.

#### 5725-5850 MHz – Part 15.247 Subpart E

For operation in the 5725-5825 MHz UNII band, the B5CH114AA may be set to operate on 20 MHz channel bandwidths.

Omni antenna - 20 MHz channel bandwidth									
Modulation	Freq. (MHz)	Output power (dBm)	Conducted output power limit (dBm)	Conducted output power margin (dB)	Antenna gain (dBi)	Cable loss (dB)	EIRP (dBm)	EIRP Limit (dBm)	EIRP Margin (dB)
802.11n	5740	24.592	29.36	4.77	7	0.5	31.09	35.86	4.77
	5790	26.429	29.36	2.93	7	0.5	32.93	35.86	2.93
	5810	25.454	29.36	3.91	7	0.5	31.95	35.86	3.91
802.11a	5740	24.670	29.36	4.69	7	0.5	31.17	35.86	4.69
	5790	26.384	29.36	2.98	7	0.5	32.88	35.86	2.98
	5810	25.123	29.36	4.24	7	0.5	31.62	35.86	4.24

#### 5725-5850 MHz – Part 15.247 Subpart C

For operation in the 5725-5850 MHz ISM band, the B5CH114AA may be set to operate on 20 MHz or 40 MHz channel bandwidths.

Omni antenna - 20 MHz channel bandwidth									
Modulation	Freq. (MHz)	Output power (dBm)	Conducted output power limit (dBm)	Conducted output power margin (dB)	Antenna gain (dBi)	Cable loss (dB)	EIRP (dBm)	EIRP Limit (dBm)	EIRP Margin (dB)
802.11n	5740	23.892	29.50	5.61	7	0.5	30.39	36	5.61
	5790	26.819	29.50	2.68	7	0.5	33.32	36	2.68
	5835	23.474	29.50	6.03	7	0.5	29.97	36	6.03
802.11a	5740	23.654	29.50	5.85	7	0.5	30.15	36	5.85
	5790	26.930	29.50	2.57	7	0.5	33.43	36	2.57
	5835	23.592	29.50	5.91	7	0.5	30.09	36	5.91

Directional antennas (Point to Point P2P) – 20 MHz channel bandwidth							
Modulation	Freq. (MHz)	Output power (dBm)	Conducted output power limit (dBm)	Conducted output power margin (dB)	Antenna gain (dBi)	Cable loss (dB)	EIRP (dBm)
802.11n	5740	27.83	30	2.17	10	0.5	37.33
	5790	29.64	30	0.36	10	0.5	39.14
	5835	27.68	30	2.32	10	0.5	37.18
802.11a	5740	28.06	30	1.94	10	0.5	37.56
	5790	29.64	30	0.36	10	0.5	39.14
	5835	27.81	30	2.19	10	0.5	37.31
802.11n	5740	27.83	30	2.17	15	0.5	42.33
	5790	29.64	30	0.36	15	0.5	44.14
	5835	27.68	30	2.32	15	0.5	42.18
802.11a	5740	28.06	30	1.94	15	0.5	42.56
	5790	29.64	30	0.36	15	0.5	44.14
	5835	27.81	30	2.19	15	0.5	42.31
802.11n	5740	27.83	30	2.17	16	0.5	43.33
	5790	29.64	30	0.36	16	0.5	45.14
	5835	27.68	30	2.32	16	0.5	43.18
802.11a	5740	28.06	30	1.94	16	0.5	43.56
	5790	29.64	30	0.36	16	0.5	45.14
	5835	27.81	30	2.19	16	0.5	43.31
802.11n	5740	27.83	30	2.17	19	0.5	46.33
	5790	29.64	30	0.36	19	0.5	48.14
	5835	27.68	30	2.32	19	0.5	46.18
802.11a	5740	28.06	30	1.94	19	0.5	46.56
	5790	29.64	30	0.36	19	0.5	48.14
	5835	27.81	30	2.19	19	0.5	46.31
802.11n	5740	26.83	30	3.17	22	0.5	48.33
	5790	29.64	30	0.36	22	0.5	51.14
	5835	27.68	30	2.32	22	0.5	49.18
802.11a	5740	26.92	30	3.08	22	0.5	48.42
	5790	29.64	30	0.36	22	0.5	51.14
	5835	27.81	30	2.19	22	0.5	49.31

Directional antenna with triplexer (Point to Point P2P) – 20 MHz channel bandwidth							
Modulation	Freq. (MHz)	Output power (dBm)	Conducted output power limit (dBm)	Conducted output power margin (dB)	Antenna gain (dBi)	Cable loss (dB)	EIRP (dBm)
802.11n	5745	29.4	30	0.6	16	0.5	44.9
	5785	29.67	30	0.33	16	0.5	45.17
	5825	29.93	30	0.07	16	0.5	45.43
802.11a	5745	29.47	30	0.53	16	0.5	44.97
	5785	29.61	30	0.39	16	0.5	45.11
	5825	29.5	30	0.5	16	0.5	45

Directional antenna (Point to Multi Point P2MP) – 20 MHz channel bandwidth									
Modulation	Freq. (MHz)	output power (dBm)	Conducted output power limit (dBm)	Conducted output power margin (dB)	Antenna gain (dBi)	Cable loss (dB)	EIRP (dBm)	EIRP Limit (dBm)	EIRP Margin (dB)
802.11n	5740	26.15	26.5	0.35	10	0.5	35.65	36	0.35
	5790	25.97	26.5	0.53	10	0.5	35.47	36	0.53
	5835	26.21	26.5	0.29	10	0.5	35.71	36	0.29
802.11a	5740	26.31	26.5	0.19	10	0.5	35.81	36	0.19
	5790	26.07	26.5	0.43	10	0.5	35.57	36	0.43
	5835	26.33	26.5	0.17	10	0.5	35.83	36	0.17
802.11n	5740	21.14	21.5	0.36	15	0.5	35.64	36	0.36
	5790	21.2	21.5	0.3	15	0.5	35.7	36	0.3
	5835	21.14	21.5	0.36	15	0.5	35.64	36	0.36
802.11a	5740	21.25	21.5	0.25	15	0.5	35.75	36	0.25
	5790	21.34	21.5	0.16	15	0.5	35.84	36	0.16
	5835	20.81	21.5	0.69	15	0.5	35.31	36	0.69
802.11n	5740	19.88	20.5	0.62	16	0.5	35.38	36	0.62
	5790	20.21	20.5	0.29	16	0.5	35.71	36	0.29
	5835	20.09	20.5	0.41	16	0.5	35.59	36	0.41
802.11a	5740	19.94	20.5	0.56	16	0.5	35.44	36	0.56
	5790	19.71	20.5	0.79	16	0.5	35.21	36	0.79
	5835	19.61	20.5	0.89	16	0.5	35.11	36	0.89

Directional antenna with triplexer (Point to Multi Point P2MP) – 20 MHz channel bandwidth									
Modulation	Freq. (MHz)	output power (dBm)	Conducted output power limit (dBm)	Conducted output power margin (dB)	Antenna gain (dBi)	Cable loss (dB)	EIRP (dBm)	EIRP Limit (dBm)	EIRP Margin (dB)
802.11n	5745	19.96	20.5	0.54	16	0.5	35.46	36	0.54
	5785	19.88	20.5	0.62	16	0.5	35.38	36	0.62
	5825	20.29	20.5	0.21	16	0.5	35.79	36	0.21
802.11a	5745	19.98	20.5	0.52	16	0.5	35.48	36	0.52
	5785	20.04	20.5	0.46	16	0.5	35.54	36	0.46
	5825	20.48	20.5	0.02	16	0.5	35.98	36	0.02



Directional antenna (Point to Point P2P) – 40 MHz channel bandwidth							
Modulation	Freq. (MHz)	Output power (dBm)	Conducted output power limit (dBm)	Conducted output power margin (dB)	Antenna gain (dBi)	Cable loss (dB)	EIRP (dBm)
802.11n	5750	26.6	30	3.4	22	0.5	48.1
	5790	29.26	30	0.74	22	0.5	50.76
	5825	26.27	30	3.73	22	0.5	47.77

## Certified Antennas:

The following antennas are certified for use:

Manufacturer	Part #	Gain (dBi)	Type
BelAir	BMAG00287-A	7 dBi	Onmi
BelAir	BNISH002-B	10 dBi	Directional
BelAir	BMDG30083-A01	15 dBi	Directional
BelAir	BNCKG0081	16 dBi	Directional
BelAir	BNCKG0082	19 dBi	Directional
BelAir	BNCKG0017	22 dBi	Directional

In order to comply with the FCC and Industry Canada rules in the USA and Canada, respectively, it is required to respect the maximum transmit power limits as follows for each of the antenna types as indicated in the above tables.

**Warning:** Use of this module in conjunction with any antenna not expressly listed above will void authority to install or operate this equipment.

**Warning:** Setting of module transmit power above the limits specified in the above table for a particular combination of antenna type, frequency of operation, and type of usage, will exceed FCC or Industry Canada limits and void authority to install or operate this equipment.

## Product Installation

Products which contain B5CH114AA shall only be installed by professional installers trained by BelAir Networks or its authorized agents. This product is to be installed on fixed permanent structures. In addition to normal installation procedures and good installation practice, professional installers are responsible to ensure that:

1. Only an approved antenna (see above) is connected to the module, and,

- The antenna is mounted in such a manner and in such a location that access to the antenna by the general population is minimized. Access to the antenna by the general population should be limited to more than the minimum safety distance. This distances are outlined according to product type and whether high gain antennas are used:

Minimum Safety Distances					
Standard Antennas		Meduim Gain Antennas		High Gain Antennas (up to 22 dBi)	
DRU 2.4GHz radio	DRU 5GHz radio	DRU 2.4GHz radio	DRU 5GHz radio	DRU 2.4GHz radio	DRU 5GHz radio
5 dBi	7 dBi	≤ 8dBi	≤ 15dBi	> 8dBi	> 15dBi
Minimum Distance		Minimum Distance		Minimum Distance	
8.1 inches		19.3 inches		42.9 inches	

Adherence to these rules by the professional installer is mandatory. See full installation procedures for the particular product for details.

## Product Labeling

The following permanent label, or one containing equivalent information, must be affixed in a conspicuous location on the exterior of every product containing this module:

FCC ID: RAR30005002 IC: 4674A-30005002
---

## Regulatory Statements

The following regulatory notes apply to the product which contains module B5CH114AA. The following sections or equivalent information shall appear in the user-manual of the final product.

### Regulatory Information and Disclaimers

Installation and use of this device must be in strict accordance with the instructions included in the user documentation provided with the product. Any changes or modifications to this product not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

The manufacturer is not responsible for any interference to radio or television equipment caused by unauthorized modification of this device, or attachment of any antennas or equipment other than those specified by the manufacturer. The manufacturer or its authorized resellers or distributors will assume no liability for any damage or violation of government regulations arising from failing to comply with these guidelines.

### Manufacturer's FCC Conformity Statement

This device complies with Part 15 of the FCC Rules.

Operation is subject to the following two conditions (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

### FCC Interference Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.

- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

## Manufacturer's Industry Canada Conformity Statement

This device has been designed to operate with an antenna having a maximum gain of 22 dBi. Antenna having a higher gain is strictly prohibited per regulations of Industry Canada. The required antenna impedance is 50 ohms.

This device has been designed to ensure that radio frequency emissions are maintained within the band of operation under all normal operating conditions listed in this manual.

Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

To reduce potential radio interference to other users, the antenna type and its gain should be so chosen that the equivalent isotropic radiated power (EIRP) is not more than that required for successful communication.

This Class B Digital apparatus meets all the requirements of the Canadian Interference-Causing Equipment Regulations.

## RF Exposure Statement

This device complies with FCC RF radiation exposure limits for an uncontrolled environment. The radiated output power of this Wireless LAN device is below the FCC radio frequency exposure limits. However, this device should still be installed and used in such a manner that the potential for human contact during normal operation is minimized. In order to comply with RF exposure limits established in the ANSI C95.1 standard, this equipment should be installed and operated at a minimum distance between the radiator and a human body. This minimum distance is:

Minimum Safety Distances					
Standard Antennas		Meduim Gain Antennas		High Gain Antennas (up to 22 dBi)	
DRU 2.4GHz radio	DRU 5GHz radio	DRU 2.4GHz radio	DRU 5GHz radio	DRU 2.4GHz radio	DRU 5GHz radio
5 dBi	7 dBi	≤ 8dBi	≤ 15dBi	> 8dBi	> 15dBi
Minimum Distance		Minimum Distance		Minimum Distance	
8.1 inches		19.3 inches		42.9 inches	

**BelAir Networks Inc.**  
 603 March Road  
 Kanata, Ontario  
 Canada  
 K2K 2M5  
 613-254-7070

**Sales**  
[sales@belairnetworks.com](mailto:sales@belairnetworks.com)  
**Support**  
[support@belairnetworks.com](mailto:support@belairnetworks.com)  
**General Information**  
[Info@belairnetworks.com](mailto:Info@belairnetworks.com)