

FCC requirements § 2.1033 (b)(3)

INSTALLATION INSTRUCTIONS

Installation Instructions (Instruction Manual) furnished to the user of the Hi-G-Seal transmitting device follow this page



Hi-G-Tek Ltd. Microelectronics & Asset Tracking Technology

Hi-G-Seal

(IG-SA-21 and IG-MA-22)

Electronic Seals and Hand Held Terminals for Sealing Assets

INSTRUCTION MANUAL

Nov. 1998

Rev. C
UM3158

Note: This equipment has been tested and found to comply with the limits for a class B digital device, pursuant to the part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in the residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Congratulations!

You have chosen Hi-G-Tek's products that are state-of-the-art in their technology and properties.

The Hi-G-Seal will lead you to a new dimension in the **field of security**.

The electronic miniaturized seals are more **reliable** and more **secure** than their mechanical counterparts.

They are cost-effective. They are reusable, save paperwork and workers time.

You can know not only if the asset was opened on its way but also when it was opened.

It is all carried out remotely.

Contents	page
1. Hi-G-Seal Components	4
2. Preparation for use – How to use the Seal	7
3. The basic operation – Understanding the System	9
4. Operating instructions	11
4.1 Initialization	11
4.2 Reading a Seal	13
4.3 Setting a Seal	16
4.4 Special Functions	18
• View Data	19
• Clear Data	26
• Statistics	29
• Setup Date	29
• Setup Time	30
• Setup Zone	30
• Display Versions	31
• Configuration	32
• Set password	32
• Set Date Format	35
5. Troubleshooting	36
6. Technical Specifications	40

1. Hi-G-Seal Components

1.1 The Seal

- **Seal Electronics**
This unit contains the electronic circuitry of the seal. It contains the transmitter, the receiver, the computer and the memory to store the events.
- **Seal Wire**
The Seal Wire with the Connectors at the end is used to seal the object.
- **Key**
To release the connectors after sealing, use the Key for convenience.

1.2 The Hand Held Terminal-HHT

- **Display**
The Hand Held Terminal displays all the information on this LCD display.
- **Indicators**
On. When power is on and the system functions O.K this indicator lights up **GREEN** color.
When it lights up **RED**, there is a problem with the unit.
When it blinks up **RED**, the batteries are low, please replace them.
- **Key Pad**
The keypad is used to operate the unit in its different modes of operation, to enter data as required.
- **Batteries.**
This is the battery compartment. Use a flat screwdriver to open it.

2. Preparation for Use – How to Use the Seal

2.1 Hand Held Terminal-HHT

2.2.1 Placing/Replacing Batteries.

One) Open the battery compartment using a screwdriver.

Two) Use “AA” size 1.5 V batteries only!

Three) Take out the old batteries if there are any.

Four) Insert 4 new batteries into the battery compartment, **verify polarity** of the batteries to match the indications inside the battery compartment!

Five) Close the cover and secure it with the screw.

2.2 How to Seal an Asset

Thread the sealing wire through the locking ring of the asset.
Inserting seal wire connectors into the seal's sockets.

2.2 How to Release the Seal

Pull out the connectors using
the Key.

1. Insert the Key into the
recess on the connector.
2. Rotate the Key upward and
pull the connector from the socket.

3. Basic Operation – Understanding the System

The basic operation of the system includes three simple stages:

The first two stages are performed at the origin site while the third stage is carried out at the destination site.

Stage I: Sealing the asset.

At this stage you seal the asset by threading the sealing wire through the locking ring of the asset, and then insertion of the seal wire connectors in the seal's sockets.

Stage II: SET the Seal

Press the ON key and verify that the green light illuminates. Place the HHT within 60 cm. from the seal and then press the SET key on the HHT.

Notes: There is an available option to write down the ID Number of the seal and the sealing stamp on the bill of lading (you may want to FAX or E-Mail the result to the destination site).

Stage III: READ the Seal.

Place the HHT within 60 cm. from the seal and then press the READ key on the HHT. If the OK notation appears on the HHT's display, you hear 2 beeps, and you know the asset was not opened on the way from the last SET site to the Reading site. If a Tampered notation appears and you hear a long beep, you know that the seal was tampered on the way. You can know when it occurred (see details below).

Note: If you chose to write down the ID Number, you can compare the ID and the sealing stamp to the written numbers you have on the bill of lading (or on the FAX copy).

4. Operating Instructions

4.1 Initialization

Turn the HHT on by pressing the **ON** key and verify that the green light illuminates.

After a few seconds the main screen appears:

<p>Hi-G-Seal H/h Termina Date: 12/03/97 Time: 12:56</p>
--

While the main screen is shown, you may change the screen **contrast** using the up (^) and down (V) keys.

NOTE: If no keys are touched for 5 minutes, the HHT will automatically shut- off, in order to save batteries.

In case you want to see the site, you are located at, which is stored in the HHT's memory, or you want to update the site to your present location, press the **SITE** key. The following screen appears:

<p><i>Present</i> Site: 123 Enter New Site: _ _ _</p>
--

Enter 3 digits (from 000 to 255) encoding your site. After each digit you enter, the cursor will move to the next digit location. Pressing the **ENTER** key will store the new site. In case the code has less than 3 digits you must enter leading zeroes (e.g. if your site code is 1, you must enter 001). The new site will be stored along with all the other sealing data till the next change of the site.

You may, of course, change the site at every stage during the operation of the HHT.

4.2 Reading a Seal

Press the **READ** key. There are 3 possible events:

One. The seal was not tampered on the way. The screen will be as follows

Seal #: 1234567890
Stamp: 11231231
OK. Set at:
12/04/97 12:45

And you will hear 2 beeps.

Two. The seal was tampered on the way. The screen will be as follows:

Seal #: 1234557890
Stamp: 12312311
Tamp. Set at:
12/04/97 12:45

And you will hear a long beep.

Three. The seal is new to the terminal. The screen will be as follows:

Seal #:1234567890 not exist. Cont? NO YES
--

And you would hear a long beep.

In this case if you want to read the seal, choose **YES**, and you will complete the **READ** procedure.

In case you want to **SET** the seal, choose **NO**, and you will have to press the **SET** button.

In case memory is full, the following display appears:

Memory is Full Delete Seals

In this case you have to delete unused seals using the Clear Data option from the Menu. If you do not delete a seal, the **READ** process will not be completed.

NOTES:

- While reading, make sure there is no other seal in the vicinity of the seal you want to read and of the HHT. Other seals must be at least 60 cm. away.
- While reading, if the seal's battery is low the following message appears.

Critical Low Battery In the SEAL!!
--

4.3 Setting a Seal

Setting a seal is a critical event in the process, an option is available for password use. According to the Configuration setting in the Menu, you may select whether to use a password or not.

Press the **SET** key.

If you have entered a password the following message appears:

Enter Password:

If you entered the wrong password, the following message appears:

**Password
Incorrect**

Press the **ENTER** key for another try.

If the password is correct, the following screen appears:

Seal #:1234567890
Stamp:11231231
Set : OK
12/04/97 12:57

If there is not enough memory, the following message appears:

Memory is Full
Erase Data?
No
Yes

You can select between the Yes and No options. Selecting the “Yes” SETs the Seal and the following display appears:

Seal #:1234567890
Stamp:11231231
Set: OK
12/04/97 12:57

Selecting the “No” option will resume the SET command.

In case the seal already exists in the HHT's memory, the following message appears:

ID 1234567890
Exist. Delete it?
Yes
No

You can select between the Yes and No options. Selecting the “Yes” SETs the Seal. Selecting the “No” option will resume the SET command.

4.4 Special Functions

In order to perform other functions press the **MENU** key. The following screen appears:

VIEW DATA
CLEAR DATA
STATISTICS
SETUP DATE

You can scroll between the options using the up (^) and down (v) arrows. A long press on an arrow causes a rapid scrolling.

While scrolling, the following options are also displayed.

SETUP TIME
SETUP ZONE
DISPLAY VER.
CONFIGURATION
DIAGNOSTICS

Pressing the **ENTER** key activates the selected function. Pressing the **Esc** key will resume to the previous screen.

- **View Data**

Data Structure

Before going into details, you must understand the basic structure in which the events’ data are organized.

An event is created after a **READ** operation, but only if something has been occurred to the seal from the previous reading. Occurrences that cause an event are: **SET** of the seal, **OPEN**ing or Closing (**CLSE**) the seal, **TAMP**ering (changing the seal's resistance) with the seal, and Low Battery (**LB**) of the seal.

Each time there is an event it is written in the reader’s database. Each time you **SET** a seal a new page is created. A page contains up to 10 events (for IG-SA-20 or up to 100 events for IG-SA-22) that occurred to the seal starting with the last **SET** operation. For example, for a new seal, the page will contain the **SET** event. If a tampering event occurs, after the next

READ operation, the page will contain the SET event and the TAMP event. If then, the seal was opened and then closed, after the next READ operation the page will contain 4 events: SET, TAMP, OPEN CLSE.

Selecting the **View Data** function displays the following screen:

View Data VIEW FROM LIST VIEW BY ID VIEW BY SITE
--

You can select between these 3 options using the arrow, up and down keys.

Selecting the **View by ID** displays the following screen:

View by ID Enter seal ID -----

Entering the Seal ID and pressing the **ENTER** key display the following screen (The first two rows are displayed alternately. If there is a TAMPering event and/or a Low Battery event, the last 2 rows will be displayed alternatively too):

Seal # 1234567890 PAGE# 001 OF 002 SET 12/04 13:57 At Site : 123 OPEN:22 CLSE:22 TAMP:01 LB
--

The above example shows the first page out of 2 pages. There are 47 events in that page : 1 - for the SET, 22 - OPENings, 22 - CLSEing, 1 - TAMPering (change of the wire) and there is a Low Battery sign for that seal.

Pressing the **ENTER** key again will open the whole page of events (The first two rows are displayed alternately).

Seal # 1234567890 EVENTS LIST CLSE 12/04 13:35 OPEN 12/04 13:32 SET 12/04 12:41

As written above, you may see up to 10 events for one page in case of IG-SA-20 (or up to 100 events in case of IG-SA-22). The first 8 events (for IG-SA-20) are consecutive events, starting at the SET operation, and the last 2 events, are the 2 last events occurred to the seal. For example, if there were 16 events including the SET event, you will see SET as the first event, then 7 consecutive other events, and then the last 2 events for events number 15 and 16 (events number 9-14 are lost). The same logic exists for

IG-SA-22. The difference is the total amount of events (100 instead of 10) and the stack for the last events (5 instead of 2)

Pressing the **ENTER** key on a specific row, displays the following detailed event window:

ID: 1234567890	
Stamp:11231231	
OPEN	at:
12/04/97	11:07

Pressing the **ENTER** key returns you to the View by ID menu.

The same logic is applied when you choose the **View from List** or the **View by Site** options, except for the initial procedure, in which you reach the desired seal.

In the **View from List** procedure you also have a down counter of events (**EV.CNT**) for each one of the seals on the list. When the counter is 0000 the seal must be replaced by a new one.

Selecting the **View from List** displays the following screen:

View From List	
Seal ID	EV.CNT
1234567890	1240
0012345678	0320

In this example, seal # 1234567890 has 1240 events left.

You may scroll between the seals using the up and down keys. You can choose the ID by pressing the **ENTER** key when the cursor is on the left of the desired seal.

Selecting the **View by Site** displays the following screen:

View by Site
Enter Your Site

Entering the Site code and pressing the **ENTER** key displays the following screen:

Seal ID Site 123
1234567890
1234567891
1234567899

The above screen displays all the seals set at the selected site. You can scroll between the rows one by one by pressing the up and down keys. You can choose the **ID** by pressing the **ENTER** key when the cursor is on the left of the desired seal. You can see the events' list by pressing the **ENTER** key again. Pressing the **ENTER** key again will show the event's details. Pressing the **ENTER** key again returns you to the View Data menu.

- **Clear Data**

Selecting the **Clear Data** function displays the following screen:

Clear Data CLEAR ALL CLEAR FROM LIST CLEAR BY ID
--

Selecting the **Clear All** option erases all the seals' data from the memory.

Pressing the **ENTER** key selects the seal to be erased.

Prior to deleting the data, the following alert window appears:

Clear Data No Yes

You can select between the options using the up and down arrows.

Pressing the **ENTER** key selects the option.

Selecting the **Clear From List** option displays the following screen:

Clear From List Seal ID 0000001029 0000001037

You select the seal to be erased and press the **ENTER** key.

You will get the following warning screen:

Clear ID 0000001029 No Yes
--

You can select between the options using the up and down arrows.

Pressing the **ENTER** key selects the option.

Selecting the **Clear By ID** option lets you enter the ID number to be deleted

<p>Clear By ID</p> <p>Enter Seal ID</p> <p>-----</p>

You enter the seal ID to be erased and press the ENTER key.

The following warning screen appears:

<p>Clear By ID</p> <p>No</p> <p>Yes</p>
--

You can select between the options using the up and down arrows.
Pressing the **ENTER** key selects the option.

- **Statistics**

This special function lets you know the available free memory left for more seals events. Choosing this option will cause the following screen to appear:

Hi-G-Seal
H/h Terminal
Free memory for
168 seals events

- **Setup Date**

Selecting the **Setup Date** function displays the following screen:

Setup Date
Date : 12/04/1997
Enter New Date:
--/--/-----

To change the date, enter the digits related to DD/MM/YY (Day/Month/Year) for the European format (if you chose this format in the configuration function). Each time you press a numeric key the cursor moves in a cyclic manner to the next digit location. Pressing the **ENTER** key sets the new date.

- **Setup Time**

Selecting the **Setup Time** function displays the following screen:

<p>Setup Time</p> <p>Time: 12:54</p> <p>Enter New Time: --:--</p>
--

To change the time, enter the digits related to HH/MM (Hour/Minute). Each time you press a numeric key the cursor moves in a cyclic manner to the next digit location. Pressing the **ENTER** key sets the new time.

- **Setup Zone**

All the seals are set according to GMT (Grinwich Mean Time). The Hand Held Terminal has the local time. In each country, for each Time Zone, an offset must be entered (time difference) between the local zone to GMT. For example: In Great Britain the difference is 0. In other Western European countries the difference is +1. In Eastern USA the difference is -5 and so on.

Choosing the **Setup Zone** function displays the following screen:

<p>Set Time Zone</p> <p>Offset hr.: +00</p>
--

By using the up (^) and down (V) arrows you can set the desired offset from the GMT. Pressing the **ENTER** key sets the chosen offset.

- **Display Ver.**

Selecting the **Display Ver.** function displays the software version:

<p>Hi-G-Seal</p> <p>H/h Terminal</p> <p>Version</p> <p>2.00</p>

- **Configuration**

Selecting the **Configuration** function displays the following screen:

Configuration
SET PASSWORD
DATE FORMAT

You can select between the options by using the up and down keys.
Pressing the **ENTER** key selects the option.

- **Set Password**

If you select the **Set Password** option, the following screen appears:

Password Setting
No
Yes

This option allows you either to decide whether you want to use a password for the SET operation or to change an existing password.
In order to enforce the use of a password for the SET function, select the “Yes” option. The following screen appears:

Password Setting
Enter New Password

Enter your new password (up to 6 digits) and press the ENTER key.
If you don't want the use of a password for the SET function, select the “No” option.
If you want to cancel the use of an existing password for the SET function, press the “No” option.
If you want to change the password press the “Yes” key.
In both cases, if you want to change the password or if you want to cancel the use of a password for the SET function, the following screen appears:

Password Setting
Enter Previous Password

In case you entered a wrong password you will see the following screen;

Password Setting Your password Is Incorrect
--

You will have to retry the whole process.

In case you entered the right password and you chose to change the password, the screen that allows you to enter your new 6 digit password appears:

Password Setting Enter New Password -----

- **Date Format**

If you select the Set Date Format, the following screen appears:

Set Date Format USA FORMAT EUROPE FORMAT

European format: DD/MM/YY

USA format: MM/DD/YY

You can select between the two formats. Select the correct one by pressing the **ENTER** key.

Selection of the Diagnostics is for technicians only.

5. Troubleshooting

5.1 Low voltage

If there is a low voltage, the following message appears:

Low Battery
Replace the Battery!

And you will hear a long beep.

The only operation you can activate now is to turn the HHT off!

Replace batteries. See para. 2.1 on how to replace batteries.

5.2 Self Test Failure

After turning on the HHT, it performs an automatic self-test. If there is any technical problem, the following message appears:




Self-Test Failed!
Call Service

If this occurs, call for a service technician or send the device to the manufacturer.

5.3 Communication Failure


When you perform the **READ** or **SET** functions, and there is a communication error between the HHT and the seal, the following message appears.



If this occurs, try to decrease the distance between the HHT and the seal.
Try to change the angle between the HHT and the seal (the optimal angle is when the HHT is below the seal and parallel to it).
Try to replace the batteries in the HHT.
Try to communicate with another seal.

5.4 Wire Failure

If the following message appears, after performing a SET function, you must check the wire connection to the seal or replace the wire.



5.5 General Failure

In case you face an unexplainable problem with your HHT, it is recommended to turn it OFF and after a minute to turn it ON again. If the problem appears again call for a service technician or send the device to the manufacturer.

5.6 Low Battery of the seal

In case there is a **LB** event while reading a seal (in the View Data procedure) it could be a temporary state. If you see the **LB** sign once in many readings, you may ignore it. When you see it every once in a while, it is a sign of the end of the seal's battery life. In this case you must use a new seal.

6. Technical Specifications

6.1 Hand Held Terminal

Power: 4 batteries, 1.5 V “AA” size.
Communication Distance: 60 cm max.
Operating Temperature: 0 ° to 50 ° C
Storage Temperature: -20 ° to 80 ° C
Storage Memory Capacity: up to 170 seals.


6.2 Seal

Power: internal lithium battery.
Communication Distance: 60 cm max.
Operating Temperature: -20 ° to 60 ° C
Storage Temperature: -20 ° to 80 ° C
Storage Memory Capacity: up to 10 events.


Operating instructions

1. The unpacked units are for continues transmission only this units cannot communicate with the reader.
2. operation instruction.


2.1 OFF




2.2 Transmit 250KHz carrier



2.3 Transmit 250KHz carrier with 2KHz data modulation



2.4 Transmit 250KHz carrier with 1KHz data modulation.



3. For continues transmission with the reader, Press MENU, select DIAGNOSTICS, select MAINTENANCE, enter password **051148**, Select operation mode.

For general operation of the reader, refer to the user manual.

4. In general , The system was not designed for continues transmission , so make this transmission as short as possible !!!!!

FCC requirements § 2.1033 (b)(4)

**CIRCUIT DESCRIPTION,
BLOCK DIAGRAM &
SCHEMATIC DIAGRAM**

This page is followed by the Hi-G-Seal transmitter description, block and schematic diagrams.

1. **General.**

HI-G-SEAL system is a system that enables sealing of containers and a verity of assets that need to be sealed against and monitored for any trail to tamper with them.

The seals will be monitored remotely by radio terminals that are part of the HI-G-SEAL system.

The seal will provide the inspector instant and comprehensive sealing verification details. The seal will log every opening and closing on top of the setting at the beginning.

With each event the seal will log the time stamp of the event and will modify the original seal stamp.

Sealing wire will be made from a multi-stranded wire with 48 strands. Only part of the strands will be connected from end to end.

The number of wires connected will be random.

2. **Seal Technical Specifications.**

2.1 Electrical Specifications.

Modulation: AM (Pulsed RF) ASK

Tx Frequency: 250 kHz \pm 1.5%.

Rx Frequency: 250 kHz \pm 0.5%.

Transmitted Output Power: 40mW max.

Data Throughput: 2 kbit/sec transmit 0.5kbit/s receive.

Current Consumption: 10 μ A max @ quiescent.

10 mA max @ Tx

2 mA max @ Rx

Seals Resistance Range: 20 - 500 Ω

Seal Resistance Stability: 100ppm max over full temperature range.

Seal Resistance Measurement Resolution: 0.5 % from full scale (8 bits A/D).

Seal Resistance Measurement Stability : \pm 3 % or \pm 1 LSB whichever is greater.

Seal Resistance Random Values: by random number of connected wires.

Seal Wire length: 25 cm, 50 cm, and 100 cm.

Power: Lithium cell battery 3.6V TL2186 model by TADIRAN or equivalent.

Battery lifetime: 4 years at 1 full memory reading per day , over full temperature range.

2.2 Functional Specifications.

Meets FCC requirements. part 15 subpart C. 15.209.

Seal Engagement: one time use or optionally multi use.

Real Time Clock: GMT. 30 min per year accuracy over full temperature range.

Memory: last 10 events or 100 events optional.

Memory Data Type: seal stamp, time of event, low battery, and random value for each new event.

Interrogation Distance: 0.6 meter max.

Receiver's Discrimination: 2 meters. (The minimum distance between two adjacent Seals)

Interrogation Rate: 1 reading per sec max (in 10-event case). 100 events

Low Battery Indication: yes

Seal wire Outer Diameter: 10 mm max.

Mounting: Wall mount unit, or directly using double stick (mechanical mounting to the container or a wall)

Mechanical Dimensions: 47 X 36 X 20 mm (not to include the seal wire or seal plate)

MTBF: 40000 hours.

Environmental Specifications.

- Operating & storage Temperature: - 20 to 70 °C.

- Mechanical Vibrations and Shocks: To suit vehicular conditions according to MIL-STD-810D.

- Splash Proof.