

INVENGO MEDIO P200u HF READER



About Invengo's Mid-Range HF Reader

Invengo's Medio P200u is a 13.56MHz HF reader for proximity read/write applications. Its small size and affordable price make it an ideal item-level tracking solution for most industrial applications. Medio P200u is packaged in a light-weight, rugged and ergonomic casing, providing a low cost of ownership RFID solution.



Invengo – the global RFID technology provider – is a leading developer and manufacturer of high quality, intelligent RAIN RFID and HF/NFC connectivity solutions and consumables (tags & inlays) utilized in the Internet of Things. With a focus on RFID innovation, Invengo has created a leading product line in retail, (industrial) laundry, library, (public) transportation, healthcare, and many other industries.

Invengo Technology Pte. Ltd. (SG) is the International Headquarters of Invengo Information Technology Co. Ltd, listed on Shenzhen Stock Exchange (SZSE: 002161.SZ). Employing over 600 people globally, Invengo is one of the largest publicly traded, RFID / IoT oriented companies in the world.

Key Benefits

- Small size and light weight
- Robust with an ergonomic casing
- Cost-effective reader solution

Product Specifications

Electrical

Operating Frequency	13,56 MHz
Protocols Supported	ISO 15693, ISO 1800-3 Mode 1, NXP ICODE 1
RF Output Power	Max 1W
Communication Protocol	Standalone Mode: ASCII Protocol, User configurable Standard Mode: Invengo STX-E Serial Communication Protocol
Communication Interface	USB
Antenna Connection	SMA
Power Supply	12 VDC (100-240V, 50/60 Hz to 12 VDC Power Supply included)

Mechanical

Dimensions	123 x 68 x 30 mm (4.8 x 2.6 x 1.2 in)
Weight	150 g (5.3 oz)
Operating Temperature	0°C to 55°C (32°F to 131°F)

Software

Configuration Tool	PxExplorer
SDK	Medio STX DLLs Package & Java Package Universal SDK (C++/.NET)

Product reference	DDP14046
--------------------------	----------

Additional Information

Communicating via its USB interface, the Medio P200u is a mid-range reader with 1W power output, operating in either standard or standalone mode. When operating in standalone mode, the reader can automatically report data from RFID tags which have been read.

Connected to a fixed or portable RFID antenna, the Medio P200u reader provides an affordable and effective RFID station to identify RFID-tagged products. It also offers a flexible platform to address various connectivity requirements.

For over 15 years, we've been providing RFID systems that exceed our customer's most demanding requirements. We work with hundreds of companies to embed RFID item-level tracking into their infrastructure. We know that by adding this capability to your product, you can offer unique advantages to deliver value-added services to your customers.

APAC

Invengo Technology Pte. Ltd
10 Kallang Avenue
#05-15 Tower 2, Aperia
Singapore 339510

Office: +65 6702 3909
sales.apac@invengo.com

Americas

Invengo Technology Corp.
2700-160 Sumner Blvd.
Raleigh, NC 27616
United States of America

Office: +1 919 890 0202
sales.americas@invengo.com

EMEA

Invengo Technologies
180 Voie Ariane – Athélia 1
13600 La Ciotat
France

Office: +33 413 96 1111
sales.emea@invengo.com

FCC warning:

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator & your body.