

KFe Series Processor Settings

November 13, 2001



KF850EF triamp

OUTPUT	Name	Low	Mid	Hi
GAIN	(dB)	2.0	-4.0	-1.0
DELAY	(ms)	0.00	0.00	0.71
POLARITY		Positive	Positive	Positive
HPF	Freq (Hz)	40	281	1410
	Slope (dB)	24	24	24
	Shape	Butterworth	Linkwitz-Riley	Butterworth
LPF	Freq (Hz)	306	1410	16000
	Slope (dB)	24	18	24
	Shape	Linkwitz-Riley	Butterworth	Butterworth
PEQ1	Freq (Hz)	79	315	1680
	Level (dB)	12.0	4.0	-1.0
	Type	Parametric	Parametric	Parametric
	Q	2.00	2.00	5.04
	(Bandwidth)	0.71	0.50	0.20
PEQ2	Freq (Hz)		2240	7550
	Level (dB)		-24.0	-1.0
	Type		Parametric	Parametric
	Q		32.00	4.00
	(Bandwidth)		0.09	0.25
PEQ3	Freq (Hz)		1370	13070
	Level (dB)		6.0	12.5
	Type		Parametric	Parametric
	Q		8.00	4.00
	(Bandwidth)		0.13	0.36
PEQ4	Freq (Hz)			
	Level (dB)			
	Type			
	Q			
	(Bandwidth)			
PEQ5	Freq (Hz)			
	Level (dB)			
	Type			
	Q			
	(Bandwidth)			

NOTE: To use system with sub, high pass LF @ 80 Hz (24 dB Butterworth) & do not use PEQ 1.

KFe Series Processor Settings

November 13, 2001



KF853D biamp/BH853

OUTPUT	Name	Low	Mid	Hi
GAIN	(dB)	4.0	1.0	0.0
DELAY	(ms)	0.00	0.03	0.00
POLARITY		Positive	Positive	Positive
HPF	Freq (Hz)	40	250	1490
	Slope (dB)	24	24	24
	Shape	Butterworth	Butterworth	Butterworth
LPF	Freq (Hz)	250	1330	thru
	Slope (dB)	24	24	
	Shape	Butterworth	Butterworth	
PEQ1	Freq (Hz)	57		2660
	Level (dB)	6.0		-5.1
	Type	Parametric		Parametric
	Q	2.00		1.33
	(Bandwidth)	0.50		0.75
PEQ2	Freq (Hz)			10990
	Level (dB)			7.0
	Type			Parametric
	Q			2.00
	(Bandwidth)			0.53
PEQ3	Freq (Hz)			7120
	Level (dB)			1.5
	Type			Parametric
	Q			4.00
	(Bandwidth)			0.25
PEQ4	Freq (Hz)			
	Level (dB)			
	Type			
	Q			
	(Bandwidth)			
PEQ5	Freq (Hz)			
	Level (dB)			
	Type			
	Q			
	(Bandwidth)			

NOTE: To use system with sub, high pass LF @ 80 Hz (24 dB Butterworth) & do not use PEQ 1.

KFe Series Processor Settings

November 13, 2001



KF855EF triamp*

OUTPUT	Name	Mid	Hi 1	Hi 2
GAIN	(dB)	-4.0	-1.0	-1.0
DELAY	(ms)	0.00	0.71	0.71
POLARITY		Positive	Positive	Positive
HPF	Freq (Hz)	280	1414	1414
	Slope (dB)	24	24	24
	Shape	Linkwitz-Riley	Butterworth	Butterworth
LPF	Freq (Hz)	1414	16000	16000
	Slope (dB)	18	24	24
	Shape	Butterworth	Butterworth	Butterworth
PEQ1	Freq (Hz)	315	1682	1682
	Level (dB)	4.0	-1.0	-1.0
	Type	Parametric	Parametric	Parametric
	Q	2.00	4.04	5.04
	(Bandwidth)	0.50	0.25	0.20
PEQ2	Freq (Hz)	2245	7551	7551
	Level (dB)	-24.0	-1.0	-1.0
	Type	Parametric	Parametric	Parametric
	Q	32.00	3.00	4.00
	(Bandwidth)	0.09	0.33	0.25
PEQ3	Freq (Hz)	1374	13071	13071
	Level (dB)	6.0	12.5	12.5
	Type	Parametric	Parametric	Parametric
	Q	8.00	3.00	4.00
	(Bandwidth)	0.13	0.48	0.36
PEQ4	Freq (Hz)			
	Level (dB)			
	Type			
	Q			
	(Bandwidth)			
PEQ5	Freq (Hz)			
	Level (dB)			
	Type			
	Q			
	(Bandwidth)			

* Use same Hi settings when paralleling HF downfill horns.

NOTE: To use system with sub, high pass LF @ 80 Hz (24 dB Butterworth) & do not use PEQ 1.

KFe Series Processor Settings

November 13, 2001



KF650e triamp

KF650e biamp

OUTPUT	Name
GAIN	(dB)
DELAY	(ms)
POLARITY	
HPF	Freq (Hz)
	Slope (dB)
	Shape
LPF	Freq (Hz)
	Slope (dB)
	Shape
PEQ1	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ2	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ3	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ4	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ5	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)

Low	Mid	Hi
6.0	1.0	0.0
0.00	0.00	1.32
Positive	Positive	Positive
45	257	1580
24	24	24
Butterworth	Linkwitz-Riley	Butterworth
210	1120	thru
24	24	
Linkwitz-Riley	Linkwitz-Riley	
61	545	1370
7.0	-2.8	-1.5
Parametric	Parametric	Parametric
2.00	8.00	5.04
0.53	0.13	0.20
	1090	2990
	2.0	1.5
	Parametric	Parametric
	2.00	1.50
	0.5	0.67
		17440
		5.0
		Parametric
		2.00
		0.50

Low	Mid/Hi
8.0	0.0
0.00	0.00
Positive	Positive
45	216
24	24
Butterworth	Butterworth
167	thru
24	
Linkwitz-Riley	
61	2590
6.0	3.5
Parametric	Parametric
2.00	1.00
0.50	1.00
	687
	1.5
	Parametric
	2.24
	0.45
	19580
	3.0
	Parametric
	2.00
	0.50
	561
	-3.0
	Parametric
	10.10
	0.10
	1290
	-2.0
	Parametric
	10.10
	0.10

NOTE: To use systems with sub, high pass LF @ 80 Hz (24 dB Butterworth) & do not use PEQ 1.

KFe Series Processor Settings

November 13, 2001



KF695e triamp

KF695e biamp

OUTPUT	Name
GAIN	(dB)
DELAY	(ms)
POLARITY	
HPF	Freq (Hz)
	Slope (dB)
	Shape
LPF	Freq (Hz)
	Slope (dB)
	Shape
PEQ1	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ2	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ3	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ4	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ5	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)

Low	Mid	Hi
4.0	1.2	0.0
0.00	0.00	0.28
Positive	Positive	Positive
40	281	1490
24	24	24
Butterworth	Butterworth	Butterworth
281	1490	thru
24	24	
Butterworth	Linkwitz-Riley	
64	578	3260
8.0	-1.0	-1.7
Parametric	Parametric	Parametric
2.00	3.00	4.00
0.56	0.33	0.25
	866	10670
	1.5	8.0
	Parametric	Parametric
	5.04	2.83
	0.20	0.40
		2000
		1.5
		Parametric
		3.00
		0.33

Low	Mid/Hi
5.0	0.0
0.00	0.00
Positive	Positive
40	297
24	24
Butterworth	Butterworth
281	thru
24	
Linkwitz-Riley	
64	2180
8.0	4.0
Parametric	Parametric
2.00	2.67
0.56	0.37
	10670
	7.0
	Parametric
	3.00
	0.35
	5820
	-2.5
	Parametric
	2.67
	0.37
	2590
	1.6
	Parametric
	0.67
	1.49

NOTE: To use systems with sub, high pass LF @ 80 Hz (24 dB Butterworth) & do not use PEQ 1.

KFe Series Processor Settings

November 13, 2001



KF300e biamp

OUTPUT	Name	Low	Mid/Hi
GAIN	(dB)	6.0	0.0
DELAY	(ms)	0.36	0.00
POLARITY		Positive	Positive
HPF	Freq (Hz)	40	459
	Slope (dB)	24	24
	Shape	Butterworth	Linkwitz-Riley
LPF	Freq (Hz)	459	thru
	Slope (dB)	24	
	Shape	Butterworth	
PEQ1	Freq (Hz)	56	944
	Level (dB)	8.0	-1.0
	Type	Parametric	Parametric
	Q	2.00	5.04
	(Bandwidth)	0.56	0.20
PEQ2	Freq (Hz)		20150
	Level (dB)		5.0
	Type		Parametric
	Q		1.00
	(Bandwidth)		1.00
PEQ3	Freq (Hz)		9510
	Level (dB)		3.0
	Type		Parametric
	Q		5.04
	(Bandwidth)		0.20
PEQ4	Freq (Hz)		561
	Level (dB)		1.5
	Type		Parametric
	Q		1.89
	(Bandwidth)		0.53
PEQ5	Freq (Hz)		2110
	Level (dB)		1.7
	Type		Parametric
	Q		4.00
	(Bandwidth)		0.25

NOTE: To use system with sub, high pass LF @ 80 Hz (24 dB Butterworth) & do not use PEQ 1.