

APX™ TWO-WAY RADIOS

# APX MOBILE 03 CONTROL HEAD USER GUIDE



Draft 1c



# ASTRO® APX™ O3 Control Head Mobile Radio Quick Reference Card

## RF Energy Exposure and Product Safety Guide for Mobile Two-way Radios




CAUTION

Before using this product, read the operating instructions for safe usage contained in the Product Safety and RF Exposure booklet enclosed with your radio.

### ATTENTION!

This radio is restricted to occupational use only to satisfy FCC RF energy exposure requirements. Before using this product, read the guide enclosed with your radio which contains important operating instructions for safe usage and RF energy awareness and control for compliance with applicable standards and regulations.

### Radio Controls



### Radio On/Off

Press the Power On/Off button to toggle the power on or off.

### Adjusting Volume

Press the Up arrow on the Volume Rocker to increase volume.

OR

Press the Down arrow on the Volume Rocker to decrease the volume.

### Selecting a Zone

1 or to ZONE.

2 Press the **Menu Select** button directly below **Zone**. The display shows the current zone and channel.

3 or until the desired zone is displayed.

4 Press or the **PTT** button to confirm the selected zone number.

5 Press the **PTT** button to begin transmitting on the displayed zone channel.

### Selecting a Channel

1 Press the **Mode Rocker Up** or **Down** to the desired channel.

OR

or to **Chan** and press the **Menu Select** button directly below **Chan**. The display shows the current zone and channel.

2 Press the **Mode Rocker Up** or **Down** to the desired channel.

3 Press or the **PTT** button to confirm the channel.

4 Press the **PTT** button to transmit on the displayed zone channel.

### Receiving and Transmitting (Conventional Mode)

1 Listen for a transmission.

2 Adjust the **Volume Rocker** if necessary.

3 If you hear no activity, press and hold the **PTT** button to start your conversation.

### Receiving and Transmitting (Trunked Mode)

1 Press the **PTT** button.

2 If you hear two, short, high-pitched tones, or if you hear no tone and the red indicator lights steadily, then proceed with your message.

3 Release the **PTT** button to receive (listen).

### Sending an Emergency Alarm

1 Press the preprogrammed **Emergency** button. A tone sounds and the display shows **Emergency**.

2 A dispatcher acknowledgment **Ack Received** display follows.

**AND, Trunking Only:**

A high-pitched tone indicates that the alarm has been received by the trunked system's central controller.

3 Press and hold the emergency button or the **PTT** button to return to normal operation.

*To exit emergency at any time, press and hold the **Emergency** button.*



PLMLN5591E

## ■ Sending an Emergency Call (Trunking Only)

- 1 Press preprogrammed **Emergency** button.
- 2 A tone sounds and the display shows **Emergency**.  
**OR**  
A short low-pitched tone sounds when the selected channel does not support emergency.
- 3 Press and hold the **PTT** button. Speak clearly into the microphone.
- 4 Release the **PTT** to end the transmission.

*To exit emergency at any time, press and hold the **Emergency** button.*

## ■ Sending a Silent Emergency Alarm

- 1 Press the preprogrammed **Emergency** button to activate the silent alarm feature.
- 2 The display does not change; the LED does not light up, and there is no tone.

*If silent emergency alarm is used with emergency call, pressing the **PTT** button exits the silent mode and initiates the emergency call..*

## ■ Display Status Icons

	Receiving a call or data.
	Transmitting a call or data.
	The more stripes, the stronger the signal strength for the current site (trunking only).
	Direct radio-to-radio communication or communication through a repeater. <b>On</b> = Direct <b>Off</b> = Repeater

	This channel is being monitored.
	Voice muting the affiliated trunking talkgroup or selected conventional channel. <b>On</b> = Enabled <b>Off</b> = Disabled
<b>H</b> OR <b>L</b>	<b>L</b> = Radio is set at Low power. <b>H</b> = Radio is set at High power.
	Scanning a scan list.
	<b>Blinking dot</b> = Detects activity on the Priority-One Channel during scan. <b>Steady dot</b> = Detects activity on the Priority-Two Channel during scan.
	The vote scan feature is enabled.
	<b>On</b> = Secure operation. <b>Off</b> = Clear operation. <b>Blinking</b> = Receiving an encrypted voice call.
	<b>On</b> = AES Secure operation. <b>Off</b> = Clear operation. <b>Blinking</b> = Receiving an encrypted voice call.


	<b>On</b> = Location feature enabled, and location signal available. <b>Off</b> = Location feature disabled. <b>Blinking</b> = Location feature enabled, but location signal unavailable.
<b>IP</b> 	<b>On</b> = User is currently associated with the radio. <b>Off</b> = User is currently not associated with the radio. <b>Blinking</b> = Device registration or user registration with the server failed due to an invalid username or pin.
	Data activity is present.
<b>HEX</b>	Indicates that the text entry is currently in hexadecimal mode.

MOTOROLA, MOTO, MOTOROLA SOLUTIONS and the Stylized M logo are trademarks or registered trademarks of Motorola Trademark Holdings, LLC and are used under license. All other trademarks are the property of their respective owners.

© 2009, 2011 – 2012 by Motorola Solutions, Inc. All Rights Reserved. 09/12  
1303 East Algonquin Road, Schaumburg, Illinois 60196, U.S.A.




## Menu Navigation



## Declaration of Conformity

This declaration is applicable to your radio **only** if your radio is labeled with the FCC logo shown below.

<p><b>DECLARATION OF CONFORMITY</b> Per FCC CFR 47 Part 2 Section 2.1077(a)</p> <p style="text-align: center;"> Draft 1c</p> <p>Responsible Party Name: Motorola Solutions, Inc. Address: Motorola Solutions, Inc. 1303 East Algonquin Road, Schaumburg, Illinois 60196, U.S.A. Phone Number: 1-800-927-2744</p> <p>Hereby declares that the product:     Model Name: <b>APX Mobile</b></p> <p>conforms to the following regulations:     FCC Part 15, subpart B, section 15.107(a), 15.107(d) and section 15.109(a)</p> <p><b>Class B Digital Device</b></p> <p>As a personal computer peripheral, this device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:</p> <ol style="list-style-type: none"><li>1. This device may not cause harmful interference, and</li><li>2. This device must accept any interference received, including interference that may cause undesired operation.</li></ol>
--

**Note:** This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Draft 1c

## Contents

This User Guide contains all the information you need to use the APX™ Mobile Radios.

### Declaration of Conformity . . . . . i

### Important Safety Information . . . . . ix

RF Energy Exposure and Product Safety Guide for Mobile Two-way Radios . . . . . ix

### Software Version . . . . . ix

Notice to Users (FCC and Industry Canada) . . . . . ix

### Informations importantes sur la sécurité . . . . . x

Sécurité du produit et respect des lignes directrices concernant l'exposition à l'énergie RF . . . . . x

### Version du logiciel . . . . . x

Avis aux utilisateurs (FCC et Industrie Canada) . . . . . xi

### Computer Software Copyrights . . . . . xi

### Documentation Copyrights . . . . . xi

### Disclaimer . . . . . xii

### Getting Started . . . . . 1

How to Use This User Guide . . . . . 1

Notations Used in This Manual . . . . . 1

Additional Performance Enhancement . . . . . 2

Dynamic System Resilience (DSR) . . . . . 2

CrossTalk Prevention . . . . . 2

Encrypted Integrated Data (EID) . . . . . 2

SecureNet . . . . . 2

What Your Dealer/System Administrator

Can Tell You . . . . . 3

### Preparing Your Radio for Use . . . . . 3

Turning On the Radio . . . . . 4

Validating Compatibility During Power Up . . . . . 4

Adjusting the Volume . . . . . 5

### Identifying Radio Controls . . . . . 5

Radio Parts and Controls . . . . . 6

O3 Control Head . . . . . 6

Programmable Features . . . . . 7

Assignable Radio Functions . . . . . 7

Assignable Settings or Utility Functions . . . . . 9

Draft 1c



Accessing the Preprogrammed Functions .....	9
Using the Menu Select Buttons .....	9
Using the Navigation Buttons .....	10
Home Button .....	10
Data Feature Button .....	10
4-Way Navigation Button .....	10
Volume Rocker .....	10
Mode Rocker .....	10
Using the Keypad .....	11
Keypad Characters – Uppercase Mode .....	11
Keypad Characters – Lowercase Mode .....	12
Keypad Characters – Numeric Mode .....	13
Keypad Characters – Hexadecimal Mode .....	14
Push-To-Talk (PTT) Button .....	15

## **Identifying Status Indicators ..... 15**

Status Icons .....	16
Text Messaging Service (TMS) Icons .....	17
Status Icons .....	18
TMS Menu Options .....	19
LED Indicator .....	20
Intelligent Lighting Indicators .....	21
Alert Tones .....	22
Phone Call Display and Alert Prompts .....	25

## **General Radio Operation ..... 26**

Selecting a Zone .....	26
Selecting a Radio Channel .....	27
Using Channel Search Button .....	27
Using Mode Select Feature .....	28
Saving a Zone and Channel to a Softkey .....	29
Saving a Zone and Channel to a Keypad Button .....	29
Receiving and Responding to a Radio Call .....	30
Receiving and Responding to a Talkgroup Call .....	30
Receiving and Responding to a Private Call (Trunking Only) .....	31
Receiving and Responding to a Telephone Call .....	32
Making a Radio Call .....	32
Making a Talkgroup Call .....	32
Making a Private Call (Trunking Only) .....	33
Making a Telephone Call .....	34
Repeater or Direct Operation .....	35
Monitoring Features .....	36
Monitoring a Channel .....	36
Conventional Mode Operation .....	37

## **Advanced Features ..... 38**

Advanced Call Features .....	38
Calling a Phone Not in the List .....	38

Draft 16



Receiving and Making a Selective Call (Conventional Only) . . . . .	39	Scan . . . . .	51
Receiving a Selective Call . . . . .	39	Turning Scan On or Off . . . . .	51
Making a Selective Call . . . . .	39	Turning Scan On While Disregarding the Squelch Code (Conventional Channels Only) . . . . .	51
Using the Talkgroup Call Feature (Conventional Operation Only) . . . . .	40	Transmitting While the Scan is On . . . . .	52
Selecting a Talkgroup . . . . .	40	Radio Programmed for Talkback Scan . . . . .	52
Sending a Status Call . . . . .	41	Radio Programmed for Non-Talkback Scan . . . . .	52
Using the Dynamic Regrouping Feature (Trunking Only)	41	Deleting a Nuisance Channel . . . . .	52
Requesting a Reprogram . . . . .	42	Restoring a Nuisance Channel . . . . .	53
Classifying Regrouped Radios . . . . .	42	Changing Priorities Status While Scan is On . . . . .	53
Contacts . . . . .	43	Restoring Priorities in a Scan List . . . . .	53
Making a Private Call from Contacts . . . . .	43	Hang Up (HUB) . . . . .	54
Adding a New Contact Entry . . . . .	45	Call Alert Paging . . . . .	54
Deleting a Contact Entry . . . . .	46	Receiving a Call Alert Page . . . . .	55
Adding a Contact to a Call List or Phone List . . . . .	46	Sending a Call Alert Page . . . . .	55
Editing a Contact in a Call List or a Phone List . . . . .	47	In-Call User Alert . . . . .	56
Editing an Entry Alias . . . . .	47	Emergency Operation . . . . .	57
Editing as Entry ID . . . . .	48	Sending an Emergency Alarm . . . . .	57
Editing a Call Type . . . . .	48	Sending an Emergency Call (Trunking Only) . . . . .	58
Scan Lists . . . . .	49	Sending an Emergency Alarm with Emergency Call 58	
Viewing a Scan List . . . . .	49	Sending a Silent Emergency Alarm . . . . .	59
Editing the Scan List . . . . .	49	Special Considerations for Emergencies . . . . .	59
Changing the Scan List Status . . . . .	50	Automatic Registration Service (ARS) . . . . .	60
Viewing and Changing the Priority Status . . . . .	50	Selecting or Changing ARS Mode . . . . .	60
		Accessing the User Login Feature . . . . .	61
		Logging In as a User . . . . .	61

Draft 1c

Logging Out .....	62	Loading the Group Encryption Keys .....	74
Text Messaging Service (TMS) .....	63	Using the Multikey Feature .....	74
Accessing TMS Feature .....	63	Selecting an Encryption Key (Conventional Only) ..	75
Composing and Sending a New Text Message ...	64	Enabling Secure Transmission .....	75
Sending a Quick Text Message .....	65	Accessing the Secure Feature .....	75
Using the Priority Status and Request Reply Features	67	Selecting a Keyset .....	76
Appending or Removing a Priority Status to a Text		Erasing the Selected Encryption Keys .....	76
Message .....	67	Requesting an Over-the-Air Rekey .....	77
Appending or Removing a Request Reply to a Text		MDC Over-the-Air Rekeying (OTAR) Page .....	77
Message .....	67	Hear Clear .....	78
Appending a Priority Status and a Reply Request to a		The Global Positioning System (GPS) .....	78
Text Message .....	67	Understanding the GPS Feature .....	78
Removing a Priority Status and a Reply Request from		Enhancing GPS Performance .....	79
a Text Message .....	68	The Outdoor Location Feature (Using GPS) .....	79
Managing Text Messages .....	68	Accessing the Outdoor Location Feature .....	80
Receiving a Text Message .....	68	Saving a Waypoint .....	81
Viewing a Text Message from the Inbox .....	69	Viewing a Saved Waypoint .....	82
Replying to a Received Text Message .....	70	Editing the Alias of a Waypoint .....	82
Accessing the Drafts Folder .....	71	Editing the Coordinates of a Waypoint .....	83
Managing Sent Text Messages .....	71	Deleting a Single Saved Waypoint .....	84
Viewing a Sent Text Message .....	71	Deleting All Saved Waypoints .....	84
Sending a Sent Text Message .....	72	Measuring the Distance and Bearing from a Saved	
Deleting Text Messages .....	73	Waypoint .....	85
Secure Operations .....	73	Using the Location Feature While in Emergency Mode	
Managing Encryption .....	73	85	
Loading a Single Encryption Key .....	73	Trunking System Controls .....	86
		Using the Failsoft System .....	86

Draft 1c

Going Out-of-Range .....	86	Using the Conventional Squelch Operation Features	95
SmartZone® .....	87	Analog Options .....	96
Using Site Trunking Feature .....	87	Digital Options .....	96
Locking and Unlocking a Site .....	87	Using the PL Defeat Feature .....	96
Viewing and Changing a Site .....	88	Using the Digital PTT ID Feature .....	96
Viewing the Current Site .....	88	Using the Smart PTT Feature (Conventional Only) .....	97
Changing the Current Site .....	88	Accessing General Radio Information .....	97
Trunked Announcement .....	89	Accessing Radio Information .....	97
Initiating an Announcement .....	89	Viewing IP Information .....	98
Ignition Switch Options .....	90	Viewing Control Assignments .....	99
Blank .....	90	Using Optional External Alarms (Horn and Lights) .....	99
Tx Inhibit .....	90	Using Non-Permanent Horn and Lights .....	99
PTT Tx Inhibit .....	90	Using Permanent Horn and Lights .....	100
Required .....	90	Changing the Selected Alarms .....	100
Soft Power Off .....	90	Receiving a Call While Alarms are Turned On .....	101
Ignition Only Power Up .....	90	Turning Off Non-Rearmable External Alarms .....	101
Emergency Power Up .....	91	Turning Off Rearmable External Alarms .....	101
Auto Power Off Timer .....	91	Using the Voice Announcement .....	102
Utilities .....	92	<b>Helpful Tips .....</b>	<b>103</b>
Viewing Recent Calls List .....	92	Caring for Your Radio .....	103
Selecting the Power Level .....	92	Cleaning the External Surface of the Radio .....	104
Selecting a Radio Profile .....	93	<b>Accessories .....</b>	<b>105</b>
Controlling the Display Backlight .....	93	Highlights for the Accessories .....	105
Turning Keypad Tones On or Off .....	94		
Turning Voice Mute On or Off .....	94		
Using the Time-Out Timer .....	95		

Draft 1c

**Appendix: Maritime Radio Use in the VHF**

**Frequency Range .....106**

- Special Channel Assignments ..... 106
  - Emergency Channel ..... 106
  - Non-Commercial Call Channel ..... 106
- Operating Frequency Requirements ..... 107

**Glossary .....109**

**Commercial Warranty and Service .....113**

Draft 1c

## Important Safety Information

### RF Energy Exposure and Product Safety Guide for Mobile Two-way Radios



Caution

Before using this product, read the operating instructions for safe usage contained in the Product Safety and RF Exposure booklet enclosed with your radio.

#### ATTENTION!

**This radio is restricted to occupational use only to satisfy FCC RF energy exposure requirements.**

Before using this product, read the guide enclosed with your radio which contains important operating instructions for safe usage and RF energy awareness and control for compliance with applicable standards and regulations.

For a list of Motorola-approved antennas and other accessories, visit the following website:

<http://www.motorolasolutions.com/APX>

*Under Industry Canada regulations, this radio transmitter may only operate using an antenna of a type and maximum (or lesser) gain approved for the transmitter by*

*Industry Canada. To reduce potential radio interference to other users, the antenna type and its gain should be so chosen that the equivalent isotropically radiated power (e.i.r.p.) is not more than that necessary for successful communication.*

### Software Version

All the features described in the following sections are supported by the radio's software version **R05.00.00** or later.

**Accessing Radio Information** on page 97 to determine your radio's software version.

Check with your dealer or system administrator for more details of all the features supported.

### Notice to Users (FCC and Industry Canada)

This device complies with Part 15 of the FCC rules, Industry Canada license-exempt RSS standard(s) and RSS 210 of the Industry Canada rules per the conditions listed below:

1 This device may not cause harmful interference.

- 2 This device must accept any interference received, including interference that may cause undesired operation.
- 3 Changes or modifications made to this device, not expressly approved by Motorola, could void the user's authority to operate this equipment.

## Informations importantes sur la sécurité

### Guide sur l'exposition aux radiofréquences et la sécurité du produit pour radios mobiles bidirectionnelles



Mise en garde

Avant d'utiliser ce produit, lisez les directives d'utilisation sécuritaire présentées dans le livret Sécurité du produit et exposition à l'énergie RF accompagnant votre radio.

#### ATTENTION!

**Cette radio est réservée à un usage professionnel seulement pour satisfaire les normes d'exposition à l'énergie RF de la FCC.** Avant d'utiliser ce produit, lisez le guide inclus avec votre radio, qui contient d'importantes informations sur le mode d'emploi

sécuritaire du produit ainsi que des informations relatives à l'énergie de RF et à son contrôle, afin d'assurer la conformité aux normes et règlements applicables.

Pour obtenir une liste d'antennes et d'autres accessoires approuvés par Motorola, consultez le site Web : <http://www.motorolasolutions.com/APX>

*Selon la réglementation d'Industrie Canada, cet émetteur radio ne peut être utilisé qu'avec une antenne dont le type et le gain maximal (ou minimal) sont approuvés par Industrie Canada pour cet émetteur. Afin de limiter les interférences radio pour les autres utilisateurs, le type et le gain de l'antenne doivent être choisis de façon à ce que la puissance isotrope rayonnée équivalente (P.I.R.E.) ne soit pas plus forte qu'il ne le faut pour établir la communication.*

## Version du logiciel

Toutes les fonctionnalités décrites dans les sections suivantes sont prises en charge par la version du logiciel **R05.00.00** ou ultérieure de la radio.

Vérifiez auprès de votre détaillant ou de l'administrateur de système pour obtenir des renseignements toutes les fonctionnalités prises en charge.

## Avis aux utilisateurs (FCC et Industrie Canada)

Cet appareil est conforme à la Partie 15 des règlements de la FCC, normes CNR (cahiers des charges sur les normes radioélectriques) pour les appareils exempts de licence d'Industrie Canada et RSS 210 du règlement d'Industrie Canada selon les conditions énumérées ci-dessous:

- 1 Ce dispositif ne doit pas causer d'interférences nuisibles.
- 2 Cet appareil doit accepter toute interférence reçue, y compris les interférences qui peuvent perturber le fonctionnement.
- 3 Les changements ou les modifications apportées à ce dispositif, non expressément approuvées par Motorola, peuvent annuler le droit de l'utilisateur à utiliser cet équipement.

---

## Computer Software Copyrights

The Motorola products described in this manual may include copyrighted Motorola computer programs stored in semiconductor memories or other media. Laws in the United States and other countries preserve for Motorola certain exclusive rights for copyrighted computer

programs including, but not limited to, the exclusive right to copy or reproduce in any form the copyrighted computer program. Accordingly, any copyrighted Motorola computer programs contained in the Motorola products described in this manual may not be copied, reproduced, modified, reverse-engineered, or distributed in any manner without the express written permission of Motorola. Furthermore, the purchase of Motorola products shall not be deemed to grant either directly or by implication, estoppel, or otherwise, any license under the copyrights, patents or patent applications of Motorola, except for the normal non-exclusive license to use that arises by operation of law in the sale of a product.

## Documentation Copyrights

No duplication or distribution of this document or any portion thereof shall take place without the express written permission of Motorola. No part of this manual may be reproduced, distributed, or transmitted in any form or by any means, electronic or mechanical, for any purpose without the express written permission of Motorola.

Draft 1c

---

## Disclaimer

The information in this document is carefully examined, and is believed to be entirely reliable. However, no responsibility is assumed for inaccuracies. Furthermore, Motorola reserves the right to make changes to any products herein to improve readability, function, or design. Motorola does not assume any liability arising out of the applications or use of any product or circuit described herein; nor does it cover any license under its patent rights, nor the rights of others.

Draft 1c



## Getting Started

Take a moment to review the following:

How to Use This User Guide . . . . .	page 1
Notations Used in This Manual . . . . .	page 1
Additional Performance Enhancement . . . . .	page 2
What Your Dealer/System Administrator Can Tell You . . . . .	page 3

## How to Use This User Guide

This User Guide covers the basic operation of the APX™ Mobile Radios.

However, your dealer or system administrator may have customized your radio for your specific needs. Check with your dealer or system administrator for more information.

## Notations Used in This Manual

Throughout the text in this publication, you will notice the use of **WARNING**, **Caution**, and **Note**. These notations are used to emphasize that safety hazards exist, and the care that must be taken or observed. The following special notations identify certain items:



An operational procedure, practice, or condition, etc., which may result in injury or death if not carefully observed.





Caution

An operational procedure, practice, or condition, etc., which may result in damage to the equipment if not carefully observed.

**Note:**

An operational procedure, practice, or condition, etc., which is essential to emphasize.

Example	Description
Home button or 	Buttons and keys are shown in bold print or as an icon.
PHONE	Menu entries are shown similar to the way they appear on the radio's display.
	This means "Press the right side of the 4-way Navigation button."

## ■ Additional Performance Enhancement

The following are some of the latest creations designed to enhance the security, quality and efficiency of APX Mobile Radios.

### Dynamic System Resilience (DSR)

DSR ensures the radio system is seamlessly switched to a backup master site dynamically in case of system failure. DSR also provides additional indication e.g. failure detection, fault recovery, and redundancy within the system to address the user in need. Mechanisms related to the Integrated Voice and Data (IV & D) or data centric are all supported by DSR.

### CrossTalk Prevention

This feature prevents crosstalk scenario from happening, especially when a wideband antenna is used. This feature allows the adjustment of the Trident Transmitting SSI clock rate in the radio to be varied from the Receiving Frequency. This subsequently reduced the possibilities of radio frequency interfering spurs and prevents the issues of crosstalk.

### Encrypted Integrated Data (EID)

EID provides security encryption and authentication of IV & D data bearer service communication between the radio and the Customer Enterprise Network.

### SecureNet

SecureNet allows user to perform secured communications on an Analog or Motorola Data Communication (MDC) channel. The MDC OTAR feature will allow users to perform OTAR activities on an MDC channel.

Draft 1.0

## ■ What Your Dealer/System Administrator Can Tell You

---

Check with your dealer or system administrator, if the radio is to be operated in extremely cold temperatures (less than -30 °C or more than +60 °C), for the correct radio settings to ensure proper operation.

You can also consult your dealer or system administrator about the following:

- Is your radio preprogrammed with any preset conventional channels?
- Which buttons have been programmed to access other features?
- What optional accessories may suit your needs?

Draft 1c

## Preparing Your Radio for Use

Turning On the Radio . . . . .	page 4
Validating Compatibility During Power Up . . . . .	page 4
Adjusting the Volume . . . . .	page 5

## ■ Turning On the Radio


Press the **Power On/Off Button** briefly to power on the radio.

### OR

Press the **PTT Button** briefly to power on the radio.

After a short time, the green LED lights up. The display then shows Zone and channel text, and menu items display on the screen.

The backlight will turn on to the last selected dim level.



**Note:** Pressing the **Power On/Off Button** before the LED lights up will be ignored.

If **Fail ###/##** appears in the display, the radio will not function until the condition has been corrected.

If **Error ###/##** appears, some non-critical data has been changed. If either of these displays appear, if the display goes blank, or if the unit appears to be locked up, see **Helpful Tips** on page 103 for more information.

If **CH mismatch** appears, means that either the Control Head has been connected to an incompatible transceiver, or vice versa.

If your radio does not power up, contact your dealer.

To turn off the radio, press the **Power On/Off Button** after the LED lights up.

**Note:** The radio powers off when Inactivity Auto Power Off Timer expires.

### 📄 Validating Compatibility During Power Up

The radio validates and updates the software and hardware of your control head during power up. Follow the procedure below when your radio runs this task.

#### Procedure:

- 1 The display shows **Maintenance Mode Remote Device**; promptly followed by other maintenance statuses.
- 2 The display shows **Update Done Please Reset** upon completion.  
**OR**  
The display shows **Update Failed Please Reset** when it fails to update.
- 3 Press the **Power On/Off Button** to reset. The radio runs the usual power up operation if the software updates are complete.

**OR**


The radio runs the Maintenance Mode if the updates are not complete and repeat step 1.

**Note:** If **SW Incomplete** appears, use Flashport Recovery Tool to update the control heads before you power on the radio again.

## ■ Adjusting the Volume

To increase the volume, press the Up arrow on the Volume Rocker.

To decrease the volume, press the Down arrow on the Volume Rocker.





## Identifying Radio Controls

Take a moment to review the following:


Radio Parts and Controls . . . . .	page 6
O3 Control Head . . . . .	page 6
Programmable Features . . . . .	page 7
Assignable Radio Functions. . . . .	page 7
Assignable Settings or Utility Functions . . . . .	page 9
Accessing the Preprogrammed Functions . . . . .	page 9
Using the Menu Select Buttons . . . . .	page 9
Using the Navigation Buttons . . . . .	page 10
Using the Keypad. . . . .	page 11
Keypad Characters – Uppercase Mode . . . . .	page 11
Keypad Characters – Lowercase Mode . . . . .	page 12
Keypad Characters – Numeric Mode . . . . .	page 13
Keypad Characters – Hexadecimal Mode . . . . .	page 14
Push-To-Talk (PTT) Button. . . . .	page 15

## Radio Parts and Controls

### O3 Control Head



Draft 1c



## ■ Programmable Features

Any reference in this manual to a control that is “preprogrammed” means that the control must be programmed by a dealer or a qualified radio technician using the radio’s programming software, in order to assign a feature to that control.

The programmable buttons can be programmed as shortcuts to radio functions or preset channels/groups depending on the duration of a button press:

- **Press** – Pressing and releasing rapidly.
- **Long press** – Pressing and holding for the programmed duration (between 0.25 seconds and 3.75 seconds).
- **Hold down** – Keeping the button pressed.

### Assignable Radio Functions

**Call Alert** – Allows the radio to function like a pager, or to verify if a radio is active on the system.

**Call Response** – Allows you to answer a private call or phone call.

**Channel** – Selects a channel.

**Contacts** – Selects the Contacts menu.

**Dynamic ID (Conventional Only)** – Allows you to edit the radio’s ASTRO Individual ID and/or MDC Primary ID.

**Dynamic Priority (Conventional Only)** – Allows any channel in a scan list (except for the Priority-One channel) to temporarily replace the Priority-Two channel.

**Emergency** – Depending on the programming, initiates or cancels an emergency alarm or call.

**Information** – Displays the basic radio information, IP-related information, and buttons or switches control mapping.

**Internet Protocol Address** – Displays the Internet Protocol (IP) address, device name, and status of the radio.

**Location** – Determines the current location (latitude, longitude, time and date), and also the distance and bearing to another location. Or, turns the GPS functionality on or off for all locations.

**Message** – Enters the current message list.

**Monitor (Conventional Only)** – Monitors a selected channel for all radio traffic until function is disabled.

**Multiple Private Line (Conventional Only)** – Selects the Multiple Private Line lists.

**Nuisance Delete** – Temporarily removes an unwanted channel, except for priority channels or the designated transmit channel, from the scan list.

**One Touch 1 – 4** – Launches a specific feature with one single button-press. You can setup as much as four separately programmed buttons for four different features.

Draft 16

**Phone** – Allows you to make and receive calls similar to standard phone calls.

**Private Call (Trunking Only)** – Allows a call from an individual radio to another individual radio.

**Radio Profiles** – Allows for easy access to a set of preprogrammed visual and audio settings of the radio.

**Recent Calls** – Allows for easy access to the list of calls recently received or made.

**Rekey Request** – Notifies the dispatcher that you require a new encryption key.

**Repeater Access Button (RAB) (Conventional Only)** – Allows to manually send a repeater access codeword.

**Reprogram Request (Trunking Only)** – Notifies the dispatcher that you want a new dynamic regrouping assignment.

**Request-To-Talk (Conventional Only)** – Notifies the dispatcher that you want to send a voice call.

**Scan** – Toggles scan on or off.

**Secure/Clear** – Toggles secure transmission on or off.

**Selective Call (Conventional Only)** – Calls an assigned radio.

**Site Display (Trunking Only)** – Views the current site or enable a site search for SmartZone operation.

**Site Lock/Unlock (Trunking Only)** – Toggles between lock and unlock mode when using the SmartZone option.

**Status** – Sends data calls to the dispatcher about a predefined status.

**Talkaround/Direct (Conventional Only)** – Toggles between using a repeater and communicating directly with another radio.

**Talkgroup (Conventional Only)** – Allows a call from an individual radio to a group of radios.

**Text Messaging Service (TMS)** – Selects the text messaging menu.

**TMS Quick Text** – Selects a predefined message.

**User** – Automatically registers with the server.

**Zone Down** – Toggles downward through the zones in the radio.

**Zone Select** – Allows selection from a list of zones.

**Zone Up** – Toggles upward through the zones in the radio.



## 📄 Assignable Settings or Utility Functions

**Dim** – Changes the display brightness.

**Horns/Lights** – Toggles horns and lights feature on or off.

**Low Power** – Toggles transmit power level between high and low.

**Voice Announcement** – Audibly indicates the current feature mode, Zone or Channel the user has just assigned.

**Voice Mute** – Toggles voice mute on or off for the channels which have enabled In-Call User Alert. When Voice Mute is active, the radio remains muted to all conventional dispatch calls and affiliated trunking group calls.

## ■ Accessing the Preprogrammed Functions

You can access various radio functions through one of the following ways:

- A short or long press of the relevant programmable buttons.

OR

- Use the **Menu Select Buttons** (🕒).


### 📄 Using the Menu Select Buttons

The **Menu Select Buttons** allow to access the menu entries of features.

**Note:** Check with your dealer or system administrator for the list of features activated in your radio.

Your radio may be preprogrammed differently from the following example, but the steps for selecting a channel may appear as shown below:


- Press the **Menu Select** button (🕒) directly below **Chan**.





Draft 1e


## Using the Navigation Buttons

### Home Button

The  button returns you to the home (default) display. In most cases, this is the current mode.

For selected radio features, the  button is also used to save user-edited radio settings or information before returning you to the Home screen.

**Note:** Some features do not require you to press  to go to the Home screen. Refer to the individual feature sections in this manual for further details on saving user-edited radio settings or information.

The  button also can revert to home channel. Check with your dealer or system administrator for more information.

### Data Feature Button

Use this button to access data-related features, such as the Text Messaging Service (TMS) feature screen.

### 4-Way Navigation Button

Use this button to scroll up, down, left or right.

Press and release one of the button to scroll from one entry to the next one. Press and hold one of the button to have the radio toggles through the list automatically (release the button to stop).

### Volume Rocker

Use this Volume Rocker to adjust the volume of the speaker by pressing the Up or Down arrows on the Volume Rocker.

### Mode Rocker

Use this Mode Rocker to scroll through the channels by pressing the Up or Down arrows on the Mode Rocker.

Draft 11

## ■ Using the Keypad

You can use the 3 x 4 alphanumeric keypad to access your radio's features. The keypad functions in a manner similar to a standard telephone keypad when entering numeric digits. When the keypad is used to edit a list, each key can generate different characters of the alphabet. The tables below show the number of times a key needs to be pressed to generate the required character.

### 📄 Keypad Characters – Uppercase Mode

Key	Number of Times Key is Pressed																				
	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21
1	1	.	,	?	!	;	@	_	-	*	#	&	\$	/	+	=	\	"	'	(	)
2 abc	A	B	C																		
3 def	D	E	F																		
4 ghi	G	H	I																		
5 jkl	J	K	L																		
6 mno	M	N	O																		
7 pqrs	P	Q	R	S																	
8 tuv	T	U	V	8																	
9 wx yz	W	X	Y	Z																	
0	Toggle between mixed case mode, uppercase mode, and lowercase mode.																				
*	Space																				
#	Toggle between numeric and letter mode.																				

Draft 1c

## Keypad Characters – Lowercase Mode

Key	Number of Times Key is Pressed																				
	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21
1	1	.	,	?	!	;	@	_	-	*	#	&	\$	/	+	=	\	“	‘	(	)
2 abc	a	b	c																		
3 def	d	e	f																		
4 ghi	g	h	i																		
5 jkl	j	k	l																		
6 mno	m	n	o																		
7 pqrs	p	q	r	s																	
8 tuv	t	u	v																		
9 wx yz	w	x	y	z																	
0	Toggle between mixed case mode, uppercase mode, and lowercase mode.																				
*	Space																				
#	Toggle between numeric and letter mode.																				

Draft 1c

## Keypad Characters – Numeric Mode

Key	Number of Times Key is Pressed																				
	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21
1	1	.	,	?	!	;	@	_	-	*	#	&	\$	/	+	=	\	“	’	(	)
2 abc	2																				
3 def	3																				
4 ghi	4																				
5 jkl	5																				
6 mno	6																				
7 pqrs	7																				
8 tuv	8																				
9 wx yz	9																				
0	0																				
*	Space																				
#	Toggle between numeric and letter mode.																				

Draft 1c

## Keypad Characters – Hexadecimal Mode

Key	Number of Times Key is Pressed																				
	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21
1	1																				
2 abc	2	A	B	C																	
3 def	3	D	E	F																	
4 ghi	4																				
5 jkl	5																				
6 mno	6																				
7 pqrs	7																				
8 tuv	8																				
9 wx yz	9																				
0	0																				
*	Not applicable																				
#	Not applicable																				

Draft 1c

## ■ Push-To-Talk (PTT) Button


The **PTT** button on the side of the microphone serves two basic purposes:

- While a call is in progress, the **PTT** button allows the radio to transmit to other radios in the call.

Press and hold down **PTT** button to talk. Release the **PTT** button to listen.

The microphone is activated when the **PTT** button is pressed.

- While a call is not in progress, the **PTT** button is used to make a new call. See **Making a Radio Call** on page 32 for more information.



Draft 1c

## Identifying Status Indicators

Your radio indicates its operational status through the following:

Status Icons . . . . .	page 16
Text Messaging Service (TMS) Icons . . . . .	page 17
Status Icons . . . . .	page 18
TMS Menu Options . . . . .	page 19
LED Indicator . . . . .	page 20
Intelligent Lighting Indicators . . . . .	page 21
Alert Tones . . . . .	page 22
Phone Call Display and Alert Prompts . . . . .	page 25

## ■ Status Icons

The liquid crystal display (LCD) of your radio shows the radio status, text entries, and menu entries.

The following are the icons that appear on the radio's display.



### Receiving

Radio is receiving a call or data.



### Transmitting

Radio is transmitting a call or data.



### Received Signal Strength Indicator (RSSI)

The number of bars displayed represents the received signal strength for the current site, for trunking only. The more stripes in the icon, the stronger the signal.



### Direct

- **On** = Radio is currently configured for direct radio-to-radio communication (during conventional operation only).
- **Off** = Radio is connected with other radios through a repeater.



### Monitor (Carrier Squelch)

Selected channel is being monitored (during conventional operation only).



### In-Call User Alert

- **On** = The feature is enabled. Voice muting of the affiliated trunking talkgroup or selected conventional channel is activated.
- **Off** = The feature is disabled. Voice muting of the affiliated trunking talkgroup or selected conventional channel is deactivated.



### Power Level

- **L** = Radio is set at Low power.
- **H** = Radio is set at High power.



### Scan

Radio is scanning a scan list.



### Priority Channel Scan

- **Blinking dot** = Radio detects activity on channel designated as Priority-One.
- **Steady dot** = Radio detects activity on channel designated as Priority-Two.

Draft 1c



**Vote Scan Enabled**

The vote scan feature is enabled.

**Secure Operation**

- **On** = Secure operation.
- **Off** = Clear operation.
- **Blinking** = Receiving an encrypted voice call.

**AES Secure Operation**

- **On** = AES Secure operation.
- **Off** = Clear operation.
- **Blinking** = Receiving an encrypted voice call.

**Location Signal**

- **On** = Location feature is enabled, and location signal is available.
- **Off** = Location feature is disabled.
- **Blinking** = Location feature is enabled, but no location signal is available.

**User Login Indicator (IP Packet Data)**

- **On** = User is currently associated with the radio.
- **Off** = User is currently not associated with the radio.
- **Blinking** = Device registration or user registration with the server failed due to an invalid username or pin.

**Data Activity**

Data activity is present.

**Hexadecimal**

Indicates that the text entry is currently in hexadecimal mode.

**Text Messaging Service (TMS) Icons**

This feature allows you to send and receive text messages. See **Text Messaging Service (TMS)** on page 63 for more information.

Draft 1

## Status Icons

The following icons appear on the radio's display for TMS features:



### **Inbox Full**

The Inbox is full.



### **Message Sent**

The text message is sent successfully.



### **Message Unsent**

The text message cannot be sent.



### **Unread Message**

- User receives a new message.
- The selected text message in the Inbox has not been read.



### **Read Message**

The selected text message in the Inbox has been read.



### **Normal Message**

User is composing a message with normal priority and without a request for a reply.

3/6

## **Message Index**

Indicates the index of the current message the user is viewing.

Example: If the user is looking at the third message out of a total of 6 messages in the Inbox folder, the icon is displayed as the icon on the left column.

## **Priority Status**



- The "Priority" feature is toggled on before the message is sent.
- Messages in the Inbox folder are flagged with "Priority".



## **Request Reply**



- The "Request Reply" feature is toggled on before the message is sent.
- Messages in the Inbox folder are flagged with "Request Reply".



Draft 1c

### Priority Status and Request Reply



- User is composing a message with a priority status and a request for a reply.
- Messages in the Inbox folder are flagged with “Priority” and “Request Reply”.

123

### Numeric

Indicates that the text entry is currently in numeric mode.

Abc

### Mixed Case

Indicates that the text entry is currently in normal text mode.

ABC

### Uppercase

Indicates that the text entry is currently in uppercase mode.

abc

### Lowercase

Indicates that the text entry is currently in lowercase mode.

### TMS Menu Options

Menu Option	Description/Function
Inbx	Brings you to your incoming messages screen.
Comp	Brings you to the compose screen.


Menu Option	Description/Function
Drft	Brings you to the saved message screen.
Sent	Brings you to the sent messages screen.
Back	Brings you back to the previous menu screen.
Edit	Edits a draft message or key in a target address.
Save	Saves the messages you have edited to the Draft folder.
Rply	Replies to a message.
Del	Deletes a message or a character text during editing mode.
New	Creates a new message.
List	Brings you to the predefined messages screen.
Impt	Toggles the “Priority Status” icon on or off for an outgoing message.
RqRp	Toggles “Request Reply” icon on or off for an outgoing message.
Curr	Deletes the current selected message.
All	Selects to delete all the messages in the current folder.

Draft 1c

Menu Option	Description/Function
<b>Yes</b>	Deletes all the messages in the current folder.
<b>No</b>	Cancel the delete all messages options.
<b>Exit</b>	Exits to the Home screen.
<b>Oprt</b>	Brings you to the Options main screen.
<b>Sel</b>	Selects a predefined message or address.
<b>Send</b>	Sends the message.

## LED Indicator

LED indicator shows the operational status of your radio.



**Solid red** – Radio is transmitting.

**Rapidly blinking red** – Radio has failed the self test upon powering up or encountered a fatal error.

**Solid yellow** – Channel is busy.

**Blinking yellow** – Radio is receiving a secured transmission.

**Solid green** – Radio is powering up, or is on a non-priority channel while in the Scan List Programming mode.

**Blinking green** – Radio is receiving an individual or telephone call, or is on a Priority-Two channel while in the Scan List Programming mode.

**Rapidly blinking green** – Radio is on a Priority-One channel while in the Scan List Programming mode.

Draft 1.0

## ■ Intelligent Lighting Indicators

This feature temporarily changes the radio's display bar color and the alert text background color to help signal that a radio event has occurred.

**Note:** This feature must be preprogrammed by a qualified radio technician.

Bar Color	Event	When
Orange	Emergency Alerts	The radio initiates an emergency alarm or call.
		The radio receives an emergency alarm or call.
Red	Critical Alerts	The radio is out of range.
		The radio enters failsoft mode.
		The radio is unable to establish a full connection with the system.
		The radio is unable to authenticate or register with the system.
Green	Call Alerts	The radio receives a private call.
		The radio receives a phone call.
		The radio receives a call alert.
		The radio receives a selective call.

## ■ Alert Tones

An alert tone is a sound or group of sounds. Your radio uses alert tones to inform you of your radio's conditions. The following table lists these tones and when they occur.

You Hear	Tone Name	Heard
<b>Short, Low-Pitched Tone</b>	Radio Self Test Fail	When radio fails its power-up self test.
	Reject	When an unauthorized request is made.
	Time-Out Timer Warning	Four seconds before time out.
	No ACK Received	When radio fails to receive an acknowledgment.
<b>Long, Low-Pitched Tone</b>	Individual Call Warning Tone	When radio is in an individual call for greater than 6 seconds without any activity.
	Time-Out Timer Timed Out	When the Time-Out Timer has expired.
	Talk Prohibit/ <b>PTT</b> Inhibit	(When <b>PTT</b> button is pressed) transmissions are not allowed.
	Out of Range	(When <b>PTT</b> button is pressed) the radio is out of range of the system.
<b>A Group of Low-Pitched Tones</b>	Invalid Mode	When radio is on an unpreprogrammed channel.
	Busy	When system is busy.

Draft 1e

You Hear	Tone Name	Heard
<b>Short, Medium-Pitched Tone</b>	Valid Key-Press	When correct key is pressed.
	Radio Self Test Pass	When radio passes its power-up self test.
	Clear Voice	At beginning of a non-coded communication.
	Priority Channel Received	When activity on a priority channel is received.
	Emergency Alarm Entry	When entering the emergency state.
	Central Echo	When central controller has received a request from a radio.
<b>Long, Medium-Pitched Tone</b>	Volume Set	When volume is changed on a quiet channel.
	Emergency Exit	When exiting the emergency state.
<b>A Group of Medium-Pitched Tones</b>	Failsoft	When the trunking system fails.
	Automatic Call Back	When voice channel is available from previous request.
	Talk Permit	(When <b>PTT</b> button is pressed) verifying system accepting transmissions.
	Keyfail	When encryption key has been lost.
	Console Acknowledge	When status, emergency alarm, or reprogram request ACK is received.
	Received Individual Call	When Call Alert or Private Call is received.
	Call Alert Sent	When Call Alert is received by the target radio.
Site Trunking	When a SmartZone trunking system fails.	




You Hear	Tone Name	Heard
Ringing	Fast Ringing	When system is searching for target of Private Call.
	Enhanced Call Sent	When waiting for target of Private Call to answer the call.
	Phone Call Received	When a land-to-mobile phone call is received.
Gurgle	Dynamic Regrouping	(When the <b>PTT</b> button is pressed) a dynamic ID has been received.
Unique, Low-Pitched Chirp	New Message	When a new message is received.
Unique, High-Pitched Chirp	Priority Status	When a priority message is received.

Draft 1c



## ■ Phone Call Display and Alert Prompts

The radio uses the following tones to indicate the current status related to phone calls.

You Hear	You See	When	Notes
A Long Tone	No phone	You press the <b>PTT</b> button and the phone system is not available.	Press  to hang up. The radio returns to the Home screen.
	Denied	The phone system is busy.	Press  to exit the phone mode and try your call later.
A Busy Tone	Phone busy	When a channel is not available.	The radio automatically connects when a channel opens.
–	No acknowledge	The call is not acknowledged.	Press  to hang up. The radio returns to the Home screen.
A High-Pitched Tone	–	When you release the <b>PTT</b> button.	The radio indicates to the landline party that he or she may begin talking.

**Note:** You have the option of sending additional digits (overdial), such as an extension number, or credit card or PIN numbers, to the phone system. If the radio is preprogrammed for live overdial, every digit entered after the call is connected is sent to the phone system.

If the radio is preprogrammed for buffered overdial, the digits pressed are entered into memory and then sent when the **PTT** button is pressed. Press the **PTT** button to send either digits or voice, but not both at the same time.

## General Radio Operation

Once you understand how your APX Mobile Radio is configured, you are ready to use your radio.

Use this navigation guide to familiarize yourself with the basic Call features:






Selecting a Zone . . . . .	page 26
Selecting a Radio Channel . . . . .	page 27
Using Channel Search Button . . . . .	page 27
Using Mode Select Feature . . . . .	page 28
Receiving and Responding to a Radio Call . . . . .	page 30
Making a Radio Call . . . . .	page 32
Repeater or Direct Operation . . . . .	page 35
Monitoring Features . . . . .	page 36

## Selecting a Zone

A zone is a group of channels.

**Note:** Your radio must be preprogrammed to allow you to use these features.

### Procedure:

- 1  or  to **Zone**.
- 2 Press the **Menu Select** button directly below **Zone**. The display shows the current zone and channel.
- 3  or  button until the desired zone is displayed.
- 4 Press  or the **PTT** button to confirm the selected zone number.
- 5 Press the **PTT** button to begin transmitting on the displayed zone channel.

## ■ Selecting a Radio Channel

---

A channel is a group of radio characteristics, such as transmit/receive frequency pairs.

Use the following procedure to select a channel.

### Procedure:

- 1 Press the **Mode Rocker Up** or **Down** to the desired channel.  
**OR**  
☞ and press the **Menu Select** button directly below **Chan.**  
The display shows the current zone and channel.
  - 2 Press the **Mode Rocker Up** or **Down** to the desired channel.
  - 3 Press **⏏** or the **PTT** button to confirm the channel.
  - 4 Press the **PTT** button to transmit on the displayed zone channel.
- 

## ■ Using Channel Search Button

---

This feature allows you to do a quick search for a specific channel in the radio by key in the alias of the channel. If the name matches, your radio prompts the first found matched channel name.

### Procedure:

Press the preprogrammed **Channel Search** button.

### OR

Follow the procedure below.

- 1 ☞ or ☛ to **CSrh**.
  - 2 Press the **Menu Select** button directly below **CSrh** to key in the channel name.
  - 3 A blinking cursor appears on the **Channel Search** screen. Use the keypad to type or edit your message.  
Press ☛ to move one space to the left.  
Press ☞ to move one space to the right.  
Press the **Menu Select** button directly below **Del** to delete any unwanted characters.  
Press **(\*)** to add a space.  
Press **(0)** to toggle between mixed case mode, uppercase mode, and lowercase mode.  
Press **(#)** to toggle between numeric and letter mode.
- 

Draft 1.0

- 4 Press the **Menu Select** button directly below **CSrh** once the entry is done to initiate searching.  
**OR**  
Press the **Menu Select** button directly below **Cncl** to exit.
- 5 The display shows **Searching**.  
**OR**  
If the radio is triggered to search for an empty entry, the display shows **Invalid Entry**. Repeat step 3.
- 6 Once found, the display shows the matched channel name and the radio changed its transmission to this channel.  
**OR**  
If the entry does not match, the display shows **Channel name not found**. Repeat from step 3 if want to search again; or press **↵** or the **Menu Select** button directly below **Exit** to exit.

## ■ Using Mode Select Feature

---

Mode Select allows a long press to save the radio's current zone and channel to a programmable button, keypad button or a softkey; then once programmed, the short-press of that button or softkey jumps the transmission to the saved zone and channel.

There are two methods to save the selected zone and channel:

- Softkeys
- Programmable buttons and keypad buttons (digit 0 to 9)



**Note:** Your radio must be preprogrammed to allow you to use this feature.

Draft 1c

## Saving a Zone and Channel to a Softkey

Five softkeys are available for you to save the frequent used zone and channel.

### Procedure:

- 1 Toggle your zone and channel to the required zone and channel.
- 2  or  to **MS1, MS2 ... or MS13**.
- 3 Press and hold the **Menu Select** button directly below the softkey.
- 4 You hear a short, medium-pitched tone when the zone and channel is saved.

**Note:** To change the programmed zone and channel, repeat this procedure.

*Short press of the programmed softkey changes your current transmission to the zone and channel programmed in this softkey.*

## Saving a Zone and Channel to a Keypad Button

All the programmable buttons and keypad digit 0 to 9 buttons allow you to save the frequent used zone and channel.

### Procedure:

- 1 Toggle your zone and channel to the required zone and channel.
- 2 Press and hold the digit button you desire to program.
- 3 You hear a short, medium-pitched tone when the zone and channel is saved.


**Note:** Repeat this procedure to change the zone and channel of the programmed button.

*Short press of the programmed button changes your current transmission to the zone and channel programmed in this button.*

Draft 1c

## ■ Receiving and Responding to a Radio Call

Once you have selected the required channel and/or zone, you can proceed to receive and respond to calls.



You see solid red while the radio is transmitting, and solid yellow when the radio is receiving a transmission (conventional mode only). There is no LED indication when the radio receives a transmission in trunking mode.

If the radio is receiving a secure transmission, the LED blinks yellow.

## 📄 Receiving and Responding to a Talkgroup Call

To receive a call from a group of users, your radio must be configured as part of that talkgroup.

### Procedure:

When you receive a talkgroup call (while on the Home screen), depending on how your radio is preprogrammed:

#### 1 **ASTRO Conventional Only:**

The LED lights up solid yellow. The display shows the talkgroup alias or ID, and the caller alias or ID.

#### **OR**

#### **Trunking Only:**

The display shows the caller alias or ID.

2 Hold the microphone vertically 1 to 2 inches (2.5 to 5.0 cm) from your mouth.

3 Press the **PTT** button to respond to the call. The LED lights up solid red.

4 Release the **PTT** button to listen.

See **Making a Talkgroup Call** on page 32 for details on making a Talkgroup Call.

Draft 10

## Receiving and Responding to a Private Call (Trunking Only)

A Private Call is a call from an individual radio to another individual radio.

These one-to-one calls between two radios are not heard by others in the current talkgroup. The calling radio automatically verifies that the receiving radio is active on the system and can display the caller ID.

**Note:** If the feature inactivity timer is enabled, your radio automatically exits the feature when your radio is left idle long enough for the time to expire. You will hear the Menu Inactive Exit Tone upon feature exit.

### Procedure:


When you receive a Private Call:

- 1 You hear two alert tones and the LED blinks green. The display shows **Call received** and the caller alias or ID.
- 2 Press the **Menu Select** button directly below **Resp** within 20 seconds after the call indicators begin.

- 3 During the call, the display shows the caller alias (name), if it is in the call list.

**OR**

During the call, the display shows the caller ID (number), if the caller's name is not in the call list.

- 4 Press and hold the **PTT** button to talk. Release the **PTT** button to listen.
- 5 Press  to hang up and return to the Home screen.

**Note:** If you press **PTT** button before pressing the **Menu Select** button directly below **Resp**, your conversation will be heard by all members of the talk group.

If 20 seconds pass before you press the **Menu Select** button directly below the **Resp**, you will not respond privately to the call just received. Instead, you initiate a Private Call.

See **Making a Private Call (Trunking Only)** on page 33 for details on making a Private Call.


Draft 1c

## Receiving and Responding to a Telephone Call

This feature allows you to receive calls similar to standard phone calls from a landline phone.

**Note:** If the feature inactivity timer is enabled, your radio automatically exits the feature when your radio is left idle long enough for the time to expire. You will hear the Menu Inactive Exit Tone upon feature exit.

### Procedure:

- 1 You hear a telephone-type ringing and the LED blinks green. The backlight of the screen turns green. The display shows **Phone Call** and the call received icon blinks.
- 2 Press the **Menu Select** button directly below **Resp.**
- 3 Press and hold the **PTT** button to talk. Release the **PTT** button to listen.
- 4 Press  or the **Menu Select** button directly below **Exit** to hang up and return to the **Home** screen.

See *Making a Telephone Call* on page 34 for details.

## Making a Radio Call

You can select a zone, channel, subscriber ID, or talkgroup by using:

- The preprogrammed Zone menu
- The Mode Rocker
- A preprogrammed **One Touch** button
- The Contacts list (see **Contacts** on page 43).



**Note:** If the feature inactivity timer is enabled, your radio automatically exits the feature when your radio is left idle long enough for the time to expire. You will hear the Menu Inactive Exit Tone upon feature exit.

## Making a Talkgroup Call

To make a call to a group of users, your radio must be configured as part of that talkgroup.

### Procedure:

#### 1 **ASTRO Conventional Only:**

 or  to **Tgrp** and press the **Menu Select** button directly below **Tgrp**.

The display shows the last-selected talkgroup. Press the **Menu Select** button directly below **Sel**.

**OR**



Use the **Mode Rocker** to select the channel with the desired talkgroup.

---

- 2 Hold the microphone vertically 1 to 2 inches (2.5 to 5.0 cm) from your mouth.

---

- 3 Press the **PTT** button to make the call.

---

- 4 **ASTRO Conventional Only:**  
The LED lights up solid red. The display shows the talkgroup alias or ID.  
**OR**  
**Trunking Only:**  
The LED lights up solid red.

---

- 5 Speak clearly into the microphone.

---

- 6 Release the **PTT** button to listen.

---

### Making a Private Call (Trunking Only)



This feature allows you to send an individual Call Alert or page if there is no answer from the target radio. Your radio must be preprogrammed to allow you to use this feature.

#### **Procedure:**

Press the preprogrammed **Quick Access (One-Touch) Enhanced Private Call** button to dial the preprogrammed ID and proceed to Step 5.

#### **OR**



Follow the procedure below.

- 1  or  to **Call**.

---

- 2 Press the **Menu Select** button directly below **Call**. The display shows the last transmitted or received.

---

- 3 Press the **Menu Select** button directly below **Cnts** to scroll through and select the required ID.  
**OR**  
Press the **Menu Select** button directly below **List** to go to the first number of the call list.  
**OR**  
 or  to the required ID.  
**OR**  
Use the keypad to enter the required ID.

---

Draft 1.0

- 4 Press the **PTT** button to start the Private Call.

---

- 5 A telephone-type ringing sounds if the receiving unit is in service. The display shows **Calling... <Number>** or **Calling <Alias>**.

---

- 6 Hold the microphone vertically 1 to 2 inches (2.5 to 5.0 cm) from your mouth.

---

- 7 When you are connected, the display shows the ID of the target radio. Press and hold the **PTT** button to talk. Release the **PTT** button to listen.  
**OR**  
 If no acknowledgment is received, the display shows **No Ack.**  
**OR**  
 If the target radio does not respond before the time out, the display shows **No answer.**

---

- 8 Press **Home** to return to the **Home** screen.

See **Sending a Call Alert Page** on page 55 for more information.

## Making a Telephone Call



This feature allows you to make calls similar to standard phone calls to a mobile or landline phone.

### Procedure:

Press the preprogrammed **Quick Access (One-Touch) Phone Call** button to dial the preprogrammed phone number and proceed to Step 5.

### OR



Follow the procedure below.


- 1  or  to **Phon.**

---

- 2 Press the **Menu Select** button directly below **Phon.** The display shows the last transmitted phone number.

---

- 3 Press the **Menu Select** button directly below **Cnts** to scroll through and select the required ID.  
**OR**  
 Press the **Menu Select** button directly below **List** to go to the first number of the call list.  
**OR**  
 or  to the required phone number.  
**OR**  
 Use the keypad to enter the required phone number.

- 4 Press and release the **PTT** button to dial the phone number.
- 5 Hold the microphone vertically 1 to 2 inches (2.5 to 5.0 cm) from your mouth.
- 6 When your call is answered, press the **PTT** button to talk.
- 7 Release the **PTT** button to listen.
- 8 Press  to return to the Home screen.

See **Alert Tones** on page 22 for more information if your call is **NOT** answered.

## ■ Repeater or Direct Operation

The **REPEATER** operation increases the radio's range by connecting with other radios through a repeater. The transmit and receive frequencies are different.



The **DIRECT** or "talkaround operation" allows you to bypass the repeater and connect directly to another radio. The transmit and receive frequencies are the same.

### Procedure:

Press the preprogrammed **Repeater/Direct** switch to toggle between talkaround and repeater modes.

### OR

Follow the procedure below.

- 1  or  to **Dir**.
- 2 Press the **Menu Select** button directly below **Dir**.
- 3 The display shows **Repeater mode** if the radio is currently in Repeater mode.  
**OR**  
The display shows **Direct mode** and the Talkaround icon if the radio is currently in Direct mode (during conventional operation only).

*You can repeat step 2 to toggle between the two modes. Once in Direct Mode, press **PTT** button to start conversation with the radios nearby.*

Draft 1.0

## ■ Monitoring Features

---

Radio users who switch from analog to digital radios often assume that the lack of static on a digital channel is an indication that the radio is not working properly. This is not the case.

Digital technology quiets the transmission by removing the “noise” from the signal and allowing only the clear voice or data information to be heard.

Monitor a channel to ensure the channel is clear before transmitting.

### Monitoring a Channel

#### Procedure:


Lift the control head off hook.

#### Conventional Modes Only:

- 1 Listen for activity on that channel.
- 2 Adjust the **Volume Rocker** if necessary.
- 3 If you hear no activity, press and hold the **PTT** button to start your conversation.

OR

#### Trunked Modes Only:

- 1 Press the **PTT** button.
- 2 If you hear two, short, high-pitched tones, or if you hear no tone and the red  indicator lights steadily, then proceed with your message.
- 3 Release the **PTT** button to receive (listen).

*If you are not in the range of the system, you may hear a continuous low-pitched tone and the display shows **Out of range**.*

Draft 1c

## Conventional Mode Operation



This feature allows you to monitor channel traffic on conventional channels by defeating the coded squelch. Thus you can listen to another user active on the channel. This way, you may be prevented from talking over someone else's conversation.

**Note:** This feature must first be enabled by a qualified radio technician or system administrator.

### **Procedure:**

Take the control head off hook. (This is the same as monitor on. You hear all channel traffic.)

OR

- 1 At **Home** mode where the default zone and channel are being displayed,  or  button to **Mon**.
- 2 Press the **Menu Select** button directly below **Mon** momentarily to activate monitoring. The display shows **Monitor on**.
- 3 Press the **Menu Select** button to deactivate the monitoring. The display shows **Monitor off**.

***Monitor on** shown on the display indicates that the radio is monitoring. Pressing the **Menu Select** button again turns monitor off and you don't hear all channel traffic. If you try to transmit on a receive-only channel, you hear an invalid tone until you release the **PTT** button.*

Draft 1c




## Advanced Features

Use this navigation guide to learn more about advanced features available with your radio:

Advanced Call Features . . . . .	page 38
Contacts . . . . .	page 43
Scan Lists . . . . .	page 49
Scan . . . . .	page 51
Call Alert Paging . . . . .	page 54
Emergency Operation . . . . .	page 57
Automatic Registration Service (ARS) . . . . .	page 60
Text Messaging Service (TMS) . . . . .	page 63
Secure Operations . . . . .	page 73
The Global Positioning System (GPS) . . . . .	page 78
Trunking System Controls . . . . .	page 86
Ignition Switch Options . . . . .	page 90
Utilities . . . . .	page 92

## Advanced Call Features

### Calling a Phone Not in the List

- 1  or  to **Phon**.
- 2 Press the **Menu Select** button directly below **Phon**.
- 3 Enter the desired phone number from the keypad on the control head. The display updates as the numbers are entered.
- 4 Press **PTT** button on the control head to make the call.
- 5 Press and hold the **PTT** button to talk. Release the **PTT** button to listen.
- 6 Press  or **Menu Select** button directly below **Phon** to exit.

## Receiving and Making a Selective Call (Conventional Only)

This feature allows you to receive a call from or to call a specific individual. It is intended to provide privacy and to eliminate the annoyance of having to listen to conversations that are of no interest to you.

### Receiving a Selective Call

#### Procedure:

- 1 When you receive a Selective Call, you hear two alert tones and the LED lights up solid yellow. The call received icons blink and the display shows **Call received** and back to the home display.
- 2 The speaker unmutes.
- 3 Hold the microphone vertically 1 to 2 inches (2.5 to 5.0 cm) from your mouth.
- 4 Press and hold the **PTT** button to talk. Release the **PTT** button to listen.

**Note:** If you press **PTT** button before pressing the **Menu Select** button directly below **Call**, your conversation will be heard by all members of the talk group.

If 20 seconds pass before you press the **Menu Select** button directly below the **Call**, you will not respond privately to the call just received. Instead, you initiate a Selective Call. See **Making a Selective Call** on page 39.





### Making a Selective Call

#### Procedure:

Press the preprogrammed **Quick Access (One-Touch) Selective Call** button to dial the preprogrammed ID and proceed to Step 4.

#### OR

Follow the procedure below.

- 1  or  to **Call**.
  - 2 Press the **Menu Select** button directly below **Call**. The display shows the last transmitted or received ID.
  - 3 Press the **Menu Select** button directly below **Cnts** to scroll through and select the required ID.
- OR**
- Press the **Menu Select** button directly below **List** to go to the last number dialed.
- OR**
-  or  to the required ID.
- OR**
- Use the keypad to enter the required ID.

- 4 Hold the microphone vertically 1 to 2 inches (2.5 to 5.0 cm) from your mouth.
- 5 Press and hold the **PTT** button to start the Selective Call. The display shows the ID of the target radio.
- 6 Release the **PTT** button to listen.
- 7 Press **⏠** to return to the Home screen.

*If you do not press **⏠** button to hang up, your radio will remain in Selective Call state with the other unit. You will miss all subfleet traffic and incoming phone calls.*

### Using the Talkgroup Call Feature (Conventional Operation Only)

This feature allows you to define a group of conventional system users so that they can share the use of a conventional channel.

**Note:** Encryption keys are associated to talkgroups. When talkgroups are enabled, encryption keys are changed by changing the active talkgroup. See **Secure Operations** on page 73 for more information.

### Selecting a Talkgroup

#### Procedure:

- 1 **⏪** or **⏩** to **Tgrp**.
- 2 Press the **Menu Select** button directly below **Tgrp**. The display shows the last talkgroup that was selected and stored.
- 3 **⏪** or **⏩** to **Preset** for the preset preprogrammed talkgroup.  
**OR**  
**⏪** or **⏩** to the required talkgroup.  
**OR**  
Use the keypad to enter the number of the corresponding talkgroup in the list.
- 4 Press the **Menu Select** button directly below **Sel** to save the currently selected talkgroup and return to the **Home** screen.
- 5 If the encryption key associated to the new talkgroup is erased, a momentary key fail tone sounds and the display shows **Key fail**.  
**OR**  
If the encryption key that is associated to the new talkgroup is not allowed, a momentary key fail tone sounds and the display shows **Illegal key**.
- 6 Press **⏠** or the **PTT** button to exit.

Draft 1c



## Sending a Status Call

This feature allows you to send data calls to the dispatcher about a predefined status.

Each status can have up to a 14-character name. A maximum of eight status conditions is possible.



**Note:** If the feature inactivity timer is enabled, your radio automatically exits the feature when your radio is left idle long enough for the time to expire. You will hear the Menu Inactive Exit Tone upon feature exit.

### Procedure:

Press the preprogrammed **Status** button and proceed to Step 3.

**OR**

Follow the procedure below.

- 1  or  to **Sts**.



---

  - 2 Press the **Menu Select** button directly below **Sts**.

---

  - 3 The display shows the last acknowledged status call, or the first status in the list.

---

  - 4  or  to the required status.
- OR**
- Use the keypad to enter a number corresponding to the location in the status list.
- 

5 Press the **PTT** button to send the status. The display shows **Please wait**.


---

6 When the dispatcher acknowledges, four tones sound and the display shows **Ack received**. The radio returns to normal dispatch operation.


**OR**

If no acknowledgment is received, a low-pitched tone sounds and the display shows **No Ack**.

---

7 Press  to return to the Home screen.

---

*No traffic is heard on trunked channels while Status Calls is selected. If the radio detects no Status Call activity for six seconds, an alert tone sounds until you press  or the **PTT** button.*

## Using the Dynamic Regrouping Feature (Trunking Only)

This feature allows the dispatcher to temporarily reassign selected radios to a single special channel so they can communicate with each other. This feature is typically used during special operations and is enabled by a qualified radio technician.

You will not notice whether your radio has this feature enabled until a dynamic regrouping command is sent by the dispatcher.

Draft 1.0

**Note:** If you try to access a zone or channel that has been reserved by the dispatcher as a dynamically regrouped mode for other users, an invalid tone sounds.

**Procedure:**

- 1 When your radio is dynamically regrouped, it automatically switches to the dynamically regrouped channel. A “gurgle” tone sounds and the display shows the dynamically regrouped channel’s name.
- 2 Press the **PTT** button to talk. Release **PTT** button to listen.

*When the dispatcher cancels dynamic regrouping, the radio automatically returns to the zone and channel that you were using before the radio was dynamically regrouped.*

 **Requesting a Reprogram**



This feature lets you notify the dispatcher that you want a new dynamic regrouping assignment.

**Procedure:**

Press the preprogrammed **Reprogram Request** button to send reprogram request to the dispatcher and proceed to Step 3.

**OR**

Follow the procedure below.


- 1  or  to **Rpgm**.
- 2 Press the **Menu Select** button directly below **Rpgm** to send reprogram request to the dispatcher.

3 The display shows **Reprgrm rqst** and **Please wait**.

4 If you hear five beeps, the dispatcher has acknowledged the reprogram request. The display shows **Ack received** and the radio returns to the Home screen.

**OR**

If the dispatcher does not acknowledge the reprogram request within six seconds, a low-pitched alert tone sounds and the display shows **No Ack**.

Try again or press  to cancel and return to the Home screen.

 **Classifying Regrouped Radios**

The dispatcher can classify regrouped radios into either of two categories: **Select Enabled** or **Select Disabled**.

- Select-enabled radios are free to change to any available channel, including the dynamic-regrouping channel, once the user has selected the dynamic-regrouping position.
- Select-disabled radios cannot change channels while dynamically regrouped. The dispatcher has forced the radio to remain on the dynamic-regrouping channel.

The Scan or Private Call feature cannot be selected while your radio is Select Disabled.

Draft 10

## ■ Contacts

This feature provides “address-book” capabilities on your radio. Each entry corresponds to an alias (name) or ID (number) that you use to initiate a call.

Contact entries are alphabetically sorted according to entry alias. Each alias can have up to 5 IDs of different call types associated with it.

Additionally, each entry, depending on context (conventional, trunking, or phone), associates with one or more of the four types of calls: Phone Call, Selective Call, Private Call, or Call Alert.

Each entry within Contacts displays the following information:

- Call Alias (Name)
- Call ID (Number)
- Call Type (Icon)
- WACN ID (Astro 25 Trunking IDs only)
- System ID

**Note:** Your radio must be preprogrammed to allow you to add, edit, or delete the contact entries.

Your radio also supports a maximum of 50 call lists. Each list can store up to 100 IDs (numbers).

**Note:** Your radio is preprogrammed with a number of contacts per Call Lists. Check with your dealer or system administrator for more information.



If the feature inactivity timer is enabled, your radio automatically exits the feature when your radio is left idle long enough for the time to expire. You will hear the Menu Inactive Exit Tone upon feature exit.

### Making a Private Call from Contacts

**Note:** Your radio must be preprogrammed to allow you to use this feature.

#### **Procedure:**



Use the Options Menu.

- 1  or  to **Cnts**.

---

- 2 Press the **Menu Select** button directly below **Cnts** to the call list. The display shows Contact Alias.



---

- 3  or  to the required subscriber alias.



---

- 4 Press the **Menu Select** button directly below **Optn**.

---

- 5  or  to **Call** and press the **Menu Select** button directly below **Sel**.

---

- 6  or  to select the call type.

---

7 Hold the microphone vertically 1 to 2 inches (2.5 to 5.0 cm) from your mouth.

---

8 Press the **PTT** button to initiate the call. During the call, the display shows the subscriber alias.

---

9 Press and hold the **PTT** button to talk. The LED lights up solid red.

**OR**

Release the **PTT** button to listen. The LED lights up solid green.

---

10 If there is no voice activity for a programmed period of time, the call ends.



**OR**

The call ends when it reaches the maximum ring time.

---

**OR**



Use the **PTT** button:

1  or  to **Cnts**.

---

2 Press the **Menu Select** button directly below **Cnts**.

---

3  or  to the required subscriber alias.

---

4 Press the **Menu Select** button directly below **Sel**. The display shows Contact Alias.

---

5 Hold the microphone vertically 1 to 2 inches (2.5 to 5.0 cm) from your mouth.

---

6 Press the **PTT** button to initiate the call. During the call, the display shows the subscriber alias.

---

7 Press and hold the **PTT** button to talk. The LED lights up solid red.

**OR**

Release the **PTT** button to listen. The LED lights up solid yellow.

---

8 If there is no voice activity for a preprogrammed period of time, the call ends.

**OR**



The call ends when it reaches the maximum ring time.

---

Draft 16

## Adding a New Contact Entry



### Procedure:

- 1  or  to **Cnts**.






---

- 2 Press the **Menu Select** button directly below **Cnts**. The entries are alphabetically sorted.

---

- 3  or  to **[New Contact]** and press the **Menu Select** button directly below **Sel**.



---

- 4 The display shows **Name**. Press the **Menu Select** button directly below **Edit**.  
Use the keypad to enter the name.  
Press  to move one space to the left.  
Press  to move one space to the right.  
Press the **Menu Select** button below **DEL** to delete any unwanted characters.  
Press  to add a space.  
Press  to toggle between mixed case mode, uppercase mode, and lowercase mode.  
Press  to toggle between numeric and letter mode.

---

- 5 Press the **Menu Select** button directly below **Ok** once you have entered the name.  
**OR**  
Press the **Menu Select** button directly below **Cncl** to return to the previous screen.



---

- 6  or  to **[Add Number]** and press the **Menu Select** button directly below **Sel**. The display shows **Type 1 <Default Type>**.





---

- 7 Press **Menu Select** button directly below **Edit**.

---

- 8  or  to the required channel and press the **Menu Select** button directly below **Ok**.

---

- 9  or  to **Number 1** and press the **Menu Select** button directly below **Edit**.  
The display shows **Number 1** and a cursor appears.  
Use the keypad to enter the number.  
Press  to move one space to the left.  
Press  to move one space to the right.  
Press the **Menu Select** button directly below **Del** to delete any unwanted characters.

---

- 10 Press the **Menu Select** button directly below **Ok** once you have entered the number.  
**OR**  
Press the **Menu Select** button directly below **Cncl** to return to the previous screen.

---

- 11 Press the **Menu Select** button directly below **Done** once you have finished.

---

- 12 The display shows **<Entry> stored**, confirming that the contact entry has been added.

---







- 13 The radio returns to the main Contacts screen.

---

Draft 1.0











## Deleting a Contact Entry

### Procedure:

- 1  or  to **Cnts**.
- 2 Press the **Menu Select** button directly below **Cnts**. The entries are alphabetically sorted.
- 3  or  to the entry you want to delete and press the **Menu Select** button directly below **Optn**.
- 4  or  to **Delete** and press the **Menu Select** button directly below **Sel**. The display shows **<Entry> Confirm del?**.
- 5 Select **Yes** to delete the entry. The display shows **<Entry> deleted** and the radio returns to the main screen for Contacts.  
**OR**  
Select **No** to return to the main screen for Contacts.

## Adding a Contact to a Call List or Phone List

### Procedure:



- 1  or  to **Cnts**.
- 2 Press the **Menu Select** button directly below **Cnts**. The entries are alphabetically sorted.
- 3  or  to the entry you want to add to the call list and press the **Menu Select** button directly below **Optn**.
- 4  or  to **Add to CallLst** or **Add to PhonLst** and press the **Menu Select** button directly below **Sel**.
- 5  or  until the display shows **[Available]** and press the **Menu Select** button directly below **Add** to add as a new entry.  
**OR**  
 or  until the display shows **<Entry>** and its associated number and press the **Menu Select** button directly below **Rplc** to replace the existing entry.
- 6 The display shows **<Entry> added**, confirming the addition of the contact to the list.
- 7 The radio returns to the main display for Contacts.

Draft 16

## Editing a Contact in a Call List or a Phone List

### Editing an Entry Alias



#### Procedure:

- 1  or  to **Cnts**.



---

- 2 Press the **Menu Select** button directly below **Cnts**. The entries are alphabetically sorted.



---

- 3  or  to the entry you want to edit and press the **Menu Select** button directly below **Optn**.






---

- 4  or  to **Edit** and press the **Menu Select** button directly below **Sel**.

---

- 5  or  to the entry alias you wish to change and press the **Menu Select** button directly below **Edit**.

---

- 6 A cursor appears.  
Use the keypad to edit the name.  
Press  to move one space to the left.  
Press  to move one space to the right.  
Press the **Menu Select** button below **DEL** to delete any unwanted characters.  
Press  to add a space.  
Press  to toggle between mixed case mode, uppercase mode, and lowercase mode.  
Press  to toggle between numeric and letter mode.

---

- 7 Press the **Menu Select** button directly below **Ok** once you have finished. The display returns to the Edit Contact screen.

---



- 8 Press the **Menu Select** button directly below **Done** to save your changes and return to the main screen for Contacts.

---

Draft 1.0

## Editing as Entry ID



### Procedure:

- 1  or  to **Cnts**.



---

- 2 Press the **Menu Select** button directly below **Cnts**. The entries are alphabetically sorted.



---

- 3  or  to the entry you want to edit and press the **Menu Select** button directly below **Optn**.






---

- 4  or  to **Edit** and press the **Menu Select** button directly below **Sel**.

---

- 5  or  to the entry ID you wish to change and press the **Menu Select** button directly below **Edit**.

---

- 6 A cursor appears.  
Use the keypad to edit the number.  
Press  to move one space to the left.  
Press  to move one space to the right.  
Press the **Menu Select** button below **DEL** to delete any unwanted characters.  
Press  to add a space.  
Press  to toggle between mixed case mode, uppercase mode, and lowercase mode.  
Press  to toggle between numeric and letter mode.

---

- 7 Press the **Menu Select** button directly below **Ok** once you have finished. The display returns to the Edit Contact screen.



---

- 8 Press the **Menu Select** button directly below **Done** to save your changes and return to the main screen for Contacts.

---

## Editing a Call Type



### Procedure:

- 1  or  to **Cnts**.



---

- 2 Press the **Menu Select** button directly below **Cnts**. The entries are alphabetically sorted.



---

- 3  or  to the entry you want to edit and press the **Menu Select** button directly below **Optn**.



---

- 4  or  to **Edit** and press the **Menu Select** button directly below **Sel**.

---

- 5  or  to **Type** and press the **Menu Select** button directly below **Edit**.

---

- 6  or  to choose from the list of call types given and press the **Menu Select** button directly below **Ok** to select.

---

- 7 The display returns to the Edit Contact screen.

---

- 8 Press the **Menu Select** button directly below **Done** to save your changes and return to the main screen for Contacts.

---

Draft 1.0



## ■ Scan Lists

Scan lists are created and assigned to individual channels/groups. Your radio scans for voice activity by cycling through the channel/group sequence specified in the scan list for the current channel/group.






Your radio supports different types of Scan Lists:

- Trunking Priority Monitor Scan List
- Conventional Scan List
- Talkgroup Scan List

A maximum of 200 Scan Lists can be programmed in your radio. These lists must be preprogrammed by a qualified radio technician.

### 📄 Viewing a Scan List







#### Procedure:

- 1  or  to **ScnL**.
- 2 Press the **Menu Select** button directly below **ScnL**.
- 3  or  to view the members on the list.
- 4 Press the  to exit the current display and return to the Home screen.


### 📄 Editing the Scan List

This feature lets you change scan list members and priorities.

#### Procedure:

- 1  or  to **ScnL**.
- 2 Press the **Menu Select** button directly below **ScnL**. The display shows the lists that can be changed.
- 3  or  to the entry you want to edit.
- 4 Press the **Menu Select** button directly below **Sel** to add and/or change the priority of the currently displayed channel in the scan list.  
**OR**  
 Press the **Menu Select** button directly below **Del** to delete the currently displayed channel from the scan list.  
**OR**  
 Press the **Menu Select** button directly below **Rcl** to view the next member of the scan list.
- 5  or  to select more channels to be added or deleted.  
**OR**  
 Use the keypad to go directly to additional channels to be added or deleted.  
**OR**  
 Use the **Mode Rocker** to select additional channels to be added or deleted.






Draft 1.0

- 6 Press  to exit scan list programming and return to the Home screen.
- 

See **Viewing and Changing the Priority Status** on page 50 for more information on how to add and/or change the priority of the currently displayed channel in the scan list.

### **Changing the Scan List Status**

#### **Procedure:**

- 1 Long press the preprogrammed **Scan** side button.
  - 2  or  to the member you want to edit.
  - 3 Press the **Menu Select** button directly below **Sel** once to add the currently displayed channel to the scan list.  
**OR**  
Press the **Menu Select** button directly below **Sel**, one or more times to change the scan list status icon of the currently displayed channel.
  - 4  or  to select more list members whose scan status you want to change.  
**OR**  
Use the keypad to go directly to that scan list member.  
**OR**  
Use the **Mode Rocker** to select another scan list member.
  - 5 Press  to exit scan list programming and return to the Home screen.
- 

### **Viewing and Changing the Priority Status**

#### **Procedure:**

- 1 Below **Sel**, **Del**, and **Rcl** screen, press the **Menu Select** button directly below **Sel** to change the priority status of the currently displayed channel.  
**OR**  
Below **Sel**, **Del**, and **Rcl** screen, press the **Menu Select** button directly below **Sel**, one or more times to change the scan list status icon of the currently displayed channel.
  - 2 A Scan icon indicates that the current channel is in the scan list as a non-priority channel. The LED lights up solid green.  
**OR**  
A Priority-Two Channel Scan icon indicates that the current channel is in the scan list as the Priority-Two channel. The LED blinks green.  
**OR**  
A Priority-One Channel Scan icon indicates that the current channel is in the scan list as the Priority-One channel. The LED rapidly blinks green. You hear all traffic on the Priority-One channel, regardless of traffic on non-priority channels.  
**OR**  
No icon indicates that the current channel is deleted from the scan list.
- 

Draft 1

## ■ Scan

---

This feature allows you to monitor traffic on different channels by scanning a preprogrammed list of channels.



### 📄 Turning Scan On or Off

#### Procedure:

Press the preprogrammed **Scan** button.

**OR**

Follow the procedure below.

- 1  or  to **Scan**.

---

- 2 Press the **Menu Select** button directly below **Scan**.

---

- 3 The display shows **Scan off** if scan is disabled. Press the **Menu Select** button directly below **Scan** to enable scan.  
**OR**  
The display shows **Scan on** and the scan status icon if scan is enabled. Press the **Menu Select** button directly below **Scan** to disable scan.



---

- 4 The radio returns to the Home screen.

---

### 📄 Turning Scan On While Disregarding the Squelch Code (Conventional Channels Only)

#### Procedure:

- 1  or  to **Mon**.

---

- 2 Press the **Menu Select** button directly below **Mon**.

---

- 3 The brief **Monitor on** display indicates that the radio is disregarding the squelch code.

---

*While scanning for activity, you can still receive fleetwide, system-wide, dynamic regrouping, incoming telephone interconnect and Private Conversation/Call Alert calls.*

*Respond to these types of calls as you would normally on the selected channel. However, when scanning different channels while in talkgroup scan, incoming Private Conversation/Call Alert calls may be missed.*

## Transmitting While the Scan is On

### **Radio Programmed for Talkback Scan**

#### **Procedure:**

- 1 Press the **PTT** button to transmit on the channel indicated by the display.
- 


*The radio does not begin scanning again for a predetermined hang time after you release the **PTT** button, allowing the other party to respond. If the other party responds within the hang time, scanning does not resume until the full hang time expires after they have finished speaking, allowing the conversation to be completed.*

*To transmit on the selected channel if another channel is active, first turn scan off by pressing the **Menu Select** button below **Scan** momentarily.*

## **Radio Programmed for Non-Talkback Scan**

#### **Procedure:**

- 1 Press the **PTT** button at any time to transmit on the selected channel or fixed channel.
- 



*To make a Call Alert page, or Private Conversation call while scanning, press either the **Menu Select** button directly below **Page** or **Call**. The call is entered on the selected channel and scanning is halted until the call is exited by pressing  or pressing the **Menu Select** button below either **Page** or **Call**.*

### **Deleting a Nuisance Channel**

If a channel continually generates unwanted calls or noise (termed a “nuisance” channel), you can temporarily remove the unwanted channel from the scan list.

This capability does not apply to priority channels or the designated transmit channel.

#### **Procedure:**

- 1 When the radio is locked onto the channel to be deleted,  or  to **Nuis**.
- 
- 2 Press the **Menu Select** button directly below **Nuis**.
-

## Restoring a Nuisance Channel

### Procedure:

To restore the deleted nuisance channel, do **one** of the following:

- Turn scan off, then on.  
**OR**
- Change modes.  
**OR**
- Turn off the radio, and then turn it back on.

*Nuisance mode delete can be disabled by the system administrator.*

## Changing Priorities Status While Scan is On


While the radio is scanning, the dynamic priority change feature allows you to temporarily change any channel in a scan list (except for the Priority-One channel) to the Priority-Two channel.

This change remains in effect until scan is turned off. Scan then reverts to the preprogrammed (original) setting.

### Procedure:

- 1 Press the **Menu Select** button directly below **DynP** to change the priority of a non-priority channel in the scan list to Priority-Two.

---

- 2 Press  momentarily to exit the scan list and resume scanning.

## Restoring Priorities in a Scan List

### Procedure:

To restore the original channel priorities in a scan list, do one of the following:

- Turn scan off, then on.  
**OR**
- Change channels.  
**OR**
- Turn off the radio, and then turn it back on.

Draft 1.0

## Hang Up (HUB)

To temporarily suspend Scan Mode operation, remove the control head from the Hang Up Box (HUB). You are allowed to use the control head while scan is suspended. However, Priority Member scanning is not suspended. This feature applies to all Scan Lists and Scan Types. Scan is resumed once the control head is returned to the holding clip and the preprogrammed hang time has elapsed.

**Note:** Priority Scan List members are continuously scanned only when the Scan List, **Designated Tx Member** field is set to "Talkback" in the radio programming. Otherwise, all scan mode operation is suspended.

## ■ Call Alert Paging

---

This feature allows your radio to work like a pager.

Even if other users are away from their radios, or if they are unable to hear their radios, you can send them an individual Call Alert page. You can also verify if a radio is active on the system.

Depending on how your radio is programmed, when you make an Enhanced Private Call, the radio either automatically sends a Call Alert page if there is no answer after the maximum ring time, **OR** when you press the **PTT** button.

**Note:** This feature must be preprogrammed by a qualified radio technician.

Draft 1c

## Receiving a Call Alert Page

### Procedure:

When you receive a Call Alert page

- 1 You hear four repeating alert tone and the green LED blinks.  
**OR**  
You hear one alert tone and the green LED blinks if Call Alert Tone Auto Reset is enabled.

---

- 2 The call received icons blinks and the display shows **Page received**.

---

- 3 Press the **PTT** button to answer.  
**OR**  
Press any button to clear the Call Alert page.

---

See **Making a Talkgroup Call** on page 32 or **Making a Private Call (Trunking Only)** on page 33 for more information.

## Sending a Call Alert Page



**Note:** If the feature inactivity timer is enabled, your radio automatically exits the feature when your radio is left idle long enough for the time to expire. You will hear the Menu Inactive Exit Tone upon feature exit.

### Procedure:

Press the preprogrammed **Quick Access (One-Touch) Call Alert Paging** button to send a page to the preprogrammed ID and proceed to Step 5 of the procedure below.

### OR



Follow the procedure below.

- 1  or  to **Page**.

---

- 2 Press the **Menu Select** button directly below **Page**.

---

- 3  or  to select the required ID.

---

- 4 Press the **PTT** button to send the page.

---

- 5 The display shows **Paging...<Number>**.

---

- 6 If the call alert page is sent successfully, four highpitch tone sounds and the display shows **Ack received**.  
**OR**  
If the call alert page is not acknowledged, a low tone sounds and the display shows **No Ack**.

---

- 7 The radio returns to the Home screen.  
**OR**





Draft 1.0

Press the **Menu Select** button directly below **Ok** to return to the main screen for Contacts.

---

**OR**

Follow the procedure below.

- 1  or  to **Call**.
- 2 Press the **Menu Select** button directly below **Call**.
- 3  or  to select the required ID, press the **PTT** button to initiate the call.
- 4 If the target radio does not respond after a preprogrammed period of time, the display shows **Send Page?**.
- 5 Press the **Menu Select** button directly below **Yes** to send the call alert page.  
**OR**  
Press the **Menu Select** button directly below **No** to exit the screen without sending the call alert page.
- 6 The display shows **Paging... <Alias>**.
- 7 If the call alert page is sent successfully, a tone sounds and the display shows **Ack received**.  
**OR**  
If the call alert page is not acknowledged, a low tone sounds and the display shows **No Ack**.
- 8 The radio returns to the Home screen.  
**OR**



Press the **Menu Select** button directly below **Ok** to return to the main screen for Contacts.

---

### **In-Call User Alert**

You can enable and disable voice transmission, if needed.

#### **Procedure:**

- 1 Make sure you are in Home mode where the default zone and mode are being displayed.
- 2  or  to scroll to the **VMut**.
- 3 Press the **Menu Select** button directly below **VMut**.
- 4 Press the **Menu Select** button directly below **VMut** or the **VMut** preprogrammed button again to turn the feature off and you will be able to hear to normal dispatch calls.

*Pressing the **Menu Select** button directly below **VMut** or the **VMut** programmed button momentarily toggles between Voice mute on and Voice mute off. **Voice mute on** shown on the display indicates that the radio is muted to all conventional dispatch calls and affiliated trunking group calls.*



## ■ Emergency Operation

---

The Emergency feature is used to indicate a critical situation.

If the **Top (Orange)** button is preprogrammed to send an emergency signal, this signal overrides any other communication over the selected channel.

Your radio supports 5 Emergency modes:

- Emergency Call
- Emergency Alarm
- Emergency Alarm with Call
- Silent Emergency Alarm
- Special Considerations for Emergencies

Check with your dealer or system administrator for more information on the programming of this feature.

Only **one** of the Emergency modes above can be assigned to the preprogrammed **Emergency** button or the **Emergency** footswitch.

**Note:** To exit emergency at any time, press and hold the preprogrammed Emergency button for about a second.

## 📄 Sending an Emergency Alarm

This feature allows you to send a data transmission, which identifies the radio sending the emergency, to the dispatcher.

### Procedure:

- 1 Press the preprogrammed **Emergency** button. A tone sounds and the display shows **Emergency**.
- 2 A dispatcher acknowledgment **Ack received** display follows.  
**AND, Trunking Only:**  
A high-pitched tone indicates that the alarm has been received by the trunked system's central controller.
- 3 Press and hold the emergency button or the **PTT** button to return to normal operation.

Draft 1.0

## Sending an Emergency Call (Trunking Only)

### Procedure:

- 1 Press preprogrammed **Emergency** button.
- 2 A tone sounds and the display shows **Emergency**.  
**OR**  
A short low-pitched tone sounds when the selected channel does not support emergency.
- 3 Hold the microphone vertically 1 to 2 inches (2.0 to 2.5 cm) from your mouth.
- 4 Press and hold the **PTT** button. Speak clearly into the microphone.
- 5 Release the **PTT** to end the transmission.
- 6 Press and hold the preprogrammed Emergency button until a tone sounds to exit Emergency mode.

## Sending an Emergency Alarm with Emergency Call

This feature allows you to send an Emergency Alarm to another radio. Upon acknowledgement, both radios can communicate over a preprogrammed Emergency channel.

If the radio has both emergency call and alarm features enabled, it automatically proceeds to the call mode after the alarm is acknowledged.

### Procedure:

- 1 Press the preprogrammed **Emergency** button to activate the emergency call/alarm feature.
- 2 The display shows **Emergency**.
- 3 A high-pitched tone sounds, indicating that the alarm has been received by the trunked system's central controller. A dispatcher acknowledgment (four high-pitched tones) follows, accompanied by an **Ack received** display.
- 4 Hold the microphone vertically 1 to 2 inches (2.0 to 2.5 cm) from your mouth.
- 5 Press and hold the **PTT** button. Speak clearly into the microphone.
- 6 Release the **PTT** to end the transmission.
- 7 Press and hold the preprogrammed Emergency button until a tone sounds to exit Emergency mode.

*Turning the radio off also cancels the emergency state.*

Draft 16

## Sending a Silent Emergency Alarm

This feature allows you to send an Emergency Alarm to another radio without any audio or visual indicator.

Upon acknowledgement, your radio's microphone is automatically activated, allowing you to communicate with the other radio without pressing the **PTT** button.

This activated microphone state is also known as “**hot mic**”.

**Note:** If you press the PTT button during hot mic, and continue to press it after the hot mic duration expires, the radio continues to transmit until you release the PTT button.

### Procedure:

- 1 Press the preprogrammed **Emergency** button to activate the silent alarm feature.
- 2 Press and hold the emergency button until a tone sounds to exit the silent alarm mode.

*If silent emergency alarm is used with emergency call, pressing the **PTT** button exits the silent mode and initiates the emergency call.*

## Special Considerations for Emergencies

- If you press the emergency button while in a channel that has no emergency capability, a low-pitched tone sounds.
- If the unit is out of the range of the system and/or the emergency alarm is not acknowledged, a tone sounds and the display shows **No Ack**.
- If you press the emergency button, then change to a mode that has no emergency capability, the display shows **No emergency** and a continuous low-pitched tone sounds until a valid emergency mode is selected or until the emergency is cancelled.
- When an emergency is active, changing to another mode where emergency is enabled (trunked or conventional) causes an emergency alarm and/or emergency call to be active on the new mode.

Draft 1.0

## ■ Automatic Registration Service (ARS)

---

This feature provides an automated data application registration for the radio. When you turn on the radio, the device automatically registers with the server.

Data applications within the fixed network can determine the presence of a device on the system and send data to the device. For example: Text Messaging Service (TMS).



The Automatic Registration Service for the radio consists of two (2) modes:

- ARS Server Mode (default mode)
- ARS Non Server Mode



**Note:** The default ARS mode can be changed by a qualified radio technician using the radio's programming software.

## 📄 Selecting or Changing ARS Mode

### Procedure:

- 1 After the zone you want is displayed, use the **Mode Rocker** to toggle until the display shows the required channel.  
**OR**  
Press and hold  or  to **Chan**.  
Press the **Menu Select** button directly below **Chan**.  
The display shows the current zone is not blinking, and the channel is blinking.


---

- 2  or  or press the **Mode Rocker** to the required channel.

---

- 3 In ARS Server Mode, the display shows the User Login Indicator icon, the zone, and ARS server channel.  
**OR**  
In ARS Non-Server Mode, the display shows the User Login Indicator icon, the zone, and ARS non-server channel.  
**OR**  
If the channel or mode selected is unprogrammed, the display shows **Unprogrammed**. Repeat Step 2.

---

- 4 Press  or the **PTT** button to confirm the displayed zone and channel.

---

## Accessing the User Login Feature

This feature allows you as the user to be associated with the radio. With this association, every data application (Example: Text Messaging Service) takes on a friendly username.

You can still send text messages without logging in as a user. The user login feature only enables the recipient of your message to identify you as the sender by assigning a username to your message.



**Note:** Valid characters for a username entry are capital letters (A – Z), small letters (a – z), numbers (0 – 9), symbols (\*, #, -, /), and the space character.

The maximum length for a username is eight (8) characters. Usernames are not case sensitive in server mode but are case sensitive in non-server mode.

A predefined username may sometimes be invalid because the programming software that is used to set predefined usernames allows you to set usernames comprising of eight (8) characters or more.

## Logging In as a User

### Procedure:

- 1  or  to **User**.







---

- 2 Press the **Menu Select** button directly below **User**.

---

- 3 The display shows the User Login screen.

---

- 4  or  to **[ID Entry]** and press the **Menu Select** button directly below **Edit**.  
A blinking cursor appears beside **ID:**. Use the keypad to enter a username.  
**OR**  
 or  to scroll through the list of predefined usernames.  
Press the **Menu Select** button directly below **Logn** to select the predefined username.  
**OR**  
Press and hold  or  to scroll through the list of predefined usernames at a fast scroll rate.  
Press the **Menu Select** button directly below **Logn** to select the predefined username.

---

- 5 If the selected predefined username has more than eight (8) characters, or an invalid character in it, the display momentary shows **Invalid ID**. Repeat Step 3.  
**OR**

Draft 1

A blinking cursor appears beside **PIN**:. Use the keypad to enter your Personal Identification Number (PIN) number. The maximum PIN length is 4 digits. The PIN number appears as asterisks.

**6** Press the **Menu Select** button directly below **Logn**.

**7** In ARS Server Mode, the display shows the User Login Indicator icon, the ID, and **In progress**, with **Cncl**.

**OR**

In ARS Non-Server Mode, the display shows the User Login Indicator icon, the ID, and **Logged in**, with **Logt** and **Exit**.

**OR**

In non-ARS enabled mode, the display shows **Offline**, with **Logt** and **Exit**.

**OR**

Wait for the logged in confirmation screen. If the login process is successful, the display shows the successful user login indicator (IP indicator) icon and **Logged in**, with **Logt** and **Exit**.

**8** If the username is invalid, login fails and the user login failure indicator (IP indicator) icon blinks. The display also momentarily shows **Login failed**. Repeat Step 3.

**OR**

If the PIN is invalid, login fails and the user login failure indicator (IP indicator) icon blinks. The display also momentarily shows **Login failed**. Repeat Step 5.

**OR**

Press the **Menu Select** button directly below **Cncl** to cancel the login in progress screen and return to the initial user login screen.



**OR**

Wait for the logged in confirmation screen. If the login process is successful, the display shows the successful user login indicator (IP indicator) icon and **Logged in**, with **Logt** and **Exit**.

### **Logging Out**

Once the data application registration is completed, you can log out.

**Procedure:**

**1**  or  to **Logt**.

**2** Press the **Menu Select** button directly below **Logt**.

**3** Display shows the User Login Indicator icon and **Clear private data?**.

**4** Select **Yes** to clear all your private data. The display shows momentary **Private data cleared**.

**OR**

Select **No** to keep your private data.

**Note:** Private data refers to all messages in the text messaging Inbox, Draft and Sent folder. The next radio user will be able to access your Inbox, Draft and Sent messages if private data is not deleted.

## ■ Text Messaging Service (TMS)

---

This feature allows you to send and receive text messages. The **maximum** length of characters for a text message is **200**.

There are three (3) types of text messages:

- A new text message (free form message)
- A predefined message (quick text message)
- An edited quick text message

The main menu consists of the following options:

- Inbox
- Compose
- Drafts
- Sent

**Note:** See **Status Icons** on page 18 for more details on the TMS icons and **TMS Menu Options** on page 19 for more details on each menu option.

## 📄 Accessing TMS Feature

**Note:** If the feature inactivity timer is enabled, your radio automatically exits the feature when your radio is left idle long enough for the time to expire. You will hear the Menu Inactive Exit Tone upon feature exit.

Press the **Menu Select** button directly below **Back** at any time to return to the previous screen.

### **Procedure:**





Press the preprogrammed **Data Feature** button or the **TMS** button to access the TMS feature screen.

### **OR**

Press and hold the preprogrammed **Data Feature** button or the **TMS** button to access the Inbox screen.

### **OR**

Follow the procedure below.

- 1  or  to **TMS**.
- 2 Press the **Menu Select** button directly below **TMS** to access the TMS feature screen.
- 3  or  to scroll through the main menu options.





Draft

## Composing and Sending a New Text Message

**Note:** During the uppercase and lowercase mode, multi-tapping the keys only scrolls through the letters. For example, **A->B->C**, **a->b->c**.











During the num lock mode, except for **1**, pressing the keypad only enters the numeric digits. Subsequent presses of the same key inserts the same digit to the text message (no multi-tap).

### Procedure:

- 1  or  to **TMS**.
- 2 Press the **Menu Select** button directly below **TMS** to access the TMS feature screen.
- 3 Press the **Menu Select** button directly below **Comp** to see the compose options.
- 4 Press the **Menu Select** button directly below **New** to compose a new message.
- 5 A blinking cursor appears on the **Compose** screen. Use the keypad to type or edit your message.  
Press  to move one space to the left.  
Press  to move one space to the right.  
Press the **Menu Select** button directly below **Del** to delete any unwanted characters.  
Press **\*** to add a space.

Press **0** to toggle between mixed case mode, uppercase mode, and lowercase mode.

Press **#** to toggle between numeric and letter mode.

- 6 Press the **Menu Select** button directly below **Optn** once the message is composed.
- 7  or  to **Send** and press the **Menu Select** button directly below **Send** to send.  
**OR**  
 or  to **Back** and press the **Menu Select** button directly below **Back** to return to Compose screen if you want to edit the message.
- 8  or  to scroll through the address list and press the **Menu Select** button below **Sel** to select the required address.  
**OR**  
 or  to **[Other Recpnt]** and press the **Menu Select** button below **Edit**.  
A blinking cursor appears in the **Enter Address** screen. Use the keypad to type the address entry.  
Press  to move one space to the left.  
Press  to move one space to the right.  
Press the **Menu Select** button below **Del** to delete any unwanted characters.  
Press **\*** to add a space.  
Press **0** to toggle between mixed case mode, uppercase mode, and lowercase mode.



Press  to toggle between numeric and letter mode.

- 9** Press the **Menu Select** button below **Send** to send the message.  
**OR**  
 Press the **PTT** button to send the message.
- 10** The display shows the **Send Message** screen and **Sending msg.**
- 11** If the message is sent, a tone sounds and the display shows **Msg sent.**  
**OR**  
 If the message is not sent, a low tone sounds and the display shows **Send failed.**

*If the message fails to send, the radio returns you to the main TMS screen.*

- Note:** You can append a priority status and/or a request reply to your message. See **Using the Priority Status and Request Reply Features** on **page 67** for more information.
- Note:** You can also select the **Drft** option to save your message in the Drafts folder to send it at a later time. See **Accessing the Drafts Folder** on **page 71** for more details.

## Sending a Quick Text Message

Quick Text messages are messages that are predefined and usually consist of messages that are used most frequently.








Each Quick Text message has a **maximum** length of 50 characters.

### Procedure:

Press the preprogrammed **Quick Text** button and proceed to Step 3.

### OR

Follow the procedure below.

- 1**  or  to **TMS**.
- 2** Press the **Menu Select** button directly below **TMS** to access the TMS feature screen.
- 3** Press the **Menu Select** button directly below **Comp** to access the compose options.
- 4**  or  to **List**.
- 5**  or  to scroll through the list of messages and press the **Menu Select** button directly below **Sel** to select the required message.
- 6** The message appears on the **Compose** screen, with a blinking cursor at the end of it.  
 Use the keypad to edit the message.  
 Press  to move one space to the left.

Press **→** to move one space to the right.

Press the **Menu Select** button directly below **Del** to delete any unwanted characters.

Press **\*** to add a space.

Press **0** to toggle between mixed case mode, uppercase mode, and lowercase mode.

Press **#** to toggle between numeric and letter mode.

**7** Press the **Menu Select** button directly below **Optn**.

**8** **←** or **→** to **Send** and press the **Menu Select** button directly below **Sel** to send the message.

**9** **←** or **→** to scroll through the address list and highlight the required address.

**OR**

**←** or **→** to **[Other Recpnt]** and press the Menu Select button below **Edit**.

A blinking cursor appears in the **Enter Address** screen. Use the keypad to type the address entry.

Press **→** to move one space to the left.

Press **→** to move one space to the right.

Press the **Menu Select** button below **Del** to delete any unwanted characters.

Press **\*** to add a space.

Press **0** to toggle between mixed case mode, uppercase mode, and lowercase mode.

Press **#** to toggle between numeric and letter mode.

**10** Press the **Menu Select** button below **Send** to send the message.

**OR**

Press the **PTT** button to send the message.

**11** The display shows the **Send Message** screen and **Sending msg**.

**12** If the message is sent, a tone sounds and the display shows **Msg sent**.

**OR**

If the message is not sent, a low tone sounds and the display shows **Send failed**.

*If the message fails to send, the radio returns you to the main TMS screen.*

**Note:** You can append a priority status and/or a request reply to your message. See **Using the Priority Status and Request Reply Features** on **page 67** for more information.

## Using the Priority Status and Request Reply Features

Before sending your message, you can append a priority message and/or a request reply to your message.

### *Appending or Removing a Priority Status to a Text Message*

**Note:** The Priority Message icon on a message does not imply that the message gets higher priority over the other messages when it is being transmitted. It is just an indication that can be embedded into a message to let the receiver know that the message is important.

#### **Procedure:**

After the outgoing message is composed (see **Composing and Sending a New Text Message** on page 64 for more information):

- 1 Press the **Menu Select** button directly below **Optn.**

---

- 2 Press the **Menu Select** button directly below **Impt.**  
The priority status icon appears beside the normal message icon on the label bar.

---

- 3 Press the **Menu Select** button directly below **Impt** again.  
The priority status icon and the normal message icon disappear from the label bar.

---

### *Appending or Removing a Request Reply to a Text Message*

#### **Procedure:**

After the outgoing message is composed (see **Composing and Sending a New Text Message** on page 64 for more information):

- 1 Press the **Menu Select** button directly below **Optn.**

---

- 2 Press the **Menu Select** button directly below **RqRp.**  
The reply status icon appears beside the normal message icon on the label bar.

---

- 3 Press the **Menu Select** button directly below **RqRp** again.  
The reply status icon and the normal message icon disappear from the label bar.

---


### *Appending a Priority Status and a Reply Request to a Text Message*

#### **Procedure:**

After the outgoing message is composed (see **Composing and Sending a New Text Message** on page 64 for more information):

- 1 Press the **Menu Select** button directly below **Optn.**

---

- 2  or  to **Impt** and press the **Menu Select** button directly below **Impt** to indicate the message as important.  
**AND**

Draft 1c

☰ or ☲ to **RqRp** and press the **Menu Select** button directly below **RqRp** to request for a reply.

---

- 3 The priority status and reply status icons appear beside the normal message icon on the label bar.
- 

### **Removing a Priority Status and a Reply Request from a Text Message**

When an outgoing message is indicated with priority status and reply status icons, follow the procedure below to remove these indicators.

#### **Procedure:**

- 1 Press the **Menu Select** button directly below **Optn**.
- 

- 2 ☰ or ☲ to **Impt** and press the **Menu Select** button directly below **Impt** to remove the priority status icon.

**AND**

☰ or ☲ to **RqRp** and press the **Menu Select** button directly below **RqRp** to remove the reply status icon.

---

- 3 The priority status, reply status and normal message icons disappear from the label bar.
- 

## **Managing Text Messages**

### **Receiving a Text Message**

**Note:** When you receive a message that is flagged with the "Request Reply" icon, you must manually respond to the sender that you have received the message. The system will not automatically send back a notification that the radio has received such message.

#### **Procedure:**

When you receive a message, press and hold the preprogrammed **Data Feature** button or the **TMS Feature** button to access the Inbox and go to Step3.

**OR**

Follow the procedure below.

- 1 The new message icon appears and the display momentarily shows **New msg**.

---

- 2 Press the **Menu Select** button directly below **TMS** to access the message.



---

- 3 The display shows alias or ID with the sender of the latest received message on top.

---

## Viewing a Text Message from the Inbox

The Inbox can hold up to thirty (30) messages.

**Note:**  or  to read the message if fills more than one screen.

### Procedure:



Press the preprogrammed **Data Feature** button or the **TMS Feature** button to access the TMS feature screen, and proceed to Step 3.

### OR

Press and hold the preprogrammed **Data Feature** button or the **TMS Feature** button to access the Inbox screen and proceed to Step 4.

### OR

Follow the procedure below.

- 1  or  to **TMS**.
- 2 Press the **Menu Select** button directly below **TMS** to access the TMS feature screen.
- 3 Press the **Menu Select** button below **Inbx** to view Inbox feature screen.
- 4 The display shows alias or IDs, with the sender of the latest received message.

While on the review message screen, press the **Menu Select** button directly below **Rply**, **Del**, or **Back** to access the option.

- Select **Rply** to reply the message.
- Select **Del** to delete the message.
- Select **Back** to return to the previous screen.



**Note:** The icon at the top right corner of the screen indicates the status of the message. See **Text Messaging Service (TMS)** on page 63 for more information.

Draft 1c

## **Replying to a Received Text Message**

**Note:** The original date and time stamp, address and message content is automatically appended to the reply message.







### **Procedure:**

- 1  or  to the required aliases or ID and press the **Menu Select** button below **Sel** to view the message.

---

- 2 Press the **Menu Select** button directly below **Rply** to reply to a message.


---


- 3  or  to **New** and press the **Menu Select** button directly below **New**.  
**OR**  
 or  to **List** and press the **Menu Select** button directly below **List** for a predefined message.  
**OR**  
 or  to scroll through the list of messages and press the **Menu Select** button directly below **Sel** to select the required message.

---


- 4 A blinking cursor appears on the **Compose** screen.  
**OR**  
The predefined message appears on the **Compose** screen, with a blinking cursor at the end of it.


---

- 5 Use the keypad to type or edit your message.  
Press  to move one space to the left.

Press  to move one space to the right.

Press the **Menu Select** button below **Del** to delete any unwanted characters.



Press  to add a space.

Press  to toggle between mixed case mode, uppercase mode, and lowercase mode.

Press  to toggle between numeric and letter mode.

- 6 Press the **Menu Select** button directly below **Optn** once you have finished writing the message.

---

- 7  or  to **Send** and press the **Menu Select** button directly below **Send** to send the message.

---

- 8 The display shows the **Send Message** screen and **Sending msg**.



Press the **Menu Select** button directly below **Back** at any time to return to the previous screen.

**Note:** You can append a priority message and/or a request reply to your message. **Using the Priority Status and Request Reply Features** on page 67 for more information.

## Accessing the Drafts Folder

This folder stores the messages that were saved previously. The Drafts folder can hold up to 10 messages. The oldest draft in the folder is deleted when the 11th message comes in.



### Procedure:

- 1  or  to **TMS**.

---

- 2 Press the **Menu Select** button directly below **TMS** to access the TMS feature screen.

---

- 3  or  to **Drft** and press the **Menu Select** button below **Drft**.

---

- 4 The display shows the first draft message.

Press the **Menu Select** button directly below **Edit Del**, or **Back** to access the option.

- Select **Edit** to edit the message before sending it.
- Select **Del** to delete the message.
- Select **Back** to return to the previous screen.

## Managing Sent Text Messages

Once a message is sent to another radio, it is saved in the Sent folder. The most recent sent text message is always added to the top of the Sent list.

The Sent folder is capable of storing a maximum of ten (10) last sent messages. When the folder is full, the oldest text message in the folder is deleted when the 11th message comes in.

## Viewing a Sent Text Message



The icon at the top right corner of the screen indicates the status of the message. **Text Messaging Service (TMS)** on page 63 for more information.

### Procedure:

Press the preprogrammed **Data Feature** button or the **TMS Feature** button to access the TMS feature screen, and proceed to Step 3.

### OR



Follow the procedure below.

- 1  or  to **TMS**.

---

- 2 Press the **Menu Select** button directly below **TMS** to access the TMS feature screen.

---

- 3  or  to **Sent** and press the **Menu Select** button below **Sent**.

Draft 10








Press the **Menu Select** button directly below **Optn**, **Del**, or **Back** to access the option.


- Select **Optn** to send to the message.
- Select **Del** to delete the message.
- Select **Back** to return to the previous screen.


**Note:** The icon at the top right corner of the screen indicates the status of the message. See **Text Messaging Service (TMS) Icons** on page 17 for more information.


### **Sending a Sent Text Message**

#### **Procedure:**

- 1 Press the **Menu Select** button directly below **Optn** while viewing the message.
- 2  or  to **Send** and press the **Menu Select** button directly below **Send** to send the message.
- 3  or  to scroll through the address list and highlight the required address.  
**OR**  
 or  to **[Other Recpnt]** and press the Menu Select button below **Edit**.  
A blinking cursor appears in the **Enter Address** screen.  
Use the keypad to type the address entry.  
Press  to move one space to the left.

Press  to move one space to the right.  
Press the **Menu Select** button below **Del** to delete any unwanted characters.

Press  to add a space.

Press  to toggle between mixed case mode, uppercase mode, and lowercase mode.

Press  to toggle between numeric and letter mode.

- 4 Press the **Menu Select** button below **Send** or the **PTT** button to send the message.
- 5 The display shows the **Send Message** screen and **Sending msg**.
- 6 Press the **Menu Select** button directly below **Back** to return to the previous screen.



**Note:** You can append a priority message and/or a request reply to your message. See **Using the Priority Status and Request Reply Features** on page 67 for more details.



## **Deleting Text Messages**

### **Procedure:**

From the Inbox, Draft, or Sent screen:

- 1  or  to scroll through the messages.
- 2 Press the **Menu Select** button directly below **Del** to view the delete options.
- 3 Press the **Menu Select** button directly below **Curr** to delete the current message.  
**OR**  
Press the **Menu Select** button directly below **All** to delete all the messages.

## **Secure Operations**

Secure radio operation provides the highest commercially available level of voice security on both trunked and conventional channels.



Unlike other forms of security, Motorola digital encryption provides signaling that makes it virtually impossible for others to decode any part of an encrypted message.

### **Managing Encryption**

**Note:** Refer to the Key-Variable Loader (KVL) manual for equipment connections and setup.

### **Loading a Single Encryption Key**

#### **Procedure:**



- 1 Attach the KVL to your radio. Upon attaching the KVL, the radio display shows **Keyloading**.
- 2 Press the **Menu Select** button below **Target**.
- 3 Press the **Menu Select** button below **Load**.
- 4 Press the **Menu Select** button below **Key**.
- 5  or  to required key.
- 6 Press the **Menu Select** button below **Load** to load the key to your radio.

Draft 1.0

- 7 When the key has been loaded successfully, the radio sounds a short tone for single-key radios.

### **Loading the Group Encryption Keys**

#### **Procedure:**

- 1 Attach the KVL to your radio.
- 2 Press the **Menu Select** button below **Target**.
- 3 Press the **Menu Select** button below **Load**.
- 4 Press the **Menu Select** button below **Group**.
- 5  or  to required group.
- 6 Press the **Menu Select** button below **Load** to load the key to your radio.
- 7 Your mobile radio display shows **Keyloading** when it is loading key(s) from KVL.
- 8 When the key has been loaded successfully, the radio sounds an alternating tone for multikey radios.

### **Using the Multikey Feature**

This feature allows the radio to be equipped with different encryption keys and supports the DES-OFB algorithm.



There are two types of multikey:

- **Conventional Multikey** – The encryption keys can be tied (strapped), on a one-per-channel basis, through Customer Programming Software. In addition, you can have operator-selectable keys, operator-selectable keysets, and operator-selectable key erasure. If talkgroups are enabled in conventional, then the encryption keys are strapped to the talkgroups.
- **Trunked Multikey** – If you use your radio for both conventional and trunked applications, you have to strap your encryption keys for trunking on a per-talkgroup or announcement-group basis. In addition, you may strap a different key to other features, such as dynamic regrouping, failsaft, or emergency talkgroup. You can have operator-selectable key erasure.

Draft 11

## **Selecting an Encryption Key (Conventional Only)**



### **Procedure:**

- 1  or  to **Key**.


---

- 2 Press the **Menu Select** button directly below **Key**. The display shows the last user-selected and stored encryption key, and the available menu selections.

---

- 3  or  to scroll through the encryption keys.  
**OR**  
Use the keypad to enter the number of the desired key.

---




- 4 Press the **Menu Select** button directly below **Sel** to save the newly selected key and return to the Home screen.  
**OR**  
Press , the **PTT** button, or the **Menu Select** button directly below **Exit** to exit.

---

- Note:** If the selected key is erased, a momentary keyfail tone sounds and the display shows **Key fail**.  
**OR**  
If the selected key is not allowed, a momentary illegal key tone sounds and the display shows **Illegal key**.

## **Enabling Secure Transmission**

### **Procedure:**

- 1  or  to **Sec** and Press the **Menu Select** button directly below **Sec**. The display shows  and the current key if multi-key has been enabled.

---

- 2 Monitor the mode to be sure it is not in use.

---

- 3 Press **PTT** button to transmit.



---

- Note:** If the selected channel is preprogrammed for clear-only operation – when you press the **PTT** button, an invalid mode tone sounds and the display shows **Clear TX** only.

The radio does not transmit until you disable the secure mode.

## **Accessing the Secure Feature**

### **Procedure:**

- 1  or  to **Sec**.

---

- 2 Press and hold the **Menu Select** button directly below **Sec** to display Secure feature screen.

---

- 3 The display shows the **Secure** screen.

---


Draft 1c

## **Selecting a Keyset**





This feature allows you to select one or more groups of several encryption keys from among the available keys stored in the radio.

For example, you could have a group of three keys structured to one keyset, and another group of three different keys structured to another keyset; by changing keysets, you would automatically switch from one set of keys to the other.

Every channel to which one of the original keys was tied now has the equivalent new key instead.

**Note:** Press , the **PTT** button, or the **Exit** menu selection to exit this menu at any time without changing the keyset selection.

### **Procedure:**





- 1  or  to **KSet**.
- 2 Press the **Menu Select** button directly below **KSet**. The display shows the last user-selected and stored keyset, and the available keyset menu selections.
- 3  or  to scroll through the keysets.  
**OR**  
Use the keypad to enter the number of the desired keyset.
- 4 Press the **Menu Select** button directly below **Sel** to save the newly selected keyset.

- 5 The radio exits keyset selection and returns to the Home screen.

## **Erasing the Selected Encryption Keys**

This feature allows you to erase all or selected encryption keys.

### **Procedure:**



- 1  or  to **Eras**.
- 2 Press the **Menu Select** button directly below **Eras**. The display shows the last user-selected and stored encryption key, and the available menu selections.
- 3  or  to the desired encryption key.  
**OR**  
Use the keypad to enter the number of the desired key.
- 4 Press the **Menu Select** button directly below **All** to delete all keys.  
**OR**  
Press the **Menu Select** button directly below **Sngl** to delete current shown key.  
**OR**  
Press the **Menu Select** button directly below **Abrt** to abort this screen and return to Home screen.

Draft 1.0

## **Requesting an Over-the-Air Rekey**

This feature, also known as **OTAR**, allows the dispatcher to reprogram the encryption keys in the radio remotely. The dispatcher performs the rekey operation upon receiving a rekey request from the user.


### **Procedure:**

- 1  or  to **Rekey**.

---

- 2 Press the **Menu Select** button directly below **Rekey**.

---

- 3 Press the **PTT** button to send the rekey request.  
**OR**  
Press the **PTT** button again, or the  or **Emergency** button, to exit the feature and transmit in normal mode.

---

- 4 If the rekey operation fails, a bad-key tone sounds and the display shows **Rekey fail**.

---

**Note:** The rekey operation failure indicates that your radio does not contain the Unique Shadow Key (USK). This key must be loaded into the radio with the key-variable loader (KVL) before the rekey request can be sent.

Refer to your local key management supervisor for more information.

## **MDC Over-the-Air Rekeying (OTAR) Page**

This feature allows to view or define MDC Over-the-Air Rekeying (OTAR) features. It is applied only when operating in secure encrypted mode and only for conventional communications. In addition to Rekey Requests, OTAR transmissions include Delayed Acknowledgements, and Power-up Acknowledgements.

Some of the options selected may also need to be set up at the Key Management Controller (KMC) site to work properly.

**Note:** This feature must be preprogrammed by a qualified radio technician. Check with your dealer or system administrator for more information.

Draft 1c

## **Hear Clear**

There are two components of Hear Clear.

### **1 Companding:**

Reduces the channel noise, e.g. OTA transmission, that is predominantly present in UHF2 and 900 MHz channel with the following features.

- **Compressor** – reduces the background noise flow and the speech signal at transmitting radio.
- **Expander** – expands the speech while the noise flow remains the same at receiving radio.

### **2 Random FM Noise Canceller (Flutter Fighter):**

Reduces the unwanted effects of random FM noise pulses caused by channel fading under high Signal-to-Noise (S/N) conditions such as in a moving in a transportation. The fading effects, heard as audio pops and clicks, are cancelled without affecting the desired audio signal.

The Random FM Noise Canceller operates only in receive mode.

**Note:** This feature must be preprogrammed by a qualified radio technician. Check with your dealer or system administrator for more information.

## **The Global Positioning System (GPS)**

This feature uses information from the Global Positioning System (GPS) satellites orbiting the Earth to determine the approximate geographical location of your radio, expressed as latitude and longitude. The availability and accuracy of this location information (and the amount of time that it takes to calculate it) varies depending on the environment in which you are using the GPS feature.

For example, GPS location fixes are very difficult to obtain indoors, in covered locations, between high buildings, or in situations where you have not established a clear broad view of the sky.

### **Understanding the GPS Feature**

The GPS technology uses radio signals from earth orbiting satellites, to establish the location co-ordinates, maximizing your view of clear unobstructed sky is essential for optimum performance.

Where adequate signals from multiple satellites are not available (usually because you cannot establish a view of a wide area of the sky), the GPS feature of your radio will not work. Such situations include but are not limited to:

- In underground locations
- Inside of buildings, trains, or other covered vehicles

- Under any other metal or concrete roof or structure
- Between tall buildings or under dense tree-cover
- In temperature extremes outside the operating limits of your radio

Even where location information can be calculated in such situations, it may take longer to do so, and your location estimate may not be as accurate. Therefore, in any emergency situation, always report your location to your dispatcher.

**Note:** Even where adequate signals from multiple satellites are available, your GPS feature only provides an approximate location, usually within 20 meters from your actual location, but sometimes further away.

Keep in mind that the accuracy of the location information and the time it takes to obtain it varies depending upon circumstances, particularly the ability to receive signals from an adequate number of satellites.

**Note:** The satellites used by the GPS feature are controlled by the U.S. government and are subject to changes implemented in accordance with the Department of Defense GPS user policy and the Federal Radio Navigation Plan. These changes may affect the performance of the GPS feature on your radio.

## Enhancing GPS Performance

Sometimes, the GPS feature may be unable to complete a location calculation successfully. You then see a message indicating that your radio cannot connect to enough visible satellites.

To maximize the ability of your radio to determine a fix, please note the following guidelines:

- For your initial fix, hold the radio in the face position.
- Stay in the open. The GPS feature works best where there is nothing between your radio and a large amount of open sky.

## The Outdoor Location Feature (Using GPS)

This feature allows you to determine your current location using a location menu, as well as your current distance and bearing in relation to another location. Radio location may be requested and reported over-the-air.

Your radio stores up to a maximum of sixty (60) programmable location coordinates, also known as waypoints. When the memory is full, the next waypoints automatically replaces the oldest waypoints in the radio.

The radio also stores four (4) preprogrammed waypoints. These coordinates cannot be deleted.





Programmable Waypoints	Preprogrammed Waypoints
User-configurable location coordinates.	Fixed location coordinates: <ul style="list-style-type: none"><li>• Home</li><li>• Emergency</li><li>• Last Known Location</li><li>• Destination</li></ul>
Only the alias is editable, not the coordinates.	The Home and Destination coordinates are editable.
Coordinates can be deleted one at a time, or all at once.	Coordinates cannot be deleted.

**Note:** If the feature inactivity timer is enabled, your radio automatically exits the feature when your radio is left idle long enough for the time to expire. You will hear the Menu Inactive Exit Tone upon feature exit.

## **Accessing the Outdoor Location Feature**

**Note:** An **ON** menu key may be present on the location menu if it is preprogrammed by the dealer or system administrator.

### **Procedure:**


- 1  or  to **Loc**.
- 2 Press the **Menu Select** button directly below **Loc**. The display shows **Location off <Latitude> <Longitude>**.
- 3 Press the **Menu Select** button directly below **On** to turn on the GPS. The display shows **Previous loc <Latitude> <Longitude>**.
- 4  or  to check the time and date of the last successful location fix.
- 5 Press the **Menu Select** button directly below **Rfsh** to obtain a new location fix.
- 6 The top line temporarily displays **Please wait** while the new location is being determined. While the new location is being determined, the location signal can be a solid or blinking icon.
- 7 Once the location coordinates are fixed, the display shows the current latitude and longitude. Toggle to see the time and date.



The location coordinates are updated automatically every five seconds while the location signal is present.







- 8 Press the **Menu Select** button directly below **Exit** to exit the feature and return to the main screen.


**OR**

Press  or the **PTT** button (if preprogrammed) to exit this menu.

**OR**

Follow the procedure below to turn off the GPS (This feature is enabled by a qualified radio technician.):

- 1  or  to **Loc.**
  - 2 Press the **Menu Select** button directly below **Loc.** The display shows **Previous loc <Latitude> <Longitude>**.
  - 3  or  to check the time and date of the last successful location fix.
  - 4 Press the **Menu Select** button directly below **Optn.**
  - 5  or  to **Turn Off GPS** (if preprogrammed).
  - 6 Press the **Menu Select** button directly below **Sel** to turn off the GPS. The display shows **Location off.**
  - 7 Press the **Menu Select** button directly below **Exit** to exit the feature and return to the main screen.
- OR**



Press  or the **PTT** button (if preprogrammed) to exit this menu.

*The radio also exits the menu if the emergency button is pressed.*



### **Saving a Waypoint**

**Procedure:**



While in the current location display:


- 1 Press the **Menu Select** button directly below **Optn.**
- 2  or  to **Save as Waypt** and press the **Menu Select** button directly below **Sel.**


**OR**

 or  to **Save as Home** and press the **Menu Select** button directly below **Sel** and proceed to Step 5.


**OR**

 or  to **Save as Dest.** and press the **Menu Select** button directly below **Sel** and proceed to Step 5.
- 3 A blinking cursor appears in the **Save As Waypt** screen. Use the keypad to type the alias via multi-tap.
 

Press  to move one space to the left.

Press  to move one space to the right.

Press the **Menu Select** button below **Del** to delete any unwanted characters.

Press  to add a space.

Press **0** to toggle between mixed case mode, uppercase mode, and lowercase mode.

Press and hold **#** to toggle between numeric and letter mode.

**4** Press the **Menu Select** button directly below **Ok** once you are done.

**5** The display shows **Saved as <Waypoint name>**.

**OR**

The display shows **Saved as Home**.

**OR**

The display shows **Saved as Dest..**

**6** Press **⏏** or the **PTT** button (if preprogrammed) to exit this menu.

### **Viewing a Saved Waypoint**

#### **Procedure:**

While in the current location display:

**1** Press the **Menu Select** button directly below **Optn**.

**2** **⏪** or **⏩** to **Waypoints**.

**3** Press the **Menu Select** button directly below **Sel**.

**4** **⏪** or **⏩** to desired waypoint.

**5** Press the **Menu Select** button directly below **Optn**. The display shows **View**.

**6** Press the **Menu Select** button directly below **Sel**.

**7** **⏪** or **⏩** again to view time and date the waypoint was detected.

**8** Press the **Menu Select** button directly below **Back** to return to previous Waypoint screen.

**OR**

Press **⏏** or the **PTT** button (if preprogrammed) to exit this menu.

### **Editing the Alias of a Waypoint**

#### **Procedure:**

While in the current location display:

**1** Press the **Menu Select** button directly below **Optn**.

**2** **⏪** or **⏩** to **Waypoints**.

**3** Press the **Menu Select** button directly below **Sel**.


**4** **⏪** or **⏩** to desired waypoints.


**5** Press the **Menu Select** button directly below **Optn**.

**6** **⏪** or **⏩** to **Edit Name** and press the **Menu Select** button directly below **Sel**.


**7** A blinking cursor appears in the **Edit Name** screen. Use the keypad to edit the alias.


Draft 1c


Press  to move one space to the left.

Press  to move one space to the right.

Press the **Menu Select** button below **Del** to delete any unwanted characters.

Press  to add a space.

Press  to toggle between mixed case mode, uppercase mode, and lowercase mode.


Press and hold  to toggle between numeric and letter mode.

- 8 Press the **Menu Select** button directly below **Ok** once you are done.

**OR**

Press the **Menu Select** button directly below **Cncl** to return to the Waypoints main screen.



- 9 The display shows **<Waypoint name> Updated.**

- 10 Press  or the **PTT** button (if preprogrammed) to exit this menu.

### *Editing the Coordinates of a Waypoint*



#### **Procedure:**

While in the current location display:

- 1 Press the **Menu Select** button directly below **Optn.**
- 2  or  to **Waypoints** and press the **Menu Select** button directly below **Sel.**


- 3  or  to desired waypoints.



- 4 Press the **Menu Select** button directly below **Optn.**

- 5  or  to **Edit Location** and press the **Menu Select** button directly below **Sel.**

- 6 The first number blinks.


Press  to move to the previous number/coordinates.


Press  to move to the next number/coordinates.

Press  or  to change the North (N), South (S), East (E) or West (W) direction.

Press the **Menu Select** button below **Edit** to change the number/coordinates.

- 7 A blinking cursor appears in the **Edit Location** screen.

Press  to move one space to the left.

Press  to move one space to the right.

Press the **Menu Select** button below **Del** to delete any unwanted characters.

- 8 Press the **Menu Select** button directly below **Ok** once you are done.

**OR**

Press the **Menu Select** button directly below **Cncl** to return to the previous screen.

- 9 Press the **Menu Select** button directly below **Ok** once you are done with the new coordinates.

**OR**

Draft 7.0

Press the **Menu Select** button directly below **Cncl** to return to the previous screen then skip to step 11.

**10** The display shows **[Home] Updated** and the radio returns to the Waypoints main screen.

**OR**

The display shows **[Destination] Updated** and the radio returns to the Waypoints main screen.

**11** Press **⏠** or the **PTT** button (if preprogrammed) to exit this menu.

### **Deleting a Single Saved Waypoint**

#### **Procedure:**

While in the current location display:

**1** Press the **Menu Select** button directly below **Optn.**

**2** **⏪** or **⏩** to **Waypoints**.

**3** Press the **Menu Select** button directly below **Sel.**

**4** **⏪** or **⏩** to desired waypoints.

**5** Press the **Menu Select** button directly below **Optn.**

**OR**

Press the **Menu Select** button directly below **Del** and then skip to step 7.

**6** **⏪** or **⏩** to **Delete** and press the **Menu Select** button directly below **Sel.** The display shows **<Waypoint name> Confirm del?**

**7** Press the **Menu Select** button directly below **Yes** to delete. The display shows **<Waypoint name> Deleted.**

**OR**

Press the **Menu Select** button directly below **No** to return to previous Waypoint screen.

**8** Press **⏠** or the **PTT** button (if preprogrammed) to exit this menu.

### **Deleting All Saved Waypoints**

#### **Procedure:**

**1** Press the **Menu Select** button directly below **Optn.**

**2** **⏪** or **⏩** to **Waypoints** and press the **Menu Select** button directly below **Sel.**

**3** **⏪** or **⏩** to desired waypoints and press the **Menu Select** button directly below **Optn.**


**4** **⏪** or **⏩** to **Delete All** and press the **Menu Select** button directly below **Sel.**

**5** The display shows **All saved wayp Confirm del?**

**6** Press the **Menu Select** button directly below **Yes** to delete. The display shows **All saved wayp deleted.**

**OR**





Press the **Menu Select** button directly below **No** to return to previous Waypoint screen.

- 7 Press  or the **PTT** button (if preprogrammed) to exit this menu.


### **Measuring the Distance and Bearing from a Saved Waypoint**

#### **Procedure:**

While in the current location display:

- 1 Press the **Menu Select** button directly below **Optn**.
- 2  or  to **Dist frm here** and press the **Menu Select** button directly below **Sel**.
- 3  or  to the required waypoint, and press the **Menu Select** button directly below **Sel**.
- 4 The display shows the distance and bearing from the current to the selected coordinates.
- 5 Press the **Menu Select** button directly below **Back** to return to the previous Waypoint screen.

**OR**

Press  or the **PTT** button (if preprogrammed) to exit this menu.

### **Using the Location Feature While in Emergency Mode**

When the Emergency feature is activated by pressing the emergency button, the radio exits the Location menu and returns to the home (default) display so that you can see which channel the emergency signal is going out on.

However, you may re-enter the Location menu while still in emergency mode, provided that Silent Emergency has not been activated.

If you have turned Location off using the **ON/OFF** menu key, it automatically turns back on when Emergency is activated.

If there is a solid location signal during Emergency, the current location and the location information received is saved as Emergency and Last Known Location waypoints, respectively.

## ■ Trunking System Controls

---

### 📄 Using the Failsoft System

The failsoft system ensures continuous radio communications during a trunked system failure. If a trunking system fails completely, the radio goes into failsoft operation and automatically switches to its failsoft channel.

The failsoft condition is indicated by a faint beeping tone every nine seconds (radio unsquelched) until the trunking system returns to normal operation.

To continue, in Failsoft, to communicate with other talkgroups, refer to the following procedure.

#### Procedure:

- 1 Press the **Mode Rocker** to change to a different repeater frequency.
  - 2 Press the **PTT** button to talk, and release the button to listen.
- 

*When the trunking system returns to normal operation, your radio automatically leaves failsoft operation and returns to trunked operation.*

### 📄 Going Out-of-Range

**Out of range** when your radio goes out of the range of the system, it can no longer lock onto a control channel.

#### Procedure:

- 1 A low-pitched tone sounds.

#### **AND/OR**

The display shows the currently selected zone/channel combination and **Out of range**.

---

- 2 Your radio remains in this out-of-range condition until:  
It locks onto a control channel.

#### **OR**

It locks onto a failsoft channel.

#### **OR**

It is turned off.

---

Draft 10

## SmartZone®

The SmartZone® feature extends communications beyond the reach of a single-trunked site (antenna location) when operating in a SmartZone system. SmartZone units provide expanded wide-area coverage.

SmartZone automatically switches the radio to a different site when the current site signal becomes unacceptable. This usually happens when the vehicle in which the radio is located is driven out of the range of one site, and into the range of another.

Under normal conditions, a SmartZone-enabled radio functions invisibly to the operator. However, the operator does have some manual controls on the Control Head – the **RSSI** menu entry. This button can be used to check, or change, the SmartZone operation.

## Using Site Trunking Feature

If the zone controller loses communication with any site, that site reverts to site trunking.

The display shows the currently selected zone/channel combination and **Site trunking**.

**Note:** When this occurs, you can communicate only with other radios within your trunking site.

## Locking and Unlocking a Site



This feature allows your radio to lock onto a specific site and not roam among wide-area talkgroup sites. This feature should be used with caution, since it inhibits roaming to another site in a wide-area system.

### Procedure:

Use the preprogrammed **Site Lock/Unlock** button to toggle the lock state between locked and unlocked.

### OR

Follow the procedure below.

- 1  or  to **Site**.
- 2 Press the **Menu Select** button directly below **Site**.
- 3 Press the **Menu Select** button directly below **Lock** to lock the site.

### OR

Press the **Menu Select** button directly below **Unlk** to unlock the site.



- 4 The radio saves the new site lock state and returns to the Home screen.

## Viewing and Changing a Site

This feature allows you to view the number of the current site or force your radio to change to a new one.

### Viewing the Current Site

#### Procedure:

- 1 Press the preprogrammed **Site Search** button.  
**OR**  
 or  to **RSSI**.
- 2 The display momentarily shows the name of the current site and its corresponding received signal strength indicator (RSSI).

### Changing the Current Site

#### Procedure:

- 1 Press and hold down the preprogrammed **Site Search** button.  
**OR**  
Press and hold down the **Menu Select** button directly below **RSSI**.
- 2 A tone sounds and the display momentarily shows **Scanning site**.

*When the radio finds a new site, it returns to the Home screen.*

Draft 1c



## Trunked Announcement

The announcement capability allows you to make announcements to the entire user group, as well as monitor talkgroup calls and other announcements.

Announcement calls are handled in two different ways, depending on the trunked central controller configuration. The two types are called *ruthless* and *non-ruthless* preemption.

- **Ruthless Preemption:**

When a ruthless preemption announcement call is initiated, the requesting radio begins transmitting immediately. All associated talkgroup calls taking place on other channels are immediately halted, and the radios are steered to the announcement call.

Transmitting radios continue to transmit until the **PTT** button is released, at which time they also unmute for the announcement call. Individual calls (Private Conversation and telephone interconnect) are not affected.

- **Non-Ruthless Preemption:**

When a non-ruthless preemption announcement is initiated, the initiating unit receives a telephone-type busy tone, followed by a call back when all associated talkgroup conversations end.

Once an announcement call is pending, any attempts by other users to initiate a talkgroup call will result in a telephone-type busy tone. These users will not receive a call back until the announcement call is complete.

## Initiating an Announcement

If your radio has been programmed to allow announcement calls:

### Procedure:

- 1 Press the **Mode Rocker** to locate the announcement-group mode.

---

- 2 Press the control head **PTT** button to initiate the announcement.

---

Draft 1c

## ■ Ignition Switch Options

This feature allows the user to select the radio's functionality based on the Ignition State of the radio user's vehicle. The available options are as follows.

### 📄 Blank

This option allows the user to power on and power off the radio through the **Power** button regardless of the Ignition's current state.

### 📄 Tx Inhibit

This option allows the user to power on and power off the radio through the **Power** button regardless of the Ignition's current state. In addition, if the Ignition is not present, then all transmissions are inhibited. This includes receiving any Trunking dispatch communications since the radio will not affiliate with the Trunking systems.

### 📄 PTT Tx Inhibit

This option allows the user to power on and power off the radio through the **Power** button regardless of the Ignition's current state. In addition, if the Ignition is not present, then all **PTT** button transmissions are inhibited. However, the radio is able to affiliate with the Trunking systems.

### 📄 Required

This option allows the user to power on the radio only if the Ignition is present. The radio can be powered off either through **Power** button press or when Ignition is lost. In addition, the radio automatically powers on when the Ignition is present only if the radio was turned off due to the ignition being removed.

This option allows the radio to power off when Inactivity Auto Power Off Timer expires, or, when Ignition Auto Power Off Timer expires.

### 📄 Soft Power Off

This option allows the user to power on the radio either through **Power** button presses or when the Ignition is detected. Meanwhile, if the **Power** button was pressed or the Ignition was removed, the radio will be turned off.

This option allows the radio to power off when Inactivity Auto Power Off Timer expires, or, when Ignition Auto Power Off Timer expires.

### 📄 Ignition Only Power Up

This option allows the user to power on the radio only when Ignition is detected and will power off when it is removed. The radio does not power on or off with the **Power** button press.

This option allows the radio to power off when Inactivity Auto Power Off Timer expires, or, when Ignition Auto Power Off Timer expires.

**Note:** While "Ignition" is not present, the radio powers-off with a radio-user Power Off button / knob selection if the radio was powered-up with an Emergency Power Up footswitch-press or Ignition Auto Power Off timer is running.

While "Ignition" is present, the radio powers-on with a radio-user Power On button / knob selection only if the radio was powered-down with Inactivity Auto Power Off timer.

### **Emergency Power Up**

This feature allows the user to power on the radio and automatically transmits an emergency mode transmission on personalities with emergency enabled, with the use of a footswitch. In addition, when the Ignition Switch option is set to either Tx Inhibit or PTT Tx Inhibit, this feature will not be available to the users.

Press the footswitch to turn on the radio and launch Emergency. A tone sounds and the display shows **Emergency**.

### **Auto Power Off Timer**

Auto Power Off feature powers off the radio when no user actions occur during a preprogrammed length of time. There are two different version of Auto Power Off:

**Inactivity Auto Power Off Timer** – This timer begins once the radio is power-on. While the timer is active any user interaction with the radio resets the timer.

**Ignition Auto Power Off Timer** – This timer begins once the vehicle key is removed, when the voltage at the ignition sense is removed. While the timer is active any user interaction with the radio resets the timer. When the vehicle key is reapplied, the voltage at the ignition is reconnected, this timer is stopped.

Although both Inactivity Auto Power Off and Ignition Auto Power Off can be enabled together, Ignition Auto Power Off timer is mutually exclusive with Inactivity Auto Power Off timer when both are enabled.

During the last two minutes of the timer countdown, the radio generates continuous low tone and blinks **Powering Off** warning on the display until the timer expires or the timer is reset. The radio automatically powers off after the timer expires. The duration of the timer is preprogrammed.

## Utilities

---






### Viewing Recent Calls List

This feature allows you to view the recent incoming and outgoing call information of the following call types:

- Call Alert
- Selective Call
- Private Call
- Phone Call (Outgoing only)

**Note:** The radio can also be preprogrammed to log the radio IDs associated with incoming Dispatch Calls. Check with your dealer or system administrator for more information.

#### Procedure:

- 1  or  to **Rcnt**.
- 2 Press the **Menu Select** button directly below **Rcnt** to access the **Recent Calls** feature screen.
- 3  or  to scroll through the list.
- 4 Press the **Menu Select** button directly below **Exit** to return to Home screen.  
**OR**  
Press  or the **PTT** button to return to the Home screen.

**Note:** If the feature inactivity timer is enabled, your radio automatically exits the feature when your radio is left idle long enough for the time to expire. You will hear the Menu Inactive Exit Tone upon feature exit.

### Selecting the Power Level

You can select the power level at which your radio transmits. The radio always turns on to the default setting.

**Note:** This feature must be preprogrammed by a qualified radio technician.

#### Settings:

- Select **Low** for a shorter transmitting distance and to conserve power.
- Select **High** for a longer transmitting distance.

#### Procedure:

Use the preprogrammed **Transmit Power Level Switch** to toggle transmit power level between high and low power.

#### **OR**

Follow the procedure below.

- 1  or  to **Pwr**.
- 2 Press the **Menu Select** button directly below **Pwr**.

- 3 The display shows **Low power** and the low power icon.  
**OR**  
 The display shows **High power** and the high power icon.
- 

### **Selecting a Radio Profile**

This feature allows you to manually switch the visual and audio settings of the radio. The display, backlight, alert tones, and audio settings are defined according to the preprogrammed radio settings of each radio profile.

Please refer to a qualified technician for more information.



**Note:** If the feature inactivity timer is enabled, your radio automatically exits the feature when your radio is left idle long enough for the time to expire. You will hear the Menu Inactive Exit Tone upon feature exit.

#### **Procedure:**

Use the preprogrammed **Profile** button and proceed to Step 3.

#### **OR**



Follow the procedure below.

- 1  or  to **Prfl**.

---

- 2 Press the **Menu Select** button directly below **Prfl** to access the **Profiles** feature screen.

---

- 3  or  to scroll through the menu selections.

---

- 4 Press the **Menu Select** button directly below **Sel** to select the required radio profile.

#### **OR**

Press the **Menu Select** button directly below **Exit** to exit the screen without making any changes.

---

- 5 The radio returns to the Home screen. The profile name on the Home screen indicates the current selected radio profile.
- 

### **Controlling the Display Backlight**

You can enable or disable the radio's display backlight as needed, if poor light conditions make the display or keypad difficult to read.

Depending on how your radio is preprogrammed, you can also maintain a minimum backlight level on the radio's display.

#### **Procedure:**

- Note:** Press the **DIM** button to toggle the backlight on or off.  
**OR**  
 Press any key of the keypad, the **Menu Select** or **Menu Navigation** buttons, or any programmable radio controls or buttons to turn the backlight on.

## Turning Keypad Tones On or Off



You can enable and disable keypad tones if needed.

### Procedure:

Press the preprogrammed **Keypad Mute** button to turn the tones on or off.

### OR

Follow the procedure below.

- 1  or  to **Mute**.
  - 2 Press the **Menu Select** button directly below **Mute**.
  - 3 The display momentarily shows **Tones off**, indicating that the keypad tones are disabled.
- OR**
- The display momentarily shows **Tones on**, and a short tone sounds, indicating that the keypad tones are enabled.

## Turning Voice Mute On or Off



You can enable and disable voice muting of the affiliated trunking talkgroup or selected conventional channel, if needed.

### Procedure:

Press the preprogrammed Voice Mute button to turn the feature on or off.

### OR

Follow the procedure below.

- 1  or  to **VMut**.
  - 2 Press the **Menu Select** button directly below **VMut**.
  - 3 The display momentarily shows **Voice mute off**, and a short tone sounds, indicating that the feature is disabled.
- OR**
- The display momentarily shows **Voice mute on**, and a short tone sounds, indicating that the feature is enabled.

## Using the Time-Out Timer

This feature turns off your radio's transmitter. You cannot transmit longer than the preset timer setting.

If you attempt to do so, the radio automatically stops your transmission, and you hear a talk-prohibit tone.

The timer is defaulted at 60 seconds, but it can be preprogrammed from 3 to 120 seconds, in 15-second intervals, or it can be disabled entirely for each radio mode, by a qualified radio technician.

**Note:** You will hear a brief, low-pitched, warning tone four seconds before the transmission times out.



### Procedure:

- 1 Hold down the **PTT** button longer than the preprogrammed time. You hear a short, low-pitched warning tone, the transmission is cut-off, and the LED goes out until you release the **PTT** button.
- 2 Release the **PTT** button. The LED relights and the timer resets.
- 3 Press the **PTT** button to re-transmit. The time-out timer restarts and the LEDs lights up solid red.

## Using the Conventional Squelch Operation Features

This feature filters out unwanted calls with low signal strength or channels that have a higher than normal background noise.

### 1 Procedure:

 or  to **Sql**.

### 2 Press the **Menu Select** button directly below **Sql**.

The display shows **Squelch**, a volume bar and **XX** value for the current squelch.

### 3 Press the **Menu Select** button directly below “+” to increase the squelch volume.

#### OR

Press the **Menu Select** button directly below “-” to decrease the squelch volume.

### 4 Press to return to the selected channel.

Draft 1.0

## Analog Options

Tone Private Line (PL), Digital Private-Line (DPL), and carrier squelch can be available (preprogrammed) per channel.

Option	Result
Carrier squelch (C)	You hear all traffic on a channel.
PL or DPL	The radio responds only to your messages.

## Digital Options

One or more of the following options may be preprogrammed in your radio. Consult your dealer or system administrator for more information.

Option	Result
Digital Carrier-Operated Squelch (COS)	You hear any digital traffic.
Normal Squelch	You hear any digital traffic having the correct network access code.
Selective Switch	You hear any digital traffic having the correct network access code and correct talkgroup.

## Using the PL Defeat Feature

This feature allows you to override any coded squelch (DPL or PL) that might be preprogrammed to a channel. The radio also unmutes to any digital activity on a digital channel.

### Procedure:

Place the preprogrammed **PL Defeat** switch in the PL Defeat position. You hear any activity on the channel.

### OR

The radio is muted if no activity is present.

**Note:** When this feature is active, the Carrier Squelch status indicator is displayed.

## Using the Digital PTT ID Feature

This feature allows you to the radio ID (number) of the radio from whom you are currently receiving a transmission. This ID, consisting up to a maximum of eight characters, can be viewed by both the receiving radio and the dispatcher.

Your radio's ID number is also automatically sent every time the PTT button is pressed. This is a per-channel feature. For digital voice transmissions, your radio's ID is sent continuously during the voice message.



## Using the Smart PTT Feature (Conventional Only)

Smart **PTT** is a per-personality, programmable feature used in conventional radio systems to keep radio users from talking over other radio conversations.

When smart **PTT** is enabled in your radio, you cannot transmit on an active channel.

If you try to transmit on an active smart-**PTT** channel, you hear an alert tone, and the transmission is inhibited. The LED lights up solid yellow to indicate that the channel is busy.

Three variations of smart PTT are available:

Mode	Description
Transmit Inhibit on Busy Channel with Carrier	You cannot transmit if any traffic is detected on the channel.
Transmit Inhibit on Busy Channel with Wrong Squelch Code	You cannot transmit on an active channel with a squelch code or (if secure-equipped) encryption key other than your own. If the PL code is the same as yours, the transmission is not prevented.
Quick-Key Override	This feature can work in conjunction with either of the two above variations. You can override the transmit-inhibit state by quick-keying the radio. In other words, two PTT button presses within the preprogrammed time limit.

## Accessing General Radio Information

Your radio contains information on the following:

- Radio Information
- IP Display
- Control Assignments


**Note:** If the feature inactivity timer is enabled, your radio automatically exits the feature when your radio is left idle long enough for the time to expire. You will hear the Menu Inactive Exit Tone upon feature exit.

## Accessing Radio Information








This feature displays the following information of your radio: :

- Host Version
- Secure Version
- CH 1 – 4 Version (depending on the number of channels connected.)
- TIB Version
- TRC Version
- URC Version
- DSP Version
- KG (Secure Algorithm)
- Serial Number
- MCHIB Version
- CHIB Version
- AUX CH Version
- Siren Version
- VRS Version
- DVRS App Version (only when DVRS is available)

- DVRS DSP Version (only when DVRS is available)
- Model Number
- ESN
- Flash Code
- Tuning Version
- DVRS CP Version (only when DVRS is available)
- Serial Number
- Flash Size & Type
- RF Band
- Processor Version

**Note:** Press  at any time to return to the Home screen.

**Procedure:**

- 1  or  to **Info**.
  - 2 Press the **Menu Select** button directly below **Info**.
  - 3  or  to **Radio Info** and press the **Menu Select** button directly below **Sel**.
  - 4 The display shows the Information screen.
  - 5  or  to scroll through the various information.
- OR**  
Press the **Menu Select** button directly below **Back** to return to previous screen.
- OR**  
Press  to exit and return to the home display.

 **Viewing IP Information**

This feature displays the device name, IP address, and status of your radio.








**Note:** The device name of your radio is preprogrammed. Check with your dealer or system administrator for more information.

**Procedure:**

Press the preprogrammed Info button and proceed to Step 3.

**OR**

Follow the procedure below.



- 1  or  to **Info**.
  - 2 Press the **Menu Select** button directly below **Info**.
  - 3  or  to **IP Info** and press the **Menu Select** button directly below **Sel**.
  - 4  or  to scroll through the various information.
- OR**  
Press the **Menu Select** button directly below **Back** to return to previous screen.
- OR**  
Press  to exit and return to the Home display.

## Viewing Control Assignments

This feature displays the programmable radio functions assigned to the controls of your radio for the currently selected channel.

See **Programmable Features** on page 7 for more information on the various programmable features of your radio.



### Procedure:

- 1  or  to **Info**.




---

- 2 Press the **Menu Select** button directly below **Info**.

---

- 3  or  to **Control Map** and press the **Menu Select** button directly below **Sel**.

---

- 4  or  to scroll through the various information.  
**OR**  
 Press the **Menu Select** button directly below **Back** to return to previous screen.  
**OR**  
 Press  to exit and return to the Home display.

---

## Using Optional External Alarms (Horn and Lights)

All control heads can be equipped for external alarms (horn and lights) that are activated when a Call Alert page, Private Conversation call, or phone call is received.

The radio always powers up with the horn and lights feature enabled.

**Note:** The horn and lights feature must be enabled by a qualified radio technician.

## Using Non-Permanent Horn and Lights

### Procedure:

- 1 Press the **Menu Select** button directly below **H/L** momentarily. The last selected alarm(s) are enabled, and the display shows the enabled alarm(s) until it is turned off.

---

- 2 Press the **Menu Select** button directly below **H/L** momentarily to enable the last selected alarm(s). The display briefly shows the enabled alarm(s).

---

Draft 1.0

## Using Permanent Horn and Lights

If Permanent Horn and Lights is enabled, horn and lights will automatically be turned on when the radio powers up.

### Procedure:

- 1 Press the **Menu Select** button directly below **H/L** once to turn off the alarm(s).
- 2 Press the **Menu Select** button directly below **H/L** momentarily to enable the last selected alarm(s). The display briefly shows the enabled alarms.

## Changing the Selected Alarms

### Procedure:

- 1 Press the **Menu Select** button directly below **H/L** until the display shows the required alarm.
- 2 Press the **Menu Select** button directly below the required entry and the display exits to Home screen.

Press the **Menu Select** button directly below the entry activates the option. Below are the selections available.

- Select **H+L** to turn on both horn and lights. The display shows **Horn/Lites on**.
- Select **Lgts** to turn on the lights. The display shows **Lights on**.
- Select **Horn** to turn on the horn. The display shows **Horn on**.

An **Off** entry is shown at the softkey when one of the features above is active. Selecting the **Off** deactivates the current active alarm.

Draft 1c

### **Receiving a Call While Alarms are Turned On**

When you receive a call with the Alarms turned on:

#### **Procedure:**

- 1 You hear the vehicle's horn sounds for four seconds, and/or the car lights turn on for 60 seconds.
- 2 The display shows the type of call received (**CALL**, **PAGE**, or **PHONE**) and the selected mode name.

*The time interval can be modified by a qualified radio technician.*

### **Turning Off Non-Rearmable External Alarms**

#### **Procedure:**

- 1 Press the **Menu Select** button directly below **Call**, **Page** or **Phon** will turn off the external alarm(s) and place you directly in that feature.  
**OR**  
Press the **PTT** button or any control-head button to turn off the external alarm(s).
- 2 Press the **Menu Select** button directly below **H/L** momentarily to rearm the horn and lights feature.

*The **Volume Rocker** and the **DIM** button have no effect on the state of the external alarm(s).*

### **Turning Off Rearmable External Alarms**

#### **Procedure:**

- 1 Press the **Menu Select** button directly below **Call**, **Page** or **Phon** to turn off the external alarm(s) and place you directly in that feature.  
The external alarm(s) is turned off and automatically rearmmed so that when you exit the entry, the external alarm(s) will automatically turn on.  
**OR**  
Press the **PTT** button or any control head button other than the **Menu Select** button directly below **H/L** to turn off the external alarm(s).  
The external alarm(s) is turned off and automatically rearmmed so that when you exit the entry, the external alarm(s) will automatically turn on.  
**OR**  
Press the **Menu Select** button directly below **H/L** to turn off the external alarm(s) and exit the Horn and Lights feature.  
Press the **Menu Select** button directly below **H/L** momentarily to rearm the horn and lights feature.

*The **Volume rocker** and the **DIM** button have no effect on the state of the external alarms.*

Draft 1

## Using the Voice Announcement

This feature enables the radio to audibly indicate the current feature mode, Zone or Channel the user has just assigned. This audio indicator can be customized per customer requirements. This is typically useful when the user is in a difficult condition to read the content shown on the display.

Each voice announcement is within a limit of three seconds maximum. The sum total duration for all voice announcements in a radio shall be no more than 1000 seconds.

**Note:** This feature must be preprogrammed by a qualified radio technician.

The features which Voice Announcement supports are:

- Zone
- Scan
- Talkaround/Direct
- Emergency On/Off
- ICUA
- Multi Functional Button
- Channel
- PL Disabled
- Tx Inhibit
- Secure/Clear
- Keypad/Control Lock

**Note:** Voice announcements support certain number of zone-channel, but not all.

Seek advice from your dealer or qualified technician for the best selections for this feature.

The two options of priority for the Voice Announcement available are:

- **High** – enables the voice of the feature to announce even when the radio is receiving calls.
- **Low** – disables the voice of the feature from announcing when the radio is receiving calls.

### **Procedure:**

You hear a voice announcement when the features below are preprogrammed in the radio.

- The radio powers up. The radio announces the current zone and channel it is transmitting.
- Press the preprogrammed voice announcement button (which specifically programmed to playback the current zone and channel). The radio announces the current zone and channel it is transmitting.

Draft

**Note:** Pressing this preprogrammed playback button will always enable the voice feature to announce in High priority.

All the three programmable buttons at the side of the radio support this feature.

- Change to a new zone. The radio announces the current zone and channel it is transmitting.
- Change to a new channel within the current zone. The radio announces the current channel.
- Press either the **Menu Select** button or preprogrammed button of the radio to launch or terminate Scan, Monitor, Talkaround/Direct or Transmit Inhibit. The radio announces the corresponding feature activation or deactivation.

## Helpful Tips

Caring for Your Radio . . . . . page 103

Cleaning the External Surface of the Radio . . . . . page 104

### ■ Caring for Your Radio

The following are suggestions to assist you in troubleshooting possible operating problems.



Caution

The cables that connect to the rear of the radio could have live voltage on some of their pins. Do not remove or reconnect these cables. Only a qualified radio technician should perform this task. Service performed by unauthorized personnel may cause the radio to transmit an emergency alarm even if the unit is turned off.

Draft 10

If your radio is locked up or the display shows **Fail 01-90**, turn the radio off and then back on. If this does not correct the condition, take the radio to a qualified radio technician for service.

If radio operation is intermittent, check with other persons using the system for similar problems before taking the radio in for service. Similar problems indicate a system malfunction rather than a radio failure.

If symptoms persist or, if your unit exhibits other problems, contact a qualified radio technician.

## ■ Cleaning the External Surface of the Radio

---

### Procedure:

- 1 Combine one teaspoon of mild dishwashing detergent to one gallon of water (0.5% solution).
- 2 Apply the solution sparingly with a stiff, non-metallic, short-bristled brush, making sure excess detergent does not get entrapped near the connectors, controls or crevices.
- 3 Dry the radio thoroughly with a soft, lint-free cloth.



Caution

- Do not use solvents to clean your radio. Spirits may permanently damage the radio housing.
- Do not submerge the radio in the detergent solution.

Draft 4c



## Accessories

The accessory link below is for the family of products for APX. Not all accessories are FCC certified for operation with all APX models and/or bandsplits. Please refer to the specific subscriber APX price pages for a list of FCC certified accessories or contact your sales representative for accessory compatibility.

<http://www.motorolasolutions.com/APX>

## ■ Highlights for the Accessories

- 1 **GPS only antenna** is only used in either a single band UHF or 700/800 application where the Public Safety Microphone (PSM) is used with the corresponding PSM antenna. This antenna is only for GPS reception and cannot be used for receive/transmit operation at UHF, VHF or 700/800. This antenna is never to be used on the PSM.

Draft 1c

## Appendix: Maritime Radio Use in the VHF Frequency Range

Take a moment to review the following:

Special Channel Assignments. . . . . page 106

Operating Frequency Requirements. . . . . page 107

### ■ Special Channel Assignments

#### 📄 Emergency Channel

If you are in imminent and grave danger at sea and require emergency assistance, use **VHF Channel 16** to send a distress call to nearby vessels and the United States Coast Guard. Transmit the following information, in this order:

- 1 "MAYDAY, MAYDAY, MAYDAY."
- 2 "THIS IS \_\_\_\_\_, CALL SIGN \_\_\_\_\_."  
*State the name of the vessel in distress 3 times, followed by the call sign or other identification of the vessel, stated 3 times.*
- 3 Repeat "MAYDAY" and the name of the vessel.

- 4 "WE ARE LOCATED AT \_\_\_\_\_."  
*State the position of the vessel in distress, using any information that will help responders to locate you, e.g.:*
  - *latitude and longitude*
  - *bearing (state whether you are using true or magnetic north)*
  - *distance to a well-known landmark*
  - *vessel course, speed or destination*
- 5 State the nature of the distress.
- 6 Specify what kind of assistance you need.
- 7 State the number of persons on board and the number needing medical attention, if any.
- 8 Mention any other information that would be helpful to responders, such as type of vessel, vessel length and/or tonnage, hull color, etc.
- 9 "OVER."
- 10 Wait for a response.
- 11 If you do not receive an immediate response, remain by the radio and repeat the transmission at intervals until you receive a response. Be prepared to follow any instructions given to you.

#### 📄 Non-Commercial Call Channel

For non-commercial transmissions, such as fishing reports, rendezvous arrangements, repair scheduling, or berthing information, use **VHF Channel 9**.

Draft 10

## ■ Operating Frequency Requirements

A radio designated for shipboard use must comply with Federal Communications Commission Rule Part 80 as follows:

- on ships subject to Part II of Title III of the Communications Act, the radio must be capable of operating on the 156.800 MHz frequency
- on ships subject to the Safety Convention, the radio must be capable of operating:
  - in the simplex mode on the ship station transmitting frequencies specified in the 156.025 – 157.425 MHz frequency band, and
  - in the semiduplex mode on the two frequency channels specified in the table below.

**Note:** Simplex channels 3, 21, 23, 61, 64, 81, 82, and 83 cannot be lawfully used by the general public in US waters.

Additional information about operating requirements in the Maritime Services can be obtained from the full text of FCC Rule Part 80 and from the US Coast Guard.

**Table A-1: VHF Marine Channel List**

Channel Number	Frequency (MHz)	
	Transmit	Receive
1	156.050	160.650

**Table A-1: VHF Marine Channel List (Continued)**

Channel Number	Frequency (MHz)	
	Transmit	Receive
2	156.100	160.700
*	156.150	160.750
4	156.200	160.800
5	156.250	160.850
6	156.300	–
7	156.350	160.950
8	156.400	–
9	156.450	156.450
10	156.500	156.500
11	156.550	156.550
12	156.600	156.600
13**	156.650	156.650
14	156.700	156.700
15**	156.750	156.750
16	156.800	156.800
17**	156.850	156.850
18	156.900	161.500
19	156.950	161.550
20	157.000	161.600
*	157.050	161.650
22	157.100	161.700
*	157.150	161.750

Table A-1: VHF Marine Channel List (Continued)

Channel Number	Frequency (MHz)	
	Transmit	Receive
24	157.200	161.800
25	157.250	161.850
26	157.300	161.900
27	157.350	161.950
28	157.400	162.000
60	156.025	160.625
*	156.075	160.675
62	156.125	160.725
63	156.175	160.775
*	156.225	160.825
65	156.275	160.875
66	156.325	160.925
67**	156.375	156.375
68	156.425	156.425
69	156.475	156.475
71	156.575	156.575
72	156.625	–
73	156.675	156.675
74	156.725	156.725
75	***	***
76	***	***
77**	156.875	–

Table A-1: VHF Marine Channel List (Continued)

Channel Number	Frequency (MHz)	
	Transmit	Receive
78	156.925	161.525
79	156.975	161.575
80	157.025	161.625
*	157.075	161.675
*	157.125	161.725
*	157.175	161.775
84	157.225	161.825
85	157.275	161.875
86	157.325	161.925
87	157.375	161.975
88	157.425	162.025

\* Simplex channels 3, 21, 23, 61, 64, 81, 82, and 83 cannot be **lawfully used** by the general public in US waters.

\*\* Low power (1 W) only

\*\*\* Guard band

**Note:** A – in the Receive column indicates that the channel is transmit only.

## Glossary


This glossary is a list of specialized terms used in this manual.

Term	Definition
<b>ACK</b>	Acknowledgment of communication.
<b>Active Channel</b>	A channel that has traffic on it.
<b>Analog Signal</b>	An RF signal that has a continuous nature rather than a pulsed or discrete nature.
<b>ARS</b>	Automatic Registration Service
<b>ASTRO 25 Trunking</b>	Motorola standard for wireless digital trunked communications.
<b>ASTRO Conventional</b>	Motorola standard for wireless digital conventional communications.
<b>Autoscan</b>	A feature that allows the radio to automatically scan the members of a scan list.
<b>AUX CH</b>	Auxiliary Control Head
<b>Call Alert</b>	Privately page an individual by sending an audible tone.

Term	Definition
<b>Carrier Squelch</b>	Feature that responds to the presence of an RF carrier by opening or unmuting (turning on) a receiver's audio circuit. A squelch circuit silences the radio when no signal is being received so that the user does not have to listen to "noise".
<b>Central Controller</b>	A software-controlled, computer-driven device that receives and generates data for the trunked radios assigned to it. It monitors and directs the operations of the trunked repeaters.
<b>Channel</b>	A group of characteristics such as transmit/receive frequency pairs, radio parameters, and encryption encoding.
<b>CHIB</b>	Control Head Interface Board
<b>Control Channel</b>	In a trunking system, one of the channels that is used to provide a continuous, two-way/data communications path between the central controller and all radios on the system.
<b>Conventional</b>	Typically refers to radio-to-radio communications, sometimes through a repeater (see Trunking).
<b>Conventional Scan List</b>	A scan list that includes only conventional channels.

Draft 10

Term	Definition
<b>CP</b>	Codeplug
<b>Cursor</b>	A visual tracking marker (a blinking line) that indicates a location on the display.
<b>Deadlock</b>	Displayed by the radio after three failed attempts to unlock the radio. The radio must be powered off and on prior to another attempt.
<b>Digital Private Line (DPL)</b>	A type of coded squelch using data bursts. Similar to PL except a digital code is used instead of a tone.
<b>Digital Signal</b>	An RF signal that has a pulsed, or discrete, nature, rather than a continuous nature.
<b>Dispatcher</b>	An individual who has radio system management duties.
<b>DSP</b>	Digital Signal Processing
<b>Dynamic Regrouping</b>	A feature that allows the dispatcher to temporarily reassign selected radios to a single special channel so they can communicate with each other.
<b>ESN</b>	Electrical Serial Number

Term	Definition
<b>Failsoft</b>	A feature that allows communications to take place even though the central controller has failed. Each trunked repeater in the system transmits a data word informing every radio that the system has gone into failsoft.
<b>FCC</b>	Federal Communications Commission.
<b>FM</b>	Frequency Modulation
<b>Hang Up</b>	Disconnect.
<b>Home screen</b>	The first display information after the radio completes its self test.
<b>KVL</b>	Key-variable loader: A device for loading encryption keys into the radio.
<b>LCD</b>	Liquid crystal display.
<b>LED</b>	Light-emitting diode.
<b>Menu Entry</b>	A software-activated feature shown at the bottom of the display – selection of these features is controlled by the  .
<b>MCHB</b>	Millennium Control Head Board

Draft 1c

Term	Definition
<b>Monitor</b>	Check channel activity through menu entries. If the channel is clear, you hear static. If the channel is in use, you hear conversation. It also serves as a way to check the volume level of the radio, since the radio “opens the squelch” when the monitor button is pressed.
<b>Multi-System Talkgroup Scan List</b>	A scan list that can include both talkgroups (trunked) and channels (conventional).
<b>Network Access Code</b>	Network Access Code (NAC) operates on digital channels to reduce voice channel interference between adjacent systems and sites.
<b>Non-Tactical/ Revert</b>	The user talks on a preprogrammed emergency channel. The emergency alarm is sent out on this same channel.
<b>OTAR</b>	Over-the-air rekeying
<b>Page</b>	A one-way alert, with audio and/or display messages.
<b>Personality</b>	A set of unique features specific to a radio.
<b>PIN</b>	Personal Identification Number
<b>Preprogrammed</b>	Refers to a software feature that has been activated by a qualified radio technician.

Term	Definition
<b>Private (Conversation) Call</b>	A feature that lets you have a private conversation with another radio user in the talkgroup.
<b>Private Line (PL)</b>	A sub-audible tone that is transmitted such that only receivers decoding the tone receives it.
<b>Programmable</b>	Refers to a radio control that can have a radio feature assigned to it.
<b>PTT</b>	Push-To-Talk – the <b>PTT button</b> engages the transmitter and puts the radio in transmit (send) operation when pressed.
<b>Radio Frequency (RF)</b>	The part of the general frequency spectrum between the audio and infrared light regions (about 10 kHz to 10,000,000 MHz).
<b>Repeater</b>	A conventional radio feature, where you talk through a receive/transmit facility that re-transmits received signals, in order to improve communications range and coverage.
<b>Selective Call</b>	A feature that allows you to call a select individual, intended to provide privacy and to eliminate the annoyance of having to listen to conversations of no interest to you.

Term	Definition
<b>Selective Switch</b>	Any digital P25 traffic having the correct Network Access Code and the correct talkgroup.
<b>Squelch</b>	Special electronic circuitry, added to the receiver of a radio, that reduces, or cuts off, unwanted signals before they are heard in the speaker.
<b>Standby</b>	An operating condition whereby the radio's speaker is muted but still continues to receive data.
<b>Status Calls</b>	Pre-defined text messages that allow the user to send a conditional message without talking.
<b>Tactical/ Non-Revert</b>	The user talks on the channel that was selected before the radio entered the emergency state.
<b>Talkaround</b>	Bypass a repeater and talk directly to another unit for easy local unit-to-unit communications.
<b>Talkgroup</b>	An organization or group of radio users who communicate with each other using the same communication path.
<b>TMS</b>	Text Messaging Service

Term	Definition
<b>Trunking</b>	The automatic sharing of communications paths between a large number of users (see Conventional).
<b>Trunking Priority Monitor Scan List</b>	A scan list that includes talkgroups that are all from the same trunking system.
<b>USK</b>	Unique Shadow Key
<b>UTC</b>	Coordinated Universal Time. The international time standard (formerly Greenwich Mean Time, or GMT). Zero hours UTC is midnight in Greenwich, England, which is located at 0 degrees longitude. Everything east of Greenwich (up to 180 degrees) is later in time; everything west is earlier. There are 42 time authorities around the world that are constantly synchronizing with each other. Abbreviated as UTC (English backronym = Universal Time, Coordinated), it is also known as Zulu (Z) Time.
<b>Zone</b>	A grouping of channels.

Draft 1c



# Commercial Warranty and Service

## Limited Warranty

### MOTOROLA COMMUNICATION PRODUCTS

#### I. WHAT THIS WARRANTY COVERS AND FOR HOW LONG:

MOTOROLA SOLUTIONS INC. ("MOTOROLA") warrants the MOTOROLA manufactured Communication Products listed below ("Product") against defects in material and workmanship under normal use and service for a period of time from the date of purchase as scheduled below:

APX Mobile Radio	One (1) Year
Product Accessories	One (1) Year

MOTOROLA, at its option, will at no charge either repair the Product (with new or reconditioned parts), replace it (with a new or reconditioned Product), or refund the purchase price of the Product during the warranty period provided it is returned in accordance with the terms of this warranty. Replaced parts or boards are warranted for the balance of the original applicable warranty period. All replaced parts of Product shall become the property of MOTOROLA.

This express limited warranty is extended by MOTOROLA to the original end user purchaser only and is not assignable or transferable to any other party. This is the complete warranty for the

Product manufactured by MOTOROLA. MOTOROLA assumes no obligations or liability for additions or modifications to this warranty unless made in writing and signed by an officer of MOTOROLA. Unless made in a separate agreement between MOTOROLA and the original end user purchaser, MOTOROLA does not warrant the installation, maintenance or service of the Product.

MOTOROLA cannot be responsible in any way for any ancillary equipment not furnished by MOTOROLA which is attached to or used in connection with the Product, or for operation of the Product with any ancillary equipment, and all such equipment is expressly excluded from this warranty. Because each system which may use the Product is unique, MOTOROLA disclaims liability for range, coverage, or operation of the system as a whole under this warranty.

#### II. GENERAL PROVISIONS:

This warranty sets forth the full extent of MOTOROLA'S responsibilities regarding the Product. Repair, replacement or refund of the purchase price, at MOTOROLA'S option, is the exclusive remedy. THIS WARRANTY IS GIVEN IN LIEU OF ALL OTHER EXPRESS WARRANTIES. IMPLIED WARRANTIES, INCLUDING WITHOUT LIMITATION, IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, ARE LIMITED TO THE DURATION OF THIS LIMITED WARRANTY. IN NO EVENT SHALL MOTOROLA BE LIABLE FOR DAMAGES IN EXCESS OF THE PURCHASE PRICE OF THE PRODUCT, FOR ANY LOSS OF USE, LOSS OF TIME, INCONVENIENCE, COMMERCIAL LOSS, LOST PROFITS OR SAVINGS OR OTHER INCIDENTAL, SPECIAL OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OR

INABILITY TO USE SUCH PRODUCT, TO THE FULL EXTENT SUCH MAY BE DISCLAIMED BY LAW.

### III. STATE LAW RIGHTS:

SOME STATES DO NOT ALLOW THE EXCLUSION OR LIMITATION OF INCIDENTAL OR CONSEQUENTIAL DAMAGES OR LIMITATION ON HOW LONG AN IMPLIED WARRANTY LASTS, SO THE ABOVE LIMITATION OR EXCLUSIONS MAY NOT APPLY.

This warranty gives specific legal rights, and there may be other rights which may vary from state to state.

### IV. HOW TO GET WARRANTY SERVICE:

You must provide proof of purchase (bearing the date of purchase and Product item serial number) in order to receive warranty service and, also, deliver or send the Product item, transportation and insurance prepaid, to an authorized warranty service location. Warranty service will be provided by MOTOROLA through one of its authorized warranty service locations. If you first contact the company which sold you the Product (e.g., dealer or communication service provider), it can facilitate your obtaining warranty service. You can also call MOTOROLA at 1-800-927-2744 US/Canada.

### V. WHAT THIS WARRANTY DOES NOT COVER:

- A) Defects or damage resulting from use of the Product in other than its normal and customary manner.
- B) Defects or damage from misuse, accident, water, or neglect.

- C) Defects or damage from improper testing, operation, maintenance, installation, alteration, modification, or adjustment.
- D) Breakage or damage to antennas unless caused directly by defects in material workmanship.
- E) A Product subjected to unauthorized Product modifications, disassembles or repairs (including, without limitation, the addition to the Product of non-MOTOROLA supplied equipment) which adversely affect performance of the Product or interfere with MOTOROLA's normal warranty inspection and testing of the Product to verify any warranty claim.
- F) Product which has had the serial number removed or made illegible.
- G) Rechargeable batteries if:
  - any of the seals on the battery enclosure of cells are broken or show evidence of tampering.
  - the damage or defect is caused by charging or using the battery in equipment or service other than the Product for which it is specified.
- H) Freight costs to the repair depot.
- I) A Product which, due to illegal or unauthorized alteration of the software/firmware in the Product, does not function in accordance with MOTOROLA's published specifications or the FCC certification labeling in effect for the Product at the time the Product was initially distributed from MOTOROLA.
- J) Scratches or other cosmetic damage to Product surfaces that does not affect the operation of the Product.
- K) Normal and customary wear and tear.

Draft

## VI. PATENT AND SOFTWARE PROVISIONS:

MOTOROLA will defend, at its own expense, any suit brought against the end user purchaser to the extent that it is based on a claim that the Product or parts infringe a United States patent, and MOTOROLA will pay those costs and damages finally awarded against the end user purchaser in any such suit which are attributable to any such claim, but such defense and payments are conditioned on the following:

- A) that MOTOROLA will be notified promptly in writing by such purchaser of any notice of such claim;
- B) that MOTOROLA will have sole control of the defense of such suit and all negotiations for its settlement or compromise; and
- C) should the Product or parts become, or in MOTOROLA's opinion be likely to become, the subject of a claim of infringement of a United States patent, that such purchaser will permit MOTOROLA, at its option and expense, either to procure for such purchaser the right to continue using the Product or parts or to replace or modify the same so that it becomes non-infringing or to grant such purchaser a credit for the Product or parts as depreciated and accept its return. The depreciation will be an equal amount per year over the lifetime of the Product or parts as established by MOTOROLA.

MOTOROLA will have no liability with respect to any claim of patent infringement which is based upon the combination of the Product or parts furnished hereunder with software, apparatus or devices not furnished by MOTOROLA, nor will MOTOROLA have any liability for the use of ancillary equipment or software not furnished by MOTOROLA which is attached to or used in connection with the Product. The foregoing states the entire liability of MOTOROLA with respect to infringement of patents by the Product or any parts thereof.

Laws in the United States and other countries preserve for MOTOROLA certain exclusive rights for copyrighted MOTOROLA software such as the exclusive rights to reproduce in copies and distribute copies of such MOTOROLA software. MOTOROLA software may be used in only the Product in which the software was originally embodied and such software in such Product may not be replaced, copied, distributed, modified in any way, or used to produce any derivative thereof. No other use including, without limitation, alteration, modification, reproduction, distribution, or reverse engineering of such MOTOROLA software or exercise of rights in such MOTOROLA software is permitted. No license is granted by implication, estoppel or otherwise under MOTOROLA patent rights or copyrights.

## VII. GOVERNING LAW:

This Warranty is governed by the laws of the State of Illinois, U.S.A.

## VIII. FOR AUSTRALIA ONLY:

This warranty is given by Motorola Solutions Australia Pty Limited (ABN 16 004 742 312) of Tally Ho Business Park, 10 Wesley Court, Burwood East, Victoria.

Our goods come with guarantees that cannot be excluded under the Australia Consumer Law. You are entitled to a replacement or refund for a major failure and compensation for any other reasonably foreseeable loss or damage. You are also entitled to have the goods repaired or replaced if the goods fail to be of acceptable quality and the failure does not amount to a major failure.

Motorola Solutions Australia's limited warranty below is in addition to any rights and remedies you may have under the Australian Consumer Law. If you have any queries, please call Motorola Solutions Australia at 1800 457 439. You may also visit our website: [http://www.motorola.com/Business/XA-EN/Pages/Contact\\_Us#support\\_tab](http://www.motorola.com/Business/XA-EN/Pages/Contact_Us#support_tab) for the most updated warranty terms.

## SERVICE

Proper repair and maintenance procedures will assure efficient operation and long life for this product. A Motorola maintenance agreement will provide expert service to keep this and all other communication equipment in perfect operating condition. A nationwide service organization is provided by Motorola to support maintenance services. Through its maintenance and installation program, Motorola makes available the finest service to those desiring reliable, continuous communications on a contract basis. For a contract service agreement, please contact your nearest Motorola service or sales representative, or an authorized Motorola dealer.

Express Service Plus (ESP) is an optional extended service coverage plan, which provides for the repair of this product for a period of three years from the date of shipment from the factory, or the date of delivery if purchased from an authorized Motorola two-way radio dealer. For more information about ESP, contact the Motorola Radio Support Center, 2204 Galvin Drive, Elgin, IL 60123, 1-800-227-6772.

Draft 1c



**MOTOROLA**

Motorola Solutions, Inc.  
1303 East Algonquin Road  
Schaumburg, Illinois 60196 U.S.A.

MOTOROLA, MOTO, MOTOROLA SOLUTIONS and the Stylized M logo are trademarks or registered trademarks of Motorola Trademark Holdings, LLC and are used under license. All other trademarks are the property of their respective owners. © 2009 – 2012 Motorola Solutions, Inc. All rights reserved. August 2012.



**6875946M01-F**

Draft 1c