

USER MANUAL

PL-1352 Lynx Power Bank



FCC ID:2ABHA0013

A.V.: Accessoires Lithium ion battery UL 2056 certified

Model: SL019
 Item No.: PL-1352
 Input: DC 5V/550mA
 Maximum input: DC 5.3V/600mA
 Output: DC 5V/1000mA
 Battery/Cell capacity: 3.6V / 2200mAh, 7.92Wh
 Product capacity: 5V / 1460mAh, 7.3Wh
 Operating temperature: 0-45°C for Charging
 0-50°C for Discharging
 Product Name: Bluetooth Speaker Power Bank

EN


CAUTION: Risk of Fire and Burns, don't open, crush, disassemble and dispose of in fire. Accessible surfaces held or touched for short periods only. Don't heat above 50 °C or Incinerate. Follow Manufacturer's Instructions.

FR

DANGER: risque d'incendie et de brûlures, ne pas ouvrir, démonter, écraser ni jeter au feu. Ne pas toucher ou tenir les surfaces accessibles sur une longue durée. Ne pas chauffer au-dessus de 50 ° C. Instructions de fabricant Suivre.

MADE IN CHINA

PRODUCT OVERVIEW



1. 5V Input Port (Micro USB)
2. 5V Output Port (USB A-type)
3. Bluetooth Button
4. LED indicator
5. 3.5mm AUX Line-in Port

How to use

Instructions:

1. Pairing a device in bluetooth mode:

Press and hold the power button until the tone sounds and the blue and red LEDs begin flashing on either side of the Micro-USB Input Port. From your mobile device, select BT SPEAKER from the available Bluetooth connections. Once the connection is successful, the red LED will turn off and the blue LED will illuminate without flashing. The blue LED will flash while audio is played. The red LED will illuminate while the speaker is charging. Once it is fully charged, the blue LED will illuminate and the red LED will turn off.

2. Charging the portable Power bank

- a. Using your mobile phone's USB adapter. Connect a USB cable to your phone's USB adapter. Using the micro USB connector, connect the other end of the USB cable to the IN port on the portable Power bank. Plug the USB adapter into the outlet to begin charging.
- b. Using your computer. Connect a USB cable to a USB outlet on your computer. Using the micro USB connector,

connect the other end of the USB cable to an IN port on the portable Power bank. Make sure the computer is on to begin charging the portable Power bank.

3. Charging mobile phones and other electronic devices.

- a. The portable power device has a USB output port which has the maximum output current of 1000 mA.
- b. Connect to USB cable to your mobile phone/device using the appropriate connector. Connect the other end of the USB cable to the OUT port of the portable Power bank. Your mobile phone/device should display the status of charging.
- c. Remove the USB cable from your mobile device when it is fully charged.

Note: In order to charge device use only accessory cable (provided with power bank) or the cable included with your own device by the manufacturer.

FEATURES:

1. Compatible with smartphones and MP3 players.
2. Bluetooth audio connection.
3. Up to 12 hours of audio.

INCLUDED:

1. Bran Speaker Power Bank
2. USB Charging Cable
3. User Manual
4. 3.5mm Audio Cable

AUDIO SPECIFICATIONS:

Output:	1W (1kHz, THD 1%)
Frequency:	200Hz - 20kHz
Signal to noise ratio:	≥75dB
Impedance:	4 ohm (Ω)
Speaker Unit:	23.8mm
Playback Time:	12-13hrs

TROUBLESHOOTING

No sound:

1. Audio cable is not fully inserted into the 3.5mm audio port on the speaker or device.
2. Audio cable is damaged.
3. Source of audio is not working.
4. No LED indication when audio cable is inserted.
5. Mini speaker requires charging.

Not charging:

1. Input power source is incorrect.
2. Micro USB of charging cable is not fully inserted into the mini speaker charging port.
3. Charging cable is damaged.
4. Battery failure.

No LED indication:

1. LED indication failure.
2. No battery power left.
3. Audio cable is not fully inserted into one or both ports.

IMPORTANT SAFETY PRECAUTION

WARNING – When using this product, basic precautions should always be followed, including the following:

1. Read all the instructions before using the product.
2. Power bank main unit contains an internal lithium ion battery. Upon initial use or after a prolonged storage period, fully charge it once. The unit's full performance is achieved only after 2 or 3 completed charge and discharge cycles.
3. Power banks are not allowed in checked luggage on commercial airline flights. Handle with care and dispose of in accordance to local regulations. Carry-on only.
4. To reduce the risk of injury, close supervision is necessary when the product is used near children.
5. Do not put fingers or hands into the product.
6. Do not expose power bank to rain or snow.
7. Use of a power supply or charger not recommended or sold by power pack manufacturer may result in a risk of fire or

FRONT

injury to persons.

8. Do not use the power bank in excess of its output rating. Overload outputs above rating may result in a risk of fire or injury to persons.

9. Do not use the power bank that is damaged or modified. Damaged or modified batteries may exhibit unpredictable behavior resulting in fire, explosion or risk of injury.

10. Do not disassemble the power bank. Take it to a qualified service person when service or repair is required. Incorrect reassembly may result in a risk of fire or injury to persons.

11. Do not expose a power pack to fire or excessive temperature. Exposure to fire or temperature above 100°C may cause explosion. The temperature of 100°C can be replaced by the temperature of 212°F.

12. Have servicing performed by a qualified repair person using only identical replacement parts. This will ensure that the safety of the product is maintained.

13. Do not use the phone or device when charging by the 2 in 1 AC adapter Power bank. Do not charge the power bank for more than 4-6 hours and do not leave unattended.

14. Disconnect the power bank when not in use.

Warning:

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

FCC STATEMENT

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

To assure continued compliance, any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment. (Example- use only shielded interface cables when connecting to computer or peripheral devices). This equipment complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

RF warning statement:
 The device has been evaluated to meet general RF exposure require

prime LINE[®]

SAVE THESE INSTRUCTIONS

BACK