



QS 9000
CERTIFIED

TVS
ELECTRONICS

**2 Year
Warranty**
(Including Print Head)

MSP 355 *XL Classic*

24 - wire • 136 column • 400 cps



**Superior
Printing
Quality for
your Business**

- ▶ Superior Printing Speed - 432cps
- ▶ Long Print Head Life - 200 Million Characters
- ▶ Wide Input Buffer - 100 KB
- ▶ Dual Interface - Parallel & Serial with Auto Sensing
- ▶ Convertible Push & Pull Tractor
- ▶ Flexible Paper Handling - Top, Rear & Bottom



MSP 355 xl *Classic* Product Specifications

Print Method	Serial Impact Dot Matrix	Input Buffer (Kilo Bytes)	100 KB
Print Direction	Bi-directional Logic Seeking	Reliability-MTBF (Power On Hours)	6,000 POH
Print Head - Type	24 - Wire	Acoustics - Noise Level	55 dB(A)
Print Width	136 Column	Emulation	ESC P/2, IBM Proprinter XL24e
Print Head Life	200 Million Characters	Interface	IEEE-P1284A Parallel & RS-232 C Serial (Auto Interface Switching)
Print Speed		Electrical Specifications	
Character Pitch (cpi)	10 12 15	Operating Voltage	150 VAC ~ 270 VAC
High Speed Draft (cps)	400	Mains Frequency	47 - 63 Hz
Draft (cps)	300 360 375	Power (Standby)	12 W
Letter Quality (cps)	83 100 125	Environmental - Operating Conditions	
Resident Printer Fonts		Temperature	+5 to +45°C
Draft	Draft, High Speed Draft	Relative Humidity	10% to 80%
Letter Quality	Roman, Sans Serif, Courier, Prestige, Script, Script-C, Orator, OCR-B, Orator-S	Physical Dimensions	
Letter Quality Scalable Fonts	Roman & Sans Serif (8 to 40 points)	Size (WxDxH) mm	608 x 379 x 147
Fast LQ*	Prestige	Weight (Kg)	7
Paper Handling		Ordering Information	
Paper Path-Standard	Top, Rear and Bottom	SKU / FRU No.	Description
Continuous-Tractor Feed-Standard	Convertible Push & Pull	1355MS09	MSP 355 xl Classic
Paper Size		Standard Configuration	CD-ROM
Continuous Form Width	4 - 16"		Quick Reference Guide
Cutsheets Width	7.2 - 16.1"		Insertion Plate
Paper Thickness (max) - Tractor feed	0.3 mm		Convertible Push/Pull
Paper Thickness (max) - Friction feed	0.3 mm		Tractor
Copy Capability	1+3 with Carbon		Black Ribbon Cartridge
Consumables - Ribbon			Parallel Interface Cable
Fabric-Ink Type	High Density (Mobius Loop)	Consumables	Power Cord
Fabric Life	3 Million Characters	3M011058	High Density Black Ribbon

1 kg = 2.2lbs; 1 inch = 2.54 cms.



Use only genuine TVS-E high density ribbons for Long Print Head Life. Counterfeits can damage your Printer.



EPA POLLUTION PREVENTER

As an Energy Star Partner TVS Electronics determines that this product meets the Energy Star Guidelines for energy efficiency.

Dealer / Channel Partner / Contact:

Note: All specifications are at standard operating conditions and are subject to change without notice.

Taking IT to the heart of India

Visit us at www.tvse.com

TVS Electronics Limited

34, Developed Plots, South Phase, Industrial Estate, Guindy, Chennai - 600 032. Ph: (44)2325506 / 09 Fax: (44)2327577

Branch Offices: ■ Ahmedabad: Ph: (79)7412325 / 35 / 37 E-mail: bm.subramanian@esa.tvse.co.in ■ Bangalore: Ph: (80)6566172 / 6568156

E-mail: kh.hema@esa.tvse.co.in ■ Bhopal: Ph: (755)275988 E-mail: vnj.vivek@esa.tvse.co.in ■ Chandigarh: Ph: (172)605581

E-mail: rr.rajagopalan@esa.tvse.co.in ■ Chennai: Ph: (44)8526290 / 8526469 E-mail: ct.chandrashekar@esa.tvse.co.in

■ Hyderabad: Ph: (40)7816667 / 7845144 E-mail: pgr.gopalrao@esa.tvse.co.in ■ Kochi: Ph: (484)355433 / 360462 / 3 / 4

E-mail: rr.ramesh@esa.tvse.co.in ■ Kolkata: Ph: (33)4769611-14 E-mail: ak.barua@esa.tvse.co.in ■ Lucknow: Ph: (522)285614 / 282042

E-mail: ak.rai@esa.tvse.co.in ■ Mumbai: Ph: (22)7912766-70 / 7668496 / 7668498 E-mail: ad.ashokdesikan@esa.tvse.co.in

■ New Delhi: Ph: (11)4603367-69 / 4603714 E-mail: kbh.harish@esa.tvse.co.in ■ Pune: Ph: (20)5674508 / 5675364 E-mail: rj.jaishankar@esa.tvse.co.in



NOTE: THE MANUFACTURER IS NOT RESPONSIBLE FOR ANY RADIO OR TV INTERFERENCE CAUSED BY UNAUTHORIZED MODIFICATIONS TO THIS EQUIPMENT. SUCH MODIFICATIONS COULD VOID THE USER'S AUTHORITY TO OPERATE THE EQUIPMENT.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.