

User's Manual

Tobii I-Series

I-12

I-15



Tobii I-Series User's manual

Version 1.0.4

05/2013

All rights reserved.

© Tobii Technology AB

The information contained in this document is proprietary to Tobii Technology. Any reproduction in part or whole without prior written authorization by Tobii Technology is prohibited.

Products that are referred to in this document may be either trademarks and/or registered trademarks of the respective owners. The publisher and the author make no claim to these trademarks.

While every precaution has been taken in the preparation of this document, the publisher and the author assume no responsibility for errors or omissions, or for damages resulting from the use of information contained in this document or from the use of programs and source code that may accompany it. In no event shall the publisher and the author be liable for any loss of profit or any other commercial damage caused or alleged to have been caused directly or indirectly by this document.

Content subject to change without notice.

Please check Tobii web site www.tobii.com for updated versions of this document.

The following products are protected by U.S. Patent 7,572,008:

- I-12 ET
- I-12 ETR
- I-15 ET
- I-15 ETR

You can locate the Type of I-Series device on the label on the back side.

Table of Contents

1	Introduction	1
1.1	Explanation of Admonitions	1
1.2	Symbols and Markings	1
1.3	Intended Use	3
1.3.1	Portable Use.....	3
1.3.2	Mounted Use.....	4
1.4	Package Contents.....	4
2	Safety.....	5
2.1	Avoiding Hearing Damage	5
2.2	Temperature	5
2.3	Power Supply and Batteries.....	6
2.4	Mounting.....	6
2.5	Emergency	7
2.6	Infrared — Eye Tracker	7
2.7	Epilepsy	7
2.8	Electricity	7
2.9	Child Safety.....	7
2.10	Environmental Control.....	7
2.11	Gaze Interaction.....	7
3	Overview of the Tobii I-12 and I-15	8
3.1	Key Features.....	8
3.2	Product Layout.....	8
3.2.1	The Tobii I-12 and Tobii I-15	8
3.2.2	Ports, Sensors and Device Buttons.....	9
3.3	Preinstalled Software	11
3.4	Configuring the Device.....	11
3.5	Accessing the microSD-Card	12
3.5.1	Removing the microSD-card.....	12
3.5.2	Inserting the microSD-Card.....	13
3.6	Tobii Quick Release Adapter Plate.....	13
3.6.1	Mounting the Tobii QR Adapter Plate	14
3.6.2	Removing the Tobii QR Adapter Plate	14
4	Batteries in the Tobii I-Series.....	15
4.1	Batteries	15
4.1.1	Hot Swappable.....	15
4.2	Charging.....	15
4.2.1	Checking Charge Level.....	16
4.3	Inserting and Releasing the Batteries	16
4.3.1	Inserting the Batteries.....	16
4.3.2	Releasing the Batteries	16
5	Using the Tobii I-Series	18
5.1	Starting the Device	18
5.1.1	Password Information	18
5.1.2	I-Series Welcome Guide.....	18
5.2	Shutting Down the Device	18
5.3	Using Tobii Gaze Interaction	19

5.3.1	Positioning	19
5.3.2	Track Box.....	19
5.3.3	Track Status Viewer.....	20
5.3.4	Positioning Guide.....	20
5.4	Using Windows Control	21
5.4.1	Windows Control Type	21
5.4.2	Starting and Disabling Tobii Windows Control.....	21
5.4.3	Using Gaze Selection	22
5.4.4	Using Mouse Emulation.....	26
5.5	Wake the I-Series from Sleep with Gaze Interaction.....	28
5.6	Pause/Resume Gaze Interaction and Put the I-Series to Sleep with Gaze Interaction.....	29
5.7	Using the Cameras	30
5.8	Using the GEWA Programmable IR Remote Control	30
5.8.1	Handling Tobii Product Key.....	30
5.9	Adjusting the Volume	30
5.10	Adjusting the Sound	31
5.11	Performing a Factory Recovery	31
5.12	Calibrating the Touch Screen.....	32
6	Configuring the I-Series with the I-Series Control Center.....	33
6.1	Buttons.....	34
6.1.1	Play Sound when Pressed.....	34
6.1.2	Disable All Buttons	34
6.2	Display.....	35
6.2.1	Brightness Adjustment.....	35
6.2.2	Display Rotation.....	35
6.3	Switches.....	36
6.3.1	Play Sound when Pressed.....	36
6.3.2	Configuring a Switch to Power On	36
6.3.3	Configuring a Switch to Power Off	37
6.4	Wake-on-Gaze®	37
6.5	Wireless.....	38
6.5.1	WLAN	38
6.5.2	Bluetooth® for Mobile Phone Communication.....	39
6.6	Safety.....	40
6.6.1	Audio.....	40
6.6.2	Temperature Control.....	40
6.7	Tobii Product Key	41
6.8	Setup & Updates.....	42
6.8.1	I-Series Welcome Guide.....	42
6.8.2	I-Series Update Notifier	42
6.9	System.....	43
6.9.1	Version & Model.....	43
6.9.2	Backup	44
6.10	Creating Shortcuts to Actions	45
6.10.1	Available Actions.....	45
6.10.2	Selecting Actions	45
7	Tobii Gaze Interaction Settings	47
7.1	Accessing the Tobii Gaze Interaction Settings.....	47
7.2	Calibration.....	47

7.2.1	Starting Calibration.....	48
7.2.2	Interrupting Calibration.....	48
7.2.3	Customizing Active Eye.....	48
7.2.4	Improving Calibration Point(s).....	49
7.2.5	Removing Calibration Point(s).....	50
7.2.6	Customizing the Calibration.....	50
7.2.7	Customizing the Calibration Area.....	51
7.3	Interaction.....	52
7.4	User Profile.....	53
7.4.1	Creating a New Profile.....	53
7.4.2	Selecting Current User Profile.....	54
7.4.3	Deleting a Profile.....	54
7.5	Windows Control.....	54
7.5.1	Auto Start.....	54
7.5.2	Windows Control Type.....	54
7.6	System Settings.....	56
7.6.1	System Off-Screen Menu.....	56
7.6.2	Positioning Guide.....	57
7.7	System Information.....	57
8	Gaze Selection Settings.....	59
8.1	The General Settings Tab.....	59
8.2	The Keyboard Settings Tab.....	60
9	Product Care.....	61
9.1	Temperature & Humidity.....	61
9.1.1	General Use.....	61
9.1.2	Transportation and Storage.....	61
9.2	Cleaning.....	61
9.2.1	Cleaning of the Speakers.....	61
9.3	Placement.....	61
9.4	Transporting the I-Series Device.....	61
9.5	Disposing of the Batteries.....	62
9.6	Disposing of the I-Series Device.....	62
Appendix A	Support, Warranty, Training Resources.....	63
A1	Customer Support.....	63
A2	Warranty.....	63
A3	Training Resources.....	63
Appendix B	Compliance Information.....	64
B1	FCC Statement.....	64
B1.1	For P15B Equipment.....	64
B1.2	For Portable Devices.....	64
B2	Radio Wave Exposure and Specific Absorption Rate (SAR) Information.....	64
B3	Industry Canada Statement.....	68
B4	CE Statement.....	68
B5	Standards.....	68
Appendix C	Computer Device States of Operation.....	70
Appendix D	Maximum Allowed Temperature.....	72
Appendix E	Technical Specifications.....	73
E1	Standard I-Series.....	73
E2	Radio Free I-Series.....	74

E3	Battery pack	76
E4	Eye Tracker	76
Appendix F	Approved Accessories	78

1 Introduction

Thank you for purchasing a Tobii I-Series device from Tobii Technology!

To ensure the optimal performance of this product, please take the time to read this manual carefully.

The Tobii I-Series device is available in two different sizes: the Tobii I-12 with a 12.1" screen and the Tobii I-15 with a 15.0" screen. The Tobii I-Series is a Gaze Interaction device but can be ordered without the Gaze Interaction function.

This User's Manual covers:

- The I-Series device, models Tobii I-12 and Tobii I-15.
- The I-Series Control Center (for controlling the device and the Tobii Product Key).
- The Tobii Gaze Interaction functions

1.1 Explanation of Admonitions

In this manual we use three (3) levels of admonitions as follows:



Is used for notifying the user of something important or of something that needs special attention.



Is used to inform of something that could cause harm to, or malfunction of, the equipment.



Is used to inform of something in which there is a conceivable risk of harm to the user if the Warning is ignored.



Is used to inform of something that can cause damage to hearing.


























Is used to inform of something that cause permanent bodily harm with prolonged skin contact if the Warning is ignored.

1.2 Symbols and Markings

This appendix provides information about the symbols that are used on the I-Series, its accessories or packaging.

Symbol or Markings	Description
	USB 3.0 Port
	USB 2.0 Ports
	Power On
	RJ 45 Ethernet Port
SW1	3.5 mm Switch port 1
SW2	3.5 mm Switch port 2

Symbol or Markings	Description
	Power Connector
	Head phone jack 3,5 mm
	Connector for an HDMI 1.3 cable
	To release the right battery
	To release the left battery
	Dispose of in accordance with your country's requirements.
	CE is the abbreviation of the European Communities and this mark tells customs officials in the European Union that the product complies with one or more of the EC Directives
	This mark is a certification mark employed on electronic products manufactured or sold in the United States which certifies that the electromagnetic interference from the device is under limits approved by the Federal Communications Commission.
	China Compulsory Certificate
	UL Classification Marks for Canada and the United States
	RoHS Compliant
	Consult User's Manual
	Li-Ion rechargeable battery. Must be recycled or disposed properly
	Recyclable material
	Type L and Type R Listing Marks for Canada and the United States
	Conforms to relevant Australian EMC requirements
	Japanese certification for electrical/electronic appliances and components

Symbol or Markings	Description
	Recycling in China
	Dispose of in accordance with your country's requirements.
	Safety Class II equipment (reinforced insulation)
	This mark show the pin out polarity on the AC/DC Power Adapter.
	Recognized component mark for Canada and the United States
	The most recognized International Safety mark. This safety listing signifies that the product was tested to IEC 60601-1
IP43	Enclosure ingress protection code per IEC 60529

1.3 Intended Use

The Tobii I-Series is an Assistive and Alternative Communication (AAC) product, a purpose built Speech Generating Device (SGD) designed to provide to its users increased communication ability and greater independence.

The Tobii I-Series is intended primarily to provide, and act as, a compliment to everyday communication for people that have challenges in their ability to speak due to injury, disability or illness. This intended use is reflected in design features such as long lasting batteries, superior sound quality, high durability, built in environmental control and connectivity features.

The Tobii I-Series is a Gaze Interaction device with a built-in Tobii Eye Tracker (optional) and a capacitive touch screen for touch access. The device is intended to be used in two orientations: one, upright and mounted (or standing upright, vertically, on an appropriate surface) for Gaze Interaction use, and two, lying flat (resting in a horizontal orientation) for touch access optimization. Tobii Gaze Interaction and touch can be used in combination with switches, keyboard and/or scanning as additional input methods.

The Tobii I-Series is designed primarily for face-to-face communication and secondarily for long distance communication, computer access and on-line social interaction. The Tobii I-Series allows the user to communicate via text or symbols to generate synthesized (computer voice) or digitized (recorded voice) speech for face-to-face communication. The variety of communication methods allows Tobii I-Series users the ability to realize their full potential.

The Tobii I-Series allows its user many options of communication through text message, chat and voice calls via Bluetooth® to cell phone, WiFi to Skype®, Internet to E-mail and other third party applications such as Facebook®.

With the Tobii I-Series, users have the freedom and flexibility provided via the Microsoft® Windows environment, as well as the option to control TV's and other household appliances via the GEWA Programmable IR Remote Control.

The Tobii I-Series meets the definition for durable medical equipment; and is registered as a Class 1 medical device. The Tobii I-Series is available in two (2) sizes; and is available as a dedicated (locked) Speech Generating Device.




The I-Series device does not sustain or support life.

In case of failure of the I-Series device, the user cannot communicate using it.


1.3.1 Portable Use

A portable I-Series can be used in two (2) different positions.

- Upright orientation
- Resting orientation



Upright Orientation



Resting Orientation

The **Upright** orientation is optimized for Gaze Interaction users and the **Resting** orientation is optimized for Touch or Scan users.

1.3.2 Mounted Use

The I-Series can be mounted on to several mounting systems. Mount the Tobii Quick Release (QR) adapter plate on to the device. The Tobii QR adapter plate can be attached to the following support systems:

- Daessy
- REHAdapt

For more information, see 3.6 *Tobii Quick Release Adapter Plate*, page 13 and Appendix F *Approved Accessories*, page 78.

1.4 Package Contents

The items below are included with your I-Series package:

- 1 Device (12" or 15")
- 1 Eye tracker (built in)
- 1 Tobii QR adapter plate
- 2 Batteries
- 1 Power Supply
- 1 Windows 7 Home Premium license
- 1 Tobii Communicator (pre-installed)
- 1 Tobii Sono Suite (pre-installed)
- 1 USB stick with Tobii Communicator and Tobii Sono Suite
- 1 I-Series User's Manual (on the device as a PDF document)
- 1 Quick Start Manual (printed)
- 1 Getting Started with Essentials TC 4.8 (printed)
- Safety and Compliance documents
- Warranty Document



Keep the original packaging materials for the Tobii I-Series.

In case the device needs to be returned to Tobii for Warranty related issues or repair, it is required that the original packaging (or equal equivalent) is used for shipping.

2 Safety

The I-Series device has been tested and approved as compliant to all the Specifications and Standards listed in *Appendix B Compliance Information, page 64* of this manual and in the *Appendix E Technical Specifications, page 73* – including, but not limited to, the Medical Device Standard (Class 1/Type B). Nevertheless, in order to ensure safe operation of your Tobii I-Series device, there are a few safety warnings to bear in mind:



No modification of this equipment is allowed



The I-Series is not to be used as a life supporting Device, and it shall not be relied on in case of loss of function due to power loss or other causes.



There could be a choking hazard risk if small parts detach from the I-Series device.



The I-Series device shall not be exposed to or used in heavy rain or weather conditions outside the Technical Specification of the I-Series device.



The I-Series device shall only be used with I-Series specific Accessories that have a mounting instruction included with the accessory.



Young children or people with cognitive disabilities should not have access to, or the use of, the I-Series device without parental or guardian supervision.



Do not attach any decorations, post-it notes or similar on the screen side of the I-Series device, that may interfere with the Gaze Interaction or touch screen performance.

2.1 Avoiding Hearing Damage



Permanent hearing loss may occur if earphones, headphones or speakers are used at high volume. To prevent this, the volume should be set to a safe level. You can become desensitized over time to high sound levels which may then sound acceptable yet still could be damaging your hearing. If you experience symptoms such as ringing in your ears, please lower the volume or stop using the earphones/headphones. The louder the volume, the less time is required before your hearing could be affected.

Hearing experts suggest the following measures to protect your hearing:

- Limit the amount of time you use earphones or headphones at high volume.
- Avoid turning up the volume to block out noisy surroundings.
- Turn the volume down if you cannot hear people speaking near you.

To establish a safe volume level:

- Set your volume control at a low setting.
- Slowly increase the sound until you can hear it comfortably and clearly, without distortion.

2.2 Temperature



This device can be made to operate in two different modes, Portable and Mounted. When the device is in Mounted mode it is allowed to run at a higher temperature; it sets the maximum allowable environmental temperature to its highest level. The risk with running the device in this mode is that it can reach temperatures in which prolonged use with direct skin contact may cause permanent bodily harm. Portable mode sets the maximum device temperature shut down limit to a lower temperature, reducing the risk for permanent bodily harm caused by prolonged exposure to the skin. Only choose Mounted mode when the device is mounted on a wheelchair, table, etc, with a proper mounting system.



Due to use in direct sunshine or in any other hot environment the I-Series device may have hot surfaces. There is a built in temperature sensor that monitors the temperature. If the sensor detects temperatures above the temperature specified in *Table D.1 Maximum Allowed Temperature, page 72* for portable mode and mounted mode the device will automatically trigger a Windows Shut Down or Hibernate (depending on Windows Power Button configuration) to not cause the User any risk of harm. It may take a while before I-Series device can be restarted as the unit may first need time to cool down.

2.3 Power Supply and Batteries



The I-Series device uses Lithium Ion batteries. These batteries have a storage temperature range of between -20 °C/-4 °F and 40 °C/104 °F within 6 months.

If you are in a hot environment, be aware that it can affect the ability to charge the batteries. The internal temperature has to be between 0 °C/32 °F and 45 °C/113 °F for the batteries to charge. If the internal battery temperature raises above 45 °C/113 °F the batteries will not charge at all.

Move the I-Series device and the batteries to a cooler environment to let the batteries charge properly.



Avoid exposing the batteries to fire or to temperatures above 50 °C/122 °F. These conditions may cause a battery to malfunction, generate heat, ignite or explode. Be aware that it is possible, in a worst case scenario, for temperatures to reach greater than those stated above in, for example, the trunk of a car on a hot day. So, storing the device, with batteries installed, in a hot car trunk could conceivably lead to a malfunction.



Do not disassemble or harm the battery. Pay attention to the environmental laws and regulations which apply in your area when disposing of batteries.



For safe operation of the I-Series device, use only charger, batteries and accessories approved by Tobii Technology.



Do not open, or modify, the metal casing of the I-Series device or of the power supply, since you may be exposed to potentially hazardous electrical voltage. The device contains no serviceable parts. If the I-Series device or it's accessories are mechanically damaged, **do not to use them**.



If the batteries are not charged or the I-Series is not powered up by the power supply, the I-Series device will shut down.



If the Power Supply Cord is damaged, replaceable by Service Personnel only



Do not connect any devices with a non-medical grade power supply to any connector on the I-Series device.



The appliance coupler of the power supply or separable plug is used as the Mains Disconnection Device, please do not to position the I-Series device so that it is difficult to operate the disconnection device.



Special regulations apply to shipping Lithium-ion batteries. If dropped, crushed, or short-circuited, these batteries can release dangerous amounts of heat and may ignite, and are dangerous in fires.

Please reference IATA regulations when shipping lithium metal or lithium ion batteries or cells:

http://www.iata.org/whatwedo/cargo/dangerous_goods/Pages/lithium_batteries.aspx

2.4 Mounting



The I-Series should be mounted according to MANUFACTURER instructions of approved mounts. Tobii Technology or its agents are not liable for damage or injuries to a person or its property due to a I-Series falling from a mounted configuration. The mounting of a I-Series is done entirely at the user's own risk.

2.5 Emergency



Do not rely on the device for emergency calls or banking transactions. We recommend having multiple ways to communicate in emergency situations. Banking transactions should only be carried out with a system recommended by, and approved according to the standards of, your bank.

2.6 Infrared — Eye Tracker



When activated, the Tobii I-Series emits pulsed infrared (IR) light. Certain medical devices are susceptible to disturbance by IR light and/or radiation. Do not use the I-Series when in the vicinity of such susceptible medical devices as their accuracy or proper functionality could be inhibited.

2.7 Epilepsy



Some people with **Photosensitive Epilepsy** are susceptible to epileptic seizures or loss of consciousness when exposed to certain flashing lights or light patterns in everyday life. This may happen even if the person has no medical history of epilepsy or has never had any epileptic seizures.

A person with Photosensitive Epilepsy would also be likely to have problems with TV screens, some arcade games, and flickering fluorescent bulbs. Such people may have a seizure while watching certain images or patterns on a monitor, or even when exposed to the light sources of an eye tracker. It is estimated that about 3-5% of people with epilepsy have this type of Photosensitive Epilepsy. Many people with Photosensitive Epilepsy experience an "aura" or feel odd sensations before the seizure occurs. If you feel odd during use, move your eyes away from the eye tracker.

2.8 Electricity



Do not open the casing of the I-Series device, since you may be exposed to potentially hazardous electrical voltage. The device contains no serviceable parts.

2.9 Child Safety



The I-Series are advanced computer systems and electronic devices. As such they are composed of numerous separate, assembled parts. In the hands of a child certain of these parts have the possibility of being separated from the device, possibly constituting a choking hazard or another danger to the child.

Young children should not have access to, or the use of, the device without parental or guardian supervision.

2.10 Environmental Control



The GEWA Programmable IR Remote Control — Environmental Control Unit (ECU) is not to be relied on as the only method of interaction with IR controlled devices.

2.11 Gaze Interaction



Some people may experience a certain amount of fatigue (due to intentional eye focusing and hard concentration) or even a dryness of the eyes (due to less frequent blinking) when first getting used to Gaze Interaction. If you are experiencing fatigue or dry eyes start off slowly and limit the length of your Gaze Interaction sessions to your comfort level. Remoisturizing eye drops can be helpful to combat dryness.

3 Overview of the Tobii I-12 and I-15

3.1 Key Features

The I-Series has several built-in features. Some of these come standard and some can be ordered as additional features.

Standard features: 2 × Camera, 1 × microphone, 2 × speakers, 1 × ECU (Environmental Control Unit), 1 × Bluetooth® (for mobile phones etc) and 1 × WLAN (Wireless Local Area Network).

Radio Frequency (RF) Free features: Standard features: 2 × Camera, 1 × microphone, 2 × speakers and 1 × ECU (Environmental Control Unit)


Additional feature: Gaze Interaction.

The additional feature can be purchased with the initial order or as an additional Tobii Product Key after delivery, except for Gaze Interaction for the type I-12 R which needs to be sent in to Tobii for upgrade. To order a Tobii Product Key or Gaze Interaction for the type I-12 R, please contact Tobii Customer Service, your re-seller or your sales representative.

3.2 Product Layout

A I-Series device has a color Capacitive touch, LED Backlight screen. The Tobii I-12 has a 12.1" screen with a 1024 × 768 pixel resolution. The Tobii I-15 has a 15.0" screen with a 1024 × 768 pixel resolution.

3.2.1 The Tobii I-12 and Tobii I-15



3.2.2 Ports, Sensors and Device Buttons




Figure 3.1 Front and Back

Position	Description	Position	Description
1	Webcam 2 MP Fixed Focus (FF)	6	GEWA Programmable IR Remote Control (Transmitter) This port is just for Transmitting IR Signals, to program the device, use port in Position 27 in Figure 3.2 Bottom, Left and Right Side, page 10
2	Light sensor	7	Camera 5 MP Auto Focus (AF)
3	Microphone	8	Mounting
4	Eye Tracker (If included, built in)	9	Speakers
5	Carrying grip	30	Label




Figure 3.2 Bottom, Left and Right Side

Position	Description	Position	Description
10	Power button	20	Menu button
11	Volume Up button	21	USB 3.0 connector
12	Volume Down button	22	2 × USB 2.0 connector
13	Head phone jack 3,5 mm	23	RJ45 Network connector
14	Connector for an HDMI 1.3 cable	24	Battery
15	Switch Port 1	25	Slide lock for battery
16	Switch Port 2	26	Battery indicator
17	Power Connector	27	GEWA Programmable IR Remote Control (Transmitter and Receiver) Use this port when programming the GEWA from within Tobii Communicator.
18	Quick Access Button 1 (Configurable)	28	microSD-card (under lid)
19	Quick Access Button 2 (Configurable)	29	I/O covers (for fulfilling IP43)



Never force a connector into a port. If the connector and port do not join with reasonable ease, they probably do not match. Make sure that the connector matches the port and that you have positioned the connector correctly in relation to the port.

Be extra careful with the USB connectors.

3.3 Preinstalled Software

The I-Series device is delivered with all preordered and required software installed and ready to use. Should a reinstallation become necessary at any stage perform a Factory Recovery. For more information, see 5.11 *Performing a Factory Recovery*, page 31.

The product number for Windows® can be found on the back of the I-Series device.


3.4 Configuring the Device

Use the preinstalled **I-Series Control Center** to configure the hardware functions on the device. You can access **I-Series Control Center** in one of the following ways:

- Double-click on the **I-Series Control Center** shortcut on the desktop, .

or

1. Go to **Start menu > Control Panel**.




2. Double-click **I-Series Control Center**, , if the Control Panel is in Classic View. If the Control Panel is in Category view, select **View by: > Small icons or Large icons**, and Double-click **I-Series Control Center**

or

1. Go to **Start menu > All Programs > Tobii > I-Series > I-Series Control Center**.


2. Click I-Series Control Center, 



In the list to the left, select which hardware configuration you want to change. In the area to the right, the different settings will be revealed. The changes are instantly executed.

For more information about configuring the I-Series with the I-Series Control Center, see *6 Configuring the I-Series with the I-Series Control Center, page 33*.




Anywhere you see this icon, , an information box is displayed when you briefly rest the mouse pointer on the icon or by touching the icon on the screen.

3.5 Accessing the microSD-Card

The microSD-Card (position 28 in *Figure 3.2 Bottom, Left and Right Side, page 10*) is installed in the I-Series device by default.

3.5.1 Removing the microSD-card



To remove the microSD-card:


1. Place the I-Series device face down on a flat surface.
2. Use a Phillips screwdriver to remove the screw that fastens the lid in place.
3. Remove the lid.
4. Press to release the microSD-card.
5. Pull the card out of the socket.
6. Replace the lid.
7. Tighten the screw with a Phillips screwdriver to fasten the lid in place.

3.5.2 Inserting the microSD-Card



To install the microSD-card:


1. Place the I-Series device face down on a flat surface.
2. Use a Phillips screwdriver to remove the screw that fastens the lid in place.
3. Remove the lid.
4. Carefully push the microSD-card into the socket.

 Do not use force when pushing in the microSD-card. If the microSD-card and socket do not join with reasonable ease, they probably do not line up.


5. Replace the lid.
6. Tighten the screw with a Phillips screwdriver to fasten the lid in place.

3.6 Tobii Quick Release Adapter Plate

Tobii QR adapter plate has two sides:




Daessy



REHAdapt

Make sure the required side of the Tobii QR adapter plate is face away from the I-Series for the mounting system to use.

3.6.1 Mounting the Tobii QR Adapter Plate



To mount the Tobii QR adapter plate:

1. Place the I-Series device face down on a flat surface.
2. Select the required side of the plate, see *1.3.2 Mounted Use, page 4*.
3. Place the plate onto the device with the required side facing away from the unit.
4. Tighten the three (3) screws using a Torx T20 screwdriver to that fasten the plate to the unit.

3.6.2 Removing the Tobii QR Adapter Plate

To remove the Tobii QR adapter plate:

1. Place the I-Series device face down on a flat surface.
2. Use a Torx T20 screwdriver to remove the three (3) screws that fasten the plate to the unit.
3. Remove the plate.

4 Batteries in the Tobii I-Series

4.1 Batteries

The I-Series device has two battery compartments. The batteries are of the same size and capacity for both the Tobii I-12 and I-15, see *Appendix E Technical Specifications, page 73*.




Figure 4.1 Battery with Indicator for Remaining Capacity

4.1.1 Hot Swappable

You can remove/replace one battery without switching off the I-Series device, providing that the remaining battery is sufficiently charged. The remaining battery requires being at least ~10% charged to maintain device operation.



Please allow the I-Series device a few seconds to detect the newly inserted battery before removing the other battery.

4.2 Charging

The batteries shall only be charged using the included adapter, or by using the Tobii I-Series Table Charger (not included, separate purchase required). When the I-Series device is shut down and the adapter is plugged in, the charging of completely discharged batteries may take up to 5 hours. The device can be used while the batteries are being charged, though this may affect the time a battery takes to reach full capacity.




To be sure that charging takes place in both the I-Series device and when using the I-Series Table Charger, be sure to plug the adaptor into both the wall socket and the device or Charger **BEFORE** you insert the batteries.

The expected battery lifetime is 500 charge/discharge cycles. After that, the capacity of the battery will decrease by about 20% in usage time.

For battery storage and charging temperatures, see *2 Safety, page 5*.

4.2.1 Checking Charge Level



Click on the battery icon, , in the Notification area to see the remaining charge of the battery, which is installed in the device.



You may also, at any time, check the status of a battery by pressing the indicator button on the face of the battery. Five LEDs (light-emitting diodes) will indicate the remaining charge level. For example, three lit LEDs indicate a 60% remaining charge, see *Figure 4.1 Battery with Indicator for Remaining Capacity*, page 15.

When charging, the highest capacity LED indicator will be blinking.



The lowest capacity LED indicator (the "20" LED), will also blink when the indicator button is pressed if the battery's capacity has dropped below 10%. So don't rely upon the blinking of the 20% indicator as a guarantee for charging.




If the batteries have been deeply discharged (this can happen by leaving an empty battery inserted in the I-Series device without the power adapter connected) you may not see any indication of charging when you reconnect the adapter properly to the I-Series device or the Table Charger. It may take some time (even up to 20 minutes) before you see an LED indication that any charging is taking place. The battery IS being charged during this duration though it is a recovery charge raising the level enough to begin normal charging.

4.3 Inserting and Releasing the Batteries

For safety reasons, the I-Series device is delivered without the batteries inserted. The batteries are delivered only partially charged. The I-Series device can be used right away. It is nevertheless recommended that the batteries are charged for at least two hours before using the device.


4.3.1 Inserting the Batteries



To insert the batteries:

1. Insert a battery in the battery compartment.
2. Press the battery until it locks in place. You should hear a click that confirms that the battery is in a locked place.

4.3.2 Releasing the Batteries



If the I-Series is in Upright orientation:

1. Press the battery slide lock to the side.

2. Pull the battery out (the battery will stop after ~1 cm / 0.4”).
3. Push the battery up a little bit (Do not push the battery all the way in again).
4. Pull the battery out of the battery compartment..

If the I-Series is in Resting orientation:

1. Place the I-Series device face down on a flat surface.
2. Press the battery slide lock to the side.
3. Pull the battery out of the battery compartment.

5 Using the Tobii I-Series

No skill other than reading is necessary for setting up the device. Follow this User's Manual and the Quick Start Guide.

5.1 Starting the Device

Start the device in one of the following ways:

- Press the power button on the right side of the device. (Position 9 in *Figure 3.2 Bottom, Left and Right Side, page 10*)
- Activate a configured Switch (see *6.3 Switches*).

When you have started the device, the Power LED will shine blue or green depending on if the device is connected to AC or on batteries. For more information about the LED Behavior, see *Appendix C Computer Device States of Operation, page 70*.

5.1.1 Password Information

The I-Series device is configured to start up, using the operating system present, without a password. Though unusual, there are situations in which the password window could plausibly pop up; for example, when creating a new user in the operating system, when returning from the operating system's sleep mode or when downloading software updates from the internet.



Creating a new windows user and downloading updates from the internet could possibly compromise the system and software settings of the operating system that have been set and installed at Tobii Technology.

Should the password window pop up, requiring a password, the default password on all I-Series devices is, "Tobii" (case sensitive). In order to type in the password use the Windows On-Screen Keyboard or an external USB keyboard (not included).

If you decide to change the password, be sure to write it down in a safe place for later use.

Suggested place to keep new password: _____

Without the operating system's access password, Tobii Support may be unable to assist you with any future difficulties.

5.1.2 I-Series Welcome Guide

When you start your I-Series Device for the first time you will be greeted by the I-Series Welcome Guide. The guide is a setup wizard that will walk you through some steps that will help you make the most of your device.

Follow the instructions and select on **Next** to get to the next page of the Guide.

5.2 Shutting Down the Device

The device should be shut down using one of the following ways:

- Use the start menu in Windows (recommended when possible).
- Press a configured Switch for two to seven seconds.



Pressing the Switch for more than 7 seconds will shut down the device immediately, disregarding any unsaved changes.

Should you be unable to shut the device down using either of the above, you can hold the power button on the right side of the device down for seven seconds. The device will consequently shut down immediately, without waiting for open applications to close.



This will not work if the side buttons have been disabled in the I-Series Control Center. For more information, see *6.1.2 Disable All Buttons, page 34*.



This is not considered a "clean" Windows shut down and is thus not recommended unless completely necessary.

5.3 Using Tobii Gaze Interaction

The Tobii I-Series operate with precision regardless of glasses, contact lenses, eye color or light conditions. Gaze Interaction enables you to control the computer with your eyes using either Gaze Enabled applications (like Tobii Communicator) or through the two types of Tobii Windows Control. See 5.4.1 *Windows Control Type*, page 21.

5.3.1 Positioning




Figure 5.1 Positioning

The Tobii I-Series is designed to work optimally when it is parallel to the user's eyes at a distance of about 60 cm (23.5 inches), see Figure 5.1 *Positioning*, page 19.




Figure 5.2 Positioning when Users Leaning Sideways or Those Lying Down

This means that for those users leaning sideways or those lying down the I-Series also needs to be tilted in order to keep the users eyes parallel to the screen and at the optimal distance, see Figure 5.2 *Positioning when Users Leaning Sideways or Those Lying Down*, page 19.



Make sure the user is placed comfortably in relation to the optimal positioning of, and distance from, the unit. Be aware also that the user's comfort, as well as the Gaze Interaction performance, will be enhanced if the sun is not shining directly on the screen or into the user's eyes.

The user should be positioned at the optimal distance to allow for the best possible Gaze Interaction.

5.3.2 Track Box

The Tobii I-Series allows for extensive Freedom of Head Movement. Once the I-Series is properly calibrated and placed in front of the user, no further adjustments are required.

The Tobii I-Series produces an industry leading sized track box with the approximate dimensions of 30 cm × 20 cm × 20 cm / 11.8 in × 7.9 in × 7.9 in (Width × Height × Depth). The Track Box is an invisible box positioned approximately 60 cm (23.5 in) straight out from a point just above the middle of the screen.

At 70 cm (27.5 in) the I-Series allows for lateral Freedom of Head Movement in an area of about 50 × 36 cm (20 × 14 in).


In order to function properly for Gaze Interaction the user needs at least one eye in the track box at all times.

5.3.3 Track Status Viewer



Use the Track Status viewer (see 5.3.3.1 *Showing Track Status*, page 20 for more information on how to open the Track Status viewer) to help determine the optimal height and horizontal positioning for Gaze Interaction with the I-Series.


- Ideally, the two dots that represent the user's eyes should be in the middle of the Track Status viewer.
- Use the distance meter on the right hand side of the Track Status viewer to determine the optimal distance the user should be from the I-Series.
- The white triangle in the distance meter should hover near the center, within the green, when the optimal distance from the I-Series is reached.

 For information about calibration of the I-Series see 7.2 *Calibration*, page 47. Also check the lighting conditions, related to what is mentioned above, when calibrating.

5.3.3.1 Showing Track Status

The track status viewer is a window/dialog where you can verify that the Gaze Interaction recognizes your eyes and that you are well positioned in front of the device.

Open the track status viewer in one of the following ways:

- Open **Tobii Gaze Interaction Settings > Calibration** and select the **Track status** button.
- Right-click (long-hold finger on icon for touch screen right clicking) on the **Tobii Gaze Interaction Settings** icon,  in the Notification area and select **Show track status**.



5.3.4 Positioning Guide

For extra assistance in positioning, there is a **Positioning guide** that will show itself automatically in the bottom-right corner of your monitor.

The **Positioning guide** is a visual guide that combines the function of the Track Status viewer with six different image based instructions to help the user with correct positioning.

The 6 instructions direct the user to:

1. Move head down.
2. Move head up.
3. Move head to the right.

4. Move head to the left.
5. Move head closer to the monitor.
6. Move head farther away from the monitor



Move head closer to the monitor.



Move head to the right.

The **Positioning guide** will automatically disappear when the user's positioning is improved in the way that is directed by the guide.

Some users may not want the **Positioning guide** to pop up every time their eyes leave optimal positioning.

To turn On or Off the automatic **Positioning guide**, see *7.6 System Settings, page 56*

5.4 Using Windows Control

Windows Control allows you to access the desktop and all applications of your Windows computer with Gaze Interaction.

5.4.1 Windows Control Type


Windows Control can be used in two different modes

- Gaze Selection
- Mouse Emulation

To select which type of Windows Control you wish to use and to customize Windows Control:


- Open **Tobii Gaze Interaction Settings > Windows Control**, see *7.5 Windows Control, page 54*
- Select your preferred type of Windows Control under **Windows Control Type**

5.4.2 Starting and Disabling Tobii Windows Control

To start Windows Control, right-click on the **Tobii Gaze Interaction Settings** icon,  , in the Notification area and select **Enable Windows Control**.



Or

Double-click on the **Tobii Windows Control** shortcut on the desktop,  , This will immediately start Windows Control.

To disable Windows Control, right-click on the **Tobii Gaze Interaction Settings** icon,  , in the Notification area and select **Disable Windows Control**.

You can also start Windows Control from Tobii Communicator or alternative communication software, which has implemented the functions provided by the Tobii Eye Control SDK

Auto start

- Open **Tobii Gaze Interaction Settings > Windows Control**.
- Check the **Auto start windows control at boot** check box if you want Windows Control to auto start when the Tobii Gaze Interaction Software starts.

5.4.3 Using Gaze Selection

The Gaze Selection mode of Windows Control makes it possible for the user to control a standard Windows desktop operating system with a two step selection method which reduces the risks of unwanted clicks. It also prevents the following of the mouse cursor with your gaze as opposed to the controlling of it (there is no floating mouse cursor in Gaze Selection).


1. The first step is to select the desired Task from the docked Taskbar by looking at it.
2. The second step is to look at the desired portion of the screen (or icon on the screen) where you want to execute the Task. An automatic zoom function is enabled, ending in the selection of the icon or execution of the task.

5.4.3.1 Gaze Selection Taskbar







At the top of the Gaze Selection Taskbar there is a Track Status viewer. It allows you to verify that the eye tracker recognizes your eyes and that you are well positioned in front of the device.



The Task Buttons in the Gaze Selection Taskbar can be in three different modes as shown in the figure below.

- **Normal (Unselected)** - No Task Button for Gaze Selection is chosen.
- **Selected (Blue)** - The marked Task Button is selected and the Task will be executed after the automatic zoom when the user looks at the desired position on the screen or icon on it. If the selection method is set to Switch in the Gaze Selection Settings Dialog, the chosen Task Button will still remain active after executing the Task.
- **High Precision(Orange)** - Same as **Selected** but with a higher precision. **High Precision** means that the zoom will progress deeper before the final execution of the Task, making the desired portion of the screen bigger and easier to select within. Activate this mode by resting your gaze on the Task Button until the color changes according to the image below.



5.4.3.2 Task Buttons

Task Button	Action	Description
	Place Cursor	Task that places the mouse cursor on a desired point/position. Used for mouse over functions, etc (this is not a "click").
	Gaze Scroll	Task that, if performed on a scrollable window, enables a gaze-controlled way to scroll the page <ul style="list-style-type: none"> Select the Task Look at any scrollable area and hold your gaze, the Gaze Scroll icon will appear where you looked Look above the icon to scroll up Look below the icon to scroll down Look back at the Gaze Selection Taskbar (or outside of the screen) to end scrolling
	Left Click	Task that performs a single left-click
	Double Click	Task that performs a double left-click
	Right Click	Task that performs a single right-click
	Gaze Drag & Drop	Task that performs two "clicks", where the first one represent the starting position for the drag and the second the drop position (to move objects or select areas). <ul style="list-style-type: none"> Select the Task Look at the object you want to move or the starting point for the area selection Execute the Gaze Selection (first "click") by Switch or Gaze Look immediately at the drop position for the object or end point for the area selection. Execute the second "click" by Switch or Gaze

Task Button	Action	Description
	Gaze Keyboard	Task that opens an on-screen Gaze enabled keyboard for Gaze typing
	Settings	Task that opens the Settings Dialog For more information, see <i>8 Gaze Selection Settings, page 59</i>

5.4.3.3 Selection Methods

There are two methods to execute the chosen Task. The method of choice is set from within the Gaze Selection Settings Dialog. Before executing a selection you select a Task from the Taskbar to execute. Gaze at your chosen task until it is highlighted as "Selected" or "High Precision".

- **Gaze** - To execute the chosen Task, rest your gaze at the desired portion of the screen (or icon on the screen) where you want to execute the Task. An automatic zoom function is enabled, ending in the selection of the icon or execution of the task.
- **Switch** - Two different execution modes.
 - **Single activation of the Switch** - the zoom function will execute in the same way as with the Gaze method and according to the settings made in the Gaze Selection Settings Dialog.
 - **Activate and hold the Switch** - the zoom function will zoom continuously and end only upon the release / deactivation of the switch.



When using the Gaze method, you have to look back to the Taskbar to select a new Task after the execution of the Task, even if it is the same as you have just used.

5.4.3.3.1 Sticky Tasks for Switch

When using the Switch method, the Task buttons will become "sticky" once you select them. This means that you do not have to look back at the Taskbar if you want to repeat the execution of a selected Task, only if you want to change the Task.

This allows for excellent use cases such as quick/continual surfing of the internet by selecting the Left Click Task once and then repeatedly selecting anything desired, without having to choose the Left Click Task again.

5.4.3.3.2 Activating a Task with a Keyboard button instead of a Switch




Selecting the "Right Click Keyboard Button", on an attached keyboard will activate a Task selection. It can be used in exactly the same way as a connected switch. For more information on Switches, see *5.4.3.3 Selection Methods, page 24*.

5.4.3.4 Gaze Keyboard

By selecting the Gaze Keyboard button on the Taskbar, the Gaze Keyboard will launch as an on-screen keyboard. The Gaze Keyboard will be positioned either at the top or at the bottom of the screen depending on where the user has placed the last mouse click (or last cursor position) before launching the Gaze Keyboard. The keyboard will place itself on the opposite side from where the mouse/cursor is.

The Gaze Keyboard consists of four keyboard pages in a rotating loop. The user can easily switch between the different keyboard pages by selecting the next page buttons located to the far left and right on all pages of the Gaze Keyboard.

The key on the keyboard where the user is looking will be indicated by a light frame around the character/function on the key.



While the user is typing, the last 5-10 characters will be displayed in blue on the indicated/highlighted key. This feature assists the user in easily spotting misspellings and reduces the need for looking at the actual spot where the text is inserted, thus increasing typing speed.

The four keyboard pages are:



Figure 5.3 Default Startup Page



Figure 5.4 First Page to the Right




Figure 5.5 Second Page to the Right or Left



Figure 5.6 First Page to the Left

i The Shift, Ctrl, Alt, Win and Alt Gr keys will become "sticky" once selected. This means that they will stay selected until the user selects a new key from the keyboard. They will stay sticky if the next selected key is another sticky key.

i To write a letter with an accent:

1. Select the accent
2. Select the character
3. The character will appear with the chosen accent.

i To delete a full word at a time instead of one character at a time:

1. Select the Ctrl key
2. Select the Backspace key

5.4.3.5 Gaze Selection in Combination with Region Based Keyboards

Gaze Selection can be used in combination with other eye controlled applications. "Gaze Enabled" regions in other applications are active as long as there is no active Task in the Gaze Selection Toolbar. If you are using Gaze Selection with switch the Task Buttons will be "sticky", if you need to deselect a Task just look back at the selected Task for a short moment.

5.4.3.6 Gaze Selection with "Windows Full Screen Mode"



When using Gaze Selection to view images, films, and files or to run programs in Windows Full Screen mode the Gaze Selection Taskbar will be covered.

To be able to exit Windows Full Screen mode without the Taskbar an "Esc" command has been emulated with a Gaze selectable "X" in the top left corner of anything that is run in Windows Full Screen mode.

To exit Windows Full Screen mode:

- Rest your Gaze for a few moments on the "X" in the top left corner of the screen. The "X" will be highlighted in red while it is being activated.
- Windows Full Screen mode will then be exited



The "X" might be difficult to see sometimes depending on the colors of what is being viewed in Windows Full Screen mode. It always starts out large and shrinks to draw your attention to it.


5.4.4 Using Mouse Emulation

The Mouse Emulation mode makes it possible for the user to emulate and control a standard PC mouse pointer on the screen.

To configure the Mouse Emulation, go to Tobii Gaze Interaction Settings. For more information, see [7.5.2.2 Mouse Emulation, page 55](#)

5.4.4.1 Placing the Mouse Emulation Menu

The menu can be placed anywhere on the desktop or docked along the edge of the screen. You dock the Mouse Emulation

Menu by dragging it to the edge of the screen. You can also do this by pressing and dragging the Move icon . When the menu is docked you have to look outside the screen to bring up the Mouse Emulation Menu items.



5.4.4.2 Clicking with Windows Control in Mouse Emulation Mode

Select what type of mouse click you want to perform from the **Button** drop down list in the Mouse Emulation Menu.




Right-click simulates a right mouse click.



Left-click simulates a left mouse click.

5.4.4.3 Magnifying with Windows Control in Mouse Emulation Mode

To use the magnifier, select the magnifier icon, , in the Mouse Emulation Menu.

If you want to perform a click with the magnifier:

1. Select the magnifier.
2. Select the other options as usual. The options will now have changed to reflect the magnification state.



Right Click Zoom



Left Click Zoom

5.4.4.4 Selecting Mouse Emulation Functions

You can set different functions for clicking:



Mouse cursor



No cursor movement on screen



Single-click



Double-click



Drag and drop

5.4.4.5 Pausing Windows Control in Mouse Emulation Mode

To pause Windows Control select the Pause icon in the Windows Control Menu.





Pause



Pausing Gaze Interaction can also be accomplished by looking at (about) the Tobii logo at the bottom of the Tobii I-Series, then selecting, using Gaze Interaction, the pause icon that pops up.

For more information, see *7.6.1 System Off-Screen Menu, page 56*

5.4.4.6 Scrolling with Windows Control in Mouse Emulation Mode

The scroll buttons appear automatically in the upper right corner in any object which can be scrolled. The buttons will only appear on the window which has focus. To activate the scroll press the  icon. If the buttons are in the way you can use the  icon to hide them.

When scroll mode is activated you will see a shaded gradient over the window which will be scrolled.



To scroll, look at the top or bottom of this gradient area.

Scroll functionality can be turned off in **Tobii Gaze Interaction Settings > Windows Control > Turn off scroll functionality.**

5.5 Wake the I-Series from Sleep with Gaze Interaction

It is possible to wake the I-Series from sleep with Gaze Interaction. This makes it possible for the user to be more independent and secure while alone or without a caregiver; during the night for example. If the user wants attention from the caregiver when

the user wakes at night, the user could wake the I-Series with Gaze Interaction and use the I-Series to communicate quickly to alert the caregiver. Waking the device from sleep in this way is called: **Wake-on-Gaze®**




Figure 5.7 Wake-on-Gaze® Area

To Wake-on-Gaze®:

1. Make sure the Wake-on-Gaze® is activated, see 6.4 *Wake-on-Gaze®, page 37*.
2. Look at the area in between the two illuminators of the Eye Tracker at the bottom of the I-Series, see *Figure 5.7 Wake-on-Gaze® Area, page 29*.



The Eye Tracker will search for the users eyes every 3 seconds.

The I-Series will wake up from Sleep and will be ready to use.

5.6 Pause/Resume Gaze Interaction and Put the I-Series to Sleep with Gaze Interaction

1. While using Gaze Interaction it is possible to both Pause/Resume Gaze Interaction (if the user wants to rest their eyes for a while) and to put the I-Series to Sleep (to reduce battery consumption, or in situations where the device is not needed). Putting the device to sleep in this way is called **Sleep-on-Gaze**.




Figure 5.8 System Off-Screen Area

To Pause Gaze Interaction:

1. Make sure the **Pause/Resume** System Off-Screen menu is activated, see 7.6.1 *System Off-Screen Menu, page 56*
2. Look at the area where the System Off-Screen menu has been configured for your I-Series, see *Figure 5.8 System Off-Screen Area, page 29*

For more information and for how to configure the System Off-Screen menu, see *7.6.1 System Off-Screen Menu, page 56*.

3. Selecting, using Gaze Interaction, the  (Pause) icon that pops up.

To Sleep-on-Gaze:

1. Make sure the **Sleep-on-Gaze** System Off-Screen menu is activated, see *7.6.1 System Off-Screen Menu, page 56*
2. Look at the area where the System Off-Screen menu has been configured for your I-Series, see *Figure 5.8 System Off-Screen Area, page 29*
For more information and for how to configure the System Off-Screen menu, see *7.6.1 System Off-Screen Menu, page 56*.

3. Selecting, using Gaze Interaction, the  (Sleep-on-Gaze) icon that pops up.
4. Select **Yes** for Sleep or **No** for Cancel

5.7 Using the Cameras

The two built-in cameras allows you to take snapshots of items in front of the I-Series device and also from the display side. Use **Tobii Communicator** or other relevant software to operate the cameras.

5.8 Using the GEWA Programmable IR Remote Control


The I-Series device includes a GEWA Programmable IR Remote Control — Environmental Control Unit (ECU) with two (2) filter windows:

- 1 Transmitter filter window — Position 6 in *Figure 3.1 Front and Back, page 9*
- 1 Transmitter and Receiver filter window — Position 27 in *Figure 3.2 Bottom, Left and Right Side, page 10*

 Use the Transmitter and Receiver filter window (position 27 in *Figure 3.2 Bottom, Left and Right Side, page 10*) when programming the GEWA Programmable IR Remote Control in **Tobii Communicator**.

The GEWA Programmable IR Remote Control is a programmable Infrared device that can be used to control equipment with an IR Remote Control such as TV-sets or DVDs.

For more information about how to use and program the GEWA Programmable IR Remote Control, see **Getting Started with Essentials for Communicator 4**.

 If the device you are trying to control is not responding, try tilting the I-Series device up or down slightly to change the angle at which the IR signal is being sent.

The ECU is not to be relied on as the only method of interaction with IR controlled devices.


5.8.1 Handling Tobii Product Key

To use the GEWA Programmable IR Remote Control, a Tobii Product Key is required. To view or enter a Tobii Product Key, go to the Tobii Product Key section in the **I-Series Control Center**. See *6.7 Tobii Product Key, page 41*

When the Tobii Product Key is in place, the GEWA IR Programmable Remote Control is ready to use.

5.9 Adjusting the Volume

To adjust the volume use the Volume Up button (Position 11) and volume down button (Position 12) on right hand side of the I-Series device. For position references, see *Figure 3.2 Bottom, Left and Right Side, page 10*

 Volume adjustments can also be done in **Tobii Communicator**.

5.10 Adjusting the Sound

You can configure the built-in speakers using the **Windows 7 Control Panel > Hardware and Sound**.



We refer to Microsoft's information on how to configure the sound in the Windows 7 Control Panel.



Sound adjustments can also be done in **Tobii Communicator**.

5.11 Performing a Factory Recovery

Every I-Series device has a factory image stored on the disk. If you need to restore the device back to its original state, this can be done by using our OEM Factory Recovery Application.





This will delete any personal data or software installed after the device was delivered.

Factory Recovery means that the device will be reset to the factory mode, without anything installed. In this mode you have to re-enter your Tobii Product Key and licenses to perform the SW installation you have ordered.





Make sure you've connected the Power Supply before you start the process - do not run the device on batteries, as it might run out of power during the Factory Recovery. In such a scenario, you might have to send the unit back to Tobii for repair.


To perform a Factory Recovery for your I-Series device, follow this procedure:

1. Backup your personal data such as documents and Tobii Communicator settings etc.
2. Make sure you have the I-Series Product Key available
3. Shut down the device
4. Connect a keyboard
5. Start up device again
6. Hold down the  (Arrow Down) keyboard button continually during startup until you get into "Windows Boot Manager"
7. Select "Factory Reset" and press the  (Enter) keyboard button.
8. The I-Series Software Installation dialogue will be loaded
9. Follow the instructions on the screen. These steps are identical to the initial setup you did when you first received the device.

or

To perform a Factory Recovery for your I-Series device, follow this procedure:

1. Backup your personal data such as documents and Tobii Communicator settings etc.
2. Make sure you have the I-Series Product Key available
3. Shut down the device
4. Connect a keyboard
5. Start up device again
6. Hold down the  (F8) keyboard button continually during startup until you get into "Advanced Boot Options"
7. Press the  (Esc) keyboard button to get to the "Windows Boot Manager"

8. Select "Factory Reset" and press the  (Enter) keyboard button.
9. The I-Series Software Installation dialogue will be loaded
10. Follow the instructions on the screen. These steps are identical to the initial setup you did when you first received the device.

The Factory Recovery process will now start. This will take about 40 minutes. After the restore process is finished, the device will be reset to its original image as it was when you first received it from Tobii. If you have installed any additional Software or Tobii Product Keys after you ordered the device, these will have to be manually installed again

5.12 Calibrating the Touch Screen

There are two ways of calibrating the Touch Screen depending on if the Windows Control Panel is in Category view or Classic view with Small/Large icon.

To calibrate the Touch screen from Category View in Windows Control Panel, follow this procedure:

1. Select **Start > Control Panel**
2. Select **Hardware and Sound**
3. Select **Tablet PC Settings**
4. Select the **Calibrate...** button under Display options
5. Follow the on-screen instructions

To calibrate the Touch screen from Classic View with small/Large icons in Windows Control Panel, follow this procedure:

1. Select **Start > Control Panel**
2. Select **Tablet PC Settings**
3. Select the **Calibrate...** button under Display options
4. Follow the on-screen instructions

6 Configuring the I-Series with the I-Series Control Center


The I-Series Control Center is the program on your I-Series Device where you can access and change the settings that you have chosen during your first setup with the I-Series Welcome Guide. You can also run the Welcome Guide again at any time of your choosing.

To open the I-Series Control Center:

- Double-click on the **I-Series Control Center** shortcut on the desktop, .

or

1. Go to **Start menu > Control Panel**.




2. Double-click **I-Series Control Center**, , if the Control Panel is in Classic View. If the Control Panel is in Category view, select **View by: > Small icons or Large icons**, and Double-click **I-Series Control Center**.

or

1. Go to **Start menu > All Programs > Tobii > I-Series > I-Series Control Center**.

2. Click **I-Series Control Center**, .

6.1 Buttons



You can create shortcuts to tasks, called actions, by programming the Quick Access buttons. The Quick Access buttons are located on the left side of the I-Series device, named **1**, **2** and **Menu**.

For more information about how to program an action for a button, see *6.10 Creating Shortcuts to Actions, page 45*

6.1.1 Play Sound when Pressed

To enable Play sound when pressed:

1. Open the **I-Series Control Center > Button**.
2. Select the **Play sound when pressed** check box to allow Audio feedback when the button is activated.

To disable Play sound when pressed:

1. Open the **I-Series Control Center > Button**.
2. Select to clear the **Play sound when pressed** check box.

6.1.2 Disable All Buttons

To avoid unintentional actions, all buttons on the I-Series device can be disabled.

To Disable all buttons:

1. Open the **I-Series Control Center > Button**.
2. Select the **Disable All Buttons** check box.



The Power button will work for starting the device even if all buttons are disabled.




Pressing the Power button for more than 7 seconds will shut down the device immediately, disregarding any unsaved changes, even if all buttons are disabled.

To Enable all buttons:

1. Open the **I-Series Control Center > Button**.
2. Select to clear the **Disable All Buttons** check box to allow all buttons again.

6.2 Display



6.2.1 Brightness Adjustment

There is a sensor on the device which will automatically adjust the screen brightness according to the surrounding light, relative to the selected level from Windows®.

To disable Automatic Brightness Adjustment:

1. Open the **I-Series Control Center > Display**.
2. Select to clear the **Enable automatic brightness adjustment (recommended)** check box.

To enable Automatic Brightness Adjustment:

1. Open the **I-Series Control Center > Display**.
2. Select the **Enable automatic brightness adjustment (recommended)** check box.

To manually adjust Brightness:

1. Open the **I-Series Control Center > Display**.
2. Select the **Windows Power Options** link.
3. Make the Brightness adjustments



Using a darker setting can improve battery runtime.

6.2.2 Display Rotation

The display can rotate automatically when turned 180 degrees, to facilitate using device in Upright orientation or Resting on the speakers.



With the Automatic display rotation activated, it could take a couple of seconds (the screen could also turn black) before the display is rotated.

To enable Automatic rotation according to device position:

1. Open the **I-Series Control Center > Display**.
2. Select the **Automatic rotation according to device orientation** radio button.

To set Fixed device position:


1. Open the **I-Series Control Center > Display**.
2. Select the **Fixed in upright orientation** or the **Fixed in resting orientation** radio button.



Gaze Interaction is optimized to work properly in the Upright orientation.

For more information about Upright orientation and Resting orientation, see *1.3.1 Portable Use, page 3*.

6.3 Switches



You can enable the switches to act as power ON (see *6.3.2 Configuring a Switch to Power On, page 36*) or OFF (see *6.3.3 Configuring a Switch to Power Off, page 37*) button.

Select the **Play sound when pressed** checkbox to allow Audio feedback when the switch is activated.

Select actions for the switches by selecting **Set action**.

For more information about how to program an action for a Switch, see *6.10 Creating Shortcuts to Actions, page 45*

6.3.1 Play Sound when Pressed

To enable Play sound when pressed:

1. Open the **I-Series Control Center > Button**.
2. Select the **Play sound when pressed** check box to allow Audio feedback when the button is activated.

To disable Play sound when pressed:

1. Open the **I-Series Control Center > Button**.
2. Select to clear the **Play sound when pressed** check box.

6.3.2 Configuring a Switch to Power On

To enable a connected Switch to power on the device:

1. Open the **I-Series Control Center > Switches**.
2. Select the **Enable switch "1 or 2" to act as Power On Button** check box.

To disable a connected Switch to power on the device:

1. Open the **I-Series Control Center > Switches**.
2. Select to clear the **Enable switch “1 or 2” to act as Power On Button** check box.

6.3.3 Configuring a Switch to Power Off


To enable a connected Switch to power off the device:

1. Open the **I-Series Control Center > Switches**.
2. Select the **Enable switch “1 or 2” to act as Power Off Button** check box.

To disable a connected Switch to power off the device:

1. Open the **I-Series Control Center > Switches**.
2. Select to clear the **Enable switch “1 or 2” to act as Power Off Button** check box.

6.4 Wake-on-Gaze®



The I-Series device can be set to wake automatically from Sleep mode when your eyes are registered as looking at the display.

To enable Wake-on-Gaze for the device:


1. Open the **I-Series Control Center > Wake-on-Gaze**.
2. Select the **Enable automatic Wake-on-Gaze** check box.
3. Select **Windows Power Options** link to adjust the Power Options (if needed)

To disable Wake-on-Gaze for the device:

1. Open the **I-Series Control Center > Wake-on-Gaze**.
2. Select to clear the **Enable automatic Wake-on-Gaze** check box.

For information about how to use Wake-on-Gaze®, see *5.5 Wake the I-Series from Sleep with Gaze Interaction, page 28*.

6.5 Wireless



6.5.1 WLAN



Not applicable for RF Free units.

The built-in WLAN (Wireless Local Area Network) support enables connection to wireless networks (such as Wi-Fi™ networks and access points) in compliance with the standard 802.11 b/g/n for both the I-12 and the I-15.

6.5.1.1 Handling Tobii Product Key

To be able to use WLAN communication, a Tobii Product Key is required. To view or enter a Tobii Product Key, go to the Tobii Product Key section in the **I-Series Control Center**. See *6.7 Tobii Product Key, page 41*

6.5.1.2 Enabling and Disabling the WLAN Communication


To enable WLAN communication:

1. Open the **I-Series Control Center > Wireless**.
2. Select the **Enable Wireless Local Area Network (WLAN)** check box.

To disable WLAN communication:


1. Open the **I-Series Control Center > Wireless**.
2. Clear the **Enable Wireless Local Area Network (WLAN)** check box or select the **Disable all wireless units** check box for disabling all wireless units.


6.5.1.3 Connecting to a WLAN

1. Click on the WLAN icon,  , in the Notification area on the Desktop.
2. Select **Connect to a network**.
3. Select a network to connect to.




Notification area

 A wireless access point which supports antenna diversity is recommended when setting up a wireless network to use with a I-Series device, for reliable performance. Such access points are generally recognized by having two antennas on the router device.

 Using an antivirus program is strongly recommended.

6.5.2 Bluetooth® for Mobile Phone Communication

 Not applicable for RF Free units.

The built-in Bluetooth® enables connection to a mobile phone which complies with mobile Bluetooth® standards.

 Only for use with **Tobii Communicator** for mobile phone communication.

For more information about how to use and program an Mobile phone to work with Bluetooth® on the I-Series device, see **Getting Started with Essentials for Communicator 4**.

For information about the Mobile phones that complies with the I-Series device, see www.tobii.com

6.5.2.1 Handling Tobii Product Key

To use Bluetooth® communication in the device, a Tobii Product Key is required. To view or enter a Tobii Product Key, go to the Tobii Product Key section in the **I-Series Control Center**. See *6.7 Tobii Product Key, page 41*

6.5.2.2 Enabling and Disabling Bluetooth® Communication

To enable Bluetooth® communication:

1. Open the **I-Series Control Center > Wireless**.
2. Select the **Enable Bluetooth** check box.


To disable Bluetooth® communication:

1. Open the **I-Series Control Center > Wireless**.
2. Clear the **Enable Bluetooth** check box or select the **Disable all wireless units** check box for disabling all wireless units.

6.5.2.3 Connecting to a Bluetooth® Device

For more information see **Getting Started with Essentials for Communicator 4**.

6.6 Safety



Upon starting the device for the first time, the safety settings in the **I-Series Control Center** will be a part of the I-Series Welcome Guide. To be able to run through the guide these safety settings must be confirmed. The safety settings exist for the safety of the customer. Be sure to read the safety details before accepting any changes.

6.6.1 Audio

Before you can use the speaker functionality and adjust speaker output settings you need to confirm the Audio safety details (if not already done during first start up).

To confirm:

1. Open the **I-Series Control Center > Safety**
2. Click on the **Audio safety details** text. A new dialog box opens and displays the safety text. Please read this thoroughly.
3. Select the **I have read and understand the safety details and I want to enable the speaker functionality** check box to confirm that you have read and understood the safety text.

6.6.2 Temperature Control

Before you can set the device usage in **I-Series Control Center > Temperature Control** you need to confirm the Temperature control safety details (if not done during first start up).

To confirm:

1. Open the **I-Series Control Center > Safety**
2. Click on the **Temperature Control safety details** text. A new dialog opens and displays the safety text. Please read this thoroughly.
3. Select the **I have read and understand the safety details and I want to enable the temperature control functionality** check box to confirm that you have read and understood the safety text.



You can use the device in a portable or mounted mode. Your choice will affect the maximum allowed device temperature. While having the device mounted, it is allowed to run at a higher temperature.

Both the I-12 and the I-15 can be used both as a portable and mounted device and can be operated in both portable and mounted mode.



If the device gets overheated the device will shut down. It may take a while before it can be restarted as the unit may first need time to cool down. If the device is still too hot, the power button will flash purple for a couple of seconds when trying to restart the I-Series device. For more information, see *Appendix C Computer Device States of Operation, page 70* and *Table D.1 Maximum Allowed Temperature, page 72*.

6.6.2.1 Device Usage


Specifying device usage mode takes place outside of the **Safety** settings but within **I-Series Control Center**.

To specify device usage:

1. Open the **I-Series Control Center > Safety**.
2. Click on preferred option for **Device usage**.
 - **Portable** — Portable mode sets the maximum device temperature shut down limit to a lower temperature, reducing the risk for permanent bodily harm caused by prolonged exposure to the skin
 - **Mounted** — Mounted mode sets the maximum device temperature to a higher temperature shut down limit

For more information, see *Table D.1 Maximum Allowed Temperature, page 72*

6.7 Tobii Product Key




The following features on the I-Series needs a licence for use:

- Eye tracker
- Bluetooth®
- WLAN
- IR
- Communicator


To view existing Tobii Product Key:

- Open the **I-Series Control Center > Tobii Product Key**.


If the  symbol is visible after a feature, the Tobii Product Key(s) on the device are valid for that feature.

To add a Tobii Product Key:

1. Open the **I-Series Control Center > Tobii Product Key**.
2. In the **Enter a Tobii product key** box, type the new Tobii Product Key.

To type the Tobii Product Key use either a connected keyboard or enable the on-screen keyboard by selecting this button .

6.8 Setup & Updates



Manage Tobii applications related to setting up your device and updating to the latest software.

6.8.1 I-Series Welcome Guide

The I-Series Welcome Guide guides the user through the setup procedure, such as License Agreement and Safety Setting etc.



If the I-Series Welcome Guide is not finished, it will automatically start up next time the I-Series is powered up.

To run the I-Series Welcome Guide at next start up, follow these step:

1. Open the **I-Series Control Center > Setup & Updates**.
2. Select the **Run at next startup** check box.

To run the I-Series Welcome Guide at once, follow these steps:

1. Open the **I-Series Control Center > Setup & Updates**.
2. Select the **Run now** button.

6.8.2 I-Series Update Notifier

The I-Series Update Notifier is a program that notifies you when the latest software updates for your Tobii Software are available (either automatically, on a regular basis, or manually, at a time of your choosing) and assists you in installing the updates.

If you have chosen to "Enable automatic updates" in either the I-Series Welcome Guide or, later, in the I-Series Control Center, the Update Notifier will actively search Tobii's sites for version Updates of your software.



To keep your I-Series device running properly it is highly recommended that you update your Tobii Software on a regular basis and it is therefore highly recommended that you enable automatic updates.

To Enable automatic search for updates:

1. Open the **I-Series Control Center > Setup & Updates**.
2. Select the **Enable automatic search for updates (recommended)** check box.

If an update is found the following Update Notifier window will pop up:

The update or updates available will show themselves in the Step One window of Update Notifier as large button with a green check mark on the right side. You will also be able to see the version number of the software that you currently have and the version number of the update.


If you choose not to download one or more of the available updates you can click on the button of the update you do not want and the check mark will turn into a red "X" mark.

Proceed in the following way:

- Click the **Download** button to download the updates to your Device and continue to Step Two.
- In Step Two, Click the **Install** button to install the chosen updates on your device and proceed to Step Three.
- Step Three informs you that your system has been updated, select the **Done** button to close the Update Notifier.

If you choose not to "Enable automatic updates" you can still check for updates for your Tobii software and update them manually using the I-Series Update Notifier.


To open and activate the I-Series Update Notifier manually (this opens the Step One window shown above and starts the same automatic update process):

- Navigate in Windows from your desktop to **Start Menu > All Programs > Tobii > I-Series** and select the I-Series Update Notifier icon, .

or

1. Open the **I-Series Control Center > Setup & Updates**.
2. Select the **Run now** button.

6.9 System



6.9.1 Version & Model

To view the version and model of the device:

- Open the **I-Series Control Center > System**.



Please have this information available if you have problems with the device and need to contact Customer Support.

To save the version and model of the device to a file:

1. Open the **I-Series Control Center > System**.
2. Select the **Save information to file** button.



You can attach the file containing all the information into an e-mail.

6.9.2 Backup

This is a system backup specific to your Tobii software-related files. The device automatically and regularly, once a week, backs up the data that is associated with your Tobii communications applications (Tobii Communicator Page Sets, files, settings, etc.), your Gaze Interaction files (profiles, calibration settings, interaction settings, etc.) and your device specific settings from the Control Center. You can manually start the backup below and/or restore the data from one of the three latest backups. Be aware that the changes made since the latest backup will be reverted if you choose to restore from a previous backup. All files in the My Documents folder will be backed up as well, if space is available on the microSD-card, as a second priority after the Tobii software-related files. **To back up all files on your device please use Microsoft's own Windows Backup and Restore application.**

The backup process executes once a week (every Sunday at 15.00) and the three latest backups are saved on the microSD-card.



If your I-Series device is not up and running at this time the backup will be performed at next start up.

The process backs up files for all users. If the backup drive does not have enough space some files will not be backed up. Image files have the lowest priority (backed up last). The largest file size for the backup of individual files is 100 MB, files larger than this will be excluded.

The backup files are placed in the directory **Q:\Backup\ (On the microSD-card).**



Tobii will not take responsibility for any other data than the "Tobii applications data"

6.9.2.1 User Profile Card

The I-Series device comes with a 32 GB microSD-card installed. The purpose of this card is to backup personal settings and data. In the case of fatal damage to the I-Series device. The microSD-card can be removed and inserted into a new device for quick and easy retrieval and restoration of personal data and settings.

6.9.2.2 Backup Manually by the User

To perform a manual backup of the system:

1. Open the **I-Series Control Center > System**.
2. Select the **Backup now** button.

When the backup is finished, the following will show up on the screen:




Backup finished.

6.9.2.3 Restoring Backup Files by the User

To restore one of the three last backup of the system:

1. Open the **I-Series Control Center > System**.
2. Select the **Restore from backup** button.
3. Select the one of the last backups by selecting the **Restore from this backup** button next to the date of the stored backup.

When the restore is finished, the following text will show up on the screen: **Restore finished** and the  symbol will show up next to the date that was selected to restore from.

Copies of these backup files can be saved anywhere you wish, to an external hard drive, for example, or to a USB stick. Copy the folders in the directory **Q:\Backup\ to any external directory or drive of your choosing.**

6.9.2.4 Backup Failed

One likely reason that the backup failed is that there are too many files in the My Documents folder. Try moving the files that are not backup-critical to another location (such as pictures, music files, etc.).

6.10 Creating Shortcuts to Actions

You can create shortcuts, called actions, by programming the Quick Access buttons and connected Switches. The Quick Access buttons are located on the left side of the I-Series device, named **1**, **2** and **Menu**.

Switches are connected to the Switch connectors.

6.10.1 Available Actions

This is a short description of each action available to set:

- Send input – Allows the user to send input to an alternative program (keystroke, mouse click or text).
- Start Program – Allows the user to start a program.
- Volume – Allows the user to adjust the volume up or down or to set mute on or off.
- Backlight – Allows the user increase or decrease the backlight of the screen.
- Gaze Interaction – Allows the user to show and hide the track status window, calibrate or pause the Gaze Interaction ON or OFF.
- Wireless – Allows the user to either set all radio connections on or off, or a specific wireless connection.
- Tobii Communicator – Actions are set and customized in Tobii Communicator.

The available actions are the same for the Quick Access buttons and Switches.


To create a shortcut to an action:

1. Open the **I-Series Control Center**.
2. Select **Buttons** or **Switches**, depending on which one you want to customize.
3. Click **Set action** to view the dialog box where you can select the action you would like the button to perform. By selecting one of the actions, the options for this action will be revealed below the chosen action.



If you would like the Quick Access button to make a sound when pressed, select the **Play sound** check box after having set an action.

6.10.2 Selecting Actions



- **No Action Selected** – Default – choose to delete a previous set task
- **Send Input** – choose either to send a keyboard input, a mouse click or specified text by selecting the option you want the device button or Switch to perform.
 - **Send keyboard input** – In the **Send keyboard input list**, select the keystroke you want to send to an alternative program.
 - **Send mouse click** – In the **Send mouse click list**, select the desired mouse click: left, middle or right mouse click.

– **Send text** – In the **Send text box**, type the text you want to send to an alternative program.

- **Start Program** – Click **Browse** the first time you are using this option to find and select a program. The next time you select the **Start Program** option a list of previously selected programs will be displayed. You can then directly select a program from the list or select **Browse** if you want to start a program not in the list.

For the selected program it is possible to add program arguments. However, this is normally not required. If the program should require program arguments and you do not know what to enter, please contact the company you purchased the software from.

- **Volume** – choose to increase, decrease or mute the volume by selecting the preferred option.
- **Backlight** – choose to either increase or decrease the screen backlight by selecting the preferred option.
- **Gaze Interaction** – choose to toggle track status window, calibrate Gaze Interaction, Pause the Gaze Interaction or toggle Windows Control ON/OFF.



To enable this option the I-Series device must have an Eye Tracker and the Tobii Gaze Interaction Software installed.

- **Wireless** – you can either set all radio connections on/off or each individual wireless unit on/off one by one, by selecting the options.
- **Tobii Communicator** – Actions are set and customized in Tobii Communicator



If actions for a Switch are customized both in the **I-Series Control Center** and in **Tobii Communicator** or in alternative communication software all actions will be performed simultaneously. Ensure that the specified action for a Switch does not conflict with an action set for the same Switch in **Tobii Communicator** or in alternative communication software.






To get back from slide in menus, just select the arrows in the greyed out areas.

7 Tobii Gaze Interaction Settings

7.1 Accessing the Tobii Gaze Interaction Settings

Tobii Gaze Interaction Settings is a program for quick and easy access to control functions such as Track Status, Calibration and common settings.

Start **Tobii Gaze Interaction Settings** in one of the following ways:

- Go to **Start menu > All Programs > Tobii > Gaze Interaction > Tobii Gaze Interaction Settings**.
- Double-click on the **Tobii Gaze Interaction Settings** icon, , in the Notification area, or on the shortcut, , on the Desktop (if one has been made).
- Right-click (long-hold finger on icon for touch screen right clicking) on the **Tobii Gaze Interaction Settings** icon, , in the Notification area and then select **Settings**.





In the list to the left in **Tobii Gaze Interaction Settings**, select which option you want to change. In the list to the right, the available options will be revealed.

Click **OK** to save changes. This will also close Tobii Gaze Interaction Settings.

Click **Cancel** to cancel the changes. This will also close Tobii Gaze Interaction Settings.

Click **Apply** to save changes. Tobii Gaze Interaction Settings will remain open.



Anywhere you see this icon, , there is an information box with additional information for the feature.

7.2 Calibration

This section will describe how to calibrate an individual, enabling optimal Gaze Interaction with the I-Series device.

7.2.1 Starting Calibration

The calibration can be started in one of the following ways:

- Open **Tobii Gaze Interaction Settings > Gaze Interaction** and then select the **Start Calibration...** button.
- Right-click (long-hold finger on icon for touch screen right clicking) on the **Tobii Gaze Interaction Settings** icon, in the Notification area and select **Start Calibration**.




7.2.2 Interrupting Calibration

Interrupt the calibration in one of the following ways:

- Press **Esc**.
- Left-click on the screen using a mouse.
- Touch the screen (on a touch screen device).

7.2.3 Customizing Active Eye


Based on certain conditions, or disabilities, you may only have one eye that functions well with Gaze Interaction. In this case, and if you know which eye is most functional, you can select which eye to track for Gaze Interaction.



To select the eye you want to be tracked by the eye tracker, follow these steps:

1. Open **Tobii Gaze Interaction Settings > Calibration**.
2. Select the **Track only this eye for Gaze Interaction** check box under Left or Right Eye Calibration Result box.

7.2.4 Improving Calibration Point(s)



After calibration, you may want to improve one or more points.

There is a color scheme used that will help you to understand the quality of your calibration.



All three color statuses are the result of a **successful** calibration.

- If the background color of the Calibration Result is light red, you have achieved a successful, but relatively low quality calibration. You can improve one or more points individually, or recalibrate completely, to achieve better Gaze Interaction results.



Improving even one (or more) of the calibrations points can significantly improve the calibration.


- If the background color of the Calibration Result is light yellow, you have achieved successful and good quality calibration. You might be able achieve better Gaze Interaction results by improving one or more points individually.
- If the background color of the Calibration Result is green, you have achieved a successful and high quality calibration.



Be aware that no matter what quality of calibration you have achieved you will be able to select **OK** or **Apply** and begin using Gaze Interaction. It is the accuracy and functionality of the Gaze Interaction that is affected by the quality of the calibration results. Try for the best calibration possible.

Remember! In the end it is the personal experience that counts!

The closer the lines within the calibration point are to a dot in the center of the circle of the calibration point, the better the cali-

bration is of that point, . You can choose the points to be improved and calibrate only those points again.

To improve one or more calibration points, follow these steps :

1. Open **Tobii Gaze Interaction Settings > Calibration**.
2. Select the point(s) you want to improve under **Calibration Result**.
3. Select the **Improve Point(s)** button and a calibration for the selected point(s) will start.


7.2.5 Removing Calibration Point(s)

If there is a calibration point that is consistently bad after calibration (the green lines are scattered all around and outside the circle of the calibration point) you can remove that point completely from the calibration, this *may* improve the calibration of the other points. Be aware that if you remove a point, that area of the screen will be uncalibrated and Gaze Interaction will not function properly there.

To remove one or more calibration points, follow these steps:

1. Open **Tobii Gaze Interaction Settings > Calibration**.
2. Select the point(s) you want to remove under **Calibration Result**.
3. Select the **Remove Point(s)** button.

7.2.6 Customizing the Calibration



To customize the calibration, follow these steps:

1. Open **Tobii Gaze Interaction Settings > Calibration**.
2. Select the **Settings...** button

General

3. Select calibration background by selecting the background color button and select the desired color.
4. Specify the number of points you want to calibrate with (two, five or nine) from the **Calibration points** drop down list. The higher number of points, the more accurate the calibration.
5. Select if you want to have sound feedback or not from the **Sound feedback** drop down list.

Stimulus


6. Select the stimulus type from the **Stimulus type** drop down list. There are three types available, each with different customizing options:
 - Dot:
 - Select color of the dot by selecting the **Stimulus color** button.
 - Select size of the dot by selecting from the **Stimulus size** drop down list.
 - Select speed of the dot by selecting from the **Stimulus speed** drop down list.
 - Image:

- Select primary stimulus by selecting **Browse** and selecting an image.
 - Select secondary stimulus by selecting **Browse** and selecting an image.
 - Select size of the image by selecting from the **Stimulus size** drop down list.
 - Select speed of the image by selecting from the **Stimulus speed** drop down list.
 - Video:
 - Select primary stimulus by selecting **Browse** and selecting a video.
 - Select secondary stimulus by selecting **Browse** and selecting a video.
 - Select size of the video by selecting from the **Stimulus size** drop down list.
 - Select speed of the video by selecting from the **Stimulus speed** drop down list.
7. Check the **Animate stimuli** check box if you want the stimuli to be animated (as opposed to static).
8. If you want to control the calibration, i.e. decide when to move the calibration stimuli, with a keyboard, check the **Keyboard step-through** check box.
- For **Keyboard step-through**, use the 'S' key to step (to move the calibration stimuli) and the 'Esc' key, the Left mouse button or touching the touch screen to interrupt calibration. When using Image or Video calibration, use the 'T' key to toggle between primary and secondary stimulus images.



To get back from slide in menus, just select the arrows in the greyed out areas.

7.2.7 Customizing the Calibration Area




Customizing the calibration area can be useful if you have discovered that the user cannot access certain areas of the screen using Gaze Interaction. By sizing the calibration area to exclude the areas that the user cannot access it can improve the overall calibration.


To customize the calibration area, follow these steps:

1. Open **Tobii Gaze Interaction Settings > Calibration**.
2. Select the **Setting...** button.
3. Select the Calibration area: **Change...** button.

4. A blue semi-transparent area is displayed on the desktop. You can move and resize the blue area to make it fit your preferred calibration area.



7.3 Interaction



To adapt the interaction method and visual feedback for Gaze Interaction, follow these steps:

1. Open **Tobii Gaze Interaction Settings > Interaction**.

Scope

If different settings are needed for different Gaze Interaction applications, make the adaptations here.

2. Select how the interactions settings should be reflected:
 - Select **Default settings of the currently selected user profile** if you want to apply the new settings to the whole user profile and not only to a particular application.
 - Select **Application specific settings of the currently selected user profile** if you want to apply the new settings to a specific application of a user profile. Then select the available application in the **Application** drop down list.

Method


3. Select the activation method from the **Activation method** drop down list. There are three methods available, each with different activation times:

- Dwell. Adjust the dwell time by moving the **Dwell time** slider.
- Switch. Adjust the minimum time for a click duration and the minimum time between clicks by moving the respective slider.
- Blink. Adjust the minimum and maximum duration for a blink by moving the respective slider.

Visual Feedback

4. Select the symbol for visual feedback from the **Dwell feedback type** drop down list.
5. Select the color of the feedback symbol in the **Feedback color** drop down list.
6. Specify the dot size and opacity of the feedback symbol by moving the respective slider.
7. Select the **Show visible outline around the activated region** check box to see a dashed line around the activated area in all instances of Gaze Interaction selection
8. Select **Simulate activation** if you want to see how the activation method will appear on the screen. The example is shown above the **Simulate activation** button.

7.4 User Profile



7.4.1 Creating a New Profile

Use of different profiles allows you to store multiple people’s calibrations and feedback preferences on one device. Alternatively, one person might want to store multiple profiles for him/herself if that person wears glasses occasionally or uses multiple means of accessing the device.

To create a new profile:

1. Open **Tobii Gaze Interaction Settings**, select **User Profiles**.
2. Enter a new name in the **Profile name** field.
3. Select an existing profile in the **Based on profile** drop down list. The new profile will inherit all settings from the selected profile. Note that if no profiles have been created previously, the only one to select is the default profile.
4. Click **Create** to save the new profile. The new profile is saved directly upon selecting **Create**.

7.4.2 Selecting Current User Profile

To select current user profile:

1. Open **Tobii Gaze Interaction Settings**.
2. Select a user profile in the **Current User Profile** drop down list.
3. Select **Apply**

7.4.3 Deleting a Profile

To delete a profile:

1. Open **Tobii Gaze Interaction Settings > User Profiles**.
2. Select a profile in the **Profile to delete** drop down list.
3. Click **Delete** to delete the selected profile. The profile is deleted directly upon selecting Delete. Note that the default profile cannot be deleted.

7.5 Windows Control

Windows Control allows you to access the desktop and all applications of your Windows computer with Gaze Interaction.

7.5.1 Auto Start

To enable Windows Control automatically when the your device starts up:

- Select the **Auto start Windows Control at boot** check box.

To disable Windows Control automatically when the your device starts up:


- Select to clear the **Auto start Windows Control at boot** check box.

7.5.2 Windows Control Type

Select which type of Windows Control you wish to use:

- **Gaze Selection** — Select the Gaze Selection radio button. For more information about using Gaze Selection, see [5.4.3 Using Gaze Selection, page 22](#)
- **Mouse Emulation** — Select the Mouse Emulation radio button. For more information about using Mouse Emulation, see [5.4.4 Using Mouse Emulation, page 26](#)

7.5.2.1 Gaze Selection




The settings for Gaze Selection are found in the Gaze Selection Taskbar, docked to the screen when Gaze Selection



Windows Control is running. Gaze at the settings icon to select it and the Gaze Selection Settings will open. For information about the Gaze Selection Settings, see [8 Gaze Selection Settings, page 59](#)

7.5.2.2 Mouse Emulation



7.5.2.2.1 Mouse Control Speed

- Customize the mouse control speed by moving the **Mouse control speed** slider. Move the slider to the right to increase the speed and to the left to decrease it.

7.5.2.2.2 Magnifier Size and Zoom

- Customize the size of the magnifier by moving the **Magnifier Size slider**. Move the slider to the right to increase the size and to the left to decrease it.
- Customize the zoom factor by moving the **Zoom Factor slider**. Move the slider to the right to increase the zoom factor and to the left to decrease it.

7.5.2.2.3 Auto Switch from Right to Left Click

- Check this check box if you want Windows Control Mouse Emulation mode to automatically switch the desired mouse click selection back to a left click, , after a right click, , has been chosen and performed.

7.5.2.2.4 Turn off Scroll Functionality

- Check the **Turn off scroll functionality** check box if you do not want Gaze Interactions scrolling to be active.

7.5.2.2.5 Custom Cursors

Custom cursors is a feature that turns the regular mouse cursor into a number of different cursors when using Windows Control in Mouse Emulation mode.

The different cursors visually represent the type of "mouse click" for Gaze Interaction that you have chosen from the Mouse Emulation Menu (for the definitions of the Mouse Emulation Menu symbols see [5.4.4.2 Clicking with Windows Control in Mouse Emulation Mode, page 27](#), [5.4.4.3 Magnifying with Windows Control in Mouse Emulation Mode, page 27](#) and [5.4.4.4 Selecting Mouse Emulation Functions, page 27](#)).

 or  +  = cursor type  (move cursor, no clicking)





 +  = cursor type  (single left click)

 +  = cursor type  (single right click)

 +  = cursor type  (double left click)

 +  = cursor type  (double right click)

 or  +  = cursor types  (drag) and  (drop)

 or  +  = cursor type  (no movement)

- Check the Custom cursors check box to activate custom cursors for Windows Control in Mouse Emulation mode.

7.6 System Settings

7.6.1 System Off-Screen Menu

Select the **Position** Drop down menu to make changes to where the System Off-Screen menu appear on the screen.

The System Off-Screen menu can be set to appear:

- Bottom (Default)
- Top
- Left
- Right
- None




Figure 7.1 System Off-Screen Menu Areas

Select the **Available menu buttons: > Pause/Resume Gaze Interaction** check box to activate the possibility to Pause/Resume Gaze Interaction. For information about how to use Pause/Resume, see *5.6 Pause/Resume Gaze Interaction and Put the I-Series to Sleep with Gaze Interaction, page 29*.

Select the **Available menu buttons: > Sleep-on-Gaze** check box to activate the possibility to put the device to sleep with Gaze Interaction. For information about how to use Sleep-on-Gaze, see *5.6 Pause/Resume Gaze Interaction and Put the I-Series to Sleep with Gaze Interaction, page 29*.

7.6.2 Positioning Guide

To turn On the Positioning Guide:


1. Open **Tobii Gaze Interaction Settings > System Settings**.
2. Select the **Enable positioning guide** check box.

To turn Off the Positioning Guide:

1. Open **Tobii Gaze Interaction Settings > System Settings**.
2. Select to clear the **Enable positioning guide** check box.

For more information about the Positioning Guide, see *5.3.4 Positioning Guide*

7.7 System Information



To view the version and model of the device:

Open the **Tobii Gaze Interaction Settings > System Information**.


Please have this information available if you have problems with the device and need to contact Customer Support.

By clicking **Copy all information** you can paste the information into a document (such as Notepad or WordPad) or directly into an e-mail.

8 Gaze Selection Settings

The Gaze Selection Settings Dialog is controlled by Gaze Interaction and the user can make all changes without using a keyboard and/or a mouse.

8.1 The General Settings Tab



Selection

- **Gaze** - Choose Gaze to use your gaze position to activate the zooming function that ends with the execution of the desired Task.
- **Switch** - Choose Switch to use a switch to activate the zooming function that ends with the execution of the desired Task.


Precision

The zoom precision can be set to 8 different levels, just look at the desired position to change the setting. Changing the Precision will adjust how deep the zoom will go before executing the Task. The further to the right on the scale the deeper the zoom.

Speed

The zoom speed can be set to 8 different levels, just look at the desired position to change the setting. Changing the Speed will affect how fast the zoom is before the execution of the Task. The further to the right on the scale the faster the zoom.

8.2 The Keyboard Settings Tab



Keyboard layout

The selected language keyboard layout is shown. Select the Change button to change the keyboard layout to another language. There are a number of different language keyboard layouts available.

Gaze typing speed

The Gaze typing speed can be set to 8 different levels, just look at the desired position to change the setting. Changing the Gaze typing speed will adjust how long the user must fix their gaze on a button before the Task is executed. The scale presents lower Gaze typing speeds to the left and higher to the right.

Sound feedback

- **On** - Choose On to activate sound feedback when selecting a button on the Gaze keyboard.
- **Off** - Choose Off to deactivate sound feedback when selecting a button on the Gaze keyboard.

To finish, select **OK** to save or **Cancel** to abort you changes.

9 Product Care

9.1 Temperature & Humidity

9.1.1 General Use

The Tobii I-Series is best kept in dry conditions at room temperature. The recommended range for temperature and the humidity value for the device is as follows:

Portable mode:

- Ambient temperature: 0°C to 24°C (32°F to 75°F)
- Humidity: Max 70% (no condensation on the device)

Mounted mode:

- Ambient temperature: 0°C to 37°C (32°F to 99°F)
- Humidity: Max 70% (no condensation on the device)

9.1.2 Transportation and Storage

For transportation and storage excluding batteries the recommended range for temperature and the humidity value for the device is as follows:

- Temperature: -40°C to 70°C (-40°F to 158°F)
- Humidity: 20% to 70% (no condensation on the device)

The Tobii I-Series is not waterproof or fully water resistant. The device should not be kept in excessively humid, damp or otherwise wet conditions. Do not submerge the device in water or in any other liquid. Be careful not to allow liquids to be spilled upon the device especially in the connector areas without the I/O covers in place (Position 29 in *Figure 3.2 Bottom, Left and Right Side, page 10*). The device is registered as IP Class 43 (with I/O covers in place).

9.2 Cleaning

Before cleaning the I-Series device shut it down, unplug all cables, attach the I/O covers (Position 29 in *Figure 3.2 Bottom, Left and Right Side, page 10*) and remove the batteries. Use a soft, slightly damp, lint-free cloth or Alcohol Cleaning Wipes (i.e. damp cloth with 96% alcohol). Avoid getting moisture in openings on the device. Don't use window cleaners, household cleaners, aerosol sprays, solvents, alcohol, ammonia, or abrasives to clean the device.

9.2.1 Cleaning of the Speakers

If the openings for the speakers are clogged carefully use cotton sticks and/or a toothbrush to avoid damaging the IP-protection for I-Series speakers.

9.3 Placement

Only use the recommended mounts specified by the your local reseller or sales represent and make sure that they are mounted and fastened correctly according to the instructions. Do not place the device on unstable and uneven surfaces.

9.4 Transporting the I-Series Device

Disconnect all the cables and use the handle on the back side of the device to hold the device while carrying it.

When you transport the device for repair, shipment or traveling, use the original casing and packaging materials.



Keep the original packaging materials for the Tobii I-Series.

In case the device needs to be returned to Tobii for Warranty related issues or repair, it is required that the original packaging (or equal equivalent) is used for shipping.

9.5 Disposing of the Batteries

Do not dispose of the batteries in general household or office waste. Follow your local regulations for the disposal of batteries.

9.6 Disposing of the I-Series Device

Do not dispose of the I-Series Device in general household or office waste. Follow your local regulations for the disposal of electrical and electronic equipment.

Appendix A Support, Warranty, Training Resources

A1 Customer Support

For support, please contact your local representative or Support at Tobii. In order to receive assistance as quickly as possible, make sure you have access to your I-Series device and, if possible, an Internet connection. You should also be able to supply the serial number of the device, which you find on the back of the device, in the I-Series Control Center or Tobii Gaze Interaction Settings, see *6.9 System, page 43* and *7.7 System Information, page 57*.

For further product information and other support resources, please visit the Tobii website www.tobii.com.

A2 Warranty

Please read this User's Manual carefully before using the device. The warranty is only valid if the device is used according to the User's Manual and the warranty seal is not broken. Disassembling the I-Series device will void the warranty.

Please read the Manufacturer's Warranty paper included in the package.



Keep the original packaging materials for the Tobii I-Series.

In case the device needs to be returned to Tobii for Warranty related issues or repair, it is required that the original packaging (or equal equivalent) is used for shipping.

A3 Training Resources

Tobii offers a range of training resources for the I-Series products and related communication products. You can find them on the Tobii website, www.tobii.com, including Getting Started Guides, webinars and Quick guides. The I-Series Getting Started Guide is delivered with, and stored on, the I-Series device.

Appendix B Compliance Information

B1 FCC Statement

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference and (2) this device must accept any interference received, including interference that may cause undesired operation.



Modifications not expressly approved by Tobii Technology could void the user's authority to operate the equipment under FCC rules.

B1.1 For P15B Equipment

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

B1.2 For Portable Devices

FCC RF Radiation Exposure Statement:

1. This Transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.
2. This equipment complies with FCC RF radiation exposure limits set forth for an uncontrolled environment. This device was tested for typical hand held operations with the device contacted directly to the human body to the sides of the device. To maintain compliance with FCC RF exposure compliance requirements, avoid direct contact to the transmitting antenna during transmitting.

B2 Radio Wave Exposure and Specific Absorption Rate (SAR) Information

The I-Series device has been tested as a Class 1 Medical Device. Medical electrical equipment such as this requires special caution regarding Electro-magnetic Compatibility (EMC) and thus needs to be installed and placed into service according to the information provided in this manual.



Using other cables and accessories other than those provided or that are integrated in the device may affect EMC performance.

The SAR (Specific Absorption Rate) limit as dictated by the FCC (in the USA) is 1.6W/kg averaged over 1 gram of tissue. In Europe/EU (CE regulations) it is 2.0 W/kg averaged over 10 grams of tissue. The Devices, Tobii I-12 (FCC ID: W5MTOBIII12A) and Tobii I-15 (FCC ID: W5MTOBIII15A) have been tested against these SAR limits to maintain compliance with FCC/CE RF exposure requirements.

This equipment complies with FCC RF radiation exposure limits set forth for an uncontrolled environment.

The highest SAR value for the I-12 device is 0.501 W/kg. The highest SAR value for the I-15 device is 0.017 W/kg.

Guidance and manufacturer's declaration – electromagnetic emissions

The I-Series is intended for use in the electromagnetic environment specified below. The customer or the user of the I-Series device should assure that it is used in such an environment.

Emissions Test	Compliance	Electromagnetic environment – guidance
RF (Radio Frequency emissions CISPR 11	Group 1	The I-Series must emit electromagnetic energy in order to perform its intended function. Nearby electronic equipment may be affected
RF emissions CISPR 11	Class B	
Harmonic emissions IEC 61000-3-2	Not Applicable	The product has an active power of $P \leq 75$ W at rated load conditions. Therefore no limits are applicable.
Voltage Fluctuations/flicker emissions IEC 61000-3-3	Not Applicable	The product has an active power of $P \leq 75$ W at rated load conditions. Therefore it is not likely to produce voltage fluctuations or flicker above the limit values.



The I-Series device should not be used adjacent to or stacked with other equipment.

Guidance and manufacturer's declaration – electromagnetic immunity

The I-Series device is intended for use in the electromagnetic environment specified below. The customer or the user of the I-Series device should assure that it is used in such an environment.

IMMUNITY test	IEC 60601 test level	Compliance level	Electromagnetic environment – guidance
Electrostatic discharge (ESD) IEC 61000-4-2	± 6 kV contact ± 8 kV air	± 6 kV contact ± 8 kV air	Floors should be wood, concrete or ceramic tile. If floors are covered with synthetic material, the relative humidity should be at least 30 %.
Electrical fast transient/burst IEC 61000-4-4	± 2 kV for power supply lines ± 1 kV for input/output lines	± 2 kV for power supply lines ± 1 kV for input/output lines	Mains power quality should be that of a typical commercial or hospital environment.
Surge IEC 61000-4-5	± 1 kV line to line	± 1 kV line to line	Mains power quality should be that of a typical commercial or hospital environment.

Guidance and manufacturer's declaration – electromagnetic immunity

The I-Series device is intended for use in the electromagnetic environment specified below. The customer or the user of the I-Series device should assure that it is used in such an environment.

IMMUNITY test	IEC 60601 test level	Compliance level	Electromagnetic environment – guidance
Voltage dips, short interruptions and voltage variations on power supply input lines. IEC 61000-4-11	< 5 % UT (>95 % dip in UT) for 0.5 cycles. 40 % UT (60 % dip in UT) for 5 cycles. 70 % UT (30 % dip in UT) for 25 cycles. < 5 % UT (>95 % dip in UT) for 5 s	< 5 % UT (>95 % dip in UT) for 0.5 cycles. 40 % UT (60 % dip in UT) for 5 cycles. 70 % UT (30 % dip in UT) for 25 cycles. < 5 % UT (>95 % dip in UT) for 5 s	Mains power quality should be that of a typical commercial or hospital environment. If the user of the I-Series device requires continued operation during mains interruptions, it is recommended that the I-Series device batteries are in place or that the device be powered from an uninterruptable power supply (UPS). UT is at 100 VAC 60 Hz or 230 VAC 50 Hz.
Power frequency (50/60 Hz) magnetic field IEC 61000-4-8	3 A/m	3 A/m	Power frequency magnetic fields should be at levels characteristic of a typical location in a typical commercial or hospital environment.


Guidance and manufacturer's declaration – electromagnetic immunity

The I-Series device is intended for use in the electromagnetic environment specified below. The customer of the user of the I-Series device should assure that it is used in such an environment.

Immunity test	IEC 60601 test level	Compliance level	Electromagnetic environment - guidance
Conducted RF IEC 61000-4-6	3 Vrms 150 kHz to 80 MHz	3 V	Portable and mobile RF communications equipment should be used no closer to any part of the I-Series device, including cables, than the recommended separation distance calculated from the equation applicable to the frequency of the transmitter. Recommended separation distance $d = \frac{3,5}{3} \sqrt{P}$ for 150 kHz to 80 MHz $d = \frac{3,5}{3} \sqrt{P}$ for 80 MHz to 800 MHz $d = \frac{7}{3} \sqrt{P}$ for 800 MHz to 2.5 GHz
Radiated RF IEC 61000-4-3	3 V/m 80 MHz to 2.5 GHz	3 V/m	

Guidance and manufacturer's declaration – electromagnetic immunity

The I-Series device is intended for use in the electromagnetic environment specified below. The customer of the user of the I-Series device should assure that it is used in such an environment.

Immunity test	IEC 60601 test level	Compliance level	Electromagnetic environment - guidance
			<p>where "P" is the maximum output power rating of the transmitter in watts (W) according to the transmitter manufacturer and "d" is the recommended separation distance in meters (m).</p> <p>Field strengths from fixed RF transmitters, as determined by an electromagnetic site survey,ⁱ should be less than the compliance level in each frequency range.ⁱⁱ</p> <p>Interference may occur in the vicinity of equipment marked with the following symbol.</p> 

NOTE 1 At 80 MHz and 800 MHz, the higher frequency range applies.

NOTE 2 These guidelines may not apply in all situations. Electromagnetic propagation is affected by absorption and reflected from structures, objects and people.

- i. Field strengths from fixed transmitters, such as base stations for radio (cellular/cordless) telephones and land mobile radios, amateur radio, AM and FM radio broadcast and TV broadcast cannot be predicted theoretically with accuracy. To assess the electromagnetic environment due to fixed RF transmitters, an electromagnetic site survey should be considered. If the measured field strength in the location in which the I-Series device is used exceeds the applicable RF compliance level above, the I-Series device should be observed to verify normal operation. If abnormal performance is observed, additional measures may be necessary, such as reorienting or relocating the I-Series device.
- ii. Over the frequency range 150 kHz to 80 MHz, field strengths should be less than 3 V/m.

Recommended separation distances between portable and mobile RF (Radio Frequency) communications equipment and the I-Series device.

The I-Series device is intended for use in the electromagnetic environment in which radiated RF disturbances are controlled. The customer or the user of the I-Series device can help prevent electromagnetic interference by maintaining a minimum distance between portable and mobile RF communication equipment (transmitters) and the I-Series device as recommended below, according to the maximum output power of the communications equipment.

Rated maximum output power of transmitter W	Separation distance according to frequency of transmitter		
	150 kHz to 80 MHz	80 MHz to 800 MHz	800 MHz to 2.5 GHz
0.01	0.12 m	0.12 m	0.24 m
0.1	0.37 m	0.37 m	0.74 m
1	1.2 m	1.2 m	2.4 m
10	3.7 m	3.7 m	7.4 m
100	11.7 m	11.7 m	23.4 m

Under test specifications specified in 6.2.1.10 EN 60 601-1-2 (2007) the I-Series device shall not:

- Exhibit component failure
- Exhibit changes in its programmable parameters
- Reset unintentionally to factory defaults
- Emit false alarms
- Initiate any unintended operation, even if accompanied by alarm

With regard to the test specifications specified in 6.2.1.10 EN 60 601-1-2 (2007) the cessation or interruption of any intended operation, even if accompanied by an alarm, is allowed in the I-Series device due to it not performing any safety critical operations.

Also with regard to the test specifications specified in 6.2.1.10 EN 60 601-1-2 (2007) errors of a displayed numerical value sufficiently large to affect diagnosis or treatment is not applicable for the I-Series device.

In order to maintain compliance as a Class 1 Medical device, the switches that are used in combination with the I-Series device must fulfill the isolation requirements of IEC/EN60601-1 based on 15 V DC. They must be electrically floating switches (switches that are not grounded).

B3 Industry Canada Statement

Low-power license-exempt radio communication devices (ICES-003)

De faible puissance exempts de licence des appareils de communication radio (CNR-210)

- a. Common information
Operation is subject to the following two conditions:
 - 1. This device may not cause interference, and
 - 2. This device must accept any interference, including interference that may cause undesired operation of the device.
- b. Operation in 2.4 GHz band
To prevent radio interference to the licensed service, this device is intended to be operated indoors and installation outdoors is subject to licensing.
- a. Informations communes
Son fonctionnement est soumis aux deux conditions suivantes:
 - 1. Ce dispositif ne peut causer des interférences, et
 - 2. Ce dispositif doit accepter toute interférence, y compris les interférences qui peuvent causer un mauvais fonctionnement du dispositif.
- b. Le fonctionnement en bande de 2,4 GHz
Pour prévenir les interférences radioélectriques aux services sous licence, cet appareil est destiné à être exploité à l'intérieur et à l'extérieur d'installation est soumise à licence.

This device has been tested to the safety requirements for exposure to radio waves (SAR) in RSS-102 to the General Public (Uncontrolled Environment) limits (1.6W/Kg). The highest SAR value for the I-12 device is 0.501 W/kg. The highest SAR value for the I-15 device is 0.017 W/kg. This device can be operated safely with a minimum distance 0 cm between the equipment and the user's body.

Ce dispositif a été testé aux exigences de sécurité pour l'exposition aux ondes radio (SAR) dans le CNR-102 à le grand public (environnement non contrôlé) des limites (1.6W/Kg). La valeur maximale mesurée de SAR pour le I-12 dispositif est: 0.501 W/kg. La valeur maximale mesurée de SAR pour le I-15 dispositif est: 0.017 W/kg. Ce dispositif peut être exploité en toute sécurité avec un 0cm distance minimale entre le matériel et les corps de l'utilisateur.

This Class B digital apparatus complies with Canadian ICES-003.

Cet appareil numérique de la classe B est conforme à la norme CNR-210 du Canada.

B4 CE Statement

This equipment complies with the requirements relating to electromagnetic compatibility, EN 300386 class B for ITE, the essential protection requirement of Council Directive 2004/108/EC on the approximation of the laws of the Member States relating to electromagnetic compatibility and R&TTE Directive 1999/5/EC to meet the regulation of the radio equipment and telecommunications terminal equipment.

B5 Standards

The Tobii Device complies with the following standards:

- Medical Device Directive (MDD) 93/42/EEC
- Restriction of Hazardous Substances (RoHS) 2002/95/EC
- Electromagnetic Compatibility Directive (EMC) 2004/108/EC
- Low Voltage Directive (LVD) 2006/95/EC
- Part 15 of the FCC Rules
- CAN/CSA-C22.2No. 60601-1-08
- ANSI/AAMIES60601-1:2005
- IEC 60601-1:2005
- IEC/EN60601-1-6:2010
- IEC 60601-1-11 : 2010
- IEC/EN60601-1-11 : 2010
- ISO 14971 : 2009
- IEC 60601-1-2: 2007
- IEC 60950-1:2005+A1 : 2009
- GB4943-2011
- GB9254-2008
- GB17625.1-2003
- AS/NZS 60950.1
- AS/NZSCISPR22
- SANS 60950
- CISPR 22
- FCC Part 18
- FCC Part 15C (P15.247) - BT - WLAN
- EN300328 - BT
- EN300328_2.4G - WLAN
- RSS_210 - BT - WLAN
- AS/NZS 4268 - BT - WLAN (2.4G)
- FCC - SAR - OET65
- SAR - EN62209_2
- SAR - RSS_102
- SAR - ACA EMR 2003.Schedules 1 and 2
- EMC FCC - Part 15B
- EMC EN301489_1/EN301489_17
- EMC EN55022/EN55024
- EMC EN60601_1_2
- EMC ICES_003
- ICES-001
- EMC AS/N2S CISPR 22
- FCC LPD

Appendix C Computer Device States of Operation

Table C.1 Computer Device States of Operation

Advanced Configuration and Power Interface (ACPI) State	Description
S0 (Working)	Normal operating state - Windows session is running Display will dim and turn off after a time of idle. The 1, 2, Menu and Volume Up and Down buttons are however always illuminated in state S0.
S3 (Sleep)	The device is sleeping. The Windows session is suspended to RAM, allowing a quick resume to state S0 by: <ol style="list-style-type: none"> Pressing the power button Pressing a button connected to a switch port configured to have power on functionality Wake on Gaze (if enabled) The device is consuming a small amount of power in state S3. Fully charged batteries (no AC adapter attached) will last a minimum of 24 h in state S3. Windows Critical battery level is monitored in state S3 to prevent the batteries from being fully drained. The device will enter state S4 (Hibernate) if the critical value is reached.
S4 (Hibernate)	The device is in hibernation. The Windows session is suspended to the SSD (hard drive) and the device is powered off. The session can be resumed to state S0 by: <ol style="list-style-type: none"> Pressing the power button Pressing a button connected to a switch port configured to have power on functionality
S5 (Soft Off)	Windows is shut down. The device is powered off. Batteries (not drained) and/or AC adapter attached.
S5 Overheat (Safety State)	Special safety state for I-Series, entered if the chassis is overheated. It is not possible to start the device until it has cooled down below the safety temperature level.
G3 (Mechanical Off)	All power sources removed (no batteries and no AC adapter attached).

Table C.2 Power Button Normal Operation, LED Behavior

ACPI State	Power Button Illumination		Button 1, 2, Menu, Volume Up and Volume Down Buttons White Illumination
	No Battery Charging	Battery Charging	
S0 (Working)	Green Light	Blue Light	ON
S3 (Sleep)	Green Blinking Light	Blue Blinking Light	OFF
S4 (Hibernate)	OFF	Blue Light	OFF
S5 (Soft off)	OFF	Blue Light	OFF

Table C.3 Power Button Error or Warning, LED Behavior

Error or Warning	ACPI State and condition	Power Button Illumination	Comment
Chassis near overheating	In state ACPI S0 (Working) , when the chassis temperature is ≤ 1 degree Celsius from the Maximum Threshold according to the Safety Settings specified in <i>Table D.1 Maximum Allowed Temperature, page 72</i> .	Purple Light	Purple light as a warning to the user when the Device is close to the overheat threshold.
Chassis overheated	In state ACPI S5 Overheat , when the power button ⁱ is pressed.	Purple Quick Blinking Light for 5 seconds.	The Device will blink the LED and remain in the state ACPI S5 Overheat.
Low Battery Level for Battery Packs	In state ACPI S4 (Hibernate) and S5 (Soft off) , when the power button ⁱ is pressed and: <ol style="list-style-type: none"> 1. No DC plug inserted (i.e. no charging possible) and 2. Both battery packs are totally drained 	Blue Quick Blinking Light for 5 seconds.	

i. Or a switch port configured to have power button functionality.

Appendix D Maximum Allowed Temperature

Table D.1 Maximum Allowed Temperature

Allowable maximum temperature for the I-Series metal external surfaces which are likely to be touched	Maximum Temperature °C/°F	
	Portable Mode	Mounted Mode
Mounted Mode temperature threshold: External surfaces temperature allowed External surfaces temperature allowed in an area unlikely to be touched, see position 1 in <i>Figure D.1 Temperature Threshold Area, page 72</i> for the position of this area.		55/131 60/140
Portable Mode temperature threshold: External surfaces temperature allowed External surfaces temperature allowed in an area unlikely to be touched, see position 1 in <i>Figure D.1 Temperature Threshold Area, page 72</i> for the position of this area.	43/109 46/115	




Figure D.1 Temperature Threshold Area

Appendix E Technical Specifications

E1 Standard I-Series

Standard	Tobii I-12	Tobii I-12	Tobii I-15
Type/Model	I-12 R	I-12 ETR	I-15 ETR
Screen	12.1", Aspect ratio: 4:3, LED Backlight Unit, White Luminance 500 cd/m ²		15.0", Aspect ratio: 4:3, LED Backlight Unit White Luminance 400 cd/m ²
Screen Resolution	1024 × 768 pixels (XGA)		
Touch Panel	Projected Capacitive Touch with Gorilla® Glass, 10 point multi touch		
Dimensions (WxHxD)	30,7 × 27,4 × 10,5 cm 12.1 × 10.8 × 4.1 inches		36,9 × 32,6 × 11,2 cm 14.5 × 12.8 × 4.4 inches
Weight	2,8 kg 6.2 lbs		3,8 kg 8.4 lbs
Speakers	2 × 3 W Closed Box Speakers		
Microphone	1 × Analog Microphone		
Processor	Intel® Atom™ Dual Core Processor N2800 (1M Cache, 1.86 GHz)		
Chipset	Intel® NM10 Express Chipset		
RAM	4 GB DDR3		
Operating system	Microsoft Windows 7		
Hard disk drive	2.5" SSD 120 GB minimum		
SD-Card	MicroSD-Card 32 GB		
Connectors	1 × Connector for an HDMI 1.3 Connector Type A cable 2 × USB 2.0 (Current limit = 1000 mA) 1 × USB 3.0 (Current limit 1500 mA) 1 × RJ45 100/1000 Mbit/s (Ethernet) 2 × 3.5 mm Switch connector interface, (Pin out for mono plug: Sleeve = Common ground, Tip = Signal) 1 × 3.5 mm" Headphone jack (stereo) with jack detection 1 × 24 VDC in 2.5/5.5 mm (Power connector)		
Buttons	1 × Power On 1 × Volume Up 1 × Volume Down 1 × Menu 2 × Programmable		
WLAN (optional)	IEEE802.11 b/g/n Dual antenna diversity system		
Bluetooth® (optional)	Bluetooth® 3.0+HS		


Standard	Tobii I-12	Tobii I-12	Tobii I-15
Type/Model	I-12 R	I-12 ETR	I-15 ETR
IR Remote Control (Environmental Control Unit)	GEWA Programmable IR Remote Control (Environmental Control Unit), 19 – 455 kHz, 940 nm, compatible with a wide range of remote controls Resting Orientation: 1 × IR filter window with 1 × IR Receive Sensor, 3 × IR Transmit Diodes and 1 × Red Status LED Upright Orientation: 1 × IR filter window with 4 × IR Transmit Diodes Total peak transmit power (7 diodes): 8.4 W		
Camera	User Camera (back) 5 MP AF (Auto Focus) Web Camera (front) 2 MP FF (Fixed Focus)		
Eye Tracker	N/A	Tobii IS20 Module	
Battery Run Time ⁱ	~10.5 h	~9 h	~9.5/8 ⁱⁱ h
Battery Charge Time	Maximum 5.4 h (0-100%)		
Battery Storage Time	Maximum 6 months @ 40 – 60 % charge		
Deskstand	Integrated		
Mounting Systems Supported	Tobii QR adapter plate for Daessy and REHAdapt		
Power Supply	Adapter Technology Co. Ltd, ATM065-A240 Input: Universal 100 ~ 240 VAC / 50 ~ 60 Hz Output: +24VDC / 0~2.71A		
IP class	IP 43 (with I/O covers in place)		
<p>i. Indoor with continuous communication and with Gaze Interaction if applicable. ~24 hours with a Power optimized scenario.</p> <p>ii. 9.5 hours without the Eye tracker activated, 8 hours with the Eye tracker activated</p>			

E2 Radio Free I-Series

RF Free	Tobii I-12	Tobii I-15
Type/Model	I-12 ET	I-15 ET
Screen	12.1", Aspect ratio: 4:3, LED Backlight Unit, White Luminance 500 cd/m ²	15.0", Aspect ratio: 4:3, LED Backlight Unit White Luminance 400 cd/m ²
Screen resolution	1024 x 768 pixels (XGA)	
Touch Panel	Projected Capacitive Touch with Gorilla® Glass, 10 point multi touch	
Dimensions (WxHxD)	30,7 × 27,4 × 10,5 cm 12.1 × 10.8 × 4.1 inches	36,9 × 32,6 × 11,2 cm 14.5 × 12.8 × 4.4 inches
Weight	2,8 kg 6.2 lbs	3,8 kg 8.4 lbs
Speakers	2 × 3 W Closed Box Speakers	
Microphone	1 × Analog Microphone	
Processor	Intel® Atom™ Dual Core Processor N2800 (1M Cache, 1.86 GHz)	
Chipset	Intel® NM10 Express Chipset	
RAM	4 GB DDR3	
Operating system	Microsoft Windows 7	

RF Free	Tobii I-12	Tobii I-15
Type/Model	I-12 ET	I-15 ET
Hard disk drive	2.5" SSD 120 GB minimum	
SD-Card	MicroSD-Card 32 GB	
Connectors	1 × Connector for an HDMI 1.3 Connector Type A cable 2 × USB 2.0 (Current limit = 1000 mA) 1 × USB 3.0 (Current limit 1500 mA) 1 × RJ45 100/1000 Mbit/s (Ethernet) 2 × 3.5 mm Switch connector interface, (Pin out for mono plug: Sleeve = Common ground, Tip = Signal) 1 × 3.5 mm" Headphone jack (stereo) with jack detection 1 × 24 VDC in 2.5/5.5 mm (Power connector)	
Buttons	1 × Power On 1 × Volume Up 1 × Volume Down 1 × Menu 2 × Programmable	
IR Remote Control (Environmental Control Unit)	GEWA Programmable IR Remote Control (Environmental Control Unit), 19 – 455 kHz, 940 nm, compatible with a wide range of remote controls Resting Orientation: 1 × IR filter window with 1 × IR Receive Sensor, 3 × IR Transmit Diodes and 1 × Red Status LED Upright Orientation: 1 × IR filter window with 4 × IR Transmit Diodes Total peak transmit power (7 diodes): 8.4 W	
Camera	User Camera (back) 5 MP AF (Auto Focus) Web Camera (front) 2 MP FF (Fixed Focus)	
Eye Tracker	Tobii IS20 Module	
Battery Run Time ⁱ	~9h	~9.5/8 ⁱⁱ h
Battery Charge Time	Maximum 5.4 h (0-100%)	
Battery Storage Time	Maximum 6 months @ 40 – 60 % charge	
Deskstand	Integrated	
Mounting Systems Supported	Tobii QR adapter plate for Daessy and REHAdapt	
Power Supply	Adapter Technology Co. Ltd, ATM065-A240 Input: Universal 100 ~ 240 VAC / 50 ~ 60 Hz Output: +24VDC / 0~2.71A	
IP Class	IP 43 (with I/O covers in place)	
i. Indoor with continuous communication and with Gaze Interaction if applicable. ~24 hours with a Power optimized scenario. ii. 9.5 hours without the Eye tracker activated, 8 hours with the Eye tracker activated		

E3 Battery pack

Item	Specification	Remark
Battery Technology	Li-Ion rechargeable battery pack with gas gauge (SMBus v1.1 interface)	
Cell	6× Panasonic NCR18650 (3S2P)	
Battery Pack Capacity	62.64 Wh	Initial capacity, new battery pack
Nominal Voltage	10.8 V	
Charge Time	Maximum 5.4 h	Charge from 0 to 100%
Cycle Life	500 cycles	Minimum 75% of initial capacity remaining
Allowable Operating Temperature	0 – 45 °C, 45-85%RH -20 – 60 °C, 45-85%RH	Charge condition Discharge condition
Storage Temperature	-20 – 35 °C, 45-85%RH -20 – 40 °C, 45-85%RH -20 – 45 °C, 45-85%RH -20 – 50 °C, 45-85%RH	1 year 6 months 1 month 1 week
Storage Time ⁱ	Minimum 6 months @ charge ≥ 40%	 Do not long time store battery packs with less than 40% charge level
i. Batteries shall not be stored in the device		

E4 Eye Tracker

Technical Specifications	Tobii IS20 Module
Working Distance	40 - 90 cm 18 - 35 inches
Freedom of Head Movement ⁱ @ 70 cm / 27.5 inches (Width x Height)	50 × 36 cm 20 × 14 in
Head Movement Speed (optimal)	11.8 in/s 30 cm/s
Gaze Data Rate	30 Hz
Gaze Accuracy ⁱⁱ Under ideal conditions Across 30 × 20 × 20 cm head box	0.4° (Std dev 0.1°) 0.5° (Std dev 0.2°)
Screen Size ⁱⁱⁱ <19" screen (<28° gaze angle)	Excellent
Gaze Precision (=sample to sample noise) ^{iv} Under ideal conditions, without filter, on artificial eyes Across head box, without filter, on human eyes	Pending 0.4° (Std dev 0.1°)
Mounting	Built in
Power Supply	Built in

- i. Freedom of head movement describes the volume in front of the tracker in which the user must have at least one of the eyes. The numbers are specified parallel/orthogonal to screen surface, assuming eye tracker is at 20 degree angle to screen.
- ii. Gaze accuracy describes the angular average distance from the actual gaze point to the one measured by the eye tracker. Accuracy under ideal conditions is measured with users placed in the center of the eye tracker track box with the head resting on a chin rest, and the room and screen illumination constant at 300 lux.
Accuracy across head box is measured with users after calibration systematically positioned at varying positions ranging from center of the head box up to +/- 15 cm horizontal, +/- 10 cm vertical and +/- 10 cm distance.
Accuracy across varying background illumination is measured with users' head resting on a chin rest, and after calibration modifying background illumination from 1 to 1000 lux.
- iii. Gaze angles describe the quality of gaze accuracy when user looks at the upper two corners of 16:9 ratio screens, @ 60 cm user distance to Eye Tracker.
- iv. Gaze Precision describes the point-to-point variation between individual gaze samples (here specified with binocular data, ie both eyes, and measured on artificial eyes). Gaze Precision with Stampe filter is with Stampe stage 2 noise-reduction algorithm applied to raw data (Stampe, Behavior Research Methods, Instruments & Computers 1993, 25 (2), 137-142). Precision without filter is based on raw data, without any de-noising filter applied, either inside or outside the eye tracker.
Precision under ideal conditions is measured with users placed in the center of the eye tracker track box with the head resting on a chin rest, and the room and screen illumination constant at 300 lux.
Precision across head box is measured with users after calibration systematically positioned at varying positions ranging from center of the head box up to +/- 15 cm horizontal, +/- 10 cm vertical and +/- 10 cm distance.

Appendix F Approved Accessories

Description	Model	Tobii Part No.
I-Series AC Adapter (Power Supply)	AdapterTech ATM065-A240	12002664
Battery pack	TISB1	12002548

For information about the latest approved Tobii Accessories, please visit the www.tobii.com website or contact your local Tobii reseller.



Support for Your Tobii Device

Get Help Online

Before contacting us, see the product-specific Support page for your Tobii device. It contains up-to-date information about issues and tips & tricks related to the product. Find our Support page online at: <http://www.tobii.com/assistivesupport>.

Contact Your Reseller

For questions or problems with your product, contact Customer Support at your Tobii Reseller for assistance. They are most familiar with your personal setup and can best help you with tips and product training. For our Resellers contact details, see <http://www.tobii.com/en/assistive-technology/global/Contact/>

Tobii Support Offices

North Europe

support@tobii.com
Phone: +46 8 522 950 20
Support hours: 8 AM - 6 PM
Between July-August: 9 AM - 5 PM
(Central European Time, UTC +1)

Central Europe

support@tobii.com
Phone: +49 69 24 75 03 4-28
Support hours: 8 AM - 6 PM
Between July-August: 9 AM - 5 PM
(Central European Time, UTC +1)

North America

techsupport@tobiiATI.com
Toll-Free: +1-800-793-9227
Phone: +1-781-461-8200
Support hours: 9 AM - 9 PM
(US Eastern Standard Time, UTC -6)

China

support.cn@tobii.com
Phone: +86 512 6936 2880-814
Support hours: 9 AM - 5:30 PM
(China Standard Time, UTC +8)

©Tobii®. Illustrations and specifications do not necessarily apply to products and services offered in each local market. Technical specifications are subject to change without prior notice. All other trademarks are the property of their respective owners.

Europe, Africa, South America

Tobii Technology AB
Karlsrovägen 2D
S-182 53 Danderyd
Sweden
Phone : +46 8 663 69 90
Fax: +46 8 30 14 00
www.tobii.com
sales@tobii.com

Central Europe

Tobii Technology GmbH
Niederuau 45
D-60325 Frankfurt am Main
Germany
Phone: +49 69 24 75 03 40
Fax: +49 69 24 75 03 429
www.tobii.com
sales.de@tobii.com

North America

Tobii ATI
333 Elm Street
Dedham, MA 02026
USA
Phone: +1-781-461-8200
Fax: +1-781-461-8213
www.tobiiATI.com
sales.us@tobii.com

China

Tobii Electronics Technology Suzhou Co., Ltd
No. 678, Fengting Avenue
Land Industrial Park
Weiting, Suzhou 2, Post code: 21512
China
Phone: +86 (0) 13585980539
www.tobii.com
sales.cn@tobii.com

Pacific, South Asia

Tobii Technology
69 Cumming Street
Craigburn Farm SA 5051
Australia
Phone: +61 (0) 450 460 668
Fax: +61 (0) 8 8278 8671
www.tobii.com
sales@tobii.com