

MW70-3S0

Dual LGA2011 sockets R3 motherboard for Intel® E5-2600 V3/V4 series processors

User's Manual

Rev. 1003

Copyright

© 2015 GIGA-BYTE TECHNOLOGY CO., LTD. All rights reserved.

The trademarks mentioned in this manual are legally registered to their respective owners.

Disclaimer

Information in this manual is protected by copyright laws and is the property of GIGABYTE.

Changes to the specifications and features in this manual may be made by GIGABYTE without prior notice. No part of this manual may be reproduced, copied, translated, transmitted, or published in any form or by any means without GIGABYTE's prior written permission.

Documentation Classifications

In order to assist in the use of this product, GIGABYTE provides the following types of documentations:

- For detailed product information, carefully read the User's Manual.

For more information, visit our website at:

<http://b2b.gigabyte.com>

You are a professional?

Get an access to our complete source of sales, marketing & technical materials at:

<http://reseller.b2b.gigabyte.com>



<https://www.facebook.com/gigabyteserver>

Table of Contents

Box Contents	6
MW70-3S0 Motherboard Layout	7
Block Diagram	10
Chapter 1 Hardware Installation	11
1-1 Installation Precautions	11
1-2 Product Specifications	12
1-3 Installing the CPU and CPU Cooler	14
1-3-1 Installing the CPU	14
1-3-2 Installing the CPU Cooler	17
1-4 Installing the Memory	18
1-4-1 Four Channel Memory Configuration	18
1-4-2 Installing a Memory	19
1-4-3 DIMM Population Table	19
1-5 Back Panel Connectors	20
1-6 Internal Connectors	22
1-7 Jumper Settings	39
Chapter 2 BIOS Setup	44
2-1 The Main Menu	46
2-2 Advanced Menu	49
2-2-1 Offboard SATA Controller Configuration	50
2-2-2 Serial Port Console Redirection	51
2-2-3 PCI Subsystem Settings	55
2-2-3-1 PCI Express Settings	57
2-2-3-2 PCI Hot-Plug Settings	59
2-2-4 Network Stack	60
2-2-5 CSM Configuration	61
2-2-6 Post Report Configuration	63
2-2-7 NVMe Configuration	64
2-2-8 Trusted Computing	65
2-2-9 USB Configuration	66
2-2-10 Chipset Configuration	67
2-2-11 AST2400 HWM	68
2-2-12 Intel (R) Thunderbolt	69
2-2-13 SIO Configuration	71
2-2-14 iSCSI Configuration	74
2-3 Intel RC Setup Menu	75

2-3-1	Processor Configuration	76
2-3-1-1	Pre-Socket Configuration	79
2-3-2	Advanced Power Management Configuration	81
2-3-2-1	CPU P State Control	82
2-3-2-2	CPU C State Control	83
2-3-2-3	CPU T State Control	84
2-3-3	Common RefCode Configuration	85
2-3-4	QPI Configuration	86
2-3-5	Memory Configuration	88
2-3-5-1	Memory Topology	90
2-3-5-2	Memory Thermal	91
2-3-5-3	Memory Map.....	92
2-3-5-4	Memory RAS Configuration.....	93
2-3-6	I/O Configuration	94
2-3-6-1	IOAT Configuration	95
2-3-6-2	Intel VT for Directed I/O (VT-d)	96
2-3-7	PCH Configuration	97
2-3-7-1	PCH Devices	98
2-3-7-2	PCH sSATA Configuration	99
2-3-7-2-1	SATA Mode Options.....	102
2-3-7-3	PCH SATA Configuration	104
2-3-7-3-1	SATA Mode Options.....	107
2-3-7-4	USB Configuration.....	109
2-3-7-5	Azalia Configuration	110
2-3-8	Miscellaneous Configuration	111
2-3-9	Server ME Configuration	112
2-3-10	Runtime Error Logging	113
2-3-10-1	Whea Setting.....	114
2-3-10-2	Memory Error Enabling.....	115
2-3-10-3	PCI/PCI Error Enabling.....	116
2-4	Event Logs Menu	117
2-4-1	Change Smbios Event Log Settings.....	118
2-4-2	View Smbios Event Log.....	119
2-5	Security Menu	120
2-5-1	Secure Boot menu	121
2-5-1-1	Key Management	122
2-6	Boot Menu.....	124
2-7	Save & Exit Menu.....	126
2-8	BIOS POST Codes	128
2-9	BIOS POST Beep code.....	132
2-9-1	PEI Beep Codes	132
2-9-2	DEX Beep Codes	132

2-10 BIOS Recovery Instruction..... 133

Chapter 3 Appendix 134


3-1 Regulatory Statements..... 134

Box Contents

- ☒ Motherboard
- ☒ Driver CD
- ☒ User's Manual
- ☒ Two SATA cables
- ☒ I/O Shield

- The box contents above are for reference only and the actual items shall depend on the product package you obtain.
The box contents are subject to change without notice.
- The motherboard image is for reference only.

MW70-3S0 Motherboard Layout




Item	Code	Description
1	CPU1_FAN	CPU1 fan connector (for Secondary CPU)
2	HD_AUDIO	Audio connectors
3	USB3_LAN1	LAN port (top) / USB 3.0 ports (bottom)
4	USB2_LAN2	LAN port (top) / USB 2.0 ports (bottom)
5	COM1	Serial port
6	P12V_AUX2	8 pin power connector (for secondary CPU)
7	DIMM_P1_G0	Channel 3 slot 0 (for secondary CPU)
8	DIMM_P1_G1	Channel 3 slot 1 (for secondary CPU)
9	DIMM_P1_H0	Channel 4 slot 0 (for secondary CPU)
10	DIMM_P1_H1	Channel 4 slot 1 (for secondary CPU)
11	CPU1	Intel LGA2011 Socket R (Secondary CPU)
12	PMBUS	PMBus connector
13	ATX1	24 pin main power connector
14	DIMM_P0_A0	Channel 1 slot 0 (for primary CPU)
15	DIMM_P0_A1	Channel 1 slot 1 (for primary CPU)
16	DIMM_P0_B0	Channel 2 slot 0 (for primary CPU)
17	DIMM_P0_B1	Channel 2 slot 1 (for primary CPU)
18	P12V_AUX1	8 pin power connector (for primary CPU)
19	CPU0	Intel LGA2011 Socket R (Primary CPU)
20	SYS_FAN5	System fan connector#5
21	CPU0_FAN	CPU0 fan connector (for Primary CPU)
22	DIMM_P0_D1	Channel 4 slot 1 (for primary CPU)
23	DIMM_P0_D0	Channel 4 slot 0 (for primary CPU)
24	DIMM_P0_C1	Channel 3 slot 1 (for primary CPU)
25	DIMM_P0_C0	Channel 3 slot 0 (for primary CPU)
26	ME_UPDATE	ME update jumper
27	BMC_FRB	Force to Stop FRB Timer jumper
28	ME_RCVR	ME recovery jumper
29	BIOS_PWD	Clearing Supervisor Password jumper
30	BIOS_RCVR	BIOS recovery jumper
31	LSI_UART1	LSI UART header
32	SW_RAID	Intel Software RAID Key jumper
33	SYS_FAN4	System fan connector#4
34	SYS_FAN3	System fan connector#3
35	MSAS_HD_1	Mini-SAS HD connector
36	SATA_SGP	SATA SGPIO header
37	IMR_KEY	LSI RAID key header
38	SSATA_SGP	sSATA SGPIO header
39	FP_1	Front panel header
40	SYS_FAN1	System fan connector#1
41	BP_1	HDD back plane board header
42	SYS_FAN2	System fan connector#2
43	SATA0	SATA 3 6Gb/s connector

44	SATA_DOM0	SATA port 0 DOM support jumper
45	CASE_OPEN	Case open intrusion alert header
46	LED5	LSI firmware readiness LED
47	SATA1	SATA 3 6Gb/s connector
48	SATA_DOM1	SATA port 1 DOM support jumper
49	SATA2/3/4/5	SATA 3 6Gb/s connectors
50	SSATA0/1/2/3	SATA 3 6Gb/s connectors
51	CLR_CMOS	Clear CMOS jumper
52	F_USB3	USB 3.0 header
53	IPMB	IPMB connector
54	F_USB2	USB 2.0 header
55	TPM	TPM module connector
56	COM2	Serial port cable header
57	SPDIF_OUT1	S/PDIF out header
58	SPDIF_IN1	S/PDIF in header
59	F_AUDIO	Front audio connector
60	PCIE_1	PCI Express x8 slot
61	S3_MASK	S3 Power On Select jumper
62	PCIE_2	PCI Express x16 slot
63	LAN1_LED	LAN #1 Active/Link connector
64	LAN2_LED	LAN #2 Active/Link connector
65	PCIE_3	PCI Express x8 slot
66	PCIE_4	PCI Express x16 slot
67	PCIE_5	PCI Express x8 slot
68	PCIE_6	PCI Express x16 slot
69	DIMM_P1_F1	Channel 3 slot 1 (for secondary CPU)
70	DIMM_P1_F0	Channel 3 slot 0 (for secondary CPU)
71	DIMM_P1_E1	Channel 4 slot 1 (for secondary CPU)
72	DIMM_P1_E0	Channel 4 slot 0 (for secondary CPU)
73	LED_BMC	BMC firmware readiness LED
74	BAT	Battery socket
75	BUZZER1	Buzzer



CAUTION! If a SATA type hard drive is connected to the motherboard, please ensure the jumper is closed and set to **2-3 pins** (Default setting), in order to reduce any risk of hard disk damage. Please refer to Page 39 for SATA_DOM0 and SATA_DOM1 jumper setting instruction.

Block Diagram



Chapter 1 Hardware Installation

1-1 Installation Precautions

The motherboard contains numerous delicate electronic circuits and components which can become damaged as a result of electrostatic discharge (ESD). Prior to installation, carefully read the user's manual and follow these procedures:

- Prior to installation, do not remove or break motherboard S/N (Serial Number) sticker or warranty sticker provided by your dealer. These stickers are required for warranty validation.
- Always remove the AC power by unplugging the power cord from the power outlet before installing or removing the motherboard or other hardware components.
- When connecting hardware components to the internal connectors on the motherboard, make sure they are connected tightly and securely.
- When handling the motherboard, avoid touching any metal leads or connectors.
- It is best to wear an electrostatic discharge (ESD) wrist strap when handling electronic components such as a motherboard, CPU or memory. If you do not have an ESD wrist strap, keep your hands dry and first touch a metal object to eliminate static electricity.
- Prior to installing the motherboard, please have it on top of an antistatic pad or within an electrostatic shielding container.
- Before unplugging the power supply cable from the motherboard, make sure the power supply has been turned off.
- Before turning on the power, make sure the power supply voltage has been set according to the local voltage standard.
- Before using the product, please verify that all cables and power connectors of your hardware components are connected.
- To prevent damage to the motherboard, do not allow screws to come in contact with the motherboard circuit or its components.
- Make sure there are no leftover screws or metal components placed on the motherboard or within the computer casing.
- Do not place the computer system on an uneven surface.
- Do not place the computer system in a high-temperature environment.
- Turning on the computer power during the installation process can lead to damage to system components as well as physical harm to the user.
- If you are uncertain about any installation steps or have a problem related to the use of the product, please consult a certified computer technician.

1-2 Product Specifications

 CPU	- Support for Intel® Xeon® E5-2600 V3/V4 series processors in the LGA2011 package - L3 cache varies with CPU - Supports Dual QuickPath Interconnect up to 9.6GT/s - Enhanced Intel® SpeedStep Technology (EIST) - Support Intel® Virtualization Technology (VT)
 Chipset	Intel® C612 Express (Wellsburg) Chipset
 Memory	16 x DIMM slots - DDR4 memory supported only - Quad channel memory architecture - ECC RDIMM / LRDIMM modules supported - Single and dual rank RDIMM modules up to 32GB supported 3DS LRDIMM modules up to 128GB supported 1.2V modules: 1600/1866/2133/2400 MHz
 LAN	2 x Intel® I210 supports dual GbE LAN ports
 Expansion Slots	1 x PCI Express x16 slot, running at x16 (Gen3/PCIE_6) 1 x PCI Express x16 slot, running at x16 (Gen3/PCIE_4/The slot shares bandwidth with the PCIE_5 slot. When PCIE_5 slot is populated, the PCIE_4 will operate at x8 mode.) 1 x PCI Express x16 slot, running at x16 (Gen3/PCIE_2/The slot shares bandwidth with the PCIE_3 slot. When PCIE_3 slot is populated, the PCIE_2 will operate at x8 mode.) 3 x PCI Express x8 slots (GEN3/PCIE_1/PCIE_3/PCIE_5)
 Audio	- Realtek ALC887 codec High Definition Audio 7.1 Channel
 Onboard Graphics	ASPEED® AST2400 supports 128MB DDR3 VRAM
 Storage Interface	10 x SATA3 6Gb/s connectors 2 x Mini-SAS HD connectors - Support for Intel® RSTe 4.0 with RAID 0, 1, 10, 5 - LSI® 3008 controller supports LSI RAID 0, 1, 1E, 10
 USB	- Up to 4 USB 3.0 ports (2 on the back panel, 2 additional ports via the USB brackets connected to the internal USB headers) - Up to 4 USB 2.0 ports (2 on the back panel, 2 additional ports via the USB brackets connected to the internal USB headers)

	Internal Connectors	♦ 1 x 24-pin ATX main power connector ♦ 2 x 8-pin ATX 12V power connector ♦ 2 x Mini-SAS HD connectors ♦ 10 x SATA3 6Gb/s connectors ♦ 1 x PMBus header ♦ 2 x CPU fan headers ♦ 5 x System fan headers ♦ 1 x Front panel header ♦ 1 x HDD Back plane board header ♦ 1 x USB 3.0 header ♦ 1 x USB 2.0 header ♦ 1 x TPM module connector ♦ 1 x Serial port connector ♦ 1 x SATA SPGIO header ♦ 1 x sSATA SPGIO header ♦ 1 x IPMB connector ♦ 1 x Software RAID key connector ♦ 1 x LSI RAID key connector ♦ 1 x S/PDIF in header ♦ 1 x S/PDIF out header ♦ 2 x LAN LED connectors ♦ 1 x Chassis intrusion alert header
	Rear Panel I/O	♦ 2 x USB 3.0 ports ♦ 2 x USB 2.0 ports ♦ 2 x RJ-45 ports ♦ 1 x COM port ♦ 5 x Audio connectors (Center/Subwoofer Speaker Out, Rear Speaker Out, Line In/Mic In, Line Out, Headphone) ♦ 1 x Optical SPDIF Out
	I/O Controller	♦ ASPEED® AST2400-VB chip
	Hardware Monitor	♦ System voltage detection ♦ CPU/System temperature detection ♦ CPU/System fan speed detection ♦ CPU/System fan speed control * Whether the CPU/system fan speed control function is supported will depend on the CPU/system cooler you install.
	BIOS	♦ 1 x 128 Mbit flash ♦ AMI BIOS
	Form Factor	♦ EATX Form Factor; 13 inch x 12 inch

* GIGABYTE reserves the right to make any changes to the product specifications and product-related information without prior notice.

1-3 Installing the CPU and CPU Cooler




Read the following guidelines before you begin to install the CPU:

- Make sure that the motherboard supports the CPU.
- Always turn off the computer and unplug the power cord from the power outlet before installing the CPU to prevent hardware damage.
- Locate the pin one of the CPU. The CPU cannot be inserted if oriented incorrectly. (Or you may locate the notches on both sides of the CPU and alignment keys on the CPU socket.)
- Apply an even and thin layer of thermal grease on the surface of the CPU.
- Do not turn on the computer if the CPU cooler is not installed, otherwise overheating and damage of the CPU may occur.
- Set the CPU host frequency in accordance with the CPU specifications. It is not recommended that the system bus frequency be set beyond hardware specifications since it does not meet the standard requirements for the peripherals. If you wish to set the frequency beyond the standard specifications, please do so according to your hardware specifications including the CPU, graphics card, memory, hard drive, etc.

1-3-1 Installing the CPU


A. Locate the alignment keys on the motherboard CPU socket and the notches on the CPU.



B. Follow the steps below to correctly install the CPU into the motherboard CPU socket.




- Before installing the CPU, make sure to turn off the computer and unplug the power cord from the power outlet to prevent damage to the CPU.
- To protect the socket contacts, do not remove the protective plastic cover unless the CPU is inserted into the CPU socket. Save the cover properly and replace it if the CPU is removed.




Step 1:

Push the lever closest to the "unlock" marking "☐" (below referred as lever A) down and away from the socket to release it.




Step 2:

Push the lever closest to the "lock" marking "☐" (below referred as lever B) down and away from the socket. Then lift the lever.



Step 3:

Gently press lever A to allow the load plate to rise. Open the load plate. (Note: DO NOT touch the socket contacts after the load plate is opened.)




Step 4:

Hold the CPU with your thumb and index fingers. Align the CPU pin one marking (triangle) with the pin one corner of the CPU socket (or align the CPU notches with the socket alignment keys) and carefully insert the CPU into the socket vertically.



Step 5:

Once the CPU is properly inserted, carefully replace the load plate. Then secure lever B under its retention tab. The protective plastic cover may pop off from the load plate during the process of engaging the lever. Remove the cover. Save the cover properly and always replace it when the CPU is not installed.




Step 6:

Finally, secure lever A under its retention tab to complete the installation of the CPU.


1-3-2 Installing the CPU Cooler

Refer to the steps below to correctly install the CPU cooler on the motherboard. (Actual installation process may differ depending the CPU cooler to be used. Refer to the user's manual for your CPU cooler.)




Step 1:

Apply an even and thin layer of thermal grease on the surface of the installed CPU.




Step 2:

Place the cooler atop the CPU, aligning the four mounting screws with the mounting holes on the ILM. (If your cooler has a fan grill which may cause interference when you tighten the screws, remove it first and replace it after tightening the screws.)



Step 3:

Use one hand to hold the cooler and the other to tighten the screws in a diagonal sequence with a screw driver. Begin tightening a screw with a few turns and repeat with the screw diagonally opposite the one you just tightened. Then do the same to the other pair. Next, fully tighten the four screws.



Step 4:

Finally, attach the power connector of the CPU cooler to the CPU fan header (CPU_FAN) on the motherboard.



Please pay more attention when removing the CPU cooler because the thermal grease/tape between the CPU cooler and CPU may adhere to the CPU. Inadequately removing the CPU cooler may damage the CPU.

1-4 Installing the Memory



Read the following guidelines before you begin to install the memory:

- Make sure that the motherboard supports the memory. It is recommended that memory of the same capacity, brand, speed, and chips be used.
- Always turn off the computer and unplug the power cord from the power outlet before installing the memory to prevent hardware damage.
- Memory modules have a foolproof design. A memory module can be installed in only one direction. If you are unable to insert the memory, switch the direction.

1-4-1 Four Channel Memory Configuration

This motherboard provides sixteen DDR4 memory sockets and supports Four Channel Technology. After the memory is installed, the BIOS will automatically detect the specifications and capacity of the memory. Enabling Four Channel memory mode will be four times of the original memory bandwidth.

The four DDR4 memory sockets are divided into four channels each channel has two memory sockets as following:

Channel 1: DIMM_P0_A0/DIMM_P0_A1 (For primary CPU)/
DIMM_P1_E0/DIMM_P1_E1 (For secondary CPU)

Channel 2: DIMM_P0_B0/DIMM_P0_B1 (For primary CPU)/
DIMM_P1_F0/DIMM_P1_F1 (For secondary CPU)

Channel 3: DIMM_P0_C0/DIMM_P0_C1 (For primary CPU)/
DIMM_P1_G0/DIMM_P1_G1 (For secondary CPU)


Channel 4: DIMM_P0_D0/DIMM_P0_D1 (For primary CPU)/
DIMM_P1_H0/DIMM_P1_H1 (For secondary CPU)



When only one DIMM is used, it must be populated in memory slot0 first.

Memory populated sequence must be followed with slot0/slot1

System will not boot normally with incorrect populated sequence.



Due to CPU limitations, read the following guidelines before installing the memory in Four Channel mode.


1. Four Channel mode cannot be enabled if only one DDR4 memory module is installed.
2. When enabling Four Channel mode with two or four memory modules, it is recommended that memory of the same capacity, brand, speed, and chips be used for optimum performance.

1-4-2 Installing a Memory

 Before installing a memory module, make sure to turn off the computer and unplug the power cord from the power outlet to prevent damage to the memory module.
Be sure to install DDR4 DIMMs on this motherboard.

Installation Step:

- Step 1. Insert the DIMM memory module vertically into the DIMM slot, and push it down.
Step 2. Close the plastic clip at both edges of the DIMM slots to lock the DIMM module.
Note: For dual-channel operation, DIMMs must be installed in matched pairs.
Step 3. Reverse the installation steps when you wish to remove the DIMM module.



1-4-3 DIMM Population Table

Two Slots Channel RDIMM Population Configuration Within a Channel


Type	Ranks Per DIMM and Data Width	Speed (MT/s); Slot Per Channel (SPC) and DIMM Per Channel (DPC)		
		1 Slot Per Channel	2 Slot Per Channel	
		1DPC	1DPC	2DPC
RDIMM	SRx4	2133	2133	1866
RDIMM	SRx8	2133	2133	1866
RDIMM	DRx8	2133	2133	1866
RDIMM	DRx4	2133	2133	1866
LRDIMM	QRx4	2133	2133	2133
LRDIMM 3DS	8Rx4	2400	2400	2400



NOTE!

DDR4 2400MHz is only available on Intel Xeon® E5-2600 V4 processor.

1-5 Back Panel Connectors



a Serial Port

Connects to serial-based mouse or data processing devices.

b USB 2.0 Port

The USB port supports the USB 2.0 specification. Use this port for USB devices such as a USB keyboard/mouse, USB printer, USB flash drive and etc.

c USB 3.0 Port

The USB port supports the USB 3.0 specification. Use this port for USB devices such as a USB keyboard/mouse, USB printer, USB flash drive and etc.

d Center/Subwoofer Speaker Out Jack (Orange)

Use this audio jack to connect center/subwoofer speakers in a 5.1/7.1-channel audio configuration.

e Rear Speaker Out Jack (Black)

Use this audio jack to connect rear speakers in a 7.1-channel audio configuration.

f Optical S/PDIF Out Connector

This connector provides digital audio out to an external audio system that supports digital optical audio. Before using this feature, ensure that your audio system provides an optical digital audio in connector.

g Line In Jack (Blue)

The default line in jack. Use this audio jack for line in devices such as an optical drive, walkman, etc.

h Line Out Jack (Green)


The default line out jack. Use this audio jack for a headphone or 2-channel speaker. This jack can be used to connect front speakers in a 4/5.1/7.1-channel audio configuration.

i Mic In Jack (Pink)

The default Mic in jack. Microphones must be connected to this jack.

j RJ-45 LAN Ports (Gigabit Ethernet LAN Ports)

The Gigabit Ethernet LAN port provides Internet connection at up to 1 Gbps data rate. The following describes the states of the LAN port LEDs.



Speed LED:

State	Description
Yellow On	1 Gbps data rate
Yellow Blink	Identify 1 Gbps data rate
Green On	100 Mbps data rate
Green Blink	Identify 100 Mbps data rate
Off	10 Mbps data rate


Link/Activity LED:

State	Description
On	Link between system and network or no access
Blinking	Data transmission or receiving is occurring
Off	No data transmission or receiving is occurring



- When removing the cable connected to a back panel connector, first remove the cable from your device and then remove it from the motherboard.
- When removing the cable, pull it straight out from the connector. Do not rock it side to side to prevent an electrical short inside the cable connector.

1-6 Internal Connectors



1) ATX1	20) BP_1
2) P12V_AUX1	21) F_USB3
3) P12V_AUX2	22) IPMB
4) PMBUS	23) F_USB2
5) CPU0_FAN (for primary CPU)	24) TPM
6) CPU1_FAN (for secondary CPU)	25) COM2
7) SYS_FAN1 (System Fan)	26) SPDIF_OUT1
8) SYS_FAN2 (System Fan)	27) SPDIF_IN1
9) SYS_FAN3 (System Fan)	28) F_AUDIO
10) SYS_FAN4 (System Fan)	29) BAT
11) SYS_FAN5 (System Fan)	30) LAN1_LED
12) SATA0	31) LAN2_LED
13) SATA1	32) LED_BMC
14) SATA2/3/4/5	33) LSI_UART1
15) SSATA0/1/2/3	34) SW_RAID
16) MSAS_HD_1	35) IMR_KEY
17) SATA_SGP	36) CASE_OPEN
18) SSATA_SGP	37) LED5
19) FP_1	




Read the following guidelines before connecting external devices:


- First make sure your devices are compliant with the connectors you wish to connect.
- Before installing the devices, be sure to turn off the devices and your computer. Unplug the power cord from the power outlet to prevent damage to the devices.
- After installing the device and before turning on the computer, make sure the device cable has been securely attached to the connector on the motherboard.

1/2/3) ATX1/P12V_AUX1/P12V_AUX2
(2x4 12V Power Connector and 2x12 Main Power Connector)


With the use of the power connector, the power supply can supply enough stable power to all the components on the motherboard. Before connecting the power connector, first make sure the power supply is turned off and all devices are properly installed. The power connector possesses a foolproof design. Connect the power supply cable to the power connector in the correct orientation. The 12V power connector mainly supplies power to the CPU. If the 12V power connector is not connected, the computer will not start.

-  To meet expansion requirements, it is recommended that a power supply that can withstand high power consumption be used (500W or greater). If a power supply is used that does not provide the required power, the result can lead to an unstable or unbootable system.



ATX1		ATX1																																																					
		<table><tr><th>Pin No.</th><th>Definition</th><th>Pin No.</th><th>Definition</th></tr><tr><td>1</td><td>3.3V</td><td>13</td><td>3.3V</td></tr><tr><td>2</td><td>3.3V</td><td>14</td><td>NC</td></tr><tr><td>3</td><td>GND</td><td>15</td><td>GND</td></tr><tr><td>4</td><td>+5V</td><td>16</td><td>PS_ON</td></tr><tr><td>5</td><td>GND</td><td>17</td><td>GND</td></tr><tr><td>6</td><td>+5V</td><td>18</td><td>GND</td></tr><tr><td>7</td><td>GND</td><td>19</td><td>GND</td></tr><tr><td>8</td><td>Power Good</td><td>20</td><td>NC</td></tr><tr><td>9</td><td>5VSB (stand by +5V)</td><td>21</td><td>+5V</td></tr><tr><td>10</td><td>+12V</td><td>22</td><td>+5V</td></tr><tr><td>11</td><td>+12V</td><td>23</td><td>+5V</td></tr><tr><td>12</td><td>3.3V</td><td>24</td><td>GND</td></tr></table>	Pin No.	Definition	Pin No.	Definition	1	3.3V	13	3.3V	2	3.3V	14	NC	3	GND	15	GND	4	+5V	16	PS_ON	5	GND	17	GND	6	+5V	18	GND	7	GND	19	GND	8	Power Good	20	NC	9	5VSB (stand by +5V)	21	+5V	10	+12V	22	+5V	11	+12V	23	+5V	12	3.3V	24	GND	
Pin No.	Definition	Pin No.	Definition																																																				
1	3.3V	13	3.3V																																																				
2	3.3V	14	NC																																																				
3	GND	15	GND																																																				
4	+5V	16	PS_ON																																																				
5	GND	17	GND																																																				
6	+5V	18	GND																																																				
7	GND	19	GND																																																				
8	Power Good	20	NC																																																				
9	5VSB (stand by +5V)	21	+5V																																																				
10	+12V	22	+5V																																																				
11	+12V	23	+5V																																																				
12	3.3V	24	GND																																																				


4) PMBUS (PMBus connector)



Pin No.	Definition
1	PMBus CLK
2	PMBus DATA
3	PMBus Alert
4	GND
5	3.3V Sense

5/6/7/8/9/10/11) CPU_FAN0/CPU_FAN1/SYS_FAN1/SYS_FAN2/SYS_FAN3/SYS_FAN4/ SYS_FAN5 (CPU Fan/System Fan Headers)

The motherboard has two 4-pin CPU fan headers, and four 4-pin system fan headers. Most fan headers possess a foolproof insertion design. When connecting a fan cable, be sure to connect it in the correct orientation (the black connector wire is the ground wire). The motherboard supports CPU fan speed control, which requires the use of a CPU fan with fan speed control design. For optimum heat dissipation, it is recommended that a system fan be installed inside the chassis.




Pin No.	Definition
1	GND
2	+12V
3	Sense
4	Speed Control



- Be sure to connect fan cables to the fan headers to prevent your CPU and system from overheating. Overheating may result in damage to the CPU or the system may hang.
- These fan headers are not configuration jumper blocks. Do not place a jumper cap on the headers.

12/13) SATA0/SATA1 (SATA 6Gb/s Connectors/SATA4/5 Support SATA DOM Function)

The SATA connectors conform to SATA 6Gb/s standard and are compatible with SATA 3Gb/s and 1.5Gb/s standard. Each SATA connector supports a single SATA device.
Please see page 35 for SATA DOM jumper setting.



Normal Mode:


Pin No.	Definition
1	GND
2	TXP
3	TXN
4	GND
5	RXN
6	RXP
7	GND

SATA DOM Mode:

Pin No.	Definition
1	GND
2	TXP
3	TXN
4	GND
5	RXN
6	RXP
7	P5V

14/15) SATA/2/3/4/5/SSATA0/1/2/3 (SATA 6Gb/s Connectors)

The SATA connectors conform to SATA 6Gb/s standard and are compatible with SATA 3Gb/s and 1.5Gb/s standard. Each SATA connector supports a single SATA device.



Pin No.	Definition
1	GND
2	TXP
3	TXN
4	GND
5	RXN
6	RXP
7	GND





- A RAID 0 or RAID 1 configuration requires at least two hard drives. If more than two hard drives are configured, the total number of hard drives must be an even number.
- A RAID 10 configuration requires four hard drives.

(Note) When a RAID configuration is built across the SATA 6Gb/s channels, the system performance of the RAID configuration may vary depends on the devices are connected.

16) MSAS_HD_1 (Mini-SAS HD connectors)


Mini-SAS HD(High Density SFF-8644) is the next-generation SAS high-density and high-speed IO interface. Mini-SAS HD is in the SAS 3.0 standard, meets the 12Gb/s SAS specification.



Pin No.	Definition	Pin No.	Definition	Pin No.	Definition	Pin No.	Definition
0A1	NC	0C1	GND	1A1	GND	1C1	GND
0A2	SGPIO_CLOCK0	0C2	GND	1A2	SGPIO_CLOCK1	1C2	GND
0A3	GND	0C3	GND	1A3	GND	1C3	GND
0A4	RXP1	0C4	TXP1	1A4	RXP5	1C4	TXP5
0A5	RXN1	0C5	TXN1	1A5	RXN5	1C5	TXN5
0A6	GND	0C6	GND	1A6	GND	1C6	GND
0A7	RXP3	0C7	TXP3	1A7	RXP7	1C7	TXP7
0A8	RXN3	0C8	TXN3	1A8	RXN7	1C8	TXN7
0A9	GND	0C9	GND	1A9	GND	1C9	GND
0B1	GND	0D1	SGPIO_DATAIN0	1B1	GND	1D1	SGPIO_DATAIN1
0B2	SGPIO_LOAD0	0D2	NC	1B2	SGPIO_LOAD1	1D2	GND
0B3	GND	0D3	GND	1B3	GND	1D3	GND
0B4	RXP0	0D4	TXP0	1B4	RXP4	1D4	TXP4
0B5	RXN0	0D5	TXN0	1B5	RXN4	1D5	TXN4
0B6	GND	0D6	GND	1B6	GND	1D6	GND
0B7	RXP2	0D7	TXP2	1B7	RXP6	1D7	TXP6
0B8	RXN2	0D8	TXN2	1B8	RXN6	1D8	TXN6
0B9	GND	0D9	GND	1B9	GND	1D9	GND

17/18) SATA_SGP/SSATA_SGP (SAS SGPIO Headers)


SGPIO stands for Serial General Purpose Input/Output which is a 4-signal (or 4-wire) bus used between a Host Bus Adapter (HBA) and a backplane. Out of the 4 signals, 3 are driven by the HBA and 1 is driven by the backplane. Typically, the HBA is a storage controller located inside a server, desktop, rack or workstation computer that interfaces with Hard disk drives (HDDs) to store and retrieve data.



Pin No.	Definition
1	DATAIN
2	No Pin
3	DATAOUT
4	GND
5	GND
6	LOAD
7	NC
8	CLOCK

19) FP_1 (Front Panel Header)

Connect the power switch, reset switch, chassis intrusion switch/sensor and system status indicator on the chassis to this header according to the pin assignments below. Note the positive and negative pins before connecting the cables.




Pin No.	Signal Name	Definition
1	PWLED+	Power LED Signal anode (+)
2	5VSB	5V Standby Power
3	NC	No Pin
4	ID_LED+	ID LED Signal anode (+)
5	PWLED-	Power LED Signal cathode(-)
6	ID_LED-	ID LED Signal cathode(-)
7	HD+	Hard Disk LED Signal anode (+)
8	SYS_LED+	System Front board LED Signal anode (+)
9	HD-	Hard Disk LED Signal cathode(-)
10	SYS_LED-	System Status LED Signal cathode(-)
11	PWR_BTN	Power Button Signal
12	L1_ACT	LAN1 active LED Signal
13	PWR_BTN_GND	Ground
14	L1_LINK-	LAN1 Link LED Signal cathode(-)
15	RST_BTN+	Reset button Signal anode (+)
16	SENSOR_SDA	SMBus Data Signal
17	RST_BTN_GND	Ground
18	SENSOR_SCL	SMBus Clock Signal
19	ID_SW+	ID Switch Signal anode (+)
20	CASE_OPEN-	Chassis intrusion Signal cathode(-)
21	ID_SW-	ID Switch Signal cathode(-)
22	L2_ACT	LAN2 active LED Signal
23	NMI_SW-	NMI switch Signal cathode(-)
24	L2_LINK-	LAN2 Link LED Signal cathode(-)



The front panel design may differ by chassis. A front panel module mainly consists of power switch, reset switch, power LED, hard drive activity LED, speaker and etc. When connecting your chassis front panel module to this header, make sure the wire assignments and the pin assignments are matched correctly.


20) BP_1 (HDD Back Plane Board Headers)



Pin No.	Definition
1	BP_SGP_CLK
2	NC
3	BP_SGP_GLD
4	FAN_GATE_N
5	BP_SGP_DOUT
6	GND
7	KEY
8	Reset
9	GND
10	BP_LED_A_N
11	BP_LED_G_N
12	GND
13	BP_SGP_DIN
14	NC
15	GND
16	SMB_BP_DATA
17	GND
18	SMB_BP_CLK
19	P_3V3_AUX
20	BMC_ACK
21	P_3V3_AUX
22	BMC_REQ
23	GND
24	KEY
25	BP_PRESENSE
26	GND


21) F_USB3 (USB 3.0 Header)

The headers conform to USB 3.0 specification. Each USB header can provide two USB ports via an optional USB bracket. For purchasing the optional USB bracket, please contact the local dealer.



Pin No.	Definition
1	Power
2	IntA_P1_SSRX-
3	IntA_P1_SSRX+
4	GND
5	IntA_P1_SSTX-
6	IntA_P1_SSTX+
7	GND
8	IntA_P1_D-
9	IntA_P1_D+
10	NC
11	IntA_P2_D+
12	IntA_P2_D-
13	GND
14	IntA_P2_SSTX+
15	IntA_P2_SSTX-
16	GND
17	IntA_P2_SSRX+
18	IntA_P2_SSRX-
19	Power
20	No Pin



22) IPMB (IPMB Connector)



Pin No.	Definition
1	Clock
2	GND
3	Data


23) F_USB2 (Front USB Header)

The header conform to USB 2.0 specification. Each USB header can provide two USB ports via an optional USB bracket. For purchasing the optional USB bracket, please contact the local dealer.



Pin No.	Definition
1	Power (5V)
2	Power (5V)
3	USB DX-
4	USB DY-
5	USB DX+
6	USB DY+
7	GND
8	GND
9	No Pin
10	NC



24) TPM (TPM Module Connector)



Pin No.	Definition
1	CLK_33M_TPM
2	P_3V3_AUX
3	LPC_RST
4	P3V3
5	LPC_LAD0
6	IRQ_SERIAL
7	LPC_LAD1
8	TPM_DET_N
9	LPC_LAD2
10	NC
11	LPC_LAD3
12	GND
13	LPC_FRAME_N
14	GND


25) COM2 (Serial Port Header)

The COM header provides one serial port via an optional COM port cable. For purchasing the optional COM port cable, please contact the local dealer.



Pin No.	Definition
1	ND CD-
2	NS IN
3	NS OUT
4	ND TR-
5	GND
6	ND SR-
7	NR TS-
8	NCT S-
9	NR I-
10	No Pin

26/27) SPDIF_OUT1/SPDIF_IN1 (SPDIF Out and SPDIF In Header)



SPDIF_OUT1

Pin No.	Definition
1	GND
2	SPDIF-OUT1





SPDIF_IN1

Pin No.	Definition
1	GND
2	SPDIF-IN
3	P_5V_AUX

28) F_AUDIO (Front Panel Audio Header)

The front panel audio header supports Intel High Definition audio (HD) audio. You may connect your chassis front panel audio module to this header. Make sure the wire assignments of the module connector match the pin assignments of the motherboard header. Incorrect connection between the module connector and the motherboard header will make the device unable to work or even damage it.



For HD Front Panel Audio:



Pin No.	Definition
1	MIC2-L
2	DGND
3	MIC2-R
4	P3V3
5	LINE2-R
6	MIC2-JD
7	FRONT IO SENSE
8	No Pin
9	LINE2-L
10	LINE2-JD



- The front panel audio header supports HD audio by default. If your chassis provides an AC'97 front panel audio module.


29) BAT (Battery)

The battery provides power to keep the values (such as BIOS configurations, date, and time information) in the CMOS when the computer is turned off. Replace the battery when the battery voltage drops to a low level, or the CMOS values may not be accurate or may be lost.



- Always turn off your computer and unplug the power cord before replacing the battery.
- Replace the battery with an equivalent one. Danger of explosion if the battery is replaced with an incorrect model.
- Contact the place of purchase or local dealer if you are not able to replace the battery by yourself or uncertain about the battery model.
- When installing the battery, note the orientation of the positive side (+) and the negative side (-) of the battery (the positive side should face up).
- Used batteries must be handled in accordance with local environmental regulations.

30/31) LAN1_LED/LAN2_LED (LAN1/LAN2 link/active LED Headers)




LAN1_LED:

Pin No.	Definition
1	P_3.3V_AUX
2	LAN1_ACT_N
3	LAN1_100M_N
4	LAN1_1G_N

LAN2_LED:


Pin No.	Definition
1	P_3.3V_AUX
2	LAN2_ACT_N
3	LAN2_100M_N
4	LAN2_1G_N

32) LED_BMC (BMC Firmware Readiness LED)



State	Description
On	BMC firmware is initial
Blinking	BMC firmware is ready
Off	AC loss

33) LSI_UART1 (LSI UART Header)




4

1

Pin No.	Definition
1	UART0_TX
2	GND
3	UART0_RX
4	P1V8

34) SW_RAID (Intel RAID Key Header)




2

1


Pin No.	Definition
1	KEY
2	GND

35) IMR_KEY (LSI RAID Key Header)




Pin No.	Definition
1	KEY
2	GND

36) CASE_OPEN (Case open intrusion alert header)




- ☐ Open: Normal operation.
- ☒ Closed: Active chassis intrusion alert.

37) LED5 (LSI Firmware Readiness LED)



State	Description
On	LSI firmware is initial
Blinking	LSI firmware is ready
Off	AC loss

1-7 Jumper Settings



1)	SATA_DOM0	6)	BMC_FRB
2)	SATA_DOM1	7)	ME_RCVR
3)	CLR_CMOS	8)	BIOS_PWD
4)	S3_MASK	9)	BIOS_RVCR
5)	ME_UPDATE		


1/2) SATA_DOM0/SATA_DOM0 (SATA port 0 and port 1 DOM Jumpers)

CAUTION!



- If the SATA DOM power is supplied by the motherboard, set the jumper to pin 1-2.
- If the SATA DOM power is supplied by external power, set the jumper to pin 2-3.
- If a SATA type hard drive is connected to the motherboard, please ensure the jumper is closed and set to **2-3 pins** (Default setting), in order to reduce any risk of hard disk damage.

Please refer to the pin definition table in the following.



For SATA_DOM0

Pin No.	Definition
1	P5V
2	SATA0 Pin7
3	GND




For SATA_DOM0

Pin No.	Definition
1	P5V
2	SATA1 Pin7
3	GND



3) CLR_CMOS (Clearing CMOS Jumper)

Use this jumper to clear the CMOS values (e.g. date information and BIOS configurations) and reset the CMOS values to factory defaults. To clear the CMOS values, place a jumper cap on the two pins to temporarily short the two pins or use a metal object like a screwdriver to touch the two pins for a few seconds.



1-2 Close: Normal operation (Default setting)




2-3 Close: Clear CMOS data.



- Always turn off your computer and unplug the power cord from the power outlet before clearing the CMOS values.
- After clearing the CMOS values and before turning on your computer, be sure to remove the jumper cap from the jumper. Failure to do so may cause damage to the motherboard.

4) S3_MASK (S3 Power On Select Jumper)




1-2 Close: Stop an initial power on when BMC is not ready.



2-3 Close: Keep initial power on. (Default setting)

5) ME_UPDATE (ME Update Jumper)




1-2 Close: Normal operation (Default setting)




2-3 Close: ME updated.


6) BMC_FRB (Force to Stop FRB Timer Jumper)



7) ME_RCVR (ME Recovery Jumper)




8) BIOS_PWD (Clearing Supervisor Password Jumper)



- 1  1-2 Close: Normal operation. (Default setting)
- 1  2-3 Close: Skip supervisor password.

9) BIOS_RVCR (BIOS Recovery Jumper)



- 1  1-2 Close: Normal operation. (Default setting)
- 1  2-3 Close: BIOS recovery mode.

Chapter 2 BIOS Setup

BIOS (Basic Input and Output System) records hardware parameters of the system in the EFI on the motherboard. Its major functions include conducting the Power-On Self-Test (POST) during system startup, saving system parameters and loading operating system, etc. BIOS includes a BIOS Setup program that allows the user to modify basic system configuration settings or to activate certain system features. When the power is turned off, the battery on the motherboard supplies the necessary power to the CMOS to keep the configuration values in the CMOS.

To access the BIOS Setup program, press the <F2> key during the POST when the power is turned on.



- BIOS flashing is potentially risky, if you do not encounter problems of using the current BIOS version, it is recommended that you don't flash the BIOS. To flash the BIOS, do it with caution. Inadequate BIOS flashing may result in system malfunction.
- It is recommended that you not alter the default settings (unless you need to) to prevent system instability or other unexpected results. Inadequately altering the settings may result in system's failure to boot. If this occurs, try to clear the CMOS values and reset the board to default values. (Refer to the **Exit** section in this chapter or introductions of the battery/clearing CMOS jumper in Chapter 1 for how to clear the CMOS values.)

BIOS Setup Program Function Keys

<<-><->>	Move the selection bar to select the screen
<↑><↓>	Move the selection bar to select an item
<+>	Increase the numeric value or make changes
<->	Decrease the numeric value or make changes
<Enter>	Execute command or enter the submenu
<Esc>	Main Menu: Exit the BIOS Setup program Submenus: Exit current submenu
<F1>	Show descriptions of general help
<F3>	Restore the previous BIOS settings for the current submenus
<F9>	Load the Optimized BIOS default settings for the current submenus
<F10>	Save all the changes and exit the BIOS Setup program

- **Main**

This setup page includes all the items in standard compatible BIOS.

- **Advanced**

This setup page includes all the items of AMI BIOS special enhanced features.

(ex: Auto detect fan and temperature status, automatically configure hard disk parameters.)

- **Intel RC Setup**

This setup page includes all the submenu options for configuring the function of processor, network, North Bridge, South Bridge, and System event logs.

- **Event Logs**

This setup page provides items for configuration of Smbios Event Log settings and display the Smbios event logs information.

- **Security**

Change, set, or disable supervisor and user password. Configuration supervisor password allows you to restrict access to the system and BIOS Setup.

A supervisor password allows you to make changes in BIOS Setup.

A user password only allows you to view the BIOS settings but not to make changes.


- **Boot**

This setup page provides items for configuration of boot sequence.

- **Save & Exit**

Save all the changes made in the BIOS Setup program to the CMOS and exit BIOS Setup. (Pressing <F10> can also carry out this task.)

Abandon all changes and the previous settings remain in effect. Pressing <Y> to the confirmation message will exit BIOS Setup. (Pressing <Esc> can also carry out this task.)



🔑 BIOS Information

🔑 Project Name

Display the project name information.

🔑 Project Version

Display version number of the BIOS setup utility.

🔑 BIOS Build Date and Time

Displays the date and time when the BIOS setup utility was created.

🔑 EC Firmware Version

Display version number of the Firmware setup utility.

🔑 Processor Information

🔑 CPU Brand String/Max CPU Speed/CPU Signature/Processors Core/Microcode Patch

Displays the technical specifications for the installed processor.

🔑 Memory Information

🔑 Total Memory

Display the total memory size of the installed memory.

🔑 Memory Frequency

Display the frequency information of the installed memory.

🔑 Onboard LAN Information

🔑 LAN1/LAN2 MAC Address

Display LAN1/LAN2 MAC address information.

☞ **System Date**


Set the date following the weekday-month-day- year format.

☞ **System Time**


Set the system time following the hour-minute- second format.

2-2 Advanced Menu

The Advanced menu display submenu options for configuring the function of various hardware components. Select a submenu item, then press Enter to access the related submenu screen.



2-2-1 Offboard SATA Controller Configuration



2-2-2 Serial Port Console Redirection

Bios Setup Utility	
Advanced	
COM1 Console Redirection [Enabled] ▶ Console Redirection Settings	Console Redirection Enable or Disable.
COM2/Serial Over LAN Console Redirection [Enabled] ▶ Console Redirection Settings	
Legacy Console Redirection ▶ Legacy Console Redirection Settings	
Serial Port for Out-of-Band Management/ Windows Emergency Management Services (EMS) Console Redirection [Enabled] ▶ Console Redirection Settings	++: Select Screen ↑↓: Select Item Enter: Select +/-: Change Opt. F1: General Help F3: Previous Values F9: Optimized Defaults F10: Save & Exit ESC: Exit

Bios Setup Utility	
Advanced	
COM1 Console Redirection Settings	Emulation: ANSI: Extended ASCII char set. VT100: ASCII char set. VT100+: Extends VT100 to support color, function keys, etc. VT-UTF8: Uses UTF8 encoding to map Unicode chars onto 1 or more bytes.
Terminal Type [ANSI]	++: Select Screen ↑↓: Select Item Enter: Select +/-: Change Opt. F1: General Help F3: Previous Values F9: Optimized Defaults F10: Save & Exit ESC: Exit
Bits per second [115200]	
Data Bits [8]	
Parity [None]	
Stop Bits [1]	
Flow Control [None]	
VT-UTF8 Combo Key Support [Enabled]	
Recorder Mode [Disabled]	
Resolution 100x31 [Enabled]	
Legacy OS Redirection Resolution [80x24]	
PuTTY KeyPad [VT100]	
Redirection After BIOS POST [Always Enable]	

Bios Setup Utility		
Advanced		
COM2/Serial Over LAN Console Redirection Settings		Emulation: ANSI: Extended ASCII char set. VT100: ASCII char set. VT100+: Extends VT100 to support color, function keys, etc. VT-UTF8: Uses UTF8 encoding to map Unicode chars onto 1 or more bytes.
Terminal Type	[ANSI]	
Bits per second	[115200]	
Data Bits	[8]	
Parity	[None]	
Stop Bits	[1]	
Flow Control	[None]	
VT-UTF8 Combo Key Support	[Enabled]	
Recorder Mode	[Disabled]	
Resolution 100x31	[Enabled]	
Legacy OS Redirection Resolution	[80x24]	
Putty KeyPad	[VT100]	
Redirection After BIOS POST	[Always Enable]	
		++: Select Screen ↑↓: Select Item Enter: Select +/-: Change Opt. F1: General Help F3: Previous Values F9: Optimized Defaults F10: Save & Exit ESC: Exit

Bios Setup Utility		
Advanced		
Out-of-Band Mgmt Port	[COM1]	Microsoft Windows Emergency Management Services (EMS) allows for remote management of a Windows Server OS through a serial port.
Terminal Type	[VT-UTF8]	
Bits per second	[115200]	
Flow Control	[None]	
Data Bits	8	
Parity	None	
Stop Bits	1	
		++: Select Screen ↑↓: Select Item Enter: Select +/-: Change Opt. F1: General Help F3: Previous Values F9: Optimized Defaults F10: Save & Exit ESC: Exit

☞ **COM1/COM2/Serial Over AN Console Redirection Settings**

☞ **Console Redirection** (Note)

Select whether to enable console redirection for specified device. Console redirection enables users to manage the system from a remote location.

Options available: Enabled/Disabled. Default setting is **Disabled**.

☞ **Console Redirection Settings**

☞ **Terminal Type**

Select a terminal type to be used for console redirection.

Options available: VT100/VT100+/ANSI /VT-UTF8. Default setting is **ANSI**.

☞ **Bits per second**

Select the baud rate for console redirection.

Options available: 9600/19200/38400/57600/115200. Default setting is **115200**.

☞ **Data Bits**

Select the data bits for console redirection.

Options available: 7/8. Default setting is **8**.

☞ **Parity**

A parity bit can be sent with the data bits to detect some transmission errors.

Even: parity bit is 0 if the num of 1's in the data bits is even.

Odd: parity bit is 0 if num of 1's in the data bits is odd.

Mark: parity bit is always 1. Space: Parity bit is always 0.

Mark and Space Parity do not allow for error detection.

Options available: None/Even/Odd/Mark/Space. Default setting is **None**.

☞ **Stop Bits**

Stop bits indicate the end of a serial data packet. (A start bit indicates the beginning). The standard setting is 1 stop bit. Communication with slow devices may require more than 1 stop bit.

Options available: 1/2. Default setting is **1**.

☞ **Flow Control**

Flow control can prevent data loss from buffer overflow. When sending data, if the receiving buffers are full, a 'stop' signal can be sent to stop the data flow. Once the buffers are empty, a 'start' signal can be sent to re-start the flow. Hardware flow control uses two wires to send start/stop signals.

Options available: None/Hardware RTS/CTS. Default setting is **None**.

☞ **VT-UTF8 Combo Key Support** (Note)

Enable/Disable VT-UTF8 Combo Key Support.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ **Recorder Mode** (Note)

When this mode enabled, only text will be send. This is to capture Terminal data.

Options available: Enabled/Disabled. Default setting is **Disabled**.

☞ **Resolution 100x31** (Note)

Enables or disables extended terminal resolution. Default setting is **Enabled**.

Options available: Enabled/Disabled.

(Note) Advanced items prompt when this item is defined.

☞ **Legacy OS Redirection Resolution** (Note)

On Legacy OS, the number of Rows and Columns supported redirection.

Options available: 80x24/80X25. Default setting is **80x24**.

☞ **Putty KeyPad** (Note)

Select function FunctionKey and KeyPad on Putty.

Options available: VT100/LINUX/XTERMR6/SCO/ESCN/VT400. Default setting is **VT100**.

☞ **Redirection After BIOS POST** (Note)

This option allows user to enable console redirection after O.S has loaded.

Options available: Always Enable/Boot Loader. Default setting is **Always Enable**.


☞ **Out-of-Bnad Mgmt Port**

Microsoft Windows Emerency Management Service (EMS) allows for remote management of a Windows Server OS through a serial port.

Options available: COM1/COM2. Default setting is **COM1**.

(Note) Advanced items prompt when this item is defined.

2-2-3 PCI Subsystem Settings



☞ PCI Express Slot #1/#2/#3/#4/#5/#6 I/O ROM

When enabled, This setting will initialize the device expansion ROM for the related PCI-E slot.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ Onboard LAN#1/#2 Controller

Enable/Disable onboard LAN devices.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ Onboard LAN #1/#2 I/O ROM

Enable/Disable onboard LAN devices and initialize device expansion ROM.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ PCI Devices Common Settings

☞ PCI Latency Timer

Value to be programmed into PCI Latency Timer Register.

Options available: 32 PCI Bus Clocks/64 PCI Bus Clocks/96 PCI Bus Clocks/128 PCI Bus Clocks/160 PCI Bus Clocks/192 PCI Bus Clocks/224 PCI Bus Clocks/248 PCI Bus Clocks/.

Default setting is **32 PCI Bus Clocks**.

☞ VGA Palette Snoop

Enable/Disable VGA Palette Registers Snooping.

Options available: Enabled/Disabled. Default setting is **Disabled**.

☞ Above 4G Decoding

Enable/Disable Above 4G Decoding.

Options available: Enabled/Disabled. Default setting is **Disabled**.

SR-IOV Support

If system has SR-IOV capable PCIe Devices, this option enables or disables Single Root IO Virtualization Support.

Options available: Enabled/Disabled. Default setting is **Disabled**.


PCI Express Settings

Press [Enter] for configuration of advanced items.

PCI Hot-Plug Settings

Press [Enter] for configuration of advanced items.

2-2-3-1 PCI Express Settings



⌵ PCI Express Device Register Settings

⌵ Relaxed Ordering

Enable/Disable PCI Express Device Relaxed Ordering feature.

Options available: Enabled/Disabled. Default setting is **Disabled**.

⌵ Extended Tag

When this feature is enabled, the system will allow device to use 8-bit Tag field as a requester.

Options available: Enabled/Disabled. Default setting is **Disabled**.

⌵ No Snoop

Enable/Disable PCI Express Device No Snoop option.

Options available: Enabled/Disabled. Default setting is **Enabled**.

⌵ Maximum Payload

Set maximum payload for PCI Express Device or allow system BIOS to select the value.

Options available: Auto/128 Bytes/256 Bytes/512 Bytes/1024 Bytes/2048 Bytes/4096 Bytes.

Default setting is **Auto**.

⌵ PCI Express Link Register Settings

⌵ Extended Synch

When this feature is enabled, the system will allow generation of Extended Synchronization patterns.

Options available: Enabled/Disabled. Default setting is **Disabled**.

⌵ Link Training Retry

Define the number of Retry Attempts software will take to retrain the link if previous training attempt was unsuccessful. Press <+> / <-> keys to increase or decrease the desired values.

Options available: Disabled/2/3/5. Default setting is **5**.

Link Training Timeout (us)

Define the number of Microseconds software will wait before polling 'Link Training' bit in Link Status register. Press <+> / <-> keys to increase or decrease the desired values. Value range is from 10 to 10000 us.

Unpopulated Links

When this item is set to 'Disable Link', the system will operate power save feature for those unpopulated PCI Express links.

Options available: Keep Link ON/ Disable Link. Default setting is **Keep Link ON**.

2-2-3-2 PCI Hot-Plug Settings



☞ PCI Hot-Plug Settings

☞ BIOS Hot-Plug Support

Enable/Disable BIOS Hot-Plug Support feature.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ PCI Buses Padding

Padd PCI Buses behind the bridge for Hot-Plug.

Options available: Disabled/1/2/3/4/5. Default setting is **1**.

☞ I/O Resources Padding

Padd PCI Resources behind the bridge for Hot-Plug.

Options available: Disabled/4 K/8 K/16 K/32 K. Default setting is **4K**.

☞ MMIO 32 bit Resources Padding

Options available: Disabled/1 M/2 M/4 M/8 M/16 M/32 M/64 M/128 M. Default setting is **16M**.

☞ PFMMIO 32 bit Resources Padding

Options available: Disabled/1 M/2 M/4 M/8 M/16 M/32 M/64 M/128 M. Default setting is **16M**.

2-2-4 Network Stack



🔑 Network stack

Enable/Disable UEFI network stack.

Options available: Enabled/Disabled. Default setting is **Disabled**.

🔑 Ipv4 PXE Support^(Note)

Enable/Disable Ipv4 PXE feature.

Options available: Enabled/Disabled. Default setting is **Enabled**.

🔑 Ipv6 PXE Support^(Note)

Enable/Disable Ipv6 PXE feature.

Options available: Enabled/Disabled. Default setting is **Enabled**.

🔑 PXE boot wait time^(Note)


Press <+> / <-> keys to increase or decrease the desired values.

🔑 Media detect time^(Note)

Press <+> / <-> keys to increase or decrease the desired values.

(Note) This item appears when **Network Stack** is set to **Enabled**.

2-2-5 CSM Configuration



☞ Compatibility Support Module Configuration

☞ CSM Support

Enable/Disable Compatibility Support Module (CSM) support.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ CSM16 Module Version

Display CSM Module version information.

☞ Gate20 Active

Upon Request: GA20 can be disabled using BIOS services.

Always: Do not allow disabling GA20; this option is useful when any RT code is executed above 1MB.

Options available: Upon Request/Always. Default setting is **Upon Request**.

☞ Option ROM Messages

Option ROM Messages.

Options available: Force BIOS/Keep Current. Default setting is **Force BIOS**.

☞ INT19 Endless Retry

Enabled: Allowed headless retry boot

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ Boot option filter

Determines which devices system will boot to.

Options available: UEFI and Legacy/Legacy only/UEFI only. Default setting is **UEFI and Legacy**.

☞ **Option ROM execution**

☞ **Network**

Controls the execution UEFI and Legacy PXE OpROM.

Options available: Do not launch/UEFI only/Legacy. Default setting is **Legacy**.

☞ **Storage**

Controls the execution UEFI and Legacy Storage OpROM.

Options available: Do not launch/UEFI only/Legacy. Default setting is **Legacy**.

☞ **Video**

Controls the execution UEFI and Legacy Video OpROM.


Options available: Do not launch/UEFI only/Legacy. Default setting is **Legacy**.

☞ **Other PCI devices**

Determines OpROM execution policy for devices other than network, Storage, or Video.

Options available: UEFI/Legacy. Default setting is **UEFI**.

2-2-6 Post Report Configuration



🔑 Post Report Configuration


🔑 Error Message Report

🔑 Post Error Message

Enable/Disable Info Error Message support.

Options available: Enabled/Disabled. Default setting is **Enabled**.


2-2-7 NVMe Configuration



NVMe Configuration

Displays NVMe controller and driver information.

2-2-8 Trusted Computing



➤ **Configuration**

➤ **Security Device Support**


Select Enabled to activate TPM support feature.

Options available: Enabled/Disabled. Default setting is **Disabled**.

➤ **Current Status Information**

Display current TPM status information.

2-2-9 USB Configuration



☞ USB Configuration

☞ USB Devices:

Display the USB devices connected to the system.

☞ XHCI Hand-off

Enable/Disable XHCI (USB 3.0) Hand-off support.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ EHCI Hand-off

Enable/Disable EHCI (USB 2.0) Hand-off function.

Options available: Enabled/Disabled. Default setting is **Disabled**.

☞ USB Mass Storage Driver Support^(Note)

Enable/Disable USB Mass Storage Driver Support.

Options available: Enabled/Disabled. Default setting is **Enabled**.


☞ Port 60/64 Emulation

Enable I/O port 60h/64h emulation support. This should be enabled for the complete USB Keyboard Legacy support for non-USB aware OS.

Options available: Enabled/Disabled. Default setting is **Enabled**.

(Note) This item is present only if you attach USB types of device.

2-2-10 Chipset Configuration



🔑 Deep Sleep (EuP)

Enable/Disable Deep Sleep mode.

Options available: Enabled/Disabled. Default setting is **Disabled**.

🔑 Chassis Opened Warning

Enable/Disable Chassis intrusion alter funtion.



Options available: Enabled/Disabled. Default setting is **Enabled**.

🔑 Chassis Opened Status


Display the chassis opened status.

2-2-11 AST2400 HWM

Press Enter to view the Hardware Monitor screen which displays a real-time record of the CPU/system temperature, and fan speed, Items on this window are non-configurable.



2-2-12 Intel (R) Thunderbolt



☞ Intel (R) Thunderbolt Configuration

☞ Thunderbolt Specification

☞ Intel Sample Code Version

☞ Intel Thunderbolt Technology^(Note)

Enable/Disable Intel Thunderbolt Technology feature.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ Security Level

Configure the security level.

Options available: Legacy Mode/Unique ID/One time saved key/DP++ only.

Default setting is **Legacy Mode**.

☞ Wake From Thunderbolt Devices

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ AIC Support (Add In Card Support)

Apply Go2Sx command before going to sleep.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ AIC Location Group

Thunderbolt AIC location group.

Options available: SB PCIE Slot/CPU0 NB PCIE Slot. Default setting is **CPU0 NB PCIE Slot**.

(Note) Advanced items prompt when this item is set to **Enabled**.

⌄ **AIC Location**

Options available: NB PCIE D01F0/NB PCIE D01F1/NB PCIE D01F2/NB PCIE D02F0/NB PCIE D02F1/
NB PCIE D02F2/NB PCIE D02F3/NB PCIE D03F0/NB PCIE D03F1/NB PCIE D03F2/NB PCIE D03F3.
Default setting is **NB PCIE D01F0**.

⌄ **Thunderbolt PCIe Cache-line Size**

Options available: 0/1/2/4/8/16/32/64/128. Default setting is **32**.

⌄ **SMI/Notify Support**

Enable/Disable SMI/Notify support feature.

Options available: Enabled/Disabled. Default setting is **Enabled**.

⌄ **SuSMI Support**

Enable/Disable SuSMI support feature.

Options available: Enabled/Disabled. Default setting is **Enabled**.

⌄ **Notify Support**

Enable/Disable Notify support feature.

Options available: Enabled/Disabled. Default setting is **Enabled**.

⌄ **Ignore Thunderbolt Option Rom**

Options available: Enabled/Disabled. Default setting is **Disabled**.

⌄ **Thunderbolt SwSMI Delay**

Configure the Thunderbolt SwSMI Delay. Press <+> / <-> keys to increase or decrease the desired values.

⌄ **TBT Device IO resource Support**

Options available: Enabled/Disabled. Default setting is **Disabled**.

⌄ **Reserved Mem per phy slot**

Press <+> / <-> keys to increase or decrease the desired values.


⌄ **Reserved PMem per phy slot**

Press <+> / <-> keys to increase or decrease the desired values.

2-2-13 SIO Configuration

Bios Setup Utility	
Advanced	
AMI SIO Driver Version : GSI0010A5.03.04 Super IO Chip Logical Device(s) Configuration ▶ [Active*] Serial Port 1 ▶ [Active*] Serial Port 2 WARNING: Logical Devices state showing at the left side of the controll, reflects current Logical Device state. Cahnges made during Setup Session will be shown after you restart the system.	View and Set Basic properties of the SIO Logical device. Like IO Base, IRQ Range, DMA Channel and Device Mode. ⇄: Select Screen ↑↓: Select Item Enter: Select +/-: Change Opt. F1: General Help F3: Previous Values F9: Optimized Defaults F10: Save & Exit ESC: Exit

Bios Setup Utility	
Advanced	
Serial Port 1 Configuration Use This Device GSI0011 [Enabled] Logical Device Settings: Current : IO=3F8h; IRQ=4; Possible: [Use Automatic Settings] WARNING: disabling SIO Logical Devices may have unwanted side effects. PROCEED WITH CAUTION.	Enable or Disable this Logical Devcie. ⇄: Select Screen ↑↓: Select Item Enter: Select +/-: Change Opt. F1: General Help F3: Previous Values F9: Optimized Defaults F10: Save & Exit ESC: Exit



🔑 AMI SIO Driver Version

Display the AMI SIO driver version information.

🔑 Super IO Chip Logical Device(s) Configuration

🔑 [*Active*] Serial Port 1/2

Press [Enter] for configuration of advanced items.

🔑 Serial Port 1 Configuration

🔑 Use This Device

When enabled allows you to configure the serial port 1 settings. When set to Disabled, displays no configuration for the serial port.

Options available: Enabled/Disabled. Default setting is **Enabled**.

🔑 Logical Device Settings:

🔑 Current:

Display the Serial Port 1 base I/O address and IRQ.

🔑 Possible:

Configure Serial Port 1 base I/O address and IRQ.

Option available:

Use Automatic Settings

IO=2F8h; IRQ=3; DMA;/

IO=3F8h; IRQ=3,4,5,7,9,10,11,12; DMA;/

IO=2F8h; IRQ=3,4,5,7,9,10,11,12; DMA;/

IO=3E8h; IRQ=3,4,5,7,9,10,11,12; DMA;/

IO=2E8h; IRQ=3,4,5,7,9,10,11,12; DMA;. Default setting is **Use Automatic Settings**.

☞ **Serial Port 2 Configuration**

☞ **Use This Device**

When enabled allows you to configure the serial port 2 settings. When set to Disabled, displays no configuration for the serial port.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ **Logical Device Settings:**

☞ **Current:**

Display the Serial Port 2 base I/O address and IRQ.

☞ **Possible:**

Configure Serial Port 2 base I/O address and IRQ.

Option available: Use Automatic Settings. Default setting is **Use Automatic Settings**.

2-2-14 iSCSI Configuration



☞ **iSCSI Initiator Name**

☞ **Add an Attempts**

Press [Enter] for configuration of advanced items.

☞ **Delete Attempts**


Press [Enter] for configuration of advanced items.

☞ **Change Attempt Order**

Press [Enter] for configuration of advanced items.

2-3 Intel RC Setup Menu



Intel RC Setup menu displays submenu options for configuring the function of North Bridge and South Bridge. Select a submenu item, then press Enter to access the related submenu screen.



RC Revision

Display Intel RC version information.

2-3-1 Processor Configuration



⌄ Processor Configuration

⌄ Pre-Socket Configuration

Press [Enter] for configuration of advanced items.

⌄ Processor Socket/Processor ID/Processor Frequency/Processor Max Ratio/ Processor Min Ratio/Microcode Revision/L1 Cache RAM/L2 Cache RAM/L3 Cache RAM/ Processor 0/1Version

Displays the technical specifications for the installed processor.

⌄ Hyper-Threading [All]

The Hyper Threading Technology allows a single processor to execute two or more separate threads concurrently. When hyper-threading is enabled, multi-threaded software applications can execute their threads, thereby improving performance.

Options available: Enabled/Disabled. Default setting is **Enabled**.

⌄ Execute Disable Bit

When enabled, the processor prevents the execution of code in data-only memory pages. This provides some protection against buffer overflow attacks.

When disabled, the processor will not restrict code execution in any memory area. This makes the processor more vulnerable to buffer overflow attacks.

Options available: Enabled/Disabled. Default setting is **Enabled**.

⌄ Enable Intel TXT Support

Enable/Disable Intel Trusted Execution Technology support function.

Options available: Enabled/Disabled. Default setting is **Disabled**.

⌄ VMX (Vanderpool Technology)

Enable/Disable Vanderpool Technology. This will take effect after rebooting the system.

Options available: Enabled/Disabled. Default setting is **Enabled**.

⌄ Enable SMX (Intel Safer Mode Extensions Technology)

Enable/Disable Intel Safer Mode Extensions (SMX) support function.

Options available: Enabled/Disabled. Default setting is **Disabled**.

⌄ Hardware Prefetcher

Select whether to enable the speculative prefetch unit of the processor.

Options available: Enabled/Disabled. Default setting is **Enabled**.

⌄ Adjacent Cache Line Prefetch

When enabled, cache lines are fetched in pairs. When disabled, only the required cache line is fetched.

Options available: Enabled/Disabled. Default setting is **Enabled**.

⌄ DCU Streamer Prefetch

Enable prefetch of next L1 Data line based upon multiple loads in same cache line.

Options available: Enabled/Disabled. Default setting is **Enabled**.

⌄ DCU IP Prefetch

Enable prefetch of next L1 Data line based upon sequential load history.

Options available: Enabled/Disabled. Default setting is **Enabled**.

⌄ DCU Mode

Configure DCU mode.

Options available: 32KB 8Way Without ECC/16KB 4Way With ECC. Default setting is **32KB 8Way Without ECC**.

☞ **Direct Cache Access (DCA)**

Options available: Auto/Enabled/Disabled. Default setting is **Auto**.

☞ **DCA Prefetch Delay**

Options available: Disabled/8/16/24/32/40/48/56/64/72/80/88/96/104/112. Default setting is **32**.

☞ **X2APIC**

Options available: Enabled/Disabled. Default setting is **Disabled**.


☞ **AES-NI**

Enable/Disable AES-NI (Intel Advanced Encryption Standard New Instructions) support function.

Options available: Enabled/Disabled. Default setting is **Enabled**.

2-3-1-1 Pre-Socket Configuration






🔑 CPU Socket 0/1 Configuration

Press [Enter] for configuration of advanced items.

🔑 Cores Enabled (for CPU socket 0/1)

Number of Cores to enable. 0 means all cores. 14 Cores is available. Press <+> and <-> keys to adjust desired values.

2-3-2 Advanced Power Management Configuration



☞ Advanced Power Management Configuration

☞ Power Technology

Option available: Disable/Energy Efficient/Custom. Default setting is **Energy Efficient**.

☞ Config TDP

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ Config TDP Level

Options available: Enabled/Disabled. Default setting is **Disabled**.

☞ CPU P State Control

Press [Enter] for configuration of advanced items.


☞ CPU C State Control

Press [Enter] for configuration of advanced items.

☞ CPU T State Control

Press [Enter] for configuration of advanced items.

2-3-2-1 CPU P State Control



☞ EIST (P-State)

Conventional Intel SpeedStep Technology switches both voltage and frequency in tandem between high and low levels in response to processor load.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ Turbo Mode

When this item is enabled, the processor will automatically ramp up the clock speed of 1-2 of its processing cores to improve its performance.

When this item is disabled, the processor will not overclock any of its core.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ P-state coordination

In HW_ALL mode, the processor hardware is responsible for coordinating the P-state among logical processors dependencies. The OS is responsible for keeping the P-state request up to date on all logical processors.

In SW_ALL mode, the OS Power Manager is responsible for coordinating the P-state among logical processors with dependencies and must initiate the transition on all of those Logical Processors.

In SW_ANY mode, the OS Power Manager is responsible for coordinating the P-state among logical processors with dependencies and may initiate the transition on any of those Logical Processors.

Options available: HW_ALL/SW_ALL/SW_ANY. Default setting is **HW_ALL**.

2-3-2-2 CPU C State Control



🔑 Package C State Limit

Configure state for the C-State package limit.

Options available: C0/C1 state/C2 state/C6(non Retention) state/C6(Retention) state.


Default setting is **C6(non Retention) state**.

🔑 CPU C3/C6 Report

Allows you to determine whether to let the CPU enter C3/C6 mode in system halt state. When enabled, the CPU core frequency and voltage will be reduced during system halt state to decrease power consumption. The C3/C6 state is a more enhanced power-saving state than C1.

Default setting for C3 is **Disabled**; default setting for C6 is **Enabled**.

2-3-2-3 CPU T State Control



ACPI T-States

Enable/Disable CPU throttling by OS. Throttling reduces power consumption.

Options available: Enabled/Disabled. Default setting is **Enabled**.

2-3-3 Common RefCode Configuration



Common RefCode Configuration



Isoc Mode


Options available: Auto/Enabled/Disabled. Default setting is **Auto**.

Numa (Non-Uniform Memory Access)

Options available: Enabled/Disabled. Default setting is **Enabled**.

2-3-4 QPI Configuration





🔑 QPI General Configuration

Press [Enter] for configuration of advanced items.

🔑 QPI Status

Press [Enter] to view QPI status.


🔑 Link Speed Mode

Options available: Slow/Fast. Default setting is **Fast**.

🔑 Link Frequency Select

Options available: 6.4GB/s/8.0GB/s/9.6GB/s/Auto/Auto Limited. Default setting is **Auto**.

2-3-5 Memory Configuration



☞ Integrated Memory Controller (iMC)

☞ Enforce POR

Enable to enforce POR restrictions for DDR4 frequency and voltage programming.

Options available: Enforce POR/Disabled/Enforce Stretch Goals. Default setting is **Enforce POR**.

☞ Memory Frequency

Configure memory frequency.

Options available: Auto/1333/1400/1600/1800/1867/2000/2133.

Default setting is **Auto**.

☞ ECC Support

Options available: Auto/Disabled/Enabled. Default setting is **Auto**.

☞ Rank Margin Tool

Options available: Auto/Disabled/Enabled. Default setting is **Auto**.

☞ RMT Pattern Length

Display RMT Pattern Length.

☞ SPD Write Lock

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ Memory Topology

Press [Enter] for configuration of advanced items.

☞ Memory Thermal

Press [Enter] for configuration of advanced items.


☞ **Memory Map**

Press [Enter] for configuration of advanced items.

☞ **Memory RAS Configuration**

Press [Enter] for configuration of advanced items.

2-3-5-1 Memory Topology



2-3-5-2 Memory Thermal



➤ Set Throttling Mode


Configure Thermal Throttling Mode. Select OLTT or CLTT mode.

Options available: Disabled/CLTT . Default setting is **CLTT**.

➤ MEMHOT Throttling Mode

Options available: Disabled/Output-only/Input-only. Default setting is **Input-only**.

2-3-5-3 Memory Map



☞ **Socket Interleave Below 4GB**

Splits the 0-4GB address space between two sockets, so that both sockets get a chunk of local memory below 4GB.

Options available: Disabled/Enabled. Default setting is **Disabled**.

☞ **Channel Interleaving**

Options available: Auto/1-way Interleave/2-way Interleave/3-way Interleave/4-way Interleave.


Default setting is **Auto**.

☞ **Rank Interleaving**

Options available: Auto/1-way Interleave/2-way Interleave/4-way Interleave/8-way Interleave.

Default setting is **Auto**.

2-3-5-4 Memory RAS Configuration



☞ RAS Mode

Enable/Disable RAS modes. Enabling Sparing and Mirroring is not supported. When this item is set to enabled, Sparing will be selected.

Options available: Disable/Mirror/Lockstep Mode. Default setting is **Disabled**.

☞ Lockstep x4 DIMMs

Options available: Auto/Disabled/Enabled. Default setting is **Auto**.


☞ Memory Rank Sparing

Options available: Disabled/Enabled. Default setting is **Disabled**.

☞ Correctable Error Threshold

Press <+> / <-> keys to increase or decrease the desired values.

2-3-6 IIO Configuration



🔑 IIO Configuration

🔑 EV DFX Features

Set this option to allow DFX Lock Bits to remain clear.

Options available: Enabled/Disabled. Default setting is **Disabled**.

🔑 IOAT Configuration

Press [Enter] for configuration of advanced items.

🔑 Intel VT for Directed I/O (VT-d)

Press [Enter] for configuration of advanced items.

2-3-6-1 IOAT Configuration



IOAT Configuration

Enable IOAT

Control to enable/disable IOAT (Intel I/O Acceleration Technology) device.
Options available: Enabled/Disabled. Default setting is **Disabled**.

No Snoop

Enable/Disable PCI Express Device No Snoop option.
Options available: Enabled/Disabled. Default setting is **Disabled**.

2-3-6-2 Intel VT for Directed I/O (VT-d)



☞ **Intel VT for Directed I/O (VT-d)**

☞ **VT-d Azalea VcP Optimizations**

Enable/Disable Azalea VcP optimizations.

Options available: Enabled/Disabled. Default setting is **Disabled**.

☞ **Intel VT for Directed I/O (VT-d)**

Enable/Disable Intel VT for Directed I/O (VT-d) support function.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ **Interrupt Remapping**

Enable/Disable interrupt remapping support function.

Options available: Enabled/Disabled. Default setting is **Enabled**.


☞ **Coherency Support (Non-Isch)**

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ **Coherency Support (Isch)**

Options available: Enabled/Disabled. Default setting is **Enabled**.

2-3-7 PCH Configuration



🔗 PCH Configuration

🔗 PCH Devices

Press [Enter] for configuration of advanced items.

🔗 PCH sSATA Configuration

Press [Enter] for configuration of advanced items.

🔗 PCH SATA Configuration

Press [Enter] for configuration of advanced items.


🔗 USB Configuration

Press [Enter] for configuration of advanced items.

🔗 Azalia Configuration

Press [Enter] for configuration of advanced items.

2-3-7-1 PCH Devices



PCH CRID

Enable/Disable Intel Compatible Revision ID.

Options available: Enabled/Disabled. Default setting is **Disabled**.

2-3-7-2 PCH sSATA Configuration

IntelRCSetup		Bios Setup Utility
PCH sSATA Configuration		Identify the SATA port is connected to Solid State Drive or Hard Disk Drive
sSATA Controller	[Enabled]	
Configure sSATA as	[RAID]	++: Select Screen F1: Select Item Enter: Select +/-: Change Opt. F1: General Help F8: Previous Values F9: Optimized Defaults F10: Save & Exit ESC: Exit
SATA test mode	[Disabled]	
sSATA RSTe Boot Info	[Enabled]	
▶ SATA Mode options		
Support Aggressive Link Power Mana	[Enabled]	
Alternate Device ID on RAID	[Disabled]	
sSATA Port 0		
Port 0	[Enabled]	
Hot Plug	[Disabled]	
Configured as eSATA	Hot Plug supported	
Spin Up Device	[Disabled]	
sSATA Device Type	[Hard Disk Drive]	
sSATA Port 1		
Port 1	[Not Installed]	
Hot Plug	[Enabled]	
Configured as eSATA	Hot Plug supported	
Spin Up Device	[Disabled]	
sSATA Device Type	[Hard Disk Drive]	
sSATA Port 2		
Port 2	[Not Installed]	
Hot Plug	[Enabled]	
Hot Plug	[Disabled]	

IntelRCSetup		Bios Setup Utility
sSATA Port 0		Identify the SATA port is connected to Solid State Drive or Hard Disk Drive
Port 0	[Not Installed]	
Hot Plug	[Enabled]	
Configured as eSATA	Hot Plug supported	
Spin Up Device	[Disabled]	
sSATA Device Type	[Hard Disk Drive]	
sSATA Port 1		
Port 1	[Not Installed]	
Hot Plug	[Enabled]	
Configured as eSATA	Hot Plug supported	
Spin Up Device	[Disabled]	
sSATA Device Type	[Hard Disk Drive]	
sSATA Port 2		
Port 2	[Not Installed]	
Hot Plug	[Enabled]	
Configured as eSATA	Hot Plug supported	
Spin Up Device	[Disabled]	
sSATA Device Type	[Hard Disk Drive]	
sSATA Port 3		
Port 3	[Not Installed]	
Hot Plug	[Enabled]	
Configured as eSATA	Hot Plug supported	
Spin Up Device	[Disabled]	
sSATA Device Type	[Hard Disk Drive]	

When SATA Type is set to IDE



☞ PCH sSATA Configuration

☞ sSATA Controller(s)

Enable/Disable sSATA controller.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ Configure sSATA as

Configure on chip SATA type.

IDE Mode: When set to IDE, the SATA controller disables its RAID and AHCI functions and runs in the IDE emulation mode. This is not allowed to access RAID setup utility.

RAID Mode: When set to RAID, the SATA controller enables both its RAID and AHCI functions. You will be allowed access to the RAID setup utility at boot time.

AHCI Mode: When set to AHCI, the SATA controller enables its AHCI functionality. Then the RAID function is disabled and cannot access the RAID setup utility at boot time.

Options available: IDE/RAID/AHCI/Disabled. Default setting is **AHCI**.

☞ SATA Test Mode

Enable/Disable SATA Test Mode.

Options available: Enabled/Disabled. Default setting is **Disabled**.

☞ SATA Mode options^(Note)

Press [Enter] for configuration of advanced items.

☞ Support Aggressive Link Power Mana^(Note)

Enable PCH to aggressively enter link power state.

Options available: Enabled/Disabled. Default setting is **Enabled**.

(Note) Only Supported When HDD is in **AHCI** or **RAID** Mode.

☞ **Alternate Device ID on RAID**

Enable /Disable Alternate Device ID on RAID mode.

Options available: Enabled/Disabled. Default setting is **Disabled**.

Please note that this option appears when HDD is in RAID Mode.

☞ **sSATA Port 0/1/2/3**

The category identifies sSATA type of hard disk that are installed in the computer.

System will automatically detect HDD type.

☞ **Port 0/1/2/3**

Enable/Disable Port 0/1/2/3 device.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ **Hot Plug (for Port 0/1/2/3)^(Note)**

Enable/Disable HDD Hot-Plug function.

Options available: Enabled/Disabled. Default setting is **Disabled**.

☞ **Configured as eSATA^(Note)**

Display Hot-Plug supported information.

☞ **Spin Up Device (for Port 0/1/2/3)^(Note)**

On an edge detect from 0 to 1, the PCH starts a COM reset initialization to the device.

Options available: Enabled/Disabled. Default setting is **Disabled**.

☞ **sSATA Device Type**

Select sSATA device type.

Options available: Hard Disk Drive/Solid State Drive. Default setting is **Hard Disk Drive**.

(Note) Only Supported When HDD is in **AHCI** or **RAID** Mode.


2-3-7-2-1 SATA Mode Options
When SATA Type is set to IDE/AHCI Mode



 SATA LED locate

When this option is enabled, LED/SGPIO hardware is attached.
Options available: Enabled/Disabled. Default setting is **Enabled**.

When SATA Type is set to RAID Mode



☞ SATA LED locate

When this option is enabled, LED/SGPIO hardware is attached.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ Intel Rapid Recovery Technology

Enable/Disable Intel Rapid Recovery Technology support function.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ RAID Option ROM UI banner

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ IRRT Only on ESATA

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ Smart Response Technology

Enable/Disable Intel Smart Response Technology support function.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ RAID OROM prompt delay


Options available: 2 Seconds/4 Seconds/6 Seconds/8 Seconds. Default setting is **2 Seconds**.

2-3-7-3 PCH SATA Configuration

Bios Setup Utility	
IntelRCSetup	
PCH SATA Configuration	
SATA Controller	[Enabled]
Configure SATA as	[RAID]
SATA test mode	[Disabled]
SATA RSTe Boot Info	[Enabled]
▶ SATA Mode options	
Support Aggressive Link Power Mana	[Enabled]
Alternate Device ID on RAID	[Disabled]
SATA Port 0	
Port 0	[Not Installed]
Hot Plug	[Enabled]
Configured as eSATA	[Disabled]
Spin Up Device	Hot Plug supported
SATA Device Type	[Hard Disk Drive]
SATA Port 1	
Port 1	[Not Installed]
Hot Plug	[Enabled]
Configured as eSATA	[Disabled]
Spin Up Device	Hot Plug supported
SATA Device Type	[Hard Disk Drive]
SATA Port 2	
Port 2	[Not Installed]
Hot Plug	[Enabled]
▲ Identify the SATA port is connected to Solid State Drive or Hard Disk Drive ++: Select Screen T1: Select Item Enter: Select +/-: Change Opt. F1: General Help F3: Previous Values F9: Optimized Defaults F10: Save & Exit ESC: Exit ▼	

Bios Setup Utility	
IntelRCSetup	
SATA Device Type	
SATA Port 2	[Hard Disk Drive]
Port 2	[Not Installed]
Hot Plug	[Enabled]
Configured as eSATA	[Disabled]
Spin Up Device	Hot Plug supported
SATA Device Type	[Hard Disk Drive]
SATA Port 3	
Port 3	[Not Installed]
Hot Plug	[Enabled]
Configured as eSATA	[Disabled]
Spin Up Device	Hot Plug supported
SATA Device Type	[Hard Disk Drive]
SATA Port 4	
Port 4	[Not Installed]
Hot Plug	[Enabled]
Configured as eSATA	[Disabled]
Spin Up Device	Hot Plug supported
SATA Device Type	[Hard Disk Drive]
SATA Port 5	
Port 5	[Not Installed]
Hot Plug	[Enabled]
Configured as eSATA	[Disabled]
Spin Up Device	Hot Plug supported
SATA Device Type	[Hard Disk Drive]
▲ Identify the SATA port is connected to Solid State Drive or Hard Disk Drive ++: Select Screen T1: Select Item Enter: Select +/-: Change Opt. F1: General Help F3: Previous Values F9: Optimized Defaults F10: Save & Exit ESC: Exit ▼	

When SATA Type is set to IDE



☞ PCH SATA Configuration

☞ SATA Controller(s)

Enable/Disable sSATA controller.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ Configure sSATA as

Configure on chip SATA type.

IDE Mode: When set to IDE, the SATA controller disables its RAID and AHCI functions and runs in the IDE emulation mode. This is not allowed to access RAID setup utility.

RAID Mode: When set to RAID, the SATA controller enables both its RAID and AHCI functions. You will be allowed access to the RAID setup utility at boot time.

AHCI Mode: When set to AHCI, the SATA controller enables its AHCI functionality. Then the RAID function is disabled and cannot be accessed in the RAID setup utility at boot time.

Options available: IDE/RAID/AHCI/Disabled. Default setting is **AHCI**.

☞ SATA Test Mode

Enable/Disable SATA Test Mode.

Options available: Enabled/Disabled. Default setting is **Disabled**.

☞ SATA RSTe Boot Info^(Note 1)

Enable/Disable SATA RSTe Boot Information.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ SATA Mode options^(Note 2)

Press [Enter] for configuration of advanced items.

(Note 1) Only Supported When HDD is in **RAID Mode**.

(Note 2) Only Supported When HDD is in **AHCI** or **RAID Mode**.

☞ **Support Aggressive Link Power Mana^(Note)**

Enable PCH to aggressively enter link power state.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ **Alternate Device ID on RAID**

Enable /Disable Alternate Device ID on RAID mode.

Options available: Enabled/Disabled. Default setting is **Disabled**.

Please note that this option appears when HDD is in RAID Mode.

☞ **sSATA Port 0/1/2/3/4/5**

The category identifies sSATA type of hard disk that are installed in the computer.

System will automatically detect HDD type.

☞ **Port 0/1/2/3/4/5**

Enable/Disable Port 0/1/2/3 device.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ **Hot Plug (for Port 0/1/2/3/4/5)^(Note)**

Enable/Disable HDD Hot-Plug function.

Options available: Enabled/Disabled. Default setting is **Disabled**.

☞ **Configured as eSATA^(Note)**

Display Hot-Plug supported information.

☞ **Spin Up Device (for Port 0/1/2/3/4/5)^(Note)**

On an edge detect from 0 to 1, the PCH starts a COM reset initialization to the device.

Options available: Enabled/Disabled. Default setting is **Disabled**.

☞ **sSATA Device Type**

Select sSATA device type.

Options available: Hard Disk Drive/Solid State Drive. Default setting is **Hard Disk Drive**.

(Note) Only Supported When HDD is in **AHCI** or **RAID** Mode.

2-3-7-3-1 SATA Mode Options

When SATA Type is set to IDE/AHCI Mode




SATA LED locate

When this option is enabled, LED/SGPIO hardware is attached.

Options available: Enabled/Disabled. Default setting is **Enabled**.

When SATA Type is set to RAID Mode



☞ SATA LED locate

When this option is enabled, LED/SGPIO hardware is attached.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ Intel Rapid Recovery Technology

Enable/Disable Intel Rapid Recovery Technology support function.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ RAID Option ROM UI banner

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ Smart Response Technology


Enable/Disable Intel Smart Response Technology support function.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ RAID OROM prompt delay

Options available: 2 Seconds/4 Seconds/6 Seconds/8 Seconds. Default setting is **2 Seconds**.

2-3-7-4 USB Configuration



USB Precondition

Precondition work on USB host controller and root ports for faster enumeration.

Options available: Enabled/Disabled. Default setting is **Disabled**.

xHCI Mode

Enable/Disable xHCI (USB 3.0) support function.

Options available: Smart Auto/Enabled/Disabled. Default setting is **Smart Auto**.

2-3-7-5 Azalia Configuration



Azalia

Enable/Disable onboard audio device.

Options available: Enabled/Disabled. Default setting is **Enabled**.

2-3-8 Miscellaneous Configuration




☞ Miscellaneous Configuration

☞ Active Video

Select active Video type.

Options available: Onboard Device/Offboard Device. Default setting is **Offboard Device**.

2-3-9 Server ME Configuration



☞ General ME Configuration

☞ Operational Firmware Version

Display Operational Firmware Version information.

☞ Recovery Firmware Version

Display Recovery Firmware Version information.

☞ ME Firmware Features

Display ME Firmware features information.

☞ ME Firmware Status #1/#2

Display ME Firmware status information.

☞ Current State (for ME Firmware)

Display ME Firmware current status information.

☞ Error Code (for ME Firmware)

Display ME Firmware status error code.

☞ MCTP Bus Owner

Configure MCTP Bus Owner.

2-3-10 Runtime Error Logging



☞ Runtime Error Logging

☞ System Errors

Enable/Disable system error logging function.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ S/W Error Injection Support

Enable/Disable software injection error logging function.

Options available: Enabled/Disabled. Default setting is **Disabled**.

☞ Whea Settings

Press [Enter] for configuration of advanced items.

☞ Memory Error Enabling

Press [Enter] for configuration of advanced items.

☞ PCI/PCI Error Enabling

Press [Enter] for configuration of advanced items.

2-3-10-1 Whea Setting




 WHEA Support (Windows Hardware Error Architecture)

Enable/Disable WHEA Support.

Options available: Enabled/Disabled. Default setting is **Enabled**.

2-3-10-2 Memory Error Enabling



☞ Memory Error Enabling

☞ Un-Correctable Errors disable Memory

Options available: Enabled/Disabled. Default setting is **Disabled**.

☞ Memory corrected Errors enabling

Options available: Enabled/Disabled. Default setting is **Disabled**.

2-3-10-3 PCI/PCI Error Enabling



PCI-Ex Error Enable

Options available: Yes/No. Default setting is **No**.

2-4 Event Logs Menu




☞ **Change Smbios Event Log Settings**

Press [Enter] for configuration of advanced items.

☞ **View Smbios Event Log**

Press [Enter] to view event logs.

2-4-1 Change Smbios Event Log Settings



☞ Enabling/Disabling Options

☞ Smbios Event Log

Choose options to Enable/Disable logging of System boot event.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ Erasing Settings

☞ Erasing Event Log

Choose options for erasing Smbios Event Log Erasing is done prior to any logging activation during reset.

Options available: No/Yes, On next reset/Yes, On every reset. Default setting is **No**.

☞ When Log is Full

Choose options for reactions to a full Smbios Event Log.

Options available: Do Nothing/Erase Immediately. Default setting is **Do Nothing**.

☞ Smbios Event Log Standard Settings

☞ Log System Boot Event

Choose options to Enable/Disable logging of System boot event.

Options available: Enabled/Disabled. Default setting is **Enabled**.

☞ MECI

Multiple Event Count Increment: The number of occurrences of a duplicate event that must pass before the multi-event counter associated with the log entry is updated, specified as numeric value in the range 1 to 33. Press <+> / <-> keys to increase or decrease the desired values.

☞ METW

Multiple Event Time Window: The number of minutes which must pass between duplicate log entries which utilize a multiple-event counter. The value ranges from 0 to 99 minutes. Press <+> / <-> keys to increase or decrease the desired values.


2-4-2 View Smbios Event Log

The Smbios Event Log is a display page of Smbios Event Log information. Items on this window are non-configurable. Press Enter to View Smbios Event Log



2-5 Security Menu

The Security menu allows you to safeguard and protect the system from unauthorized use by setting up access passwords.



⏏ Administrator Password

Press Enter to configure the Administrator password.

⏏ User Password


Press Enter to configure the user password.

⏏ Secure Boot menu

Press [Enter] for configuration of advanced items.

2-5-1 Secure Boot menu

The Secure Boot Menu is applicable when your device is installed the Windows® 8 operatin system.



☞ Secure Mode

Display the System secure mode state.

☞ Secure Boot

Display the status of Secure Boot.

☞ Secure Boot

Enable/Disable Secure Boot function.

Options available: Enabled/Disabled. Default setting is **Disabled**.

☞ Secure Boot Mode

Secure Boot requires all the applications that are running during the booting process to be pre-signed with valid digital certificates. This way, the system knows all the files being loaded before Windows 8 loads and gets to the login screen have not been tampered with.

When set to Standard, it will automatically load the Secure Boot keys from the BIOS databases.

When set to Custom, you can customize the Secure Boot settings and manually load its keys from the BIOS database.


Options available: Standard/Custom. Default setting is **Custom**.

☞ Key Management^(Note)

Press [Enter] for configuration of advanced items.

(Note) Advanced items prompt when this item is set to **Custom**.

2-5-1-1 Key Management



☞ Default Key Provisioning

Force the system to Setup Mode. This will clear all Secure Boot Variables such as Platform Key (PK), Key-exchange Key (KEK), Authorized Signature Database (db), and Forbidden Signatures Database (dbx).

Options available: Enabled/Disabled. Default setting is **Disabled**.

☞ Enroll All Factory Default Keys

Press [Enter] to install all factory default keys.

☞ Save All Secure Boot Variables

Press [Enter] to save all Secure Boot Variables.

☞ Platform Key (PK)

Display the status of Platform Key.

☞ Delete the PK

Press [Enter] to delete the existed PK. Once the PK is deleted, all the system's Secure Boot keys will not be activated.

☞ Set new PK File

Press [Enter] to configure a new PK.

☞ Key Exchange Key Database (KEK)

Display the status of Platform Key.

☞ Delete KEK

Press [Enter] to delete the KEK from your system.

☞ Set new KEK

Press [Enter] to configure a new KEK.

☞ **Append Var to KEK**

Press [Enter] to load additional KEK from a storage devices for an additional db and dbx management.

☞ **Authorized Signature Database (DB)**

Display the status of Authorized Signature Database.

☞ **Delete DB**

Press [Enter] to delete the db from your system.

☞ **Set new DB**

Press [Enter] to configure a new db.

☞ **Append aVar to DB**

Press [Enter] to load additional db from a storage devices.

☞ **Forbidden Signature Database (DBX)**

Display the status of Forbidden Signature Database.

☞ **Delete the DBX**

Press [Enter] to delete the dbx from your system.

☞ **Set DBX from File**


Press [Enter] to configure a new dbx.

☞ **Append Var to DBX**

Press [Enter] to load additional db from a storage devices.

2-6 Boot Menu

The Boot menu allows you to set the drive priority during system boot-up. BIOS setup will display an error message if the legacy drive(s) specified is not bootable.



Boot Configuration

Setup Prompt Timeout

Number of seconds to wait for setup activation key. 65535(0xFFFF) means indefinite waiting."

Press the numeric keys to input the desired value.

Bootup NumLock State

Enable or Disable Bootup NumLock function.

Options available: On/Off. Default setting is **On**.

Quiet Boot

Enables or disables showing the logo during POST.

Options available: Enabled/Disabled. Default setting is **Enabled**.

Boot Option Priorities

Boot Option #1/#2/#3#4

Press Enter to configure the boot priority.

By default, the server searches for boot devices in the following sequence:

1. UEFI device.
2. Hard drive.
3. Network device.
4. USB device

☞ **Network Device BBS Priorities**


Press Enter to configure the boot priority.

☞ **Hard Drive BBS Priorities**

Press Enter to configure the boot priority.

2-7 Save & Exit Menu

The Exit menu displays the various options to quit from the BIOS setup. Highlight any of the exit options then press **Enter**.



☞ Save Changes and Exit

Saves changes made and close the BIOS setup.

Options available: Yes/No.

☞ Discard Changes and Exit

Discards changes made and exit the BIOS setup.

Options available: Yes/No.

☞ Save Options

☞ Save Changes

Saves changes made in the BIOS setup.

Options available: Yes/No.

☞ Discard Changes

Discards changes made and close the BIOS setup.

Options available: Yes/No.

☞ Restore Defaults

Loads the default settings for all BIOS setup parameters. Setup Defaults are quite demanding in terms of resources consumption. If you are using low-speed memory chips or other kinds of low-performance components and you choose to load these settings, the system might not function properly.

Options available: Yes/No.

☞ **Boot Override**

Press Enter to configure the device as the boot-up drive.

☞ **UEFI: Built-in in EFI Shell**

Press <Enter> on this item to Launch EFI Shell from filesystem device.

2-8 BIOS POST Codes

PEI_CORE_STARTED	0x10
PEI_CAR_CPU_INIT	0x11
// reserved for CPU 0x12 - 0x14	
PEI_CAR_NB_INIT	0x15
// reserved for NB 0x16 - 0x18	
PEI_CAR_SB_INIT	0x19
// reserved for SB 0x1A - 0x1C	
PEI_MEMORY_SPD_READ	0x1D
PEI_MEMORY_PRESENCE_DETECT	0x1E
PEI_MEMORY_TIMING	0x1F
PEI_MEMORY_CONFIGURING	0x20
PEI_MEMORY_INIT	0x21
// reserved for OEM use: 0x22 - 0x2F	
// reserved for AML use: 0x30	
PEI_MEMORY_INSTALLED	0x31
PEI_CPU_INIT	0x32
PEI_CPU_CACHE_INIT	0x33
PEI_CPU_BSP_SELECT	0x34
PEI_CPU_AP_INIT	0x35
PEI_CPU_SMM_INIT	0x36
PEI_MEM_NB_INIT	0x37
// reserved for NB 0x38 - 0x3A	
PEI_MEM_SB_INIT	0x3B
// reserved for SB 0x3C - 0x3E	
// reserved for OEM use: 0x3F - 0x4E	
PEI_DXE_IPL_STARTED	0x4F
//Recovery	
PEI_RECOVERY_AUTO	0xF0
PEI_RECOVERY_USER	0xF1
PEI_RECOVERY_STARTED	0xF2
PEI_RECOVERY_CAPSULE_FOUND	0xF3
PEI_RECOVERY_CAPSULE_LOADED	0xF4
//S3	
PEI_S3_STARTED	0xE0
PEI_S3_BOOT_SCRIPT	0xE1
PEI_S3_VIDEO_REPOST	0xE2
PEI_S3_OS_WAKE	0xE3
//DXE_STATUS_CODE	
DXE_CORE_STARTED	0x60
DXE_NVRAM_INIT	0x61
DXE_SBRUN_INIT	0x62

DXE_CPU_INIT	0x63
//reserved for CPU 0x64 - 0x67	
DXE_NB_HB_INIT	0x68
DXE_NB_INIT	0x69
DXE_NB_SMM_INIT	0x6A
//reserved for NB 0x6B - 0x6F	
DXE_SB_INIT	0x70
DXE_SB_SMM_INIT	0x71
DXE_SB_DEVICES_INIT	0x72
//reserved for SB 0x73 - 0x77	
DXE_ACPI_INIT	0x78
DXE_CSM_INIT	0x79
//reserved for AMI use: 0x7A - 0x7F	
//reserved for OEM use: 0x80 - 0x8F	
DXE_BDS_STARTED	0x90
DXE_BDS_CONNECT_DRIVERS	0x91
DXE_PCI_BUS_BEGIN	0x92
DXE_PCI_BUS_HPC_INIT	0x93
DXE_PCI_BUS_ENUM	0x94
DXE_PCI_BUS_REQUEST_RESOURCES	0x95
DXE_PCI_BUS_ASSIGN_RESOURCES	0x96
DXE_CON_OUT_CONNECT	0x97
DXE_CON_IN_CONNECT	0x98
DXE_SIO_INIT	0x99
DXE_USB_BEGIN	0x9A
DXE_USB_RESET	0x9B
DXE_USB_DETECT	0x9C
DXE_USB_ENABLE	0x9D
//reserved for AMI use: 0x9E - 0x9F	
//reserved for AML use: 0xA0	
DXE_IDE_BEGIN	0xA1
DXE_IDE_RESET	0xA2
DXE_IDE_DETECT	0xA3
DXE_IDE_ENABLE	0xA4
DXE_SCSI_BEGIN	0xA5
DXE_SCSI_RESET	0xA6
DXE_SCSI_DETECT	0xA7
DXE_SCSI_ENABLE	0xA8
DXE_SETUP_VERIFYING_PASSWORD	0xA9
//reserved for AML use: 0xAA	
DXE_SETUP_START	0xAB
DXE_SETUP_INPUT_WAIT	0xAC

DXE_READY_TO_BOOT	0xAD
DXE_LEGACY_BOOT	0xAE
DXE_EXIT_BOOT_SERVICES	0xAF
RT_SET_VIRTUAL_ADDRESS_MAP_BEGIN	0xB0
RT_SET_VIRTUAL_ADDRESS_MAP_END	0xB1
DXE_LEGACY_OPROM_INIT	0xB2
DXE_RESET_SYSTEM	0xB3
DXE_USB_HOTPLUG	0xB4
DXE_PCI_BUS_HOTPLUG	0xB5
DXE_NVRAM_CLEANUP	0xB6
DXE_CONFIGURATION_RESET	0xB7
//reserved for AMI use: 0xB8 - 0xBF	
//reserved for OEM use: 0xC0 - 0xCF	
//PEI_STATUS_CODE	
//Errors	
//Regular boot	
PEI_MEMORY_INVALID_TYPE	0x50
PEI_MEMORY_INVALID_SPEED	0x50
PEI_MEMORY_SPD_FAIL	0x51
PEI_MEMORY_INVALID_SIZE	0x52
PEI_MEMORY_MISMATCH	0x52
PEI_MEMORY_NOT_DETECTED	0x53
PEI_MEMORY_NONE_USEFUL	0x53
PEI_MEMORY_ERROR	0x54
PEI_MEMORY_NOT_INSTALLED	0x55
PEI_CPU_INVALID_TYPE	0x56
PEI_CPU_INVALID_SPEED	0x56
PEI_CPU_MISMATCH	0x57
PEI_CPU_SELF_TEST_FAILED	0x58
PEI_CPU_CACHE_ERROR	0x58
PEI_CPU_MICROCODE_UPDATE_FAILED	0x59
PEI_CPU_NO_MICROCODE	0x59
PEI_CPU_INTERNAL_ERROR	0x5A
PEI_CPU_ERROR	0x5A
PEI_RESET_NOT_AVAILABLE	0x5B
//reserved for AMI use: 0x5C - 0x5F	
//Recovery	
PEI_RECOVERY_PPI_NOT_FOUND	0xF8
PEI_RECOVERY_NO_CAPSULE	0xF9
PEI_RECOVERY_INVALID_CAPSULE	0xFA
//reserved for AMI use: 0xFB - 0xFF	
//S3 Resume	

PEI_MEMORY_S3_RESUME_FAILED	0xE8
PEI_S3_RESUME_PPI_NOT_FOUND	0xE9
PEI_S3_BOOT_SCRIPT_ERROR	0xEA
PEI_S3_OS_WAKE_ERROR	0xEB
//reserved for AMI use: 0xEC - 0xEF	
// DXE_STATUS_CODE	
DXE_CPU_ERROR	0xD0
DXE_NB_ERROR	0xD1
DXE_SB_ERROR	0xD2
DXE_ARCH_PROTOCOL_NOT_AVAILABLE	0xD3
DXE_PCI_BUS_OUT_OF_RESOURCES	0xD4
DXE_LEGACY_OPROM_NO_SPACE	0xD5
DXE_NO_CON_OUT	0xD6
DXE_NO_CON_IN	0xD7
DXE_INVALID_PASSWORD	0xD8
DXE_BOOT_OPTION_LOAD_ERROR	0xD9
DXE_BOOT_OPTION_FAILED	0xDA
DXE_FLASH_UPDATE_FAILED	0xDB
DXE_RESET_NOT_AVAILABLE	0xDC
//reserved for AMI use: 0xDE - 0xDF	

2-9 BIOS POST Beep code

2-9-1 PEI Beep Codes

# of Beeps	Description
1	Memory not Installed.
1	Memory was installed twice (InstallPeiMemory routine in PEI Core called twice)
2	Recovery started
3	DXE IPL was not found
3	DXE Core Firmware Volume was not found
4	Recovery failed
4	S3 Resume failed
7	Reset PPI is not available

2-9-2 DEX Beep Codes


# of Beeps	Description
1	Invalid password
4	Some of the Architectural Protocols are not available
5	No Console Output Devices are found
5	No Console Input Devices are found
6	Flash update is failed
7	Reset protocol is not available

2-10 BIOS Recovery Instruction


The system has an embedded recovery technique. In the event that the BIOS becomes corrupt the boot block can be used to restore the BIOS to a working state. To restore your BIOS, please follow the instructions listed below:

Recovery Instruction:

1. Change xxx.ROM to amiboot.rom.
2. Copy amiboot.rom and AFUDOS.exe to USB diskette.
3. Setting BIOS Recovery jump to enabled status.



4. Boot into BIOS recovery.
5. Run Proceed with flash update.
6. BIOS update.



Chapter 3 Appendix

3-1 Regulatory Statements

Regulatory Notices

This document must not be copied without our written permission, and the contents there of must not be imparted to a third party nor be used for any unauthorized purpose. Contravention will be prosecuted. We believe that the information contained herein was accurate in all respects at the time of printing. GIGABYTE cannot, however, assume any responsibility for errors or omissions in this text. Also note that the information in this document is subject to change without notice and should not be construed as a commitment by GIGABYTE.

Our Commitment to Preserving the Environment

In addition to high-efficiency performance, all GIGABYTE motherboards fulfill European Union regulations for RoHS (Restriction of Certain Hazardous Substances in Electrical and Electronic Equipment) and WEEE (Waste Electrical and Electronic Equipment) environmental directives, as well as most major worldwide safety requirements. To prevent releases of harmful substances into the environment and to maximize the use of our natural resources, GIGABYTE provides the following information on how you can responsibly recycle or reuse most of the materials in your "end of life" product.

Restriction of Hazardous Substances (RoHS) Directive Statement

GIGABYTE products have not intended to add and safe from hazardous substances (Cd, Pb, Hg, Cr+6, PBDE and PBB). The parts and components have been carefully selected to meet RoHS requirement. Moreover, we at GIGABYTE are continuing our efforts to develop products that do not use internationally banned toxic chemicals.

Waste Electrical & Electronic Equipment (WEEE) Directive Statement

GIGABYTE will fulfill the national laws as interpreted from the 2002/96/EC WEEE (Waste Electrical and Electronic Equipment) directive. The WEEE Directive specifies the treatment, collection, recycling and disposal of electric and electronic devices and their components. Under the Directive, used equipment must be marked, collected separately, and disposed of properly.

WEEE Symbol Statement



The symbol shown below is on the product or on its packaging, which indicates that this product must not be disposed of with other waste. Instead, the device should be taken to the waste collection centers for activation of the treatment, collection, recycling and disposal procedure.

The separate collection and recycling of your waste equipment at the time of disposal will help to conserve natural resources and ensure that it is recycled in a manner that protects human health and the environment. For more information about where you can drop off your waste equipment for recycling, please contact your local government office, your household waste disposal service or where you purchased the product for details of environmentally safe recycling.

- ♦ When your electrical or electronic equipment is no longer useful to you, "take it back" to your local or regional waste collection administration for recycling.
- ♦ If you need further assistance in recycling, reusing in your "end of life" product, you may contact us at the Customer Care number listed in your product's user's manual and we will be glad to help you with your effort.

Finally, we suggest that you practice other environmentally friendly actions by understanding and using the energy-saving features of this product (where applicable), recycling the inner and outer packaging (including shipping containers) this product was delivered in, and by disposing of or recycling used batteries properly. With your help, we can reduce the amount of natural resources needed to produce electrical and electronic equipment, minimize the use of landfills for the disposal of "end of life" products, and generally improve our quality of life by ensuring that potentially hazardous substances are not released into the environment and are disposed of properly.