
#### 4CH NVR with PoE Switch **SRN-472S**





		-	
111	mo	ncio	nc
<b>U</b>	ше	nsio	115



Unit : mm (inch)

	1	
DISPLAY	Inputs	Up to 4CH
Video	Resolution	CIF ~ 5M
	Protocols	Samsung, ONVIF
P	Local Display	HDMI / VGA
Live	Multi Screen Display	[Local monitor] 1 / 4 / Auto sequence, [Web] 1 / 4 / Auto sequence
PERFORMANCE	1	
Operating System		
	Compression	H.264, MJPEG
	Recording Bandwidth Resolution	32Mbps (2M 4CH real-time recording) CIF ~ 5M
Recording	Mode	Normal, Scheduled, Event (Pre / Post)
	Event Trigger	Alarm input(4), Video loss, Camera event (Sensor, MD, Video analytics)
	Event Action	E-mail, PTZ preset, Alarm out, Buzzer, Monitor out
	Playback Bandwidth	32Mbps (4CH simultaneously)
Search &	Mode	Date & Time (Calendar) / Event log list
Playback	Simultaneous Playback	[Local monitor] Up to 4CH, [Web, CMS] Up to 4CH
	Resolution	CIF ~ 5M
	Playback Control Built-in	Fast forward / backward, Move one step up / down 1ea
Storage	Internal	2ea (Fixed)
	Capacity	Internal max. 8TB
	File Back up	[USB] : BU/Exe, [Web, CMS] : JPEG, AVI
Back up	Function	Single channel play, Date-time/title display
Sensor	Input / Output	4/3 (NO/NC selectable)
	Input	4CH (Network)
Audio	Compression	G.711, G.726
NETWORK	Audio Communication	2-way
		TCP/IP, UDP/IP, RTP (UDP), RTP (TCP), RTSP, NTP, HTTP, DHCP (Server, Client),
Protocol Support	t	PPPoE, SMTP, ICMP, IGMP, ARP, DNS, DDNS, uPnP, HTTPS, SNMP, ONVIF (Profile-S)
DDNS		Samsung iPOLiS DDNS
Transmission Ba		Min. 32Mbps
Max. Remote Us	ers	Search 3 / Live unicast 10 / Live multicast 20
IP Socurity		IPv4 / IPv6 IP address filtering, User access log, 802.1x authentication, Encryption
Security		English, French, German, Italian, Spanish, Russian, Turkish, Polish, Dutch, Swedish, Czech,
Language	GUI / Web Viewer	Portuguese, Danish, Rumanian, Serbian, Croatian, Hungarian, Greek, Norwegian, Finnish, Korean, Chinese, Japanese, Thai
OS		[Window] : XP SP2 or above, Vista, 7, 8, [Mac OS] : OSX 10.7 or above
Web Browser		[Internet Explorer] : ver.8 ~ 11, [Firefox] : ver.19.x or above
MED DIOM2EI		
MED DIOM261	Tuno	[Chrome] : ver.26.x or above, [Safari] : ver.6.0.3 or above (OSX 10.6 or above)
Viewer Software	Type CMS Support	SSM, Webviewer, SmartViewer
	Type CMS Support	
Viewer Software		SSM, Webviewer, SmartViewer SDK / CGI PnP mode, Manual mode
Viewer Software	CMS Support Register	SSM, Webviewer, SmartViewer SDK / CGI PnP mode, Manual mode IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality,
Viewer Software	CMS Support Register Setup Items	SSM, Webviewer, SmartViewer SDK / CGI PnP mode, Manual mode IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality, Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter)
Viewer Software	CMS Support       Register       Setup Items       Control	SSM, Webviewer, SmartViewer SDK / CGI PnP mode, Manual mode IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality, Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter) Via GUI, Webviewer
Viewer Software FUNCTIONS Camera Setup PTZ	CMS Support       Register       Setup Items       Control       Preset	SSM, Webviewer, SmartViewer         SDK / CGI         PnP mode, Manual mode         IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality,         Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter)         Via GUI, Webviewer         255
Viewer Software FUNCTIONS Camera Setup	CMS Support       Register       Setup Items       Control	SSM, Webviewer, SmartViewer SDK / CGI PnP mode, Manual mode IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality, Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter) Via GUI, Webviewer
Viewer Software FUNCTIONS Camera Setup PTZ Smart phone System Control	CMS Support Register Setup Items Control Preset OS Control	SSM, Webviewer, SmartViewer         SDK / CGI         PnP mode, Manual mode         IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality,         Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter)         Via GUI, Webviewer         255         Android, iOS
Viewer Software FUNCTIONS Camera Setup PTZ Smart phone	CMS Support Register Setup Items Control Preset OS Control	SSM, Webviewer, SmartViewer SDK / CGI PnP mode, Manual mode IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality, Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter) Via GUI, Webviewer 255 Android, iOS Live 4 / Playback 1 Mouse, IR Remocon
Viewer Software FUNCTIONS Camera Setup PTZ Smart phone System Control INDICATOR / INT	CMS Support Register Setup Items Control Preset OS Control	SSM, Webviewer, SmartViewer         SDK / CGI         PnP mode, Manual mode         IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality,         Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter)         Via GUI, Webviewer         255         Android, iOS         Live 4 / Playback 1         Mouse, IR Remocon         Power status LED 1ea, HDD action LED 1ea, Alarm status LED 1ea
Viewer Software FUNCTIONS Camera Setup PTZ Smart phone System Control	CMS Support         Register         Setup Items         Control         Preset         OS         Control         ERFACE         Indicator	SSM, Webviewer, SmartViewer         SDK / CGI         PnP mode, Manual mode         IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality,         Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter)         Via GUI, Webviewer         255         Android, IOS         Live 4 / Playback 1         Mouse, IR Remocon         Power status LED 1ea, HDD action LED 1ea, Alarm status LED 1ea         Record status LED 1ea, Network action LED 1ea, Back up LED 1ea
Viewer Software FUNCTIONS Camera Setup PTZ Smart phone System Control INDICATOR / INT	CMS Support         Register         Setup Items         Control         Preset         OS         Control         ERFACE         Indicator         USB	SSM, Webviewer, SmartViewer         SDK / CGI         PnP mode, Manual mode         IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality,         Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter)         Via GUI, Webviewer         255         Android, iOS         Live 4 / Playback 1         Mouse, IR Remocon         Power status LED 1ea, HDD action LED 1ea, Alarm status LED 1ea         Record status LED 1ea, Network action LED 1ea, Back up LED 1ea         2ea
Viewer Software FUNCTIONS Camera Setup PTZ Smart phone System Control INDICATOR / INT	CMS Support         Register         Setup Items         Control         Preset         OS         Control         ERFACE         Indicator	SSM, Webviewer, SmartViewer         SDK / CGI         PnP mode, Manual mode         IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality,         Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter)         Via GUI, Webviewer         255         Android, iOS         Live 4 / Playback 1         Mouse, IR Remocon         Power status LED 1ea, HDD action LED 1ea, Alarm status LED 1ea         Record status LED 1ea, Network action LED 1ea, Back up LED 1ea         2ea         1ea / 1ea
Viewer Software FUNCTIONS Camera Setup PTZ Smart phone System Control INDICATOR / INT	CMS Support         Register         Setup Items         Control         Preset         OS         Control         ERFACE         Indicator         USB         HDMI / VGA	SSM, Webviewer, SmartViewer         SDK / CGI         PnP mode, Manual mode         IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality,         Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter)         Via GUI, Webviewer         255         Android, iOS         Live 4 / Playback 1         Mouse, IR Remocon         Power status LED 1ea, HDD action LED 1ea, Alarm status LED 1ea         Record status LED 1ea, Network action LED 1ea, Back up LED 1ea         2ea
Viewer Software FUNCTIONS Camera Setup PTZ Smart phone System Control INDICATOR / INT Front	CMS Support Register Setup Items Control Preset OS Control ERFACE Indicator USB HDMI / VGA Audio Ethernet Alarm	SSM, Webviewer, SmartViewer         SDK / CGI         PnP mode, Manual mode         IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality,         Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter)         Via GUI, Webviewer         255         Android, IOS         Live 4 / Playback 1         Mouse, IR Remocon         Power status LED 1ea, HDD action LED 1ea, Alarm status LED 1ea         Record status LED 1ea, Network action LED 1ea, Back up LED 1ea         2ea         1ea / 1ea         Out 1ea (RCA, Line)         2ea (100Mbps) + PoE 4ea (10/100Mbps)         In 4ea (Terminal block) / Out 3ea (Terminal block)
Viewer Software FUNCTIONS Camera Setup PTZ Smart phone <u>System Control</u> INDICATOR / INT Front Connections	CMS Support         Register         Setup Items         Control         Preset         OS         Control         ERFACE         Indicator         USB         HDMI / VGA         Audio         Ethernet	SSM, Webviewer, SmartViewer         SDK / CGI         PnP mode, Manual mode         IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality,         Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter)         Via GUI, Webviewer         255         Android, IOS         Live 4 / Playback 1         Mouse, IR Remocon         Power status LED 1ea, HDD action LED 1ea, Alarm status LED 1ea         2ea         1ea / 1ea         Out 1ea (RCA, Line)         2ea (100Mbps) + PoE 4ea (10/100Mbps)
Viewer Software FUNCTIONS Camera Setup PTZ Smart phone System Control INDICATOR / INT Front Connections SYSTEM	CMS Support         Register         Setup Items         Control         Preset         OS         Control         ERFACE         Indicator         USB         HDMI / VGA         Audio         Ethernet         Alarm         Power Cord	SSM, Webviewer, SmartViewer         SDK / CGI         PnP mode, Manual mode         IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality,         Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter)         Via GUI, Webviewer         255         Android, iOS         Live 4 / Playback 1         Mouse, IR Remocon         Power status LED 1ea, HDD action LED 1ea, Alarm status LED 1ea         2ea         1ea / 1ea         Out 1ea (RCA, Line)         2ea (100Mbps) + PoE 4ea (10/100Mbps)         In 4ea (Terminal block) / Out 3ea (Terminal block)         AC inlet 1ea
Viewer Software FUNCTIONS Camera Setup PTZ Smart phone System Control INDICATOR / INT Front Connections SYSTEM Log	CMS Support Register Setup Items Control Preset OS Control ERFACE Indicator USB HDMI / VGA Audio Ethernet Alarm	SSM, Webviewer, SmartViewer         SDK / CGI         PnP mode, Manual mode         IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality,         Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter)         Via GUI, Webviewer         255         Android, IOS         Live 4 / Playback 1         Mouse, IR Remocon         Power status LED 1ea, HDD action LED 1ea, Alarm status LED 1ea         Record status LED 1ea, Network action LED 1ea, Back up LED 1ea         2ea         1ea / 1ea         Out 1ea (RCA, Line)         2ea (100Mbps) + PoE 4ea (10/100Mbps)         In 4ea (Terminal block) / Out 3ea (Terminal block)
Viewer Software FUNCTIONS Camera Setup PTZ Smart phone System Control INDICATOR / INT Front Connections SYSTEM	CMS Support         Register         Setup Items         Control         Preset         OS         Control         ERFACE         Indicator         USB         HDMI / VGA         Audio         Ethernet         Alarm         Power Cord         Log List	SSM, Webviewer, SmartViewer         SDK / CGI         PnP mode, Manual mode         IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality,         Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter)         Via GUI, Webviewer         255         Android, iOS         Live 4 / Playback 1         Mouse, IR Remocon         Power status LED 1ea, HDD action LED 1ea, Alarm status LED 1ea         2ea         1ea / 1ea         Out 1ea (RCA, Line)         2ea (100Mbps) + PoE 4ea (10/100Mbps)         In 4ea (Terminal block) / Out 3ea (Terminal block)         AC inlet 1ea
Viewer Software FUNCTIONS Camera Setup PTZ Smart phone System Control INDICATOR / INT Front Connections SYSTEM Log	CMS Support         Register         Setup Items         Control         Preset         OS         Control         ERFACE         Indicator         USB         HDMI / VGA         Audio         Ethernet         Alarm         Power Cord	SSM, Webviewer, SmartViewer         SDK / CGI         PnP mode, Manual mode         IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality,         Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter)         Via GUI, Webviewer         255         Android, iOS         Live 4 / Playback 1         Mouse, IR Remocon         Power status LED 1ea, HDD action LED 1ea, Alarm status LED 1ea         2ea         1ea / 1ea         Out 1ea (RCA, Line)         2ea (100Mbps) + PoE 4ea (10/100Mbps)         In 4ea (Terminal block) / Out 3ea (Terminal block)         AC inlet 1ea         System log : Max. 20000, Event log : Max. 20000         100 ~ 240V AC / 3.5A 50Hz/60Hz         Max. 30W (With 1TB HDD 1ea)
Viewer Software FUNCTIONS Camera Setup PTZ Smart phone System Control INDICATOR / INT Front Connections SYSTEM Log GENERAL	CMS Support         Register         Setup Items         Control         Preset         OS         Control         ERFACE         Indicator         USB         HDMI / VGA         Audio         Ethernet         Alarm         Power Cord         Log List         Input Voltage / Current         NVR Power Consumption         Camera Power Output	SSM, Webviewer, SmartViewer         SDK / CGI         PnP mode, Manual mode         IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality,         Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter)         Via GUI, Webviewer         255         Android, IOS         Live 4 / Playback 1         Mouse, IR Remocon         Power status LED 1ea, HDD action LED 1ea, Alarm status LED 1ea         Record status LED 1ea, Network action LED 1ea, Back up LED 1ea         2ea         1ea / 1ea         Out 1ea (RCA, Line)         2ea (100Mbps) + PoE 4ea (10/100Mbps)         In 4ea (Terminal block) / Out 3ea (Terminal block)         AC inlet 1ea         System log : Max. 20000, Event log : Max. 20000         100 ~ 240V AC / 3.5A 50Hz/60Hz
Viewer Software FUNCTIONS Camera Setup PTZ Smart phone System Control INDICATOR / INT Front Connections SYSTEM Log GENERAL Electrical	CMS Support         Register         Setup Items         Control         Preset         OS         Control         ERFACE         Indicator         USB         HDMI / VGA         Audio         Ethernet         Alarm         Power Cord         Log List         Input Voltage / Current         NVR Power Consumption         Camera Power Output         Operating Temperature	SSM, Webviewer, SmartViewer         SDK / CGI         PnP mode, Manual mode         IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality,         Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter)         Via GUI, Webviewer         255         Android, IOS         Live 4 / Playback 1         Mouse, IR Remocon         Power status LED 1ea, HDD action LED 1ea, Alarm status LED 1ea         Pea         1ea / 1ea         Out 1ea (RCA, Line)         2ea (100Mbps) + PoE 4ea (10/100Mbps)         In 4ea (Terminal block) / Out 3ea (Terminal block)         AC inlet 1ea         System log : Max. 20000, Event log : Max. 20000         100 ~ 240V AC / 3.5A 50Hz/60Hz         Max. 30W (With 1TB HDD 1ea)         15.4W per Channel, Total 61.6W (PoE, IEEE 802.3af)         +0°C ~ +40°C (+32°F ~ +104°F)
Viewer Software FUNCTIONS Camera Setup PTZ Smart phone System Control INDICATOR / INT Front Connections SYSTEM Log GENERAL	CMS Support         Register         Setup Items         Control         Preset         OS         Control         ERFACE         Indicator         USB         HDMI / VGA         Audio         Ethernet         Alarm         Power Cord         Log List         Input Voltage / Current         NVR Power Consumption         Camera Power Output         Operating Temperature         Operating Humidity	SSM, Webviewer, SmartViewer         SDK / CGI         PnP mode, Manual mode         IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality,         Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter)         Via GUI, Webviewer         255         Android, IOS         Live 4 / Playback 1         Mouse, IR Remocon         Power status LED 1ea, HDD action LED 1ea, Alarm status LED 1ea         Record status LED 1ea, Network action LED 1ea, Back up LED 1ea         2ea         1ea / 1ea         Out 1ea (RCA, Line)         2ea (100Mbps) + PoE 4ea (10/100Mbps)         In 4ea (Terminal block) / Out 3ea (Terminal block)         AC inlet 1ea         System log : Max. 20000, Event log : Max. 20000         100 ~ 240V AC / 3.5A 50Hz/60Hz         Max. 30W (With 1TB HDD 1ea)         15.4W per Channel, Total 61.6W (PoE, IEEE 802.3af)         +0°C ~ +40°C (+32°F ~ +104°F)         20% ~ 85% RH
Viewer Software FUNCTIONS Camera Setup PTZ Smart phone System Control INDICATOR / INT Front Connections SYSTEM Log GENERAL Electrical Environmental	CMS Support         Register         Setup Items         Control         Preset         OS         Control         ERFACE         Indicator         USB         HDMI / VGA         Audio         Ethernet         Alarm         Power Cord         Log List         Input Voltage / Current         NVR Power Consumption         Camera Power Output         Operating Temperature         Operating Humidity         Color / Material	SSM, Webviewer, SmartViewer         SDK / CGI         PnP mode, Manual mode         IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality,         Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter)         Via GUI, Webviewer         255         Android, iOS         Live 4 / Playback 1         Mouse, IR Remocon         Power status LED 1ea, HDD action LED 1ea, Alarm status LED 1ea         Record status LED 1ea, Network action LED 1ea, Back up LED 1ea         2ea         1ea / 1ea         Out 1ea (RCA, Line)         2ea (100Mbps) + PoE 4ea (10/100Mbps)         In 4ea (Terminal block) / Out 3ea (Terminal block)         AC inlet 1ea         System log : Max. 20000, Event log : Max. 20000         100 ~ 240V AC / 3.5A 50Hz/60Hz         Max. 30W (With 1TB HDD 1ea)         15.4W per Channel, Total 61.6W (PoE, IEEE 802.3af)         +0°C ~ +40°C (+32°F ~ +104°F)         20% ~ 85% RH         Black / Metal
Viewer Software FUNCTIONS Camera Setup PTZ Smart phone System Control INDICATOR / INT Front Connections SYSTEM Log GENERAL Electrical	CMS Support         Register         Setup Items         Control         Preset         OS         Control         ERFACE         Indicator         USB         HDMI / VGA         Audio         Ethernet         Alarm         Power Cord         Log List         Input Voltage / Current         NVR Power Consumption         Camera Power Output         Operating Temperature         Operating Humidity         Color / Material         Dimensions (WxHxD)	SSM, Webviewer, SmartViewer         SDK / CGI         PnP mode, Manual mode         IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality,         Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter)         Via GUI, Webviewer         255         Android, IOS         Live 4 / Playback 1         Mouse, IR Remocon         Power status LED 1ea, HDD action LED 1ea, Alarm status LED 1ea         Record status LED 1ea, Network action LED 1ea, Back up LED 1ea         2ea         1ea / 1ea         Out 1ea (RCA, Line)         2ea (100Mbps) + PoE 4ea (10/100Mbps)         In 4ea (Terminal block) / Out 3ea (Terminal block)         AC inlet 1ea         System log : Max. 20000, Event log : Max. 20000         100 ~ 240V AC / 3.5A 50Hz/60Hz         Max. 30W (With 1TB HDD 1ea)         15.4W per Channel, Total 61.6W (PoE, IEEE 802.3af)         +0°C ~ +40°C (+32°F ~ +104°F)         20% ~ 85% RH         Black / Metal         370.0 x 44.0 x 320.0mm (14.57" x 1.73" x 12.6") (1U)
Viewer Software FUNCTIONS Camera Setup PTZ Smart phone System Control INDICATOR / INT Front Connections SYSTEM Log GENERAL Electrical Environmental	CMS Support         Register         Setup Items         Control         Preset         OS         Control         ERFACE         Indicator         USB         HDMI / VGA         Audio         Ethernet         Alarm         Power Cord         Log List         Input Voltage / Current         NVR Power Consumption         Camera Power Output         Operating Temperature         Operating Humidity         Color / Material         Dimensions (WxHxD)         Weight	SSM, Webviewer, SmartViewer         SDK / CGI         PnP mode, Manual mode         IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality,         Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter)         Via GUI, Webviewer         255         Android, IOS         Live 4 / Playback 1         Mouse, IR Remocon         Power status LED 1ea, HDD action LED 1ea, Alarm status LED 1ea         Pea         1ea / 1ea         Out 1ea (RCA, Line)         2ea (100Mbps) + PoE 4ea (10/100Mbps)         In 4ea (Terminal block) / Out 3ea (Terminal block)         AC inlet 1ea         System log : Max. 20000, Event log : Max. 20000         100 ~ 240V AC / 3.5A 50Hz/60Hz         Max. 30W (With 1TB HDD 1ea)         15.4W per Channel, Total 61.6W (PoE, IEEE 802.3af)         +0°C ~ +40°C (+32°F ~ +104°F)         20% ~ 85% RH         Black / Metal         370.0 x 44.0 x 320.0mm (14.57" x 1.73" x 12.6") (1U)         2.73Kg (6.02 lb) without HDD
Viewer Software FUNCTIONS Camera Setup PTZ Smart phone System Control INDICATOR / INT Front Connections SYSTEM Log GENERAL Electrical Environmental	CMS Support         Register         Setup Items         Control         Preset         OS         Control         ERFACE         Indicator         USB         HDMI / VGA         Audio         Ethernet         Alarm         Power Cord         Log List         Input Voltage / Current         NVR Power Consumption         Camera Power Output         Operating Temperature         Operating Humidity         Color / Material         Dimensions (WxHxD)	SSM, Webviewer, SmartViewer         SDK / CGI         PnP mode, Manual mode         IP Address, Add Profile Edit, Bitrate, Compression, GOP, Quality,         Video Setup (MD, VA, ABF, Brightness/Contrast, Flip/Mirror, IRIS, WDR, D&N, SSNR, Shutter)         Via GUI, Webviewer         255         Android, IOS         Live 4 / Playback 1         Mouse, IR Remocon         Power status LED 1ea, HDD action LED 1ea, Alarm status LED 1ea         Record status LED 1ea, Network action LED 1ea, Back up LED 1ea         2ea         1ea / 1ea         Out 1ea (RCA, Line)         2ea (100Mbps) + PoE 4ea (10/100Mbps)         In 4ea (Terminal block) / Out 3ea (Terminal block)         AC inlet 1ea         System log : Max. 20000, Event log : Max. 20000         100 ~ 240V AC / 3.5A 50Hz/60Hz         Max. 30W (With 1TB HDD 1ea)         15.4W per Channel, Total 61.6W (PoE, IEEE 802.3af)         +0°C ~ +40°C (+32°F ~ +104°F)         20% ~ 85% RH         Black / Metal         370.0 x 44.0 x 320.0mm (14.57" x 1.73" x 12.6") (1U)

Design and specifications are subject to change without notice.



FIRST EDITION 05-2014



**SAMSUNG TECHWIN** 

## **SRN-472S 4CH NVR with PoE Switch**

SAMSUNG

SRN-472S

- Up to 32Mbps network camera recording
- Easy camera installation via dedicated 4 PoE ports
- Up to 5megapixel IP camera supported
- Max 2 internal HDDs (Max 8TB, Over 2-months @2MP)
- Alarm, MD & VA event recording & search
- Support Samsung viewers (iPOLiS mobile, SmartViewer)



www.use-ip.co.uk

SAMSUNG TECHWIN CO., LTD.

6, Pangyo-ro 319beon-gil, Bundang-gu, Seongnam-si, Gyeonggi-do, SEOUL 463-400 Rep. of KOREA Tel : +82-70-7147-8741~8749, 8752-8760 Fax : +82-31-8018-3745 www.samsungsecurity.com www.samsungcctv.com COPYRIGHT BY SAMSUNG TECHWIN. ALL RIGHT RESERVED

SAMSUNG TECHWIN AMERICA Inc. 100 Challenger Rd. Suite 700 Ridgefield Park, NJ 07660 Toll Free : +1-877-213-1222 Direct : +1-201-325-6920 Surrey, KT13 ONY, UK Fax:+1-201-373-0124

 SAMSUNG TECHWIN EUROPE LTD.
 SHANGHAI SAMSUNG TECHWIN CO., LTD.

 2nd Floor, No. 5 The Heights, Brooklands, Weybridge,
 S2F, Bik B, International Business Center,

 Surrey, KT13 0NV, UK
 No. 391 Guping Rd., Shanghai, China, 200233

 Tel : +44-1932-82-6700
 Fax: +44 1932 82 6701

01304 827609

DISTRIBUTED BY

I.H-1405



# **Better Security, Better Business**



www.samsungipolis.com

# SRN-472S lets you focus more on your business and sales.



#### You don't understand IP, don't worry! **JUST Plug and Play**

Protecting the store, it's customers and assets are important factors in the minds of the owner and management ; the understanding of network surveillance systems is not. However, the SRN-472S, with it's built-in PoE switch and zero configuration, has been specifically designed for retail it takes the away any need understand network systems or invest in additional equipment such as a PoE switch.



#### SRN-472S is designed to be harmonious with store interior

Samsung Techwin's SRN-472S and retail specific domes and fisheye cameras are all of a compact design allowing them to sit well with any interior, without compromising the stores image nor the customers comfort while at the same time securing the stores and assets.



#### Maximized the stores security while reducing costs

#### Recording 4CH in real-time for up to 2-months@full HD quality 4CH (1 HDD standard, max, 2 HDDs (4TB ea)

This gives the store peace of mind that nothing will be missed and that vital information will still be there weeks after the event. Allowing you the flexibility to search and track the data not only for criminal evidence but also for business analysis.

#### Remote Viewing

View live and playback video from anywhere, whether on the stores PC or your Smart Phone / Tablet when out and about, Samsung Techwin's free of charge software will allow you to keep in touch with the stores activities anytime of the day or night.



#### Display Full HD images on a local monitor

SRN-472S supports a HDMI full HD output as well as a standard VGA, giving the owner the option of having an "In store" monitor that demonstrates to the customers that they are being protected by a high quality professional surveillance solution.







Linked to POS (Available in 2014 4Q)

#### SRN-472S compatible PoE network cameras and management software

#### **3MP Fisheye Camera SNF-7010V**

- Real-time WDR (3M 20fps, 120dB)
- Various viewing composition
- IP66, IK10





#### 2MP Compact Dome Camera SNV-6012M/6013

- 60fps@1080p
- Day & Night (Electrical)
- WDR (120dB), Enhanced DIS, Defog
- IP66, Weatherproof IK10, Vandal-resistant



#### Samsung Retail Software **SmartViewer**

- Local & Remote Viewing
- Sequence and favorite view
- Event search sensor, Video loss, Motion, VA (Passing, Entering, Exiting, Disappearing/Appearing, Tampering, Tracking, Face detection, Audio detection)

### **iPOLiS** mobile

- Android & IOS supported
- Live, playback & PTZ control
- Up to 100 devices supported



iPOI iS mobile



SmartViewe