




SMART Board® 8055i, 8055i-SMP and 8055ie-SMP

Interactive flat panels

User's guide

Product registration

If you register your SMART product, we'll notify you of new features and software upgrades.

Register online at smarttech.com/registration.

Keep the following information available in case you need to contact SMART Support.

Serial number:

Date of purchase:

FCC warning

This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the US Federal Communications Commission Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the manufacturer's instructions, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

Trade-mark notice

SMART Board, SMART Ink, SMART Notebook, SMART Meeting Pro, DViT, SMART GoWire, smarttech, the SMART logo and all SMART taglines are trade-marks or registered trade-marks of SMART Technologies ULC in the US and/or other countries. Mac and Macintosh are trade-marks of Apple Inc., registered in the US and other countries. Windows is either a registered trade-mark or a trade-mark of Microsoft Corporation in the US and/or other countries. All third-party product and company names may be trade-marks of their respective owners.

Copyright notice

© 2012 SMART Technologies ULC. All rights reserved. No part of this publication may be reproduced, transmitted, transcribed, stored in a retrieval system or translated into any language in any form by any means without the prior written consent of SMART Technologies ULC. Information in this manual is subject to change without notice and does not represent a commitment on the part of SMART.

Patent No. US6320597; US6326954; US6741267; US6803906; US6947032; US6954197; US6972401; US7151533; US7236162; US7411575; US7619617; US7643006; US7692625; US7755613; US7757001; USD612396; US6563491; US6829372; US7880720; USD612396; USD616462; USD617332; and USD636784. Other patents pending.

06/2012

Important information for your interactive flat panel

WARNING

- Failure to follow the installation instructions sent with your SMART product could result in personal injury and product damage which may not be covered by your warranty.
- Do not open or disassemble the SMART product. You risk electrical shock from the high voltage inside the casing. Opening the casing also voids your warranty.
- Do not stand (or allow children to stand) on a chair to touch the surface of your SMART product. Rather, mount the product at the appropriate height.
- To reduce the risk of fire or electric shock, do not expose the SMART product to rain or moisture.
- If your SMART product requires replacement parts, make sure that the service technician uses replacement parts specified by SMART Technologies or parts with the same characteristics as the original.
- Ensure that any cables extending across the floor to your SMART product are properly bundled and marked to avoid a trip hazard.
- Do not insert objects inside the cabinet ventilation holes, because they could touch dangerous voltage points and cause electric shock, fire or product damage which may not be covered by your warranty.
- Do not place any heavy objects on the power cable. Damage to the cable could cause shock, fire or product damage which may not be covered by your warranty.
- Use only extension cords and sockets into which this product's polarised plug can be fully inserted.
- Use the power cable provided with this product. If a power cable is not supplied with this product, please contact your supplier. Use only power cables that match the AC voltage of the power outlet and that comply with your country's safety standards.
- If the glass is broken, do not touch the liquid crystal. To prevent injury, handle glass fragments with care when disposing of them.
- Do not move or mount the interactive flat panel by connecting rope or wire to its handles. Because the interactive flat panel is heavy, rope, wire or handle failure could lead to personal injury.
- Use only VESA®-approved mounting hardware.

IMPORTANT INFORMATION FOR YOUR INTERACTIVE FLAT PANEL

- Disconnect all power cables for your interactive flat panel from the wall socket and seek assistance from qualified service personnel when any of the following occurs:
 - The power cable or plug is damaged
 - Liquid is spilled into the interactive flat panel
 - Objects fall into the interactive flat panel
 - The interactive flat panel is dropped
 - Structural damage such as cracking occurs
 - The interactive flat panel behaves unexpectedly when you follow operating instructions

CAUTION

- Before you clean your SMART product, shut down or disconnect the computer. Otherwise, you may scramble the desktop icons or inadvertently activate applications when you wipe the screen.
- Avoid setting up and using the SMART product in an area with excessive levels of dust, humidity and smoke.
- Make sure that an electrical socket is near your SMART product and remains easily accessible during use.
- For SMART Board 8055ie-SMP interactive flat panel only: The external power supply needs to meet the Limited Power Source (LPS) requirements of CSA/UL/IEC/EN 60950-1, when required.
- This SMART product should be used only with European TN and TT power distribution systems.

It is not suitable for older, IT-type power distribution systems found in some European countries. "This system (IT-type) is widely used isolated from earth, in some installations in France, with impedance to earth, at 230/400V, and in Norway, with voltage limiter, neutral not distributed, at 230V line-to-line." (IEC 60950:1999)

Contact qualified personnel if you're uncertain of the type of power system available where you're installing your SMART product.

- You must connect the USB cable that came with your SMART Board® interactive flat panel to a computer that has a USB compliant interface and that bears the USB logo. In addition, the USB source computer must be compliant with CSA/UL/EN 60950 and bear the CE mark and CSA and/or UL Mark(s) for CSA/UL 60950. This is for operating safety and to avoid damage to the SMART Board interactive flat panel.

Contents

Important information for your interactive flat panel	i
Chapter 1: About your interactive flat panel	1
Feature highlights	2
Interactive flat panel components	3
Chapter 2: Installing your interactive flat panel	9
Environmental requirements	9
Wall-mounting your interactive flat panel	10
Chapter 3: Connecting computers and peripheral devices	13
Installing the speakers	14
Connecting a room control system	15
Connecting computers to your interactive flat panel	16
Connecting to power and computer 1	17
Installing computer 2 connection	18
Disabling the USB port on the side terminal panel	19
Connecting peripheral devices to your interactive flat panel	20
Chapter 4: Installing SMART software	21
Installing SMART Meeting Pro software	21
Installing SMART Notebook software	22
Chapter 5: Using your interactive flat panel	23
Turning your interactive flat pane on and off.	24
Understanding presence detection	25
Using the infrared remote control	26
Getting started with your SMART Board interactive flat panel	30
Playing audio files on your interactive flat panel	41
Using the USB port	42
Chapter 6: Using guest laptops with your interactive flat panel	43
Connecting a guest laptop	43
Using a SMART GoWire cable	44
Connecting computer 2	46
Chapter 7: Maintaining your interactive flat panel	47
Updating your SMART software and firmware	47
Calibrating your interactive flat panel	50
Orientating your interactive flat panel	51
Replacing a pen nib	51
Cleaning the screen	52
Cleaning the presence detection sensors	52

CONTENTS

Cleaning the camera windows and reflective tape	53
Maintaining ventilation	53
Preventing condensation	54
Checking the interactive flat panel installation	54
Removing your interactive flat panel	54
Transporting your interactive flat panel	56
Chapter 8: Troubleshooting for your interactive flat panel	57
Resolving image issues	57
Resolving touch control and digital ink issues	61
Resolving audio issues	64
Resolving remote control issues	65
Troubleshooting presence detection	65
Resolving issues using the SMART Connection Wizard	67
Resolving issues using SMART Board Diagnostics	67
Appendix A: Adjusting video settings with the on-screen display menu	69
Changing settings in the OSD menu	69
Main menu settings	70
Appendix B: Hardware environmental compliance	75
Waste Electrical and Electronic Equipment regulations (WEEE directive)	75
Restriction of Certain Hazardous Substances (RoHS directive)	75
Batteries	75
Packaging	75
Index	77

Chapter 1

About your interactive flat panel

Feature highlights	2
Commercial-grade, touch-enabled flat panel	2
Elegant, sophisticated design	2
Software	2
Presence detection	2
Dual sketch capabilities	2
SMART Ink™	2
Touch and gestures	3
Durable surface	3
Interactive flat panel components	3
Front view	3
LCD screen	3
Presence detection	3
Camera and reflective tape channel	4
Pen and eraser holders	4
Colour select module	4
Front control panel	5
Infrared remote control	5
Left side view	6
Menu control panel	6
USB port	6
Side terminal panel	6
Back view	6
Bottom terminal panel	7
Inside terminal panel	8
Speaker wire connections	8

Feature highlights

Commercial-grade, touch-enabled flat panel

Your SMART Board 8055i interactive flat panel features SMART's proprietary DViT® (Digital Vision Touch) technology on an LCD screen which enables you to select, write and erase on the interactive surface. It enables you to do everything that you can do at your computer—open and close applications, conference with others, create new documents or edit existing ones, visit websites, play and manipulate video clips and more—just by touching the interactive surface. Two users can also draw on the interactive surface at the same time and you can use an array of gestures within applications.

Elegant, sophisticated design

The professional design and crisp, eye-catching visuals of the SMART Board 8055i interactive flat panel make it perfect for any high-end workspace.

Software

To use all the features of your interactive flat panel described in this guide, go to smarttech.com/downloads and ensure that you have the latest version of SMART software and SMART Product Drivers installed on your computer.

Presence detection

The interactive flat panel has two presence detection sensors on its frame that can detect people up to 5m (16') away. When the sensors detect people in the room, the interactive flat panel turns on. When the sensors no longer detect people in the room, the interactive flat panel turns off.

Dual sketch capabilities

Two people can each pick up a pen and draw on the interactive surface at the same time, providing a higher degree of interactivity.

SMART Ink™

SMART Ink enables you to write and draw in digital ink over open applications, files, folders, websites and any other open window on your computer. When you write outside the open windows on your computer, a SMART Ink Note appears and you can write inside the note.

When you open an application that has its own ink tools, you can turn off SMART Ink and then use the application's ink tools to write in the content.

For more information, see the *SMART Ink user's guide for Windows® operating systems* (smarttech.com/kb/170191) or *SMART Ink user's guide for Mac OS X operating system software* (smarttech.com/kb/170192).

CHAPTER 1

About your interactive flat panel

Touch and gestures

You can perform mouse functions with your finger and write and erase digital ink with a pen tray pen or the eraser. The object awareness feature enables you to pick up a pen and then write, select or erase without replacing the pen.


Durable surface

The SMART Board 8055i interactive flat panel features a hardened glass screen.

Interactive flat panel components

Front view

The front of your interactive flat panel includes the LCD screen, the cameras and reflective tape channel, sensors for presence detection, the pen holders with the pens, the eraser holder with an eraser and the colour select module.



LCD screen

The screen is 133cm W x 82cm H (52 3/8" x 32 5/16"), with a 140cm (55") diagonal, 16:9 format.

For information on cleaning your LCD screen, see *Cleaning the screen* on page 52.

Presence detection

The interactive flat panel has two presence detection sensors on its frame that can detect people up to 5m (16') away. When the sensors detect people in the room, the interactive flat panel turns on. When the sensors no longer detect people in the room, the interactive flat panel turns off.

For information on cleaning your sensors, see *Cleaning the presence detection sensors* on page 52. For more information on presence detection settings, see *Proximity control settings* on page 72.

CHAPTER 1

About your interactive flat panel

i NOTE

If ECO STANDBY is enabled, presence detection functionality is limited. For more information, see *Setup settings* on page 72

Camera and reflective tape channel

The interactive flat panel screen is bordered by a channel that contains reflective tape. Each corner has a camera that tracks finger and pen positions across the screen. For information on cleaning your camera windows and reflective tape, see *Cleaning the screen* on page 52.

⚠ CAUTION

- Do not damage or remove the reflective tape.
- Keep the reflective tape dry.

👉 IMPORTANT

- Do not attach items such as adhesive notes to the screen because they will interfere with the cameras.
- Do not place anything in the channel because it will interfere with the cameras.

Pen and eraser holders


The bottom bezel contains magnetic holders for two pens and an eraser. Removing a pen or the eraser from the holders activates it and enables you to either draw or erase digital ink.

⚠ CAUTION

When returning the pen or eraser to the magnetic holder, ensure that it is centred on the holder to prevent the pen or eraser from falling and potentially being damaged.

Colour select module

The colour select module enables you to access the help function, open the on-screen keyboard, select pen colour, activate the right-click and orientate the interactive flat panel.



CHAPTER 1

About your interactive flat panel

Front control panel

The front control panel contains the volume control, mute, input and power buttons, as well as the status light and infrared remote control sensor.




IMPORTANT

Do not cover or block this area or you could have reduced use of the infrared remote control.

In normal use

- The volume, mute and input buttons are blue.
- The power button is green.
- The status light is green.

For information on diagnosing issues using the front control panel lights, see *Diagnosing blank screen issues using the front control panel lights* on page 57.



Infrared remote control


The infrared remote control enables you to turn on and turn off your interactive flat panel, change the input source, adjust the volume, access the on-screen menu and more. For more information on the infrared remote control, see *Using the infrared remote control* on page 26.

CHAPTER 1

About your interactive flat panel

Left side view

The left side of your interactive flat panel has the menu control panel and the side terminal panel.



Menu control panel

The menu control panel enables you to access the on-screen display menu to adjust display and audio settings. For more information on the on-screen display menu, see *Adjusting video settings with the on-screen display menu* on page 69.

USB port

The USB port takes a USB type A connector, such as a USB memory drive. For more information on this port, see *Using the USB port* on page 42.

NOTE

You can disable this USB port so that a computer cannot access it. For instructions, see *Disabling the USB port on the side terminal panel* on page 19.

Side terminal panel

The side terminal panel has USB and HDMI ports for connecting a guest laptop. For more information on the side terminal panel, see *Connecting a guest laptop* on page 43.

Back view


The back of the interactive flat panel includes the bottom terminal panel, the inside terminal panel and the speaker wire connections.

IMPORTANT

Connect all required cables before you wall-mount your interactive flat panel. Some connectors could be inaccessible after wall mounting.


CHAPTER 1

About your interactive flat panel



Bottom terminal panel

The bottom terminal panel contains the main power switch and several connections, including both touch control connections and connections for auxiliary input and output devices, such as DVD players, Blu-ray™ players and VCRs.



CAUTION


The AC power socket is designated for a component of the SMART Board 8055ie-SMP interactive flat panel with appliance. See *Replacing the appliance on your SMART product (FRU - Appliance - SB8)* (smarttech.com/kb/170062).

CHAPTER 1

About your interactive flat panel


Inside terminal panel

The inside terminal panel is on the left side of the interactive flat panel and contains the touch control USB connections and the room control input and output.



Speaker wire connections

The speaker wire connections are located in the bottom terminal panel.



Chapter 2

Installing your interactive flat panel

Environmental requirements	9
Wall-mounting your interactive flat panel	10
Important mounting considerations for trained installers	11
Choosing a mounting location	11
Choosing a mounting height	12

You need a team of professional installers to install your SMART Board 8055i interactive flat panel.

This chapter provides additional considerations and details for installing your interactive flat panel.



IMPORTANT

Because the ports might not be accessible after wall-installation, consider connecting cables for speakers, computers and peripheral devices whilst the interactive flat panel is still in its packaging or is suspended from a lifting device. For more information, see *Connecting computers and peripheral devices* on page 13.

Environmental requirements

Before installing your interactive flat panel, review the following environmental requirements. For more detailed information, see *SMART Board 8055i and 8055i-SMP interactive flat panel specifications* (smarttech.com/kb/170179) or *SMART Board 8055ie-SMP interactive flat panel with appliance specifications* (smarttech.com/kb/170178).

Environmental requirement	Parameter
Power requirements	0.8A to 1.8A at 100V to 240V AC, 50 Hz to 60 Hz
Power consumption at 25°C (77°F)	Typically up to 148 W (brightness at 80% and volume at 50), maximum 178 W (brightness and volume at maximum)
Operating temperature	5°C to 35°C (41°F to 95°F)
Storage temperature	-20°C to 60°C (-4°F to 140°F)

Environmental requirement	Parameter
Humidity	5% to 80% relative humidity, non-condensing
Ventilation	Maintain a 10cm (4") ventilation area around your interactive flat panel to enable its cooling fans to operate. Do not store or operate your interactive flat panel in dusty environments because dust could interfere with the product's ventilation and cooling.
Water and fluid resistance	- Intended for indoor use only. Doesn't meet any salt-spray or water ingress requirements. - Don't pour or spray liquids directly onto the interactive flat panel or any of its sub-components. These liquids might get into areas where they could damage sensitive electronic components. Refer to page 52 for detailed instructions on cleaning your interactive flat panel.

Wall-mounting your interactive flat panel

Use a team of trained, professional installers to install your interactive flat panel.

WARNING

- Improper installation can result in personal injury or product damage.
- Your interactive flat panel weighs 44.5kg (98 lb). Refer to local building regulations to ensure that your installation area can support this weight.

CAUTION

Do not allow the weight of the interactive flat panel to rest on the colour select module because it is not designed to support product weight. Attach other components whilst the interactive flat panel is either still in its packaging or suspended from a lifting device to prevent the weight of the interactive flat panel from damaging the colour select module.

IMPORTANT

- Save all product packaging so that it is available if you need to transport your interactive flat panel. If your original packaging is not available, you can purchase new product packaging from your authorised SMART reseller (smarttech.com/where).
- Attach the speakers and connect the speaker wires to the interactive flat panel before you wall-mount it. For more information, see *Installing the speakers* on page 14.


CHAPTER 2

Installing your interactive flat panel

Important mounting considerations for trained installers

Consider the following when mounting the interactive flat panel on a wall:

- Plan your workflow to include cabling because some cable connection points might not be accessible after installation.
- Carry and lift the interactive flat panel by gripping the handles and sides.



- To mount the interactive flat panel on a wall, you require a standard VESA 600 mm × 400 mm compatible wall mount bracket (not included). The wall mount bracket must have minimum depth of 14 mm to ensure sufficient space for the speakers.
- Use M8 screws to fasten the wall bracket. The screws must be 14–15 mm long plus the thickness of the bracket and the washer.
- The recommended fasten force is 11.25–13.75 N·m (99.57–121.70 in-lb.).
- Refer to the instructions included with the mounting equipment for more detailed information.

Choosing a mounting location

Consider the following when you select a location for the interactive flat panel:

- The wall must be strong enough to support the interactive flat panel and the mounting equipment. The interactive flat panel weighs 44.5kg (98lb).
- Do not install the interactive flat panel in a location where a door or gate could hit it.
- Do not install the interactive flat panel in an area where it will be subjected to strong vibrations or dust.
- Do not install the interactive flat panel near where the main power supply enters the building.
- Ensure adequate ventilation or provide air conditioning around the interactive flat panel so that heat can flow away from the unit and the mounting equipment.


CHAPTER 2

Installing your interactive flat panel

- If you mount the interactive flat panel in a recessed area, leave at least 10cm (4") of space between the interactive flat panel and the recess walls to enable ventilation and cooling.

Choosing a mounting height

Consider the general height of your user community when you choose the mounting height for the interactive flat panel.



Chapter 3

Connecting computers and peripheral devices

Installing the speakers	14
Connecting a room control system	15
Connecting computers to your interactive flat panel	16
Interactive flat panel touch control and video input connections	16
Connecting to power and computer 1	17
Computer 1 connection diagram	17
Installing computer 2 connection	18
Computer 2 connection diagram	18
Disabling the USB port on the side terminal panel	19
Connecting peripheral devices to your interactive flat panel	20
Bottom terminal panel	20

This chapter includes information on connecting your interactive flat panel to computers and other peripheral devices.




IMPORTANT

Because the cable connection points might not be accessible after wall-mounting, consider connecting these devices before wall-mounting your interactive flat panel.


Installing the speakers

Your interactive flat panel comes with two 15 W speakers.



To install the speakers

1. Attach the speakers to the speaker mounting holes on the side of the interactive flat panel with the screws included.
2. Connect the speaker wires to the speaker wire connections on the bottom terminal panel.
3. Run the speaker wire for the left speaker (when viewed from the back of the interactive flat panel) below the bottom terminal panel and secure it with the small clamps included.



Connecting a room control system

You can control your interactive flat panel from a room control system.


■ To connect your interactive flat panel to a room control system

Connect an RS-232 cable from the room control input on the inside terminal panel of the interactive flat panel to the serial output on your computer or room control system.



IMPORTANT

Do not use a null modem cable. Use only a standard RS-232 cable.



For more information about setting up and programming a room control system, see *Remotely managing your SMART Board 8055i interactive flat panel* (smarttech.com/kb/170189).


Connecting computers to your interactive flat panel

You can connect up to three computers simultaneously to your interactive flat panel:

- Computer 1 (an installed room computer) connected to USB 1 and VGA 1
- Computer 2 (a guest computer) connected to USB 2 and VGA 2
- A guest laptop connected to USB 3 and HDMI 2 connector

i NOTE

This document describes the default USB and video connections. To customise the USB and video mapping, see *Configuring the video and touch input for your SMART Board 8055i interactive flat panel* (smarttech.com/kb/170190).



Interactive flat panel touch control and video input connections


The following table shows which touch control USB connection corresponds with which video input for each computer connection.

	Touch control	Video input	Installation steps
Computer 1	USB 1 (inside terminal panel)	VGA 1	page 17
Computer 2	USB 2 (inside terminal panel)	VGA 2	page 18
Guest laptop	USB 3 (side terminal panel)	HDMI 2	page 43

Connecting to power and computer 1

Computer 1 (the room computer) is the default computer for your interactive flat panel. Connect this computer to your interactive flat panel with a VGA cable and a USB cable.

Computer 1 connection diagram



■ To connect your interactive flat panel to power and computer 1

1. Connect the VGA cable included from computer 1 to the **VGA 1** port on the bottom terminal panel.
2. Connect the USB cable included from the **USB 1** port on the inside terminal panel of the interactive flat panel to a USB port on the computer.
3. Connect the power cable included from the **AC IN** connector on the bottom terminal panel to a power socket.
4. Connect the power cable from your computer to a power socket.
5. Turn on your computer.
6. Turn on the main power switch on the bottom terminal panel, and then press the **Power** button  on the front control panel.
7. Press the **VGA 1** button on the remote control.

OR

Press the **Input** button  on the front control panel until the input source is VGA 1.

Installing computer 2 connection

You can install cabling that enables you to connect a second computer to your interactive flat panel from another location in the room, such as on a conference table. By installing this connection, you make use of connection points that might not be accessible when your interactive flat panel is wall-mounted.

You need a USB cable and a VGA cable to install the computer 2 connection. You may install these cables and run them through floors or walls to a nearby table.

Alternatively, your users can connect a laptop to the side terminal panel using the more accessible USB port and HDMI input. For more information, see *Connecting a guest laptop* on page 43. For a diagram of the various computer options, see *Connecting computers to your interactive flat panel* on page 16.


WARNING

Ensure that any cables extending across the floor to your SMART product are properly bundled and marked to avoid a trip hazard.

NOTE

You do not require a laptop to install this cabling.

Computer 2 connection diagram



To setup the computer 2 connection location

1. Connect a USB cable to the **USB 2** port on the inside terminal panel and then run the cable to the laptop connection location, such as beside the interactive flat panel or on a conference table.
2. Connect a VGA video cable to the **VGA 2** interactive flat panel port on the bottom terminal panel and then run the cable to the computer 2 connection location as above.
3. Bundle and cover the cables as appropriate to avoid a trip hazard.

To connect and use a computer using this installed connection, see *Connecting computer 2* on page 46.

Disabling the USB port on the side terminal panel

You can connect a USB drive or other USB device to the USB port on the side terminal panel of your interactive flat panel and then access the device from computer 1. For more information, see *Using the USB port* on page 42.


You can also disable this USB port so that it doesn't access any of the computers connected to your interactive flat panel.

CAUTION

Disconnect the power supply for your interactive flat panel before you disable the USB port.

To disable the USB port

1. Locate the rectangular cut-out on the back of your interactive flat panel.



CHAPTER 3

Connecting computers and peripheral devices

2. Remove the screw securing the cut-out with a Phillips screwdriver. Retain the screw and cut-out.
3. Locate the black jumper connector on the circuit board inside the panel.
4. Pull the black jumper connector off of the circuit board with the pliers.

CAUTION

To prevent damage to the circuit board, do not touch the circuit board with the pliers.

IMPORTANT

You can install the jumper connector again to enable the USB port.


Connecting peripheral devices to your interactive flat panel

Connect peripheral devices to the bottom terminal panel.

CAUTION

The AC power socket is designated for a component of the SMART Board 8055ie-SMP interactive flat panel with appliance. See *Replacing the appliance on your SMART product (FRU - Appliance - SB8)* (smarttech.com/kb/170062).

Bottom terminal panel



To connect a peripheral device

1. Turn off the interactive flat panel and the peripheral device.
2. Connect the peripheral device's input cables to the appropriate connectors on the bottom terminal panel.

NOTE

You can secure these cables with the large clamps included.

3. Turn on the interactive flat panel and then turn on the peripheral device.

Chapter 4

Installing SMART software

Installing SMART Meeting Pro software	21
Installing SMART Notebook software	22

IMPORTANT

If you already have SMART Meeting Pro software or SMART Notebook™ collaborative learning software installed on your computer, ensure that your computer has SMART Product Drivers 11 or later installed. For more information, see *Updating SMART Product Drivers* on page 49.

You need to install SMART software on the computer that's connected to your interactive flat panel in order to use the interactive flat panel. You can install either SMART Meeting Pro software or SMART Notebook software.

SMART Board 8055i-SMP interactive flat panels also include a SMART GoWire auto-launch cable that provides the features of SMART Meeting Pro software without installing the software on your computer. For more information about using the SMART GoWire auto-launch cable, see *Using a SMART GoWire cable* on page 44.

NOTE

For laptops that are only occasionally used for your interactive flat panel, you can use a SMART GoWire cable instead of installing SMART Meeting Pro software.

Once you install SMART Notebook software or SMART Meeting Pro software on the computer that's connected to your interactive flat panel, you have touch control of that computer's desktop. You can open files, move icons and write or erase digital ink using the pens and eraser included.

Installing SMART Meeting Pro software

You can download and install SMART Meeting Pro software from the SMART website.

IMPORTANT

Register your product at smarttech.com/registration so that you can obtain a software product key which is required for activation.

■ To download SMART Meeting Pro software

1. Go to smarttech.com/downloads.
2. Scroll to the *SMART Meeting Pro software* section.
3. Click **Choose a version** and then select the version that you require.
4. Follow the on-screen instructions to save the executable file to your desktop.

■ To install SMART Meeting Pro software

1. Double-click the executable file.
2. Follow the on-screen instructions.

Installing SMART Notebook software

Install SMART Notebook software from the included DVD (SMART Board 8055i interactive flat panels only) or from smarttech.com/downloads.



IMPORTANT

Connect to the Internet before you install SMART software so that you can obtain a software product key (smarttech.com/registration) and download software updates.

■ To install SMART Notebook software

1. Place the software DVD included in your computer's DVD tray.
The installation wizard appears.
2. Follow the on-screen instructions. You'll be prompted to enter your product key. You can register your interactive flat panel at smarttech.com/registration to receive your product key.
3. Click the **SMART Board** icon  in the notification area (Windows operating systems) or the Dock (Mac OS X operating system software) and then select **Check for Updates and Activation**.
The *SMART Product Update* window appears.
4. Follow the on-screen instructions to update your SMART Notebook software to the latest version.

Chapter 5

Using your interactive flat panel

Turning your interactive flat pane on and off.	24
Understanding presence detection	25
Using the infrared remote control	26
Installing batteries in the remote control	26
Infrared remote control sensor	27
Infrared remote control buttons	28
Getting started with your SMART Board interactive flat panel	30
About SMART Ink	30
SMART Ink Notes	30
SMART Ink Document Viewer	30
SMART Ink Toolbar	30
About your SMART software	31
SMART Product Drivers	31
SMART Notebook software	31
SMART Meeting Pro software	31
Writing or drawing in digital ink	31
Entering text on the interactive flat panel	31
Changing pen settings	32
Using Locked Ink mode	32
Erasing digital ink	33
Changing eraser settings	34
Manipulating objects	34
Browsing	38
Playing audio files on your interactive flat panel	41
Using the USB port	42

This chapter includes information on how to use your interactive flat panel, turn on and turn off your interactive flat panel, control your computer by touching the screen, use the remote control and more.

Turning your interactive flat pane on and off.

■ To turn your interactive flat panel on

NOTE

If presence detection is enabled, the interactive flat panel turns on and the welcome screen appears automatically when people enter the room. Dismiss the welcome screen by touching the interactive flat panel screen. For more information, see *Understanding presence detection* on the next page

1. Turn your computer on.
2. Press the **Power** button  on the front control panel.

You can also press the **POWER ON** button on the remote control.

Your computer's logon screen or desktop appears on your interactive flat panel.

IMPORTANT

If the power button light on the front control panel is off, either the interactive flat panel is not plugged in or the main power switch on the bottom terminal panel is turned off. To find the main power switch, see *Back view* on page 6.

■ To turn your interactive flat panel off

1. Turn your computer off.
2. Press the **Power** button  on the front control panel.

You can also press the **STANDBY** button on the remote control.


NOTE

If presence detection is enabled, the interactive flat panel turns off automatically when the sensors no longer detect people in the room. For more information on presence detection settings, see *Proximity control settings* on page 72

Understanding presence detection

i NOTE

If ECO STANDBY is enabled, presence detection functionality is limited. For more information, see *Setup settings* on page 72



The interactive flat panel has two presence detection sensors on its frame that can detect people up to 5m (16') away. When the sensors detect people in the room, the interactive flat panel turns on. When the sensors no longer detect people in the room, the interactive flat panel turns off.

For information on cleaning your sensors, see *Cleaning the presence detection sensors* on page 52. For more information on presence detection settings, see *Proximity control settings* on page 72.

Using the infrared remote control

The infrared remote control enables you to turn on and turn off your interactive flat panel, change the input source, change the volume and more. You can also use the remote control to open the on-screen menu and then change the interactive flat panel's settings.

If the remote control doesn't respond, see *Resolving remote control issues* on page 65.

CAUTION

- Do not subject the remote control to strong shock.
- Keep the remote control away from liquids. If it gets wet, wipe it dry immediately.
- Do not expose the remote control to heat or steam.
- Do not open any part of the remote control other than the battery compartment and picture-in-picture compartment.

IMPORTANT

The remote control system does not function when strong light strikes the remote control sensor or when there is an object between the remote control and its sensor.

Installing batteries in the remote control

Your remote control requires two 1.5V AA batteries.

WARNING

To reduce the risk associated with leaking batteries:

- use only AA type batteries
- do not mix used and new batteries
- orientate the battery's plus (+) and minus (-) terminals according to the markings found on the remote control
- do not leave the batteries in the remote control for an extended period
- do not heat, disassemble, short or recharge the batteries, or expose them to fire or high temperature
- avoid eye and skin contact if batteries have leaked
- dispose of dead batteries and product components in accordance with applicable regulations

CHAPTER 5

Using your interactive flat panel

To install batteries in the remote control

1. Press the tab on the underside of the remote control and then open the cover.
2. Remove the batteries if they are present.
3. Insert two new 1.5V AA batteries in the remote control. Ensure that the + and - markings on the batteries align with the markings in the remote control.
4. Replace the cover.


Infrared remote control sensor

The infrared remote control sensor is located on the front control panel. It enables you to control your interactive flat panel from an angle of 30° and within a distance of 7m (23') using the included remote control.



IMPORTANT

The remote control might not function when the infrared remote control sensor is blocked or when it is in direct sunlight or strong lighting.



CHAPTER 5


Using your interactive flat panel

Infrared remote control buttons

The remote control enables you to access on-screen menus and change display and input settings.

Use the remote control's POWER ON button to turn your interactive flat panel on and the STANDBY button to turn it off.

Use the remote control's input buttons to change input sources when switching between the connected computers.



Number	Function	Description
1	POWER ON STANDBY	Turns your interactive flat panel on Turns your interactive flat panel off
2	ASPECT	Selects picture aspect
3	STILL	Turns the still picture mode on or off
4	Number pad	Press buttons on the number pad to set and change passwords, change channels or to customise or change settings
5	DISPLAY	Turns the on-screen display menu on and off
6	SET	Makes selection
87	Left/Right	Increases or decreases the adjustment level within the on-screen display menu
8	AUTO SET UP	Enters auto setup menu
9	VOL +/-	Increases or decreases audio output level
10	AUDIO INPUT	Selects audio input source
11	Input buttons	Selects input signal for the interactive flat panel

CHAPTER 5

Using your interactive flat panel

Number	Function	Description
12	SLEEP	Sets a timer to turn off the interactive flat panel
13	PIP buttons	Not in use
14	OPTION	Not in use
15	INPUT	Toggles between the different input signals for the interactive flat panel
16	SOUND	Selects artificial surround sound
17	MUTE	Mutes audio inputs for your interactive flat panel
18	EXIT	Returns to previous menu
19	Up/Down	Moves the highlighted area up or down to select items within the on-screen display menu
20	MENU	Turns the menu mode on and off
21	*	Not in use
22	PICTURE MODE	Selects picture mode
23	MTS	Not in use

Getting started with your SMART Board interactive flat panel

Using your SMART Board interactive flat panel, you can write, draw and erase digital ink, manipulate objects and browse content on the screen.

About SMART Ink

SMART Ink enables you to write and draw in digital ink over open applications, files, folders, websites and any other open window on your computer.

You can write over an Internet browser window, highlight content on your screen and write over a video without pausing the video and without interfering with your ability to interact with the video. When you move, resize or minimise a window, the ink stays with the window.

You can convert your digital ink notes to text. You can also move, erase and capture your notes as an image and save it to your SMART software.

When you open an application that has its own ink tools, you can turn off SMART Ink, and then use the application's ink tools to write.

For more information see SMART Ink for Windows (smarttech.com/SupportInk1Windows) or SMART Ink for Mac (smarttech.com/SupportInk1Mac) on the SMART Support website.

SMART Ink Notes

SMART Ink Notes enable you to write in digital ink anywhere on your desktop. When you write outside of the open windows on your computer, a SMART Ink Note appears and you can write inside the note.

SMART Ink Document Viewer

If you're using a Windows operating system, the SMART Ink Document Viewer enables you to view your PDF files and to write in digital ink over your files.

SMART Ink Toolbar

If your computer is connected to a SMART interactive product, SMART Ink starts automatically when you start your computer and the SMART Ink toolbar appears in the title bar of each open window on your computer.

Use the toolbar to select ink properties for that window and to perform common tasks such as capturing your notes.

About your SMART software

SMART Ink and SMART Product Drivers are included with SMART Notebook collaborative learning software and SMART Meeting Pro software.

SMART Product Drivers

SMART Product Drivers enables your computer to detect input from your interactive flat panel.

SMART Ink works with SMART Product Drivers to enable you to write on your screen in digital ink using your interactive flat panel's pen or your finger.

NOTE

In most cases, SMART Product Drivers installs automatically when you install your SMART software. To ensure you have the most recent version of SMART Product Drivers installed, see *Updating SMART Product Drivers* on page 49.

SMART Notebook software

You can write in SMART Notebook software using your SMART interactive product's pen or your finger. The ink becomes part of your .notebook file. For more information, see the SMART Notebook software support page for Windows (smarttech.com/SupportNotebook11Windows) or SMART Notebook software support page for Mac OS X operating system software (smarttech.com/SupportNotebook11Mac).

SMART Meeting Pro software

You can write in SMART Meeting Pro software's Whiteboard mode using your SMART interactive product's pen or your finger. The ink becomes part of your .notebook file. For more information, see the SMART Meeting Pro support page (smarttech.com/SupportMeetingPro3Windows).

Writing or drawing in digital ink

Using the pen supplied with your interactive flat panel, you can write or draw digital ink over SMART software and other programs.

To write or draw digital ink

1. Pick up the pen.
2. Write or draw on the screen.

TIP

Don't rest your elbow or the palm of your hand on the screen whilst you're writing.

Entering text on the interactive flat panel

You can enter text in text boxes on the interactive flat panel using the on-screen keyboard or a keyboard attached to your computer.

To enter text

1. Select the area where you want to enter text using your finger or a mouse connected to the computer.
2. Type on a connected keyboard or on-screen keyboard.



TIP

Press the keyboard button on the interactive flat panel to open the on-screen keyboard.

Changing pen settings

You can change your pen settings, including line size and fill effects.

To change pen settings

1. Press the **SMART Board** icon  in the notification area (Windows operating systems) or the Dock (Mac OS X operating system software).

OR

Press the **SMART Meeting Pro** icon  in the notification area.

2. Press **SMART Settings**.
3. Select **Pen and Button Settings** in the drop-down list.

4. Press **Black Pen Settings**  to customise the black pen.

Press **Blue Pen Settings**  to customise the blue pen.

Press **Red Pen Settings**  to customise the red pen.

Press **Green Pen Settings**  to customise the green pen.

The *Properties* dialogue box appears.

5. Press **Line Style**.
6. Adjust the colour, thickness, line end and line style.
7. Press **Fill Effects**.
8. Adjust the transparency.
9. Press **Save Tool Settings** to save your settings.
10. Optionally, repeat steps 4 to 9 to customise other pens.
11. Press **OK** to close SMART Settings.

Using Locked Ink mode

Locked Ink mode enables you to write or draw digital ink using large objects, including eraser-sized objects.

CHAPTER 5

Using your interactive flat panel

■ To use Locked Ink mode

Press and hold a colour button on the colour select module until the light flashes.

■ To end Locked Ink mode

Press any colour button that isn't flashing on your colour select module.

Erasing digital ink

■ To erase digital ink

Pick up the eraser and then press the eraser on the screen and move it over the digital ink that you want to erase.

OR

Using your flattened fist, press the screen and move your hand over the digital ink that you want to erase.



Changing eraser settings

You can change the eraser size for either a larger or smaller eraser area.

■ To change eraser settings

1. Press the **SMART Board** icon  in the notification area (Windows operating systems) or the Dock (Mac OS operating system software) and then select **SMART Settings**.

OR

Press the **SMART Meeting Pro** icon  in the notification area and then select **SMART Settings**.


2. Press **SMART Hardware Settings**.
3. Select **Pen and Button Settings** in the drop-down list.
4. Press **Eraser Settings** .
5. Select an eraser size.
6. Press **OK** to save your settings.
7. Press **OK** to close SMART Settings.

Manipulating objects

Objects include icons, buttons, links and other components of programs that appear on your screen. You can manipulate these objects on your interactive flat panel as described below.

■ To select or clear the selection of an object

Quickly press and release the object.




NOTES

- This gesture performs a standard mouse click.
- This gesture starts programmes if your operating system is set to start applications on a single click.

■ To double-click an object

Quickly press and release the object twice in the same spot.




i NOTE

This gesture starts programs if your operating system is set to start applications on a double-click.

■ To right-click or Control-click an object

Press and hold the object.




OR

CHAPTER 5

Using your interactive flat panel

Using two fingers on the same hand, press and hold the object with your left finger and then press the screen once with your right finger.



OR


Press the **Right-Click** button on the pen tray and then press the object.

■ To move an object

1. Press and hold the object.
2. Keeping your finger on the screen, slowly move the object.
3. When you reach the position that you want to move the object to, release your finger.


■ To resize an object

1. Using one finger on each hand, press the screen at opposite ends of the object.
2. Drag your fingers in opposite directions to enlarge the object.



OR

Drag your fingers toward each other to reduce the object.




■ To rotate an object

1. Using one finger on each hand, press the screen at opposite ends of the object.
2. Rotate your fingers in the direction that you want to rotate the object.

CHAPTER 5

Using your interactive flat panel




3. When you reach the angle that you want to rotate the object to, release your fingers.

Browsing

In addition to manipulating objects, you can browse content on your screen.


■ To display the next page

Press the screen and then quickly press again directly to the right of that point.




OR

Quickly flick your finger right across the screen.




■ To display the previous page

Press the screen and then quickly press again directly to the left of that point.




OR

Quickly flick your finger left across the screen.




■ To zoom in or out

1. Using one finger on each hand, press the screen at opposite ends of the object.
2. Drag your fingers in opposite directions to zoom in.



OR

Drag your fingers towards each other to zoom out.




■ To pan horizontally or vertically

1. Using two fingers on the same hand, press and hold the screen.
2. Keeping your fingers on the screen, move up, down, left or right.

CHAPTER 5

Using your interactive flat panel



3. When you reach the area that you want to view, release your fingers.

Playing audio files on your interactive flat panel

Your interactive flat panel includes two speakers that play audio files or the audio portion of a video file.

When you play an audio file or a video file on a computer connected to your interactive flat panel, the file is streamed through the USB connection between your computer and your interactive flat panel, not through the video connection.



IMPORTANT

If your computer uses Mac OS X operating system software, you must set the audio output to USB.

■ To switch your Mac computer to USB audio output


1. Press the **Apple** menu  and then select **System Preferences**.
2. Press **Sound** under the Hardware section.
3. Press the **Output** tab.
4. Select **SBID 8055i/USB**.
5. Close System Preferences.

Using the USB port

You can connect a USB drive or device to the USB A port on the side terminal panel on your interactive flat panel, and then access it from computer 1 connected to VGA 1 and USB 1.

i NOTE

To disable the USB A port on the side terminal panel, see *Disabling the USB port on the side terminal panel* on page 19.



■ To use the USB port

1. Press the **VGA 1** button on the remote control.

Press the **Input** button  on the front control panel until the input source is VGA 1.

2. Connect a USB device to the USB port.
3. Use computer 1 to access the content on your USB device.

Chapter 6

Using guest laptops with your interactive flat panel


Connecting a guest laptop	43
Using a SMART GoWire cable	44
Connecting computer 2	46

Connecting a guest laptop

You can connect a guest laptop to the side terminal panel of the interactive flat panel. When a guest laptop is connected, the laptop's desktop is displayed on the interactive flat panel and touch interactivity is enabled. For a diagram of the various computer options, see *Connecting computers to your interactive flat panel* on page 16.

IMPORTANT

The guest laptop must have SMART Product Drivers installed. If it does not, you will need to connect the laptop to the interactive flat panel using a SMART GoWire cable. If you purchased an SBID8055i-SMP or SBID8055ie-SMP model, you can use the supplied SMART GoWire cable to connect your guest laptop to the interactive flat panel. For more information, see *Using a SMART GoWire cable* on the next page.



To connect a guest laptop

1. Connect an HDMI cable from the guest laptop's HDMI input to your interactive flat panel's side terminal panel.
2. Connect a USB cable from the laptop's USB port to your interactive flat panel's side terminal panel.



IMPORTANT

The USB A port is for USB devices only. Do not connect the guest laptop to this port.

3. Turn on the laptop.
4. Press the **HDMI 2** input button on the remote control.

OR

Press the **Input** button  on the front control panel until the input source is HDMI 2.

To return to using computer 1

1. Press the **VGA 1** button on the remote control.

OR

Press the **Input** button  on the front control panel until the input source is VGA.

Press the **Input** button  on the front control panel until the input source is VGA 1.

2. Disconnect the guest laptop from the interactive flat panel if required.

Using a SMART GoWire cable

Any computer connected to your interactive flat panel requires SMART software. Typically, you install this software on your room computer so that it's always ready to use.

However, if you want to connect a laptop that doesn't have SMART software installed, you can connect a SMART GoWire cable from the laptop to the USB cable for your interactive flat panel. The SMART GoWire cable enables you to have touch control of your laptop and use SMART Meeting Pro software without installing the software on your laptop.

A SMART GoWire cable is included with SMART Board 8055i-SMP and 8055ie-SMP interactive flat panels.



IMPORTANT

Your interactive flat panel supports the SMART GoWire cable with SMART Meeting Pro software only. It does not support the SMART GoWire cable with SMART Notebook software.

To use a SMART GoWire cable

1. Connect a video cable from your interactive flat panel to your laptop.
2. Connect the USB cable from the USB port on your interactive flat panel to your laptop.
3. Change the video input to your laptop's video connection using the remote control or the front control panel.
4. Disconnect the USB cable from your laptop and then connect it to the SMART GoWire cable's USB A port.



IMPORTANT

If the SMART GoWire cable is not connected to your interactive flat panel through a USB cable, you have access to SMART Meeting Pro software on your laptop for five minutes, and then the software closes.

5. Connect the SMART GoWire cable's USB connector to your laptop.

The *AutoPlay* dialogue box appears.

6. Select **Start SMART Meeting Pro**.

SMART Meeting Pro software starts. You have touch control of your laptop on your interactive flat panel and can use SMART Meeting Pro software while your laptop is connected to your interactive flat panel.

To disconnect a SMART GoWire cable

1. If required, save your SMART Meeting Pro software file to your laptop. You can save the file as a .ppt, .pdf or .notebook file.



IMPORTANT

You can open a .notebook file on a computer that has SMART Meeting Pro software or SMART Notebook software installed or that is connected to a SMART product through a SMART GoWire cable only.

2. Press the **SMART Meeting Pro** icon  in the notification area and then select **Exit**.
3. Disconnect the SMART GoWire cable from your laptop and the USB cable.

Connecting computer 2

You can connect a second laptop to the installed USB cable and video cable that is connected to the back terminal panel of your interactive flat panel. If those cables aren't installed, connect the laptop to the side terminal panel (see *Connecting a guest laptop* on page 43). For a diagram of the various computer options, see *Connecting computers to your interactive flat panel* on page 16.



IMPORTANT

The laptop must have SMART Product Drivers installed. If it doesn't, you need to connect the laptop to the interactive flat panel using a SMART GoWire cable. If you purchased an SBID8055i-SMP or SBID8055ie-SMP model, you can use the supplied SMART GoWire cable to connect your laptop to the interactive flat panel. For more information, see *Using a SMART GoWire cable* on page 44.

■ To connect computer 2

1. Place the laptop beside the ends of the cables at the computer 2 connection.
2. Connect the installed USB cable to a USB port on the laptop.
3. Connect the VGA cable connector to the laptop.
4. Turn on the computer.
5. Press the **VGA 2** button on the remote control.

OR

Press the **Input** button  on the front control panel until the input source is VGA 2.

■ To return to using computer 1

Press the **VGA 1** button on the remote control.

OR

Press the **Input** button  on the front control panel until the input source is VGA 1.

Chapter 7

Maintaining your interactive flat panel

Updating your SMART software and firmware	47
Updating SMART software	47
Updating your interactive flat panel firmware	48
Updating SMART Product Drivers	49
Calibrating your interactive flat panel	50
Orientating your interactive flat panel	51
Replacing a pen nib	51
Cleaning the screen	52
Cleaning the presence detection sensors	52
Cleaning the camera windows and reflective tape	53
Maintaining ventilation	53
Preventing condensation	54
Checking the interactive flat panel installation	54
Removing your interactive flat panel	54
Transporting your interactive flat panel	56

If you properly maintain your interactive flat panel, it will provide years of use.

Updating your SMART software and firmware

To use touch control and digital ink on your interactive flat panel, you require SMART software on your computer and up-to-date firmware on your interactive flat panel.

Updating SMART software

Once you have SMART software installed on your computer, you can check for software updates with SMART Product Update by selecting **Help > Check for Updates** in the software or by browsing to smarttech.com/downloads.

To check for software updates

1. Start your SMART software program.
2. Click **Help > Check for Updates**.



IMPORTANT

If you do not see the *Check for Updates* option, contact your network administrator.

3. Click the **Update** button beside the software that you want to update.

SMART software updates.



IMPORTANT

When you update SMART software on your computer, a firmware update for your interactive flat panel could download to your computer. The next time you connect your computer to your interactive flat panel you are informed that there is a firmware update for the processor in the interactive flat panel. For more information, see *Updating your interactive flat panel firmware* below.

Updating your interactive flat panel firmware



CAUTION

Only a system administrator should update interactive flat panel firmware.

Your interactive flat panel uses firmware on its processor. Once you have updated SMART software, a new firmware executable file will be saved on your computer. When you connect a computer with this file to your interactive flat panel, your interactive flat panel detects this executable file and then prompts you to run the file to update the firmware.



CAUTION

- Only one interactive flat panel can be connected to the computer during the firmware update process.
- Do not disconnect your interactive flat panel from your computer during the firmware update process.
- Do not touch your interactive flat panel's screen or input button during the firmware update process.
- Do not turn off your computer or your interactive flat panel during the firmware update process.

To update your interactive flat panel firmware

1. Ensure your interactive flat panel is connected to your computer.
2. Launch the firmware updater at the following location:

Windows computers: **C:\Program Files\SMART Technologies\SMART Product Drivers\SMARTFirmwareUpdater.exe.**

Mac computers: **HD\Applications\SMART Product Drivers\SMARTFirmwareUpdater.app.**
3. Follow the on-screen instructions using your computer's mouse and keyboard. Don't touch the interactive flat panel screen.
4. Select the tickbox for the SMART interactive product that you want to update and then click **Next**.

A progress bar appears.

NOTE

SC 14 refers to the SMART Board 8000 series interactive flat panel's serial controller.

5. When the installation is complete, calibrate your interactive flat panel. See *Calibrating your interactive flat panel* on the next page

Updating SMART Product Drivers

To use touch control and digital ink on your interactive flat panel, you require SMART Product Drivers 11 or later on your computer.

To update SMART Product Drivers

1. Click the **SMART Board** icon  in the notification area (Windows operating systems) or the Dock (Mac OS X operating system software) and then select **Check for Updates and Activation**.

OR

Click the **SMART Meeting Pro** icon  in the notification area and then select **Check for Updates and Activation**.

The *SMART Product Update* window appears.

2. If your version of SMART Product Drivers is up to date, click **OK**.

If your version of SMART Product Drivers needs to be updated, click **Update**.
3. Follow the on-screen instructions to update SMART Product Drivers to the latest version.

Calibrating your interactive flat panel

Digital cameras in the corners of the interactive flat panel track the position of the pens, eraser and your finger on the interactive surface, and then send the information to the SMART software, which interprets this information as mouse clicks, digital ink or ink removal in the appropriate location. Calibration determines the position and angles of the cameras to accurately identify the location of touches on your interactive flat panel.



IMPORTANT

If an error message appears while you are calibrating your interactive flat panel, contact SMART Support (smarttech.com/contactsupport).

To calibrate your interactive flat panel

1. Press the **SMART Board** icon  in the notification area (Windows operating systems) or the Dock (Mac OS X operating system software).

OR

Press the **SMART Meeting Pro** icon  in the notification area.

2. Select **SMART Settings**.

SMART Settings appears.

3. Press **SMART Hardware Settings**.

4. If you have more than one SMART product connected, select the interactive flat panel.

5. Select **Advanced Settings** from the drop-down list.

6. Press **Calibrate**.

The calibration screen appears. This can take a few moments.

7. Press the red target with the tip of an interactive flat panel pen. Hold the tip at the centre of the target until the target turns green and then lift the pen.

The target moves to the next location.



NOTE

You can calibrate a target again by pressing the LEFT ARROW key on your keyboard, or the **Keyboard** button or **Right-click** button on the colour select module.

8. Continue pressing targets until the calibration is complete.

A message appears stating that the calibration was successful and then the orientation screen appears.

9. Orientate your interactive flat panel.

Orientating your interactive flat panel

When the location of your touch is misinterpreted (a pointer appears a distance from the actual contact), orientate your interactive flat panel.

To orientate the interactive flat panel

1. Press the orientation button  on the colour select module.
The orientation window opens.
2. Use an interactive flat panel pen to press the red targets as they appear. Hold the tip of the pen at the centre of each target and then lift the pen. When you lift the pen, the target moves to the next orientation point.



IMPORTANT

Hold the pen perpendicular to the screen.

3. Continue until you've pressed all the targets.
The orientation window closes.

If this doesn't correct inaccurate touch control, calibrate your interactive flat panel. For more information, see *Calibrating your interactive flat panel* on the previous page.

Replacing a pen nib

To prevent damage to your interactive flat panel's anti-glare coating, replace your pen nib if it becomes worn. Four replacement pen nibs are included with your pens and you can purchase additional replacements from your authorised SMART reseller (smarttech.com/where).

To replace a pen nib

1. Grasp the worn nib on your pen with a pair of pliers and then pull and twist the nib loose.
2. Press the replacement nib into the pen.

Cleaning the screen

Follow these instructions to clean the interactive flat panel screen without damaging its anti-glare coating or other product components.

CAUTION

- Do not use permanent or dry-wipe markers on the screen. If dry-wipe markers are used on the screen, remove the ink as soon as possible with a lint-free, non-abrasive cloth.
- Do not rub the screen with a dense or rough material.
- Do not apply pressure to the screen.
- Do not use cleaning solution or glass cleaner on the interactive flat panel screen, as they can deteriorate or discolour the screen.
- Avoid touching the silver reflective tape between the screen and the bezel and ensure that it stays dry. Damage to this strip affects touch interactivity.

To clean the interactive flat panel screen

1. Shut down your computer and then disconnect the power sources for your computer and your interactive flat panel.
2. Wipe the screen with a lint-free, non-abrasive cloth.

Cleaning the presence detection sensors

The interactive flat panel has two presence detection sensors on its frame. The sensors should be inspected annually for dust and should be cleaned if any obvious dust buildup has occurred.

CAUTION

Do not use compressed air, water, chemical agents or cleaning agents to clean the sensors.

To clean the sensors

Gently wipe the sensors using a clean lint-free cloth.

Cleaning the camera windows and reflective tape

The DViT technology in your interactive flat panel uses four cameras in the corners of the frame and the reflective material between the screen and the bezels. Excessive dust buildup on the camera windows or reflective tape can impair touch performance.

These areas should be inspected annually for dust and should be cleaned if any obvious dust build-up has occurred.

CAUTION

- Do not use compressed air to clean the camera windows or borders.
- Do not use water, chemicals or cleaning agents.

To clean the camera windows and reflective tape

1. With a clean lint-free cloth, gently wipe the camera windows in the top corners and the reflective tape along the top of your interactive flat panel screen using the cloth.
2. Gently wipe the reflective tape along the sides of your interactive flat panel screen.
3. Gently wipe the camera windows in the bottom corners and the reflective strip across the bottom of your interactive flat panel screen.

Maintaining ventilation

Your interactive flat panel requires ventilation to enable the cooling fans to function. Dust buildup in the ventilation holes compromises cooling and leads to product failure.

CAUTION

Avoid setting up or using your interactive flat panel in an area with excessive levels of dust, humidity or smoke.

- Clean accessible ventilation holes monthly with a dry cloth.
- Use a vacuum cleaner with a narrow hose end fitting to clear the back ventilation holes annually. You might have to remove the interactive flat panel from your wall. For more information on removing your interactive flat panel see *Removing your interactive flat panel* on the next page.

Preventing condensation

Your interactive flat panel screen contains layers of glass that can collect condensation, especially in the following conditions:

- Temperature extremes with high humidity
- Rapid changes in humidity, which can occur when you operate the product near water, such as a sink, pool, kettle or air conditioner ventilator
- Direct exposure to sunlight

■ To evaporate condensation from your interactive flat panel

1. Remove the humidity source from the interactive flat panel, if possible.
2. Adjust the room temperature to normal operating ranges.
3. Turn on the interactive flat panel for 2–3 hours.

If the screen condensation doesn't evaporate, contact SMART Support (smarttech.com/contactsupport).

Checking the interactive flat panel installation

Inspect your interactive flat panel installation frequently to ensure that it remains securely installed.

- Check the mounting location for signs of damage or weakness that can occur over time.
- Check for loose screws, gaps, distortions or other issues that could occur with the mounting apparatus.

If you find an issue, refer to a professional installer.

Removing your interactive flat panel

To safely remove your interactive flat panel, use two or more professional installers.



IMPORTANT

Follow the instructions included with the floor stand or mounting apparatus.

■ To remove the interactive flat panel

1. Turn off your interactive flat panel and unplug the power cable from the wall socket.
2. Remove all accessible cables and connectors.

CHAPTER 7


Maintaining your interactive flat panel



WARNING

- Do not move the interactive flat panel by connecting a rope or wire to the handles on the back. The interactive flat panel can fall and cause personal injury and product damage.

- There are two lifting handles on the back of the interactive flat panel, one on each side. With one person at each end, use one hand each on the handle to support the weight of the interactive flat panel and the other hand on the upper side to balance it during lifting. The interactive flat panel weighs about 44.5kg (98 lb) .



- Lift your interactive flat panel from its mounting location.



CAUTION

- Do not allow the weight of the interactive flat panel to rest on the colour select module because it is not designed to support product weight.
- Do not leave the interactive flat panel face up, face down or upside down for an extended period of time as it could cause permanent damage to the screen.
- Do not place the interactive flat panel on a sloping or unstable trolley, stand or table, because the interactive flat panel could fall, resulting in injury or severe product damage.

Transporting your interactive flat panel

Save your original packaging so that you can repack your interactive flat panel with as much of the original packaging as possible. This packaging was designed with optimal shock and vibration protection. If your original packaging isn't available, you can purchase the same packaging directly from your authorised SMART reseller (smarttech.com/where).

CAUTION

Transport your interactive flat panel only in original or replaced packaging. Transporting your interactive flat panel without correct packaging voids your warranty and could lead to product damage.

Chapter 8

Troubleshooting for your interactive flat panel

Resolving image issues	57
Diagnosing blank screen issues using the front control panel lights	57
Resolving poor image quality	59
Resolving touch control and digital ink issues	61
Resolving audio issues	64
Resolving remote control issues	65
Troubleshooting presence detection	65
Resolving issues using the SMART Connection Wizard	67
Resolving issues using SMART Board Diagnostics	67
Checking the camera view	67

This chapter provides you with the information necessary to solve simple issues that can occur with your interactive flat panel. If issues persist, or aren't covered in this chapter, contact SMART Support (smarttech.com/contactsupport).

Resolving image issues

Complete the following steps if your interactive flat panel doesn't display an image correctly or doesn't display any image at all.

Diagnosing blank screen issues using the front control panel lights

Use the following troubleshooting table when your computer is turned on, but you don't see an image on the interactive flat panel screen.

Begin by looking at the interactive flat panel system status light and the power light in the front control panel.

Power light	Status light	Causes	Solutions
Off	Off	The interactive flat panel isn't connected to a power source.	Connect your interactive flat panel's power cable to a power outlet (see page 17).

CHAPTER 8

Troubleshooting for your interactive flat panel

Power light	Status light	Causes	Solutions
		The main power switch is off.	Turn on the main power switch on the terminal panel (see page 6).
Solid red	Off	The interactive flat panel is turned off.	Press the power button on the front control panel or the remote control.
Solid amber or red	Red	The computer is off.	Turn on your computer.
		The computer isn't connected to your interactive flat panel.	Connect your computer to your interactive flat panel with the required cable (see page 16).
		The interactive flat panel isn't set to the correct video input source.	Select your computer's input source (typically VGA 1, VGA 2 or HDMI 2) using the remote control. OR Press the Power button  until the Input button  is blue and then press the Input source button until your computer's desktop appears.
Solid green	Flashing amber	The interactive flat panel is updating firmware.	Do not touch the interactive flat panel. For more information, see page 47.
Solid green	Flashing green	The interactive flat panel detects a computer, but SMART Product Drivers isn't installed or isn't running. (For more information, see page 61).	Install SMART software on your computer (see page 21) or install a SMART GoWire cable (see page 44).
Solid green	Solid green	The interactive flat panel detects a computer with SMART Product Drivers installed.	Normal operation.

Resolving poor image quality

Symptom	Causes	Solution
The image is too large, too small or doesn't completely fill the screen.	The computer's video resolution settings don't match your interactive flat panel's native resolution.	The interactive flat panel's native resolution is 1920 × 1080 at 60 Hz. If your computer can't support this resolution, consider one of the following 16:9 resolutions as an alternative: • 1600 × 900 • 1366 × 768 • 1280 × 720 Other resolutions could result in image distortion or black bars around the desktop.
The screen resolution is correct, but the image is surrounded by black bars.	The computer's video card is underscanning the image.	Turn off or adjust the overscan/underscan feature in the video card driver software until the image fits the screen resolution. Refer to your computer's video card help for more information. i NOTE If available, select the HDTV setting (ideally 1080p) from your video card driver's advanced menu. This should provide a pixel-perfect image for your interactive flat panel.
	You have a poor quality video cable.	1. Replace your video cable with a better quality video cable. 2. Press the AUTO SET UP button on your remote control to reset your interactive flat panel. OR Press MENU on the menu control panel and then select ADJUST > AUTO SETUP in the on-screen display menu using the buttons on the menu control panel. (For more information, see page 69)
	You connected two video cables together.	1. Replace your two cables with one longer cable. OR Move your computer so that it's within a single cable length of your interactive flat panel. 2. Press the AUTO SET UP button on your remote to reset your interactive flat panel. OR Press MENU on the menu control panel and then select ADJUST > AUTO SETUP in the on-screen display menu using the buttons on the menu control panel. (For more information, see page 69)

CHAPTER 8

Troubleshooting for your interactive flat panel

Symptom	Causes	Solution
The image isn't centred on the screen.		Press the AUTO SET UP button on the remote control. OR Press MENU on the menu control panel and then select ADJUST > AUTO SETUP in the on-screen display menu using the buttons on the menu control panel. (For more information, see page 69)
The image is unstable or unfocused.	The video connection is loose.	Secure the video cable to both your computer and your interactive flat panel.
	You have a poor quality video cable	1. Replace your video cable with a better quality video cable. 2. Press the AUTO SET UP button on the remote control to reset your interactive flat panel. OR Select MENU > ADJUST > AUTO ADJUST on the menu control panel. (For more information, see page 69.)
	You connected two video cables together.	1. Replace your two cables with one longer cable. OR Move your computer so that it's within a single cable length of your interactive flat panel. 2. Press the AUTO SET UP button on your remote to reset your interactive flat panel. OR Press MENU on the menu control panel and then select ADJUST > AUTO SETUP in the on-screen display menu using the buttons on the menu control panel. (For more information, see page 69)
	Your computer's video display card is defective.	Connect a different computer to your interactive flat panel. If this improves the image quality, consider replacing the video card in the original computer.
The image is too light, too dark or has poor image quality issues.	You might have incorrect video settings.	Press MENU on the menu control panel and then select PICTURE > AUTO ADJUST in the on-screen display menu using the buttons on the menu control panel. (For more information, see page 69.)

Symptom	Causes	Solution
There is a persistent image on the screen.	An image was displayed for too long.	Turn off your interactive flat panel and leave it turned off for as long as the image was on the screen. TIP Use a screen saver to avoid persistent images.
Other display quality issues		Press MENU on the menu control panel and then select SETUP > FACTORY PRESET in the on-screen display menu using the buttons on the menu control panel. (For more information, see page 69.)

Resolving touch control and digital ink issues

Use the following troubleshooting table if you can see your computer desktop on your interactive flat panel, but you do not have touch control over the desktop.

For more information, see *SMART Ink user's guide for Mac OS X operating system software* (smarttech.com/kb/170192) or *SMART Ink user's guide for Windows operating system* (smarttech.com/kb/170191).

Symptom	Causes	Solution
When you touch the screen, no pointer appears and you can't move icons. The status light is red.	The SMART Product Drivers on your computer are not current.	Update your SMART Product Drivers (see <i>Updating SMART Product Drivers</i> on page 49).
	No USB connection from the computer to the interactive flat panel.	Verify your connections (see page 16).
	Your USB connection doesn't correspond with the selected video input.	Connect the USB to the correct port that corresponds to your computer's video input. (For more information, see page 16.)
The SMART Meeting Pro icon  or the SMART Notebook icon  doesn't appear.	SMART Product Drivers isn't installed.	Download and install SMART software from smarttech.com/downloads . OR Connect your computer or laptop to your interactive flat panel with a SMART GoWire cable. (For more information, see page 44.)

CHAPTER 8

Troubleshooting for your interactive flat panel

Symptom	Causes	Solution
	SMART software isn't running.	Open the SMART Product Drivers folder in your list of programs and then select SMART Board Tools .
The SMART Board icon  or SMART Meeting Pro icon  is crossed out in red.	Your computer can't find your interactive flat panel.	Start SMART software and then run the SMART Connection Wizard's troubleshooting procedures.
	Either the <i>SMART Board Diagnostics</i> window or <i>SMART Settings</i> is open.	Close the SMART Board Diagnostics window and the SMART Settings panel.
Touch interactivity is slow or sluggish.	Your computer is running too many applications.	Close some open applications.
	Your computer doesn't meet system requirements.	Upgrade your computer or replace it with a more powerful computer.
	You haven't used a USB 2.0 cable to connect your interactive flat panel to your computer.	Use a USB 2.0 cable and ensure that it is connected to a USB 2.0 port on your computer.
When you touch the screen the pointer appears in the wrong location.	You aren't touching the screen at right angles.	For more information, see <i>Touching and drawing on your SMART Board interactive whiteboard is Inaccurate</i> (smarttech.com/kb/131299).
	Your interactive flat panel isn't orientated.	Orientate your interactive flat panel. Press the orientate button  on the colour select module and then follow the on-screen instructions. (For more information, see page 51.)
	Your desktop isn't centred on the screen.	Press the AUTO SET UP button on your remote control to reset your interactive flat panel. OR Press MENU on the menu control panel and then select ADJUST > AUTO SETUP in the on-screen display menu using the buttons on the menu control panel. (For more information, see page 69)
 IMPORTANT You might have to do this more than once.		

CHAPTER 8

Troubleshooting for your interactive flat panel

Symptom	Causes	Solution
An area of the screen doesn't respond to your touch or when you draw digital ink, the lines are broken.	Something is blocking the cameras.	Ensure that nothing is taped to the screen.
	Something is on the reflective tape channel.	Remove items from the reflective tape channel.
	Your finger or pen is skipping as you draw. This is most common on the upstroke.	Use consistent pressure whilst drawing digital ink.
	Bright lights are interfering with the cameras.	Close blinds or shades or dim all halogen lights and LEDs.
	Your cameras require calibration, possibly due to temperature change in the room.	Calibrate your interactive flat panel. (See page 50.)
You try to erase using something other than the eraser, but you draw more digital ink. One of the colour select button lights is flashing.	You're in Locked Ink mode and all objects are interpreted as pens.	Press a colour select button that isn't flashing to exit Locked Ink mode. OR Remove the eraser from the eraser holder to enable erasing while in Locked Ink mode.
You try to erase with the eraser, but you draw more digital ink. You don't see a flashing light on the colour select module.	You're using an edge of the eraser.	Increase the contact area of your eraser.
You're trying to draw digital ink, but you see a circle beneath your pointer and you're erasing digital ink.	Your interactive flat panel is interpreting an eraser.	Lift other fingers and the heel of your hand from the interactive flat panel whilst you write because the interactive flat panel is interpreting them as an eraser. OR Use a smaller pointer, such as the pen.

Resolving audio issues



IMPORTANT

Ensure you can see your computer's desktop and have touch control and digital ink before using this table. If not, resolve those issues before completing the following steps in the table below.

Symptom	Causes	Solution
Sound doesn't play when you play a sound file.	Your computer is muted.	Turn off the mute setting.
	Your computer's volume is too low.	Turn up the volume on your computer.
	Your interactive flat panel is muted.	Turn off the mute setting using the remote control or the front control panel.
	Your interactive flat panel's volume is too low.	Use the remote control to turn up the volume on your interactive flat panel. OR Use the volume control on the front control panel.
	The wrong audio input is selected for the video input.	Select the correct audio input. Press AUDIO INPUT on the remote control.
	Your computer uses Mac OS X operating system software and is not set to Audio USB output.	Set your computer's audio output to USB. (For more information, see page 41.)

Resolving remote control issues

Your remote control provides control of your interactive flat panel up to 7m (23') from the front control panel of your interactive flat panel.

Symptom	Causes	Solution
The remote control behaves unexpectedly. The front control panel power button light is off.	Your interactive flat panel isn't receiving power.	Ensure that your interactive flat panel is plugged in and that the power switch on the bottom terminal panel is in the ON position. (For more information, see page 6.)
	You are outside the range of the infrared remote control sensor.	Move to within 7m (23') and a 30° arc of your infrared remote control sensor.
	The remote control batteries need to be replaced.	Replace the batteries. (For more information, see page 26.)
	The remote control is damaged.	Contact your authorised SMART reseller (smarttech.com/where) to inquire about a replacement remote control.

Troubleshooting presence detection

The sensors for presence detection can detect when people are within 5m (16') of the interactive flat panel and automatically turn on or off the interactive flat panel.

Symptom	Causes	Solution
Your interactive flat panel isn't turning on.	The sensors aren't enabled.	Enable presence detection. See <i>Proximity control settings</i> on page 72.
	There isn't enough of a temperature difference between the ambient temperature and human body temperature.	Reduce the room temperature.
	You aren't within 5m (16') of the interactive flat panel.	Move closer to the interactive flat panel or make bigger motions.
	Glass, acrylic or other similar material is between the person and the sensors.	Remove the material.

CHAPTER 8

Troubleshooting for your interactive flat panel

Symptom	Causes	Solution
Your interactive flat panel isn't turning off when people have left the room.	The sensors aren't enabled.	Enable presence detection. See <i>Proximity control settings</i> on page 72.
	There isn't enough of a temperature difference between the ambient temperature and human body temperature.	Reduce the room temperature.
Your interactive flat panel is turning on after it has been turned off.	The re-enable time is too short for you to exit the room before the sensors start detecting motion again.	Increase the RE.ENABLE TIME setting. See <i>Proximity control settings</i> on page 72.
	There isn't a large enough temperature difference between the ambient temperature and human body temperature.	Reduce the room temperature.
	Sunlight is hitting the sensors.	Close any blinds or shades.
	Glass, acrylic or other similar material is between the person and the sensors.	Remove the material.
Your interactive flat panel is turning on when people are not present.	There's a sudden temperature change in the room (humidifier emission, air conditioning, heating system).	Remove the source of major temperature fluctuation.
	Sunlight is hitting the sensors.	Close any blinds or shades.
Your interactive flat panel is turning off when people are present.	Over time, the sensors average the room temperature so people's body temperature becomes part of the ambient temperature.	Increase the AUTO POWER OFF setting. See <i>Proximity control settings</i> on page 72.

Resolving issues using the SMART Connection Wizard

You can resolve a variety of issues using the SMART Connection Wizard found in SMART Settings.

■ To start the SMART Connection Wizard

1. Press the **Help** button on the colour select module.

The *Help and Support for Your SMART Board Interactive Whiteboard* window opens.

2. Press **Connection Wizard**.

The *SMART Connection Wizard* opens.

NOTE

You can also access the SMART Connection Wizard by pressing the **SMART Board** icon  in the notification area (Windows operating systems) or the Dock (Mac OS X operating system software) and then selecting **SMART Settings > Connection Wizard**.

OR

Click the **SMART Meeting Pro** icon  in the notification area then select **SMART Settings > Connection Wizard**.

3. Select **SMART Board 8000 series interactive flat panel** and then press **Next**.
4. Select the option that best describes the issue that you're encountering and follow the on-screen instructions to troubleshoot your interactive flat panel.

Resolving issues using SMART Board Diagnostics

If you touch the interactive flat panel's surface and nothing happens, or if there is no digital ink or the ink appears in some locations and not in others, use SMART Board Diagnostics to help identify and resolve these issues.

IMPORTANT

Do not change diagnostic settings unless asked to do so by SMART Support.

Checking the camera view

If nothing happens when you touch the interactive flat panel's surface, check to make sure that nothing is blocking one of the cameras.

■ To check camera views

CHAPTER 8

Troubleshooting for your interactive flat panel

1. Press the **SMART Board** icon  in the notification area (Windows operating systems) or the Dock (Mac OS X operating system software).

OR

Press the **SMART Meeting Pro** icon  in the notification area.

2. Press **SMART Settings**.

SMART Settings opens.

3. Select **About Software and Product Support > Tools > Diagnostics**.

SMART Board Diagnostics opens.

4. In the *View* menu, select **SBX800/SBID8070i/SBID8055i Bar**.

The SBX800 group box appears in the *SMART Board Diagnostics* screen.

5. Press **View**.

The camera view screen appears.

6. Click **Update** to display the four camera views. This could take a few moments.

If one of the camera views remains black, the camera is blocked or can't locate the reflective tape on the interactive flat panel's inner frame.

7. Check the camera lens and ensure that nothing is blocking its view and that nothing is affixed to the interactive surface.

Appendix A

Adjusting video settings with the on-screen display menu

Changing settings in the OSD menu	69
Main menu settings	70
Picture settings	70
Adjustment settings	70
Audio settings	71
OSD settings	71
Setup settings	72
Proximity control settings	72

You can access the on-screen display (OSD) menu using either the remote control (see *Infrared remote control buttons* on page 28) or the menu control panel on the left side of the interactive flat panel (see *Left side view* on page 6).

Changing settings in the OSD menu

NOTE

You can adjust many of the interactive flat panel screen settings using the remote control.

To change settings in the OSD menu

1. Press the **MENU** button on the menu control panel or the remote control.
The on-screen menu appears.
2. Press the up and down arrows to select a menu.
3. Press **SET**.
4. Press the up and down arrows to select the setting that you want to change.
5. Press **SET**.

APPENDIX A

Adjusting video settings with the on-screen display menu

6. Press the right arrow to select the setting that you want to change and enter a setting sub-menu.
OR
Press the left arrow to decrease or the right arrow to increase the value.
OR
Press the left arrow or right arrow to select a value.
7. Press **SET**.
8. To change another setting in the menu, press the **MENU** button and then repeat steps 2–4.
9. When you finish changing settings, press the **MENU** button twice to close the on-screen display menu.

Main menu settings

Picture settings

Menu item	Function
PICTURE MODE	Sets picture mode to STANDARD, sRGB, SPORT, GAME, USER, AMBIENT and DYNAMIC.
BRIGHTNESS	Adjusts the overall brightness of the image and background.
CONTRAST	Adjusts the brightness of the image in relation to the background. The sRGB picture mode is standard and cannot be changed.
SHARPNESS	Adjusts the sharpness of the image.
BLACK LEVEL	Adjusts the brightness of the image in relation to the background. The sRGB picture mode is standard and cannot be changed.
TINT	Adjusts the tint of the screen.
COLOUR	Adjusts the colour depth of the screen.
COLOUR TEMPERATURE	Sets colour temperature to NORMAL, WARM, USER or COOL.
AMBIENT	Adjusts the AMBIENT settings when it is selected in PICTURE MODE.
NOISE REDUCTION	Adjusts the amount of noise reduction on the image.
PICTURE RESET	Restores the picture settings to their default values.

Adjustment settings

Menu item	Function
AUTO SETUP	Sets H Position, V Position and Clock Phase to adjust automatically when your interactive flat panel is turned on.

APPENDIX A

Adjusting video settings with the on-screen display menu

Menu item	Function
H POSITION	Controls the horizontal position of the image within the screen area.
V POSITION	Controls the vertical position of the image within the screen area.
CLOCK	Adjusts the width of the image.
PHASE	Adjusts the visual noise on the image.
INPUT RESOLUTION	Displays the signal at the desired resolution. After selecting this, use the AUTO SETUP option above.
LONG CABLE COMP	Adjusts the video signal for VGA video inputs if a long VGA cable is used.
ASPECT	Sets picture aspect to FULL, NORMAL, TRIM or ZOOM.
ADJUST RESET	Restores the adjustment settings to their default values.

Audio settings

Menu item	Function
BALANCE	Adjust the balance of left and right volume.
TREBLE	Adjusts the high frequency sound.
BASS	Adjusts the low frequency sound.
LINE OUT	Selects FIXED or VARIABLE audio line out.
AUDIO INPUT	Sets audio input source to IN1, IN2, IN3, HDMI or TV.
AUDIO RESET	Restores the audio settings to their default values.

OSD settings

Menu item	Function
LANGUAGE	Selects the language used by the OSD menu.
OSD TURN OFF	Turns the OSD menu off after a period of inactivity. The preset choices are 5–240 seconds.
OSD H-POSITION	Sets the horizontal position of the OSD menu.
OSD V-POSITION	Sets the vertical position of the OSD menu.
INFORMATION OSD	Selects whether the Information OSD menu is displayed.
MONITOR INFO	Displays the interactive flat panel's model number and serial number.
CARBON SAVINGS	Displays the estimated carbon saving information in kilograms.
OSD RESET	Restores the OSD settings to their default values.

APPENDIX A

Adjusting video settings with the on-screen display menu

Setup settings

Menu item	Function
POWER SAVE	When enabled, and there isn't a video input, the interactive flat panel displays No Signal for 25 seconds before turning off. i NOTE When you connect a DVI video cable, the video card might not stop sending digital data even if there is no image. In this case, the interactive flat panel doesn't enter Power Save mode.
STANDBY MODE	Lowers power consumption. Select either NORMAL or ECO STANDBY. 👉 IMPORTANT When ECO STANDBY mode is enabled, presence detection is disabled and you cannot wake the computer by touching the interactive flat panel's screen. i NOTE You can't use RS-232C Functions in ECO STANDBY mode.
DDC CI	ENABLE/DISABLE: turns the two-way communication and control of the interactive flat panel on or off.
SCAN MODE	Sets the scanning mode. Some video formats might require different modes to display the best image.
PROXIMITY CONTROL	Sets the proximity sensor settings. See <i>Proximity control settings</i> below.
HEAT STATUS	Displays the FAN, BRIGHTNESS and TEMPERATURE settings.
FAN CONTROL	Sets the cooling fan to protect the interactive flat panel from overheating. When selected, you can adjust the start temperature of the cooling fan and its speed.
USB SETTING	Configures the video and touch input. See <i>Configuring the video and touch input for your SMART Board 8055i interactive flat panel</i> (smarttech.com/kb/170190).
SETUP PRESET	Restores the setup settings to their default value.
FACTORY RESET	Restores OSD menu options to default values for all items, except for LANGUAGE.

Proximity control settings

The interactive flat panel has two presence detection sensors on its frame that can detect people up to 5m (16') away. When the sensors detect people, the interactive flat panel turns on. When the sensors no longer detect people, the interactive flat panel turns off.

APPENDIX A

Adjusting video settings with the on-screen display menu

The settings for the proximity sensors are a sub-menu in the Setup menu.

Menu item	Function
PROXIMITY	Turns the proximity sensors on the interactive flat panel on or off. If ECO STANDBY in the Setup menu is enabled, this feature is disabled.
RE-ENABLE TIME	Sets how long (1–10 minutes) the interactive flat panel will wait before detecting motion again. The default is 1 minute.
AUTO POWER OFF	Sets when (15–240 minutes) the interactive flat panel automatically turns off. The default is 60 minutes.
BRIGHTNESS	Sets the brightness of the welcome screen.

Appendix B

Hardware environmental compliance

SMART Technologies supports global efforts to ensure that electronic equipment is manufactured, sold and disposed of in a safe and environmentally friendly manner.

Waste Electrical and Electronic Equipment regulations (WEEE directive)

Electrical and electronic equipment and batteries contain substances that can be harmful to the environment and to human health. The crossed-out wheelie bin symbol indicates that products should be disposed of in the appropriate recycling stream and not as regular waste.

Restriction of Certain Hazardous Substances (RoHS directive)

This product meets the requirements of the European Union's Restriction of Certain Hazardous Substances (RoHS) directive 2011/65/EU.

Consequently, this product also complies with other regulations that have arisen in various geographical areas and that reference the European Union's RoHS directive.

Batteries

The remote contains a CR 2025 lithium battery. Recycle or dispose of batteries properly.

Perchlorate Material

Contains perchlorate material. Special handling may apply. See dtsc.ca.gov/hazardouswaste/perchlorate.

Packaging

Many countries have regulations restricting the use of certain heavy metals in product packaging. The packaging used by SMART Technologies to send products complies with applicable packaging laws.

Index

A

- Adjust settings See also Adjustment settings
- Adjustment settings 70
- audio files
 - playing 41
- Audio settings 71

B

- batteries 75
- bottom terminal panel
 - computer 1 video input 17
 - computer 2 video input 19
 - connecting a peripheral device 20
 - connections 7
 - speaker wire connections 8

C

- calibration 50
- cleaning
 - camera windows 53
 - proximity sensors 52
 - reflective tape 53
 - screen 52
- condensation 54
- connection
 - computer 1 17
 - computer 2 46
 - guest laptop 43
 - peripheral devices 20
 - room control system 15

D

- digital ink
 - drawing 31

- erasing 33
- writing 31
- disabling
 - USB port 19
- double-clicking 35

E

- European Union regulations 75

G

- gestures
 - next page 38
 - panning 40
 - previous page 39
 - resizing 37
 - rotating 37
 - zooming in and out 40
- GoWire See SMART GoWire cable

H

- HDMI connections 6-7

I

- Ink See SMART Ink
- Ink Aware See SMART Ink
- inside terminal panel
 - computer 1 USB input 17
 - computer 2 USB input 19
 - connections 8
 - room control system 15
- installation
 - choosing a location 11
 - choosing a mounting height 12
 - computer 2 connection 18
 - important information 10
 - SMART Notebook software 22

- SMARTMeeting Pro software 21
- speakers 14
- interactive flat panel
 - about 2
 - indicators and controls of 5
 - maintaining 47
 - using 23

L

- laptop
 - computer 2 connection 18
 - guest laptop connection 43
- left-clicking 34

M

- Mac OS X USB audio output 41
- menu control panel 6

O

- objects
 - resizing 37
 - rotating 37
- on-screen display See OSD
- on-screen display menu settings See OSD
- Settings
- orientation
 - about 51
- OSD
 - changing settings 69
- OSD settings 71

P

- packaging 75
- panning 40
- pen nib
 - replacing 51
- Picture settings 70
- proximity sensors
 - about 25
 - cleaning 52
 - troubleshooting 65

R

- remote control
 - about 26
 - buttons 28
 - installing batteries 26
 - sensor 27
- right-clicking 35
- RoHS directive 75

S

- Setup settings 72
- side terminal panel 6
- SMART Board interactive flat panels 30
- SMART GoWire cable 44
- SMART Ink 30
- SMART Ink Document Viewer 30
- SMART Ink Toolbar 30
- speaker wire connections 8, 14
- speakers
 - install 14

T

- transportation 56

U

- updating
 - interactive flat panel firmware 48
 - SMART Product Drivers 49
 - SMART software 47
- USB port
 - disable 19

V

- video connections 16

W

- WEEE directive 75

INDEX

Z

zoom 40

SMART Technologies

smarttech.com/support

smarttech.com/contactsupport