

User Manual for
Millar Mouse
Telemetry Systems



Wireless Solutions
for Physiological
Monitoring

Contents

Important Information	1
Disclaimer	1
Warranty	1
FCC Compliance	2
Introduction	4
Telemetry System Components	5
Quick Start Guide	6
Configurator System Setup	7
Configurator Software Installation	7
Connecting the Configurator	10
Configurator Software - Overview	11
tBase - Overview	13
tBase Laboratory Setup	14
Status lights	14
Analog Outputs and Calibration Values	15
The Mouse telemeter	16
Channel and serial numbers	16
System setup and configuration	17
Changing telemeter Channel	18
Changing tBase Channel	20
Positioning the telemeter during surgery	22
Telemeter Care and Handling	24
Diagnostics	25
tBase Technical Specifications	26
Telemeter Technical Specifications	27
Frequently Asked Questions	28
Contact Information	28

To all users;

We pride ourselves in partnering with you to achieve excellent results. If you have any questions related to the operation of your system, please contact us at **support@millar.com**

We are here to help.

Contact Information

US Head Office

Houston, Texas
Toll free (USA only) 1 800 669 2343
TEL: +1 832 667 7000
FAX: +1 713 714 8497

New Zealand Office

Auckland, New Zealand
TEL: +64 9 367 7126
FAX: +64 9 367 7157

EMAIL support@millar.com or sales@millar.com

WEB www.millar.com

Important Information

Disclaimer

Millar believes that information in this user manual is correct at the time of publishing. In the event errors may exist, Millar reserves the right to make changes to future editions without notice to holders of this edition. The reader should consult Millar if errors are suspected. In no event shall Millar be held liable for damages arising out of the use of this document or information contained within. Except as specified below, Millar makes no warranties, express or implied, and specifically disclaims any warranty of the products fitness for a particular purpose.

The customer's right to recover damages by fault or negligence of Millar are limited to the amount paid by the customer. Any action against Millar must be brought within one year after the cause of action accrues. Millar will not be held liable for any loss of data, research funding or profits and neither will it be liable for incidental or consequential damages even if advised of the possibility thereof.

Millar expresses that its products are for research purposes only. They are not designed with components and testing intended for use in medical treatment or diagnosis of humans or animals and doing so may result in serious harm.

Warranty

Telemeter Warranty

Millar warrants that at the time of sale and shipment to the original Purchaser, Millar mouse telemeters shall be free from defects in material and workmanship. This warranty voids on first use of the telemeter. If there is such a defect, Millar will, at no charge, replace the equipment as appropriate.

Telemetry Hardware Warranty

Millar warrants that at the time of sale to the original Purchaser, the telemetry hardware (excluding telemeters – see above) shall be free from defects in materials and workmanship for a period of one (1) year from its date of shipment to the original purchaser. If there is such a defect, Millar will, at no charge and at its option, either repair or replace the equipment as appropriate.

Should the hardware become damaged after expiration of the one year warranty, Millar will accept the product for a no charge evaluation with a signed RMA (return material authorization). If repairs are required, Millar will provide a detailed quote and lead time for the repair process. Repair work will not commence until approval is received from the customer.

As part of Millar's continued commitment to customer support, free online, phone and email support in the use of all telemetry equipment is available beyond all warranty periods.

The warranties above do not cover damage caused by failure to follow instructions for use, owner's abuse, misuse or negligence, user tampering or modifications, power failures or surges and events or accidents considered force majeure such as flooding, fire, etc. outside the reasonable control of Millar. In no case shall liability exceed the purchase price of the original product.

Millar provides free product evaluations during the warranty period and free return to customer shipment. All returned products should be packed safely, preferably in original packaging, cleaned/sterilized and shipped to Millar with the RMA number visible on the packaging and with all RMA documentation. In order to receive the highest level of support, the customer is responsible for notifying Millar immediately of a problem within the warranty period. Following product evaluation, Millar will replace *or repair (excluding telemeters which are non-repairable)* any product found to be defective and covered within the warranty period, while operated in accordance with instructions for use and specifications.

For complete product instructions, general insights and surgical recommendations, visit millar.com and access Millar's free online Knowledge Center. <http://millar.com/knowledge-center> Millar is committed to delivering the collaborative support you expect in facilitating scientific insight and advancing medical innovation.

Copyright © Millar, November 2016

This publication may not be reproduced or transmitted in any form, electronic or mechanical, including photocopying, recording, storing in an information retrieval system, or translating, in whole or in part, without the prior written consent of Millar.

FCC Compliance

Telemeter (MT10B)

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

1. This device may not cause harmful interference, and
2. This device must accept any interference received, including interference that may cause undesired operation.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Changes or modifications not expressly approved by Millar Inc. could void the user's authority to operate the equipment.

TR190 Configurator

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

1. This device may not cause harmful interference, and
2. This device must accept any interference received, including interference that may cause undesired operation.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Changes or modifications not expressly approved by Millar Inc. could void the user's authority to operate the equipment.

MT110 tBase

The Wireless Power Transfer System is FCC Part 18 Compliant

Note: This equipment has been tested and found to comply with part 18 of the FCC limits for non-consumer equipment. These limits are designed to provide reasonable protection against harmful interference in an industrial installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Note: There is no required maintenance of this device from a FCC compliance perspective.

The 2.4GHz Data Transmitter is FCC Part 15 Compliant

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

1. This device may not cause harmful interference, and
2. This device must accept any interference received, including interference that may cause undesired operation.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Changes or modifications not expressly approved by Millar Inc. could void the user's authority to operate the equipment.

Introduction

This User Manual contains information to help with the correct installation and basic use of the Millar Mouse Telemetry System. It is **strongly recommended that you also visit our online Knowledge Center** for more information and to view instructional videos showing telemeter implantation and recommendations for general use and care of your system. www.millar.com/knowledge-center

The Millar Mouse Telemetry system uses a unique and efficient patented inductive power transfer system for making long-term recordings in conscious mice (>22 g). No battery is required to wirelessly record high quality biological signals 24/7. Telemetered mice can be housed in a single room without the need for shielding as each mouse telemeter communicates with a tBase on one of 40 independent transmission frequencies (Channels).

The system comprises of a telemeter, tBase and Configurator System. The mouse biopotential telemeter measures the electrical potential (ECG, EMG, EEG) between the positive and negative leads and transmits the data wirelessly to the tBase. The tBase provides wireless power to the telemeter, acts as the receiver for the digital data (sampled at 2 kHz) transmitted by the telemeter and converts it to an analog signal. The Millar Mouse Telemetry System is therefore compatible with all acquisition systems with analog inputs. The Configurator System allocates telemeter and tBase data transmission frequencies and provides diagnostic information on the telemeter or tBase.

Due to continual product improvement, your system may look slightly different to the images and graphics contained in this manual. If you have any questions or need help please contact us at support@millar.com

Key Features

Accuracy:

For long term, high frequency physiological recordings. Digital wireless recording of data with the highest quality and signal integrity (sampling 2 kHz).

24/7:

Data can be collected 24 hours a day while the animal is on the tBase.

Versatility:

Telemeters send digital data wirelessly from within the animal to the tBase where it is converted to an analog signal compatible with existing data acquisition systems.

Low cost of ownership:

Millar mouse telemeters are single use items which eliminates the time and cost associated with telemeter explant and refurbishment.

Efficient housing:

Multiple animals can be housed in one location for simultaneous recordings. No specialized cages or shielding is required as each telemeter operates independently on one of 40 transmission frequencies.

Service & support:

Millar prides itself on being responsive to our customers' current and future needs. We have experienced engineers and scientists on staff to provide professional, expert and timely support and advice.

Telemetry System Components

The Mouse telemeter

All telemeters are shipped individually packaged, sterile and ready for use. The telemeters will need to be configured to a data collection Channel prior to implantation. PLEASE NOTE the telemeter does NOT need to be removed from its packaging for Configuration. *When handling the telemeter, care must be taken not to damage the telemeter body or lead wires as telemeters are non-repairable.*



The tBase

The tBase is able to detect the location of the telemeter within the operating area to efficiently provide power to the telemeter. For safe and normal operation of the tBase it needs to be placed on a flat non-metallic surface. There must not be any metal or another tBase within 10 cm of the tBase and we recommend at least a minimum of 40 cm separating distance above or below another tBase.



The Configurator System

The Configurator System (Configurator hardware and ConfigSoft software) wirelessly controls mouse telemeters and tBases to:

- Change/configure mouse telemeter and tBase transmission Channels (this must be done before implantation).
- Run and provide diagnostic information on mouse telemeters and tBases.

ONLY a single Configurator System is required to control all Millar (rat or mouse) telemetry systems in a laboratory. The Configurator System is not required for data acquisition. Note: Existing Millar rat telemetry customers with a Configurator System may only require a firmware and software update to their Configurator for use with the mouse telemetry system. Please contact support@millar.com for assistance.

**** IMPORTANT:** The ConfigSoft software supplied on the USB drive must be installed on a computer before connecting the Configurator hardware to the computer.



Quick Start Guide for Millar Mouse Telemetry System



1. Install ConfigSoft prior to connecting the Configurator

System requirements; Windows 7, 8 or 10 (USB 3.0 compatible).
Internet access may be required to install drivers. Insert USB drive and run ConfigSoft Setup.



2. Configurator Setup

The Configurator enables users to set the transmission channel of telemeters and tBases. The Configurator wirelessly communicates with the telemeter and tBase.

1. Attach aerial to rear of the Configurator.
2. Connect Configurator to computer via USB cable.



3. tBase Setup

The tBase acts as a universal inductive powering platform and data receiving station for the mouse telemeter.

1. Plug in power
2. Status light on front will turn on (initially orange)

Do not operate tBase within 10cm of any metal.



4. Prior to surgery, pair telemeter and tBase

All telemeters and tBases are initially shipped on Channel "Setup" and must be configured one at a time. For data collection, select and pair each telemeter and tBase to one of 40 Channels using the Configurator and ConfigSoft software.

DO NOT remove telemeter from sterile packaging.

1. Place telemeter in the center of the tBase, tBase status light will turn green.
2. Use ConfigSoft to change the Channel of the telemeter to a data collection Channel (Ch 1-40), status light will go orange.
3. Use ConfigSoft to change the Channel of the tBase to match the Channel of the telemeter.
The status light should now turn green.

Each tBase/telemeter pair must operate on its own individual Channel.



5. Implant telemeters

Telemeters are shipped sterile and ready to implant. Surgical instructional videos, guides and techniques are available online at: <http://millar.com/knowledge-center>

6. Connect tBase to data acquisition system

Connect each tBase to a data acquisition system using the BNC outputs. Each tBase has three analog outputs which are automatically set when the telemeter has been paired.

Output Signal Configuration:

Telemeter model	Output 1	Output 2	Output 3
MT10B	Activity	Biopotential	Data Received

7. Acquire data

When the animal is placed on the tBase, the telemeter will be automatically activated and data transmission will occur. The Configurator is not required for data acquisition.



8. Questions/support?

Please visit the Millar Knowledge Center (www.millar.com/knowledge-center) for detailed instructions on the use and care of the system along with instructional videos, or contact us at support@millar.com.

Configurator System Setup

Introduction

The Configurator System (TR190 Configurator hardware and ConfigSoft software), wirelessly communicates with the mouse telemeters and tBases. The system allows the user to:

- 1) Change/configure the transmission Channel of the tBase
- 2) Change/configure the transmission Channel of the telemeter.
- 3) Run Diagnostics on telemeters and tBases.


Only a single Configurator System is required for each laboratory and it is NOT required during data acquisition. Existing Configurator hardware in use with the Millar Rat Telemetry Systems can be used with the Millar Mouse Telemetry System however a firmware and ConfigSoft software upgrade may be required. Contact support@millar.com for assistance.

Configurator Software Installation

NOTE: ConfigSoft must be installed on the computer before connecting the Configurator hardware. Existing versions of ConfigSoft must also be uninstalled prior to installation.

System requirements: Windows 7, 8 or 10. There are two separate installers 32 bit and 64 bit, please install the version compatible with your Windows operating system. Internet connection is necessary to access and install any drivers not already installed.


- 1) Connect the supplied USB drive containing ConfigSoft to your computer.
- 2) Open the ConfigSoft folder and go to folder “ConfigSoft 32 bit” or “ConfigSoft 64 bit” according to your Windows Operating System.
- 3) Double click on “setup” to start the installation.




- 4) Once the welcome screen appears, follow the instructions for installation.




- 5) Previous versions of the ConfigSoft software *must* be removed before continuing with the installation. If you need to remove the program, follow the instructions in this window before clicking Next.




- 6) Confirm installation. Click Next




- 7) After the installation has been completed. Click Close.



- 8) The following window will automatically appear to install the driver for the TR190 Configurator if it is not already located on the computer. Click Next.




- 9) After successful installation of the TR190 Driver, Click Finish.



- 10) Installation of ConfigSoft and the TR190 Configurator drivers has been completed.


Connecting the Configurator

Front



Status light

Rear



Antenna connection

USB port

- 1) Attach the antenna to the rear of the Configurator.
- 2) After installation of ConfigSoft, connect the Configurator to the computer using the supplied USB cable. The status light on the front of the Configurator should glow **red** or **green** indicating that it is receiving power from the computer.

The status light on the front panel of the Configurator indicates the following information:

Off	Not connected, USB cable unplugged, Configurator is off
Red	Configurator is receiving power but not communicating with computer
Green	Configurator is communicating with the computer

- 3) The computer will install any additional drivers and the status light should glow **green**. If there are any problems please contact support@millar.com.
- 4) The Configurator System is now ready for use with all your mouse telemeters and tBases.

Configurator Software - Overview



ConfigSoft can be started from either the

- Desktop icon



OR


- Start>Programs>Millar Telemetry>ConfigSoft




From the main menu the user has access to the:

1. Rat Telemeter (not required for the mouse telemetry system)
2. SmartPad (not required for the mouse telemetry system)
3. Mouse Telemeter
4. tBase
5. SmartPad Status (not required for the mouse telemetry system)

Mouse Telemeter Tab



tBase Tab




tBase - Overview

The tBase is both a wireless power supply and receiver for the mouse telemeter. The top of the tBase has an indent (335mm (L) x 190mm (W) x 10mm (D)) which a mouse cage must be positioned in for the best access to the inductive power field. Only use cages that fit into the indent area with the cage base in contact with the surface of the indent.

The tBase generates an inductive power field which extends approximately 7cm above the surface of the indent. When the mouse telemeter is within the tBase power field, the telemeter will be powered and data recorded. Only telemeters paired on the same transmission Channel as the tBase will communicate, be powered and transmit data efficiently and accurately.

No data will be recorded when the telemeter is not in the power field. For optimal powering, it is recommended that the cage is centered in the tBase indent. **NOTE:** *The use of cages with base dimensions that exceed those of the tBase indent is NOT recommended and may compromise data collection.*

tBase Front



tBase Rear



When initially setting up a laboratory with multiple tBases, it is important that only **ONE** tBase is turned on at a time. **The tBases and telemeters are all shipped set to Channel "Setup"**. Before using the telemetry system each tBase and mouse telemeter needs to be configured and paired to one of the 40 transmission Channels. It is important that only one tBase and one telemeter are used on any particular channel to prevent signal interference.


The recommended arrangement of multiple tBases in a laboratory is detailed below. In particular, note the distances from other tBases and metal objects.

tBase Laboratory Setup

The tBase provides power to the telemeter using an electromagnetic field generated above and below the tBase. For this reason, it is important that a tBase is NOT placed on a metal surface or above or below other tBases (unless 40 cm apart). We recommend the use of plastic shelving for your tBases. Multiple tBases should be arranged so that there is more than 10 cm horizontal and 40 cm vertical separation between them. If using shelving that has metal supports or framing then the tBases must be >10cm away from these as well (don't forget to check the underside of the shelves for metal supports). There should also be more than 10 cm separation between the top of a metal cage lid and any tBase on a shelf above.

If metal shelves are used, the tBase needs to be raised at least 10 cm from the shelf surface but still maintaining a vertical separation of at least 40 cm between tBases.

If the tBase shows a **solid red light**, then the tBases need to be further separated (vertically and horizontally) and/or move them further away from metal brackets, supports, cables or power packs. Reset the tBase by disconnecting and reconnecting the power. If the problem continues, please contact support@millar.com.



Example tBase arrangement on plastic shelves with metal framing.

IMPORTANT:

- Connect ONLY the supplied and labelled “TR181 or MT110” Power Supply to the power socket at the rear of the MT110 tBase. **Please note: Using any other Power Supply will invalidate the warranty and may damage the tBase.**
- DO NOT obstruct the air vents at the front and rear of the MT110. Ensure that any power cables and other items are kept clear of the air vents.

Status lights

The status light at the front of the tBase provides information on the communication status between the tBase and the telemeter.

Status light	MT110 tBase
Solid Green	The tBase is communicating with a telemeter on the same Channel
Solid Orange	The tBase is turned on but is not communicating with a telemeter
Solid Red*	The tBase has detected an issue with the telemetry setup and has disabled the powering. Please see troubleshooting below for more information.
Flashing Red	The tBase is in diagnostic mode. No telemeter data will be output

The status lights on the tBase may flicker between solid green and solid orange during normal operation as the telemeter enters and leaves the power field with normal activity of the mouse i.e. mouse climbing on and off large objects in the cage.

***Troubleshooting:** When the status light is solid red, the power field of the tBase has been disabled and the telemeter will not be powered. This means that there will be no data recorded from the telemeter. **Cause:** may be due to the tBase being placed too close to a metal surface or to another tBase. Move the tBase away from any metal and then reset by turning the power off and then on

again. If the problem persists, record a diagnostic file in ConfigSoft while the tBase is showing a red status light and contact support@millar.com.

Analog Outputs and Calibration Values


After pairing the tBase/telemeter Channels, the analog outputs of the tBase will correspond to the following signal outputs:

Telemeter model	Output 1	Output 2	Output 3
MT10B	Activity	Biopotential	Data Received
Calibration values	0V = 0 RAU 3.84V = 10 RAU	2.048V = 0mV 4.096V = 2.5mV	~0V = no data received ~3.3V = data received

Activity: As the mouse moves in the power field the strength and orientation of the electromagnetic field it receives changes. These changes are detected by the tBase and collated every ~1 second to calculate an index of animal activity. The output is updated approximately every 1 second as ranges from 0V – 3.84V in 13 levels (see picture below). We recommend converting the voltage output to Relative Activity Units (RAU). The activity index can be used to determine relative changes in activity between two time periods (e.g. night vs day).

Biopotential: This is your ECG, EEG or EMG signal. The potential difference between the two electrode leads is measured by the telemeter (sampling rate 2 kHz) and transmitted to the tBase. The tBase low-pass filters the signal at 1 kHz and reconstructs the analog signal.

Data Received: This provides an easy visual representation of when data is collected or when it has been missed. When the tBase is receiving data from a telemeter, the Data Received analog output will be ~3.3V. If no data is received from a telemeter for 12 milliseconds this output will drop to ~0V until data is received again (see picture below). The most likely cause of data not being received is that the mouse and telemeter have moved outside the inductive power field e.g. the mouse is hanging off the bars of the cage lid and is more than 7cm above the tBase surface. The Data Received output can be useful during data analysis to differentiate between real periods of low signal amplitude and missing data e.g. skipped beats in ECG recordings.




Example recording showing the Activity Index, Biopotential and Data Received outputs.

The Mouse telemeter

Millar mouse telemeters are designed for single use and for 24/7 recordings from mice living in their home cages. The telemeters are designed, with a unique contour, for use as subcutaneous implants in mice >22 grams. Telemeters are shipped sterile and ready for implantation. ALL telemeters are shipped on Channel “Setup” and each telemeter **MUST** be configured to one of 40 different data recording Channels **before implantation**. DO NOT change the Channel of the telemeter while implanted in an animal. There is no need to unpack the telemeter from the sterile packaging (see right) to change the channel.



The telemeters are precision electronic devices. *Care must be taken not to damage the telemeter body or electrodes as they cannot be repaired.* Please read the section about Care and Handling of your telemeters.



The MT10B telemeter (above) can measure a single biopotential signal between the positive and negative leads for applications including ECG, EMG and EEG. For ease of identification, the negative lead is trimmed shorter than the positive lead so the wire coil is flush with the tubing.

Before implanting a telemeter make sure to write down the serial number and Channel setting.

Channel and serial numbers

All telemeters are factory set to Channel “Setup” and need to be configured to different channels before use (see page 18). The telemeter model and serial number can be found on the telemeter packaging. In the example below, the model is MT10B, the serial number is 00000. The serial number can also be found on the end of the telemeter.



System setup and configuration

Before implanting a telemeter into an animal, the telemeter and the tBase to be used with the telemeter must have their Channels paired. Please ensure that only **one** tBase and **one** telemeter are being configured and paired at any one time. **All tBases and telemeters are shipped on Channel “Setup” and should be changed to one of the 40 available data collection Channels before animal implantation. The tBase and telemeter need to be within 1 meter of the Configurator during configuration.**


- 1) Turn on the tBase (Status light should be **orange**). If this is the first time the tBase has been turned on, it should be on the Channel “Setup”. If not, use the Configurator System to configure the tBase Channel to “Setup” (see page 20 for details).




- 2) Place a telemeter (in its sterile packaging) in the center of the indent of the tBase. The tBase will automatically start powering the telemeter as both the tBase and telemeter will be on Channel “Setup”. The tBase status should turn **green**.
- 3) Using the Configurator system, first change the Channel of the mouse telemeter to one of the 40 data collection Channels (detailed instructions in the next two sections). The tBase status light should now be **orange**. Remove the mouse telemeter from the tBase.
- 4) Configure the tBase to the same data collection Channel as the mouse telemeter using ConfigSoft (detailed instructions in the next two sections). Place the telemeter on the tBase, the status light should be **green**. Your system is now paired and ready for use.

Changing telemeter Channel


- 1) Place the mouse telemeter in the center of the indent of the tBase configured to the same Channel (first use Channel = "Setup"). Ensure the telemeter and tBase are within 1 meter of the Configurator. The tBase status light should be **green** to show the telemeter is powered and communicating with the tBase.
- 2) Open ConfigSoft
- 3) Click on the "Mouse Telemeter" tab



- 4) Enter the serial number of the telemeter. The number is on the outside of the telemeter packaging or on the label at the end of the telemeter.
- 5) Select or enter the current Channel number of the telemeter (first use: Channel = "Setup").
- 6) To change the Channel number, select or enter the new Channel number in the "Configure your telemeter" section.
- 7) Click Go to activate the new Channel.
- 8) A dialog will pop up with "Only change the telemeter transmission Channel before implantation". Click OK to confirm the choice.




- 9) A message confirming the new telemeter Channel should appear. To make it easier for the future, record the telemeter Serial number and Channel number for all telemeter configurations.



Troubleshooting: Configurator – ConfigSoft - telemeter

If the Configurator cannot communicate with the telemeter an error message may appear.




Solution:

Do the following and try again:


- Check that you have entered the correct telemeter Serial number
- Check that you have entered the correct telemeter Channel number
- Make sure that the telemeter is on a tBase set to the same Channel
- Move the telemeter and paired tBase closer to the Configurator
- Check you only have one tBase/telemeter set to the same Channel
- Move the telemeter to a different position on the tBase

Changing tBase Channel

- 1) To change the tBase Channel and pair this with a telemeter, click on the “tBase” tab in ConfigSoft.



- 2) Enter the serial number of the tBase (found on the front and rear of the tBase).
- 3) Enter current Channel number of the tBase (first use: Channel = “Setup”).
- 4) Under “Configure your tBase”, enter or select a new Channel number for the tBase (this should be same as telemeter being used).
- 5) Click Go to activate the new Channel.
- 6) Click OK to confirm your choice.




6. The tBase status light will flash red for a few seconds before a message confirming that the tBase channel has been changed appears. Record the tBase serial number and new Channel number for future reference.



- 7) If a telemeter on the same Channel is placed on the tBase, the Status light should change to green. The telemeter and tBase are now on the same Channel, paired, and able to communicate for data collection and transmission.

Troubleshooting: Configurator – ConfigSoft - tBase

If the Configurator cannot communicate with the tBase the following error message may appear.




Click OK and perform the following then retry:

- Check that the light on the front of the tBase is orange.
- Check that you entered the correct Serial and/or Channel numbers.
- Move tBase closer to Configurator.
- Check you only have one tBase set to the same Channel

Repeat the above process for each of the tBases and telemeters to configure each pair to a different Channel.

Your Millar Mouse Telemetry System is now configured and ready for use.

Positioning the telemeter during surgery



The telemeter has a unique contoured shape with a curved convex front and a concave underside for better positioning in the mouse. The telemeter body is designed to fit subcutaneously, with the concave underside sitting against the flank of the mouse and the convex front side next to the skin.

Biopotential lead placement

MT10B Mouse biopotential telemeters are supplied with 8cm long stainless steel bipolar electrodes suitable for measurement of biological electric potential signals including ECG, EEG and EMG. To reduce noise in the recorded signal it is recommended that the electrode leads be trimmed to length at the time of surgery rather than coiling any excess wire. It is important however to allow some extra length in the electrode leads to allow for animal movement. For ease of identification, the negative lead is trimmed shorter than the positive lead so the wire coil is flush with the tubing.


After trimming the electrode leads to the desired length, it will be necessary to expose the coiled stainless steel electrode within the lead tubing. Care must be taken to avoid damaging the wire as this can lead to wire breakages and poor signal quality during recordings. The recommended way to expose the electrode wire is to use a surgical microscope and carefully trim the tubing from around the wire. Do not trim, stretch or disturb the wire coil within 2.5 cm of the telemeter body.

The stainless steel electrodes are coiled for maximum strength and flexibility. The coil can slip out of a suture however so it may be useful to carefully stretch the coils at the tip of the electrode to allow a suture thread to pass between the coils.



It is not recommended that sutures be placed around the leads other than around the point of contact with the tissue as this may provide a stress point on the leads and cause them to break. More information and surgical videos are available online at <http://millar.com/knowledge-center>

Example placement of electrode leads for recording of high quality ECG



Telemeter Body Placement for Powering and Signal Maximization

The tBase provides an electromagnetic field to power the mouse telemeter. This field provides effective powering of the telemeter within up to 7cm vertical distance from the bottom of the indent on the tBase. However, when the telemeter body is more than 7cm above the tBase, the telemeter will not be powered and data collection will not be available. This can occur when the mouse hangs from the wire cage lid or is physically sitting more than 7cm above the tBase.

The recommended site for telemeter placement is on the flank/side of the animal between the front and the rear limbs with the concave surface of the telemeter against the body. Placement on the right hand side of the mouse means the electrode leads will exit from the top corner of the telemeter body and can be tunneled over the shoulder for ECG placement or to the skull for measurement of EEG.

Powering may not be as effective if the telemeter is placed on the back of the animal or up near the shoulders as that creates additional distance from the tBase, especially when the animal is up on their hind legs. More information and surgical videos are available online at the Millar Knowledge Center (<http://millar.com/knowledge-center>).

It is also strongly recommended that bedding within the cage is kept to a minimum and tall items, which the mouse can climb on top of, are removed. For example, large enrichment tubes, multi-level mouse houses or other toys with elevated flat surfaces should be avoided.

Telemeter Care and Handling

All telemeters are shipped pre-sterilized using ethylene oxide gas sterilization and **can be implanted without the need for further sterilization**. Telemeters will remain sterile as long as the pouch is intact and not compromised. It is recommended that they remain in their original packaging until surgical implantation.

However, if the telemeters have been accidentally removed from the sterile packaging prior to implantation, or if they come in contact with non-sterile surfaces during surgery, they can be sterilized using one of the methods below:

Chemical Sterilants

Glutaraldehyde may be used to sterilize the telemeters. Glutaraldehyde (Fisher Scientific) must be diluted to 2% before use. Check your local chemical supply company for availability. Do not use glutaraldehyde solutions containing surfactants (i.e. do **not** use Cidex 7, Cidex Plus 28 Day or Metrocide 28). Suitable products are in the table below:

Trade Name	Manufacturer	Active Ingredient	Soak Time / Temperature
Cidex Activated Dialdehyde Solution	Advanced Sterilization Products (J&J)	Glutaraldehyde	1-2 hours / 25°C (77°F)
Cidex® OPA	Advanced Sterilization Products (J&J)	Orthophthalaldehyde	16-30 mins / 20°C (68°F)
MetriCide®	Metrex	Glutaraldehyde	1-2 hours / 25°C (77°F)

Rinse with Sterile Saline

Telemeters sterilized with a chemical sterilant should always be washed thoroughly in sterile saline before implantation to remove all traces of the sterilant.

Ethylene Oxide Gas Sterilization

Telemeters are suitable for Ethylene Oxide sterilization as long as they are not subjected to temperatures above 60°C.

*Important note:

Under no circumstances should the telemeter be autoclaved or subjected to temperatures over 60°C as this will damage the telemeter.

Do not sterilize by radiation (gamma or e-beam), plasma, alcohol, peroxide or formaldehyde vapor solutions. This will damage the telemeter.

Customers are liable for product replacement if recommended products and instructions are not used or followed. If there are any questions about a chemical or procedure please contact Millar (support@millar.com).

Warning: Some examples of chemicals that will cause damage to telemeters include, but are not limited to: alcohols, phenols, iodophors, and hypochlorite. Please confirm with Millar before using any product other than the approved products list above.

** Products with similar names are available but may not be suitable. Please use only products specified or contact Millar for clarification (support@millar.com).

Removal

The mouse telemeters are designed as a single use product. Depending on your biohazard or medical waste disposal services, it is possible to discard the biopotential leads and/or the telemeter body while still implanted in the mouse at the end of the experimental protocol.

Diagnostics

Using the Configurator System the user can view and change the Channel of the telemeter. The “Search for telemeter” function can be used to find the serial number of an implanted telemeter if this was not recorded prior to implantation.


The “Search for tBase” function will find the Channel of a specific tBase. The Configurator System can also be used to investigate the status of the temperature and power consumption of the tBase.

Diagnostics files

When sending emails to support@millar.com for troubleshooting, you may be asked to send a diagnostics file. To run diagnostics for the mouse telemeter or tBase, enter the Serial number and the Channel number in the “mouse telemeter” or “tBase” dialog, press the “Start Diagnostics” button and choose to save the file. ConfigSoft will ask you to confirm the name and location for the log file. The default filename includes the telemeter or tBase serial number and the date and time the diagnostics was started (see example below). The log file and display are both updated every 1 s. A count of the updates is shown in the bottom left hand corner of the window. Diagnostics will continue to run until you press “Stop Diagnostics”. The log file is then automatically saved. If you choose to save a log file you will not be able to stop the diagnostics for at least 2 minutes.


Please note that you cannot record data from your telemeter using a tBase that is in Diagnostics mode (the status light flashes red and a saw tooth pattern will output from the tBase analog outputs).

Mouse telemeter diagnostics



MTx10289_log_2015_6_9_16_11.txt

tBase diagnostics



Tb10253_log_2015_6_9_16_48.txt

Temperature normal

- ✓ = the temperature of the tBase is at acceptable levels.
- ✗ = the temperature is above acceptable limits. Please contact Millar (support@millar.com).

Power consumption normal

- ✓ = tBase power consumption is normal.
- ✗ = Excess power consumption has been detected. The Status light on the front of tBase will be red. The tBase may be too close to a metal surface or another tBase.

tBase Technical Specifications

tBase	MT110
tBase functions	Provides power only to mouse telemeters using inductive wireless charging, outputs standard analog voltage compatible with any data acquisition system (BNC), has a built-in fan for optimal temperature operation.
Weight	3.0 Kg
Dimensions	400(w) x 450(d) x 65(h) mm / 15.7(w) x 17.7(d) x 2.6(h) in
Cage platform dimensions	190(w) x 335(d) mm / 7.5(w) x 13.2(d) in
Power input	100-240 V, 50-60 Hz
Max Power draw	90W
Temperature Operating Range	10 to 40 degrees Celsius
Output Connectors	BNC x 3
Output Voltage Range	0 to 4V
Low Pass filtering on signal outputs	Cut off frequency = 1000 Hz

Telemeter Technical Specifications

The technical specifications in the table below are for the mouse telemeters.

Biopotential Input range	+2.5 mV
Biopotential Resolution	12 bit A/D
Biopotential High pass characteristics	AC coupled, single pole, -3dB point at 2 Hz
Biopotential Low pass characteristics	AC coupled, single pole, -3dB point at 440 Hz
Biopotential Electrode leads	8cm length, coiled stainless steel
Biopotential Electrode diameter	0.42 mm
Temperature operating range	34 to 41 degrees Celsius
Sampling frequency	2000 Hz
Low Pass filtering by tBase	Cut off frequency = 1000 Hz
Transmitted signal	Fully digital at 2.4 GHz
Channels	40 transmission frequencies are available, user set
Minimum animal weight	22 grams
Outer material	Epoxy (telemeter body) and polyurethane (leadset)
Volume	1.6 cc
On-off mechanism	Powered when placed on the tBase and deactivated when removed from the tBase.
Calibration	No user intervention required (calibration values stored within each telemeter).
Analog output calibration values	Activity: 0V output = 0 RAU 3.84V output = 10 RAU Biopotential: 2.048V output = 0mV input, 4.096V output = 2.5 mV input Data received: ~0V output = 0 (no data received), ~3.3V = 1 (data received)

Frequently Asked Questions.....

Would the animal be harmed by staying in the tBase powering field?

There are no known biological effects of the inductive field. Studies have shown that field strengths much higher than generated by the Millar tBase have no effect. The level of magnetic field is quite low and remains useable only ~7 cm above the tBase.

How many animals can be monitored at one time?

Each telemeter sends its signal on one of 40 unique transmission Channels. Therefore up to 40 telemeters and animals can be monitored at one time (on separate tBases).

Can I use the Millar Mouse Telemetry System alongside the Millar Rat Telemetry System?

Both the Millar Rat Telemetry System and Millar Mouse Telemetry System can be operated on any of the 40 independent data collection Channels with minimal interference between animals. Therefore, both systems can be operated side-by-side to monitor up to a total of 40 rats or mice, or a combination of both rats and mice, at any one time. Your existing rat Configurator system may require a firmware or software update before use with mouse telemeters (please contact Millar).

Is there any interference between mouse telemeters?

No. As long as each telemeter is set to use a different Channel they use separate transmission frequencies. No shielding is required between cages. Close proximity is possible.

Do I need to use special mouse cages with the tBase?

Special caging is not required for use with this system. The only limitation is that the cage base must sit on the surface of the tBase indent. The indent of the tBase for the mouse cage is 190mm x 335mm and is compatible with any non-metallic cage bottom which fits these dimensions.

Further questions?

Millar is proud to offer unlimited technical support and advice to all its customers. Register on our free online Knowledge Center (<http://millar.com/knowledge-center>) for surgical recommendations and hardware troubleshooting advice. If you have any further questions, our team of engineers and physiologists can advise on specific applications and equipment configurations. Please contact us.

Contact Information

US Head Office

Houston, Texas
Toll free (in USA) 1 800 669 2343
TEL: +1 832 667 7000
FAX: +1 713 714 8497

New Zealand Office

Auckland, New Zealand
TEL: +64 9 367 7126
FAX: +64 9 367 7157

EMAIL support@millar.com or sales@millar.com

WEB www.millar.com