

LED DOWNLIGHT INSTALLATION INSTRUCTIONS

Read the instruction sheet and all product labels before installing fixture. This product must be installed in full accordance with applicable electrical and building codes by a person familiar with the construction and operation of this fixture and all involved hazards. Installation should be performed by a qualified electrician in accordance with the National Electrical Code and relevant local codes.

TO PREVENT ELECTRICAL SHOCK, POWER SHOULD BE TURNED OFF AT THE FUSE BOX BEFORE INSTALLATION.

SAFETY WARNINGS:

Read all product labels and directions.

- WARNING - Risk of fire or electric shock. LED Retrofit Kit installation requires knowledge of luminaires electrical systems. If not qualified, do not attempt installation. Contact a qualified electrician.
- WARNING - Risk of fire or electric shock. Install this kit only in the luminaires that have the construction features and dimensions shown in the photographs and/or drawings.
- Installation should be performed only by a qualified electrician in accordance with the National Electrical Code and relevant local codes.
- Do not make or alter any open holes in an enclosure of wiring or electrical components during kit installation.
- WARNING - To prevent wiring damage or abrasion, do not expose wiring to edges of sheet metal or other sharp objects.
- Lamp replacement instructions shall indicate the manufacturer's custom lamp part number, and a method to order replacement lamps by phone, website and/or mail.
- The recessed luminaire is intended for mounting only in a covered ceiling (where only the led side of the luminaire will be exposed to damp or dry locations).
- **INSTALLATION SHOULD ONLY BE PERFORMED AFTER POWER TO THE FIXTURE HAS BEEN DISCONNECTED.**
- These instructions shall be included on an information sheet packaged with each unit.

FCC Notice

This device has been tested and found to comply with the limits for a Class B digital device pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This device generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this device does cause harmful interference to radio or television reception, which can be determined by turning the device off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

Reorient or relocate the receiving antenna

Increase the separation between the device and receiver

Connect the device into an outlet on a circuit different from that to which the receiver is connected

Consult the dealer or an experienced radio/television technician for help .

The manufacturer is not responsible for any radio or TV interference caused by unauthorized modifications to this equipment. Such modifications could void the user's authority to operate the equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

INSTALLATION INSTRUCTIONS:

1. Attach mounting bracket to the J-Box using the 2 provided screws.
2. Attach mounting bracket to the board using the expansion bolts and Cross Nibbed Screw.
3. Attach the hook to one of the holes in the mounting bracket.
4. The hook is then inserted into the J-box
5. Insert existing wire ends from the J-Box to the LED adapter. Black wire (L), White wire (N) and Ground wire (G). Connect the end of the LED adapter coming out of the J-Box to the fixture and wire the grounds together using the provided wire nut.
6. Then plug all wiring harnesses and fixtures into the J-Box
7. Align the wide notch. Push fixture up into the mounting bracket until it clicks into place. Make sure all wires are carefully tucked inside the J-Box and fixture is flush with the ceiling.
8. Tighten the clamp by rotating clockwise. Installation complete, restore power.

