

Fingertip Pulse Oximeter

MD300C208

USER MANUAL

Ver2.0C208

ChoiceMMed

There are 2 display directions and 2 displayed parameters shown as follows:



Notes:

1. Short press the power button to switch the screen display orientation.
2. Long press the power button to switch the displayed parameters (SpO₂&PR, SpO₂&PI).

Data Transmission


1. Turn on the device, the Bluetooth icon is flashing. After sync successfully, the Bluetooth icon is light on. Or else the Bluetooth icon still in the flashing status. When you turn off the device, the Bluetooth will break automatically.
2. The current measurement will transmit to the App automatically. After data transmission successfully, the measurement flashing for 8s, then the device will power off automatically power off. If there is no Bluetooth connection over 1min, the device will power off automatically and the data will not be stored.
3. If there is no digit appear, the device will power off automatically.

Notes:

1. With the Bluetooth 4.0 to transmit the data to App.
2. The transmission distance is 10m at most.

Battery Installation

1. Install two AAA batteries into the battery compartment. Match the plus (+) and minus (-) signs in the compartment. If the polarities are not matched, damage may be caused to the oximeter.
2. Slide the battery door cover horizontally along the arrow shown as the picture.




Notes:

- ◇ Please remove the batteries if the pulse oximeter will not be used for long periods of time.
- ◇ Please replace the battery when the power indicator starting flickering.

Using the Lanyard

1. Thread thinner end of the lanyard through the hanging hole.
2. Thread thicker end of the lanyard through the threaded end before pulling it tightly.



Warnings!

- ◇ Keep the oximeter away from young children. Small items such as the battery door, battery, and lanyard are choking hazards.
- ◇ Do not hang the lanyard from the device's electrical wire.
- ◇ Please notice that the lanyard which is tied to the oximeter may cause strangulation due to excessive length.

Maintenance and Storage

1. Replace the batteries in a timely manner when low voltage lamp is lighted.
2. Clean surface of the fingertip oximeter before it is used in diagnosis for patients.
3. Remove the batteries if the oximeter is not operated for a long time.
4. It is best to store the product in -20°C~+55°C and ≤93% humidity.
5. Keep in a dry place. Extreme moisture may affect oximeter lifetime and may cause damage.
6. Dispose of battery properly; follow any applicable local battery disposal laws.

Cleaning the fingertip pulse oximeter

Please use medical alcohol to clean the silicone touching the finger inside of oximeter with a soft cloth dampened with 70% isopropyl alcohol. Also clean the being tested finger using alcohol before and after each test. Do not pour or spray liquids onto the oximeter, and do not allow any liquid to enter any openings in the device. Allow the oximeter to dry thoroughly before reuse.

The fingertip pulse oximeter requires no routine calibration or maintenance other than replacement of batteries.

The use life of the device is five years when it is used for 15 measurements every day and 10 minutes per one measurement. Stop using and contact local service center if one of the following cases occurs:

- An error in the Possible Problems and solutions is displayed on screen.
- The oximeter cannot be powered on in any case and not the reasons of battery.
- There is a crack on the oximeter or damage on the display resulting readings cannot be identified; the spring is invalid; or the key is unresponsive or unavailable.

A functional tester cannot be used to assess the accuracy of a pulse oximeter monitor or sensor. Clinical testing is used to establish the SpO₂ accuracy. The measured arterial hemoglobin saturation value (SpO₂) of the sensors is compared to arterial hemoglobin oxygen (SaO₂) value, determined from blood samples with a laboratory CO-oximeter. The accuracy of the sensors in comparison to the CO-oximeter samples measured over the SpO₂ range of 70%~100%. Accuracy data is calculated using the root-mean-squared (Arms value) for all subjects, per ISO 9919:2005, Medical Electrical Equipment - Particular requirements for the basic safety and essential performance of pulse oximeter equipment for medical use.

A functional tester is used to measure how accurately Fingertip Pulse Oximeter is reproducing the specified calibration curve and the PR accuracy.

The model of functional tester is Index2 FLUKE simulator and the version is 2.1.3.

Specifications

1. Display Type

OLED display

2. SpO₂

Measurement range: 70%~100%


Accuracy: 70%~100%: ±2%; 0%~69% no definition

Resolution: 1%

Arms Value Analysis

Item	70~100	90~100	80~<90	70~<80
#pts	231	82	89	60
Bias	0.03	-0.06	0.07	0.12
Arms	1.07	0.92	1.13	1.18

Bland-Altman plot analysis of sampled data points on all subjects as below



3. Pulse Rate

Measure range: 30bpm~250bpm

Accuracy: 30bpm~99bpm, ±2bpm; 100~235bpm, ±2%

Resolution: 1bpm

4. PI

Measure range: 0.2%~20.0%

Accuracy: 0.2%~1.0%, ±0.2digits; 1.1%~20.0%, ±20%

Resolution: 0.1%

5. Probe LED Specifications

General Description

Oxygen Saturation is a percentage of Oxyhemoglobin (HbO₂) capacity, compounded with oxygen, by all combinative hemoglobin (Hb) capacity in blood. In other words, it is consistency of Oxyhemoglobin in blood. It is a very important parameter for the Respiratory Circulation System. Many respiratory diseases can result in oxygen saturation being lowered in human blood. Additionally, the following factors can reduce oxygen saturation: Automatic regulation of organ dysfunction caused by Anesthesia, Intensive Postoperative Trauma, injuries caused by some medical examinations. That situation might result in light-headedness, asthenia, and vomiting. Therefore, it is very important to know the oxygen saturation of a patient so that doctors can find problems in a timely manner.

The fingertip pulse oximeter features low power consumption, convenient operation and portability. Place one fingertip into the photoelectric sensor for diagnosis and the pulse rate and oxygen saturation will appear on the display. It has been proven in clinical experiments that it also features high precision and repeatability.

Measurement Principle

Principle of the oximeter is as follows: A mathematical formula is established making use of Lambert Beer Law according to Spectrum Absorption Characteristics of Reductive hemoglobin (RhB) and Oxyhemoglobin (HbO₂) in red and near-infrared zones. Operation principle of the instrument: Photoelectric Oxyhemoglobin Inspection Technology is adopted in accordance with Capacity Pulse Scanning and Recording Technology, so that two beams of different wavelength of lights (660nm red and 940nm near infrared light) can be focused onto a human nail tip through a clamping finger-type sensor. A measured signal obtained by a photosensitive element, will be shown on the oximeter's display through process in electronic circuits and microprocessor shown on the oximeter's display through electronic circuits and a microprocessor.




Diagram of Operation Principle

1. Red and Infrared-ray Emission Tube
2. Red and Infrared-ray Receipt Tube

Precautions For Use

1. Before use, carefully read the manual.
2. Operation of the fingertip pulse oximeter may be affected by the use of an electrosurgical unit (ESU).
3. Pulse Oximeters require sufficient blood flow to obtain proper readings. Poor blood circulation can result in inaccurate readings. If your hands are cold or you have poor circulation, warm your hands by rubbing them together or use another method before attempting to obtain a reading. A tourniquet, blood pressure cuff or other blood flow hindrance may also result in inaccurate readings.
4. Do not use the fingertip pulse oximeter in an MRI or CT environment.
5. Do not use the fingertip pulse oximeter in situations where alarms are required. The device has no alarms. It is not for continuous monitoring.
6. Do not use the fingertip pulse oximeter in an explosive atmosphere.
7. The fingertip pulse oximeter is intended only as an adjunct in patient assessment. It must be used in conjunction with other methods of assessing clinical signs and symptoms.
8. In order to ensure correct sensor alignment and skin integrity, the maximum application time at a single site for our device should be less than half an hour.
9. Do not sterilize the device using autoclaving, ethylene oxide sterilizing, or immersing the device in liquid. The device is not intended for sterilization.
10. Follow local ordinances and recycling instructions regarding disposal or recycling of the device and device components, including batteries.
11. This equipment complies with IEC 60601-1-2:2007 for electromagnetic compatibility for medical electrical equipment and/or systems. However, because of the proliferation of radio-frequency transmitting equipment and other sources of electrical noise in healthcare and other environments, it is possible that high levels of such interference due to close proximity or strength of a source might disrupt the performance of this device.
12. Portable and mobile RF communications equipment can affect medical electrical equipment.
13. This equipment is not intended for use during patient transport outside the healthcare facility.
14. This equipment should not be used adjacent to or stacked with other equipment.
15. It may be unsafe to:
 - use accessories, detachable parts and materials not described in the instructions for use.
 - interconnect this equipment with other equipment not described in the instructions for use.
 - disassemble, repair or modify the equipment.
16. These materials that contact with the patient's skin contain medical silicone and ABS plastic enclosure are all pass the ISO10993-5 Tests for invitro cytotoxicity and ISO10993-10 Tests for irritation and delayed-type hypersensitivity.
17. When the signal is not stable, the reading may inaccurate. Please do not reference.

Rx only: "Caution: Federal law (USA) restricts this device to sale by or on the order of a licensed practitioner."

Contraindication

It is not for continuous monitoring.

Inaccurate measurements may be caused by

1. Significant levels of dysfunctional hemoglobin (such as carboxy - hemoglobin or methemoglobin).
2. Intravascular dyes such as indocyanine green or methylene blue.
3. High ambient light. Shield the sensor area if necessary.
4. Excessive patient movement.
5. High-frequency electrosurgical interference and defibrillators.
6. Venous pulsations.
7. Placement of a sensor on an extremity with a blood pressure cuff, arterial catheter, or intravascular line.
8. The patient has hypotension, severe vasoconstriction, severe anemia, or hypothermia.
9. The patient is in cardiac arrest or is in shock.
10. Fingernail polish or false fingernails.
11. Weak pulse quality (low perfusion).
12. Low hemoglobin.

Product Features

1. Simple to operate and convenient to carry.
2. Small volume, light weight and low power consumption.
3. Dual color OLED displays SpO₂, PR, PI, Pulse bar, and waveform.
4. 2 display direction.
5. 2pcs AAA-size alkaline batteries; battery-low indicator.
6. Wireless Bluetooth for data transmission.
7. When no or low signal is detected, the pulse oximeter will power off automatically in 8 seconds
8. Compatible with iChoicelife App.

Intended Use

Fingertip pulse oximeter is a handheld non-invasive device intended for spot-checking of oxygen saturation of arterial hemoglobin (SpO₂) and pulse rate of adult and pediatric patients in hospitals, hospital-type facilities.

Operation Instructions

1. Install two AAA batteries according to the Battery Installation instructions.
2. Place one of your fingers into the rubber opening of the pulse oximeter.
3. Press the switch button one time on front panel to turn the pulse oximeter on.
4. Keep your hands still for the reading. Do not shake your finger during the test. It is recommended that you do not move your body while taking a reading.
5. Read the data from the display screen.

After turning on the Oximeter, each time you press the power switch, the Oximeter will switch to another display mode.

	Wavelength	Radiant Power
RED	660±2nm	1.8mW
IR	940±10nm	2.0mW

6. Power Requirements

Two AAA alkaline Batteries

Power consumption: Less than 30mA

Battery Life: Two AAA 1.5V, 800mAh alkaline batteries could be continuously operated as long as 28 hours.

7. Environment Requirements

Operation Temperature: 5°C~40°C

Storage Temperature: -20°C~+55°C


Ambient Humidity: ≤80% no condensation in operation; ≤93% no condensation in storage

Atmosphere pressure: 86kPa~106kPa

8. Equipment Response Time

As shown in the following figure.

Response time of slower average is 12.4s.



9. Classification

According to the type of protection against electric shock: INTERNALLY POWERED EQUIPMENT;

According to the degree of protection against electric shock: TYPE BF APPLIED PART (The application part is rubber inside of the Pulse Oximeter);

According to the degree of protection against ingress of water: IPX1

According to the mode of operation: CONTINUOUS OPERATION

FCC Declaration

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and

(2) This device must accept any interference received, including interference that may cause undesired operation.

Please take attention that changes or modification not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note: This product has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This product generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this product does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Declaration

Guidance and Manufacturer's declaration - electromagnetic emissions-For all EQUIPMENT and SYSTEMS

Guidance and Manufacturer's declaration - electromagnetic emission

The MD300C208 Pulse Oximeter is intended for use in the electromagnetic environment specified below. The customer or the user of MD300C208 Pulse Oximeter should assure that it is used in such an environment.

Emission test

Compliance

Electromagnetic Environment – guidance

RF emissions CISPR 11

Group 1

The MD300C208 Pulse Oximeter uses RF energy only for its internal function. Therefore, its RF emissions are very low and are not likely to cause any interference in nearby electronic equipment.

RF emissions CISPR 11

Class B

The pulse Oximeter (MD300C208) is suitable for use in all establishments, including domestic establishments and those directly connected to the public low-voltage power supply network that supplies buildings used for domestic purposes.

Harmonic emissions

Not Applicable

IEC 61000-3-2

Voltage fluctuations/ flicker emissions

Not Applicable

IEC 61000-3-3

Guidance and Manufacturer's declaration - electromagnetic immunity-For all EQUIPMENT and SYSTEMS

Guidance and Manufacturer's declaration - electromagnetic immunity

The MD300C208 Pulse Oximeter is intended for use in the electromagnetic environment specified below. The customer or the user of the MD300C208 Pulse Oximeter should assure that it is used in such an environment.

Immunity test

IEC 60601 test level

Compliance Level

Electromagnetic Environment – guidance

Electrostatic Discharge (ESD)

+/- 6kV contact

+/- 6kV contact

IEC 61000-4-2

+/- 8kV air

+/- 8kV air

Power frequency (50/60 Hz) magnetic field

3A/m

3A/m

IEC 61000-4-8

Floors should be wood, concrete or ceramic tile. If floor are covered with synthetic material, the relative humidity should be at least 30%.

Power frequency magnetic fields should be at levels characteristics of a typical location in a typical commercial or hospital environment.

Guidance and Manufacturer's declaration - electromagnetic immunity-For all EQUIPMENT and SYSTEMS that are not LIFE-SUPPORTING

Guidance and Manufacturer's declaration - electromagnetic immunity

The MD300C208 Pulse Oximeter is intended for use in the electromagnetic environment specified below. The customer or the user of the MD300C208 Pulse Oximeter should assure that it is used in such an environment.

Immunity test

IEC 60601 test level

Compliance Level

Electromagnetic Environment – guidance

Radiated RF

3 V/m

80 MHz to 2.5 GHz

3 V/m

Portable and mobile RF communications equipment should be used no closer to any part of the Pulse Oximeter (MD300C208), including cables, than the recommended separation distance calculated from the equation applicable to the frequency of the transmitter.

Recommended separation distance

$$d=1.2\sqrt{P} \quad 80 \text{ MHz to } 800 \text{ MHz} \quad d=2.3\sqrt{P} \quad 800 \text{ MHz to } 2.5 \text{ GHz}$$

Where P is the maximum output power rating of the transmitter in watts (W) according to the transmitter manufacturer and d is the recommended separation distance in meters (m).

Field strengths from fixed RF transmitters, as determined by an electromagnetic site survey^a, should be less than the compliance level in each frequency range.^b

Interference may occur in the vicinity of equipment marked with following symbol:



NOTE 1 At 80 MHz and 800 MHz, the higher frequency range applies.

NOTE 2 These guidelines may not apply in all situations. Electromagnetic propagation is affected by absorption and reflection

structures, objects and people.

a Field strengths from fixed transmitters, such as base station for radio (cellular/cordless) telephones and land mobile radios, amateur radio, AM and FM radio broadcast and TV broadcast cannot be predicted theoretically with accuracy. To assess the electromagnetic environment due to fixed RF transmitters, an electromagnetic site survey should be considered. If the measured field strength in the location in which the Pulse Oximeter (MD300C208) should be observed to verify normal operation. If abnormal performance is observed, additional measurements may be necessary, such as reorienting or relocating the Pulse Oximeter (MD300C208).

b Over the frequency range 150 kHz to 80 MHz, field strengths should be less than 3 V/m

Recommended separation distances between portable and mobile RF communications equipment and the EQUIPMENT or SYSTEMS - For all EQUIPMENT and SYSTEMS that are not LIFE-SUPPORTING

Recommended separation distances between portable and mobile RF communications equipment and Pulse Oximeter (MD300C208)

The Pulse Oximeter (MD300C208) is intended for use in electromagnetic environment in which radiated RF disturbances are controlled. The customer or the user of the Pulse Oximeter (MD300C208) can help prevent electromagnetic interference by maintaining a minimum distance between portable and mobile RF communications equipment (transmitters) and the Pulse Oximeter (MD300C208) as recommended below, according to the maximum output power of the communications equipment.

Rated maximum output power of transmitter (W)	Separation distance according to frequency of transmitter (m)	
	80 MHz to 800 MHz	800 MHz to 2.5 GHz
0.01	0.1167	0.2334
0.1	0.3689	0.7378
1	1.1667	2.3334
10	3.6893	7.3786
100	11.6667	23.3334

For transmitters rated at a maximum output power not listed above, the recommended separation distance in meters (m) can be estimated using the equation applicable to the frequency of the transmitter, where P is the maximum output power rating of the transmitter in watts (W) according to the transmitter manufacturer.

NOTE 1 At 80 MHz and 800 MHz, the separation distance for the higher frequency range applies.

NOTE 2 These guidelines may not apply in all situations. Electromagnetic propagation is affected by absorption and reflection from structures, objects and people.

Possible Problems and Solutions

Problems	Possible reason	Solution
SpO ₂ or PR can not be shown normally	1. Finger is not inserted correctly 2. Patient's SpO ₂ value is too low to be measured	1. Retry by inserting the finger 2. There is excessive illumination 3. Try some more times. If you can make sure no problem exist in the product, please go to a hospital timely for exact diagnosis.
SpO ₂ or PR is shown unstably	1. Finger might not be inserted deep enough. 2. Excessive patient movement	1. Retry by inserting the finger 2. Be calmness
The oximeter cannot be powered on	1. No battery or low power of battery 2. Batteries might be installed incorrectly 3. The oximeter might be damaged	1. Please replace batteries 2. Please reinstall the batteries 3. Please contact with local customer service centre
Indication lamps are suddenly off	1. The product is automatically powered off when no signal is detected longer than 8 seconds 2. The battery power is too low to work	1. Normal 2. Replace the batteries
"Error3" or "Error4" is displayed on screen	1. Err 3 means the red emission LED is damaged 2. Err 4 means the infra-red emission LED is damaged	1. Check the red emission LED 2. Check the infra-red emission LED
Error 6	Err 6 means the screen is failure	Please contact with local customer service centre
"Error7" is displayed on screen	Err 7 means all the emission LED or reception diode is damaged.	Please contact with local customer service centre

Symbol Definitions

Symbol	Definition	Symbol	Definition
	Type BF applied part.		Attention
	Protected against dripping water.		Oxygen saturation
	Pulse rate (BPM)		Low power indication
	No SpO ₂ Alarm		Serial No.
	Storage temperature and relative humidity		Follow instruction for use
	Manufacturer's information		Date of Manufacture
	Bluetooth indication		Indicate the signal is not stable

Notes:

1. The illustrations used in this manual may differ slightly from the appearance of the actual product.

2. The specifications are subject to change without prior notice.

Applicable Models

MD300C208, MD300C218, MD300C228, MD300C298, MD300C2B8, MD300C2D8, MD300C2F8

Beijing Choice Electronic Technology Co., Ltd.

Room 4104, No. A12 Yuquan Road