

Be responsible and please power on the BLINC unit before riding for your own safety.

Thank you for using BLINC™ BL300 multifunctional remote controller!

This user manual contains quick guide on how to operate BLINC™ BL300 multifunctional remote controller and information on installation, setting of the remote controller. Please read carefully before using the product.

FCC ID:2ADN5BL300



Package content

Please check following content in package:

BLINC™ BL300 multifunctional remote controller

Power on and Power off

BLINC™ BL300 multifunctional remote controller uses 27A battery and it works under power saving mode even without power off the device. The battery lasts one year under normal daily operation.

Pairing

Pairing with Blinc BL200 walkie talkie Bluetooth dongle.

Push pairing button on BL200 walkie talkie Bluetooth dongle for at least 6 seconds after power on, till LED turns stable blue which means dongle is in pairing mode. Push then release any button on BL300 multifunctional remote controller and then push and hold any three buttons at same time in the remote controller till LED light off on BL200 dongle, which means pairing success. Release all the buttons on remote controller and LED will flash in blue at BL200 which means the device is ready for operation.

Pairing with Blinc BL100 integrated Bluetooth speaker.

Push Volume button on BL100 Bluetooth speaker for at least 6 seconds after power on, till LED turns stable blue which means speaker is in pairing mode. Push then release any button on BL300 multifunctional remote controller, then push and hold any two buttons at same time in the remote controller till LED light off which means pairing success. Release all the buttons on remote controller and LED will flash in blue at Bluetooth speaker which means the device is ready for operation.

Mobile phone functions

Call answer

When there is incoming call, press and release the green phone button at remote controller to answer the incoming call.

Call end

When there is incoming call or call conversion is finished, press and release the green phone button at remote controller to hang up.

Note: The above functions can be access through BL300 remote controller only when 7 seconds after BL100 Bluetooth speaker paired with mobile phone.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules.

Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and**
- (2) this device must accept any interference received, including interference that may cause undesired operation.**