



Dell Wyse Windows 10 IoT Enterprise for Wyse 5060 Unified Build Release Notes

Software releases are created to correct defects, make enhancements, or add new features. These releases are tested on all current, actively shipping platforms and operating systems as applicable. This release notes contain details on the supported platforms, any changes in the configuration settings and licensing details as well. The bug fixes along with the workarounds are documented in the release notes. Any changes in the feature functionality from an end-user perspective are listed with the description of each feature at a high level.

Release Date: 2017-05-31

Contents

| | |
|---|----|
| Release type and definition..... | 1 |
| New features..... | 2 |
| General features..... | 2 |
| Fixed issues..... | 5 |
| Known issues..... | 5 |
| Test environment..... | 6 |
| Build details..... | 7 |
| Tested peripherals..... | 7 |
| Used and free space details..... | 9 |
| OS components..... | 9 |
| Common application/features/files | 9 |
| QFEs added in the release..... | 11 |

Release type and definition

This device is installed with Windows 10 IoT Enterprise —WIE10 v12.00 64-bit that supports Wyse 5060 thin client. This Windows version is based on Windows 10 Enterprise 2016 LTSB which is also called Redstone1—RS1 release.

This build can be pushed 64 GB flash and above, with 8 GB RAM.

This release supports WIE10 v12.00 unified build 0A52 for the Ransomware WannaCrypt susceptibility.

WannaCrypt, also known as WannaCry, targets out-of-date Windows systems. This release build contains valid WIE10 security updates—KB4016635 , to protect your system from the ransomware WannaCrypt susceptibility.

The WIE10 v12.00 unified build 0A52 supports English—en-US and the following 10 languages:

- German—de-DE
- French France—fr-FR

- French Canada—fr-CA
- Italian—it-IT
- Spanish—es-ES
- Japanese—ja-JP
- Korean—ko-KR
- Chinese Simplified—zh-CN
- Chinese traditional—zh-TW
- Brazilian Portuguese—pt-BR

New features

The following are the new features delivered in this release are:

Unified build

This build supports English (en-US), and 10 MUI languages—fr-FR, es-ES, de-DE, it-IT, fr-CA, ja-JP, ko-KR, zh-CN, zh-TW, pt-BR.

Threat Defense

Dell Data Protection | Threat Defense (powered by Cylance) detects and blocks malware before it can affect your computer. Cylance uses a mathematical approach for malware identification, using machine learning techniques instead of reactive signatures, trust-based systems, or sandboxes. Cylance's approach renders new malware, viruses, and future variants useless. Dell Data Protection | Threat Defense analyzes potential file executions for malware in the operating system. Threat Defense Agent version is 2.0.1422.6

Threat Defense is an add-on available for purchase.

General features

This section contains general features of Wyse 5060 thin client running WIE10 OS.

Hardware support information

- Rich 4K display capability.
- Option for 802.11 a/b/g/n/ac wireless.
- AMD Stepe Eagle Quad Core 2.4 GHz CPU.
- Support for video adapters (DP to DVI, DP to VGA).
- Dynamic Throttling for higher performance.

Menu driven custom/ConfigMgr sysprep

- Supports Menu driven custom/ConfigMgr sysprep where you can select the particular option.
- Shrinking of disk information available during sysprep that reduces the image pull or push time in larger disks and shrinking should be done from diskmgmt console.

New versions of connection brokers

- VMware Horizon client : v4.3.0.4209



- Citrix Receiver : v14.6.0.12010
- Ericom WebConnect : v7.5.1

Out-of-Box driver install

All the respective device drivers have been pre-installed in the OS as compared to the legacy approach wherein there are pre-staged drivers.

Newer Dell wallpapers

Wyse wallpapers and themes are replaced with the Dell wallpapers and themes.

XML driven PowerShell scripts

Customization scripts are ported to the PowerShell scripts and based on the XML file input.

Logging support

Logging support added for customization scripts.

Flash.sys

Hostname calculation and preservation – This option allows you to enable and disable the Hostname calculation in flash.sys.

- You can disable or enable the Hostname calculation.
- You must ensure that altering the MAC ID for a client does not perform a Hostname calculation.
- Rest of the logic and flow remains the same as older flash.sys implementation.
- If you require a Hostname calculation to perform after a change in MAC ID (NIC card change), then you must use MINWITHNET.

Event Viewer log preservation

This feature allows you to enable or disable Event Viewer log saving while File Based Write Filter (FBWF) is on. This feature enables you to collect event logs if they are required for debugging or analysis purposes.

Dell Thin Client Application

- Dell Thin Client Application is a replacement for Client Information Application with a new User Interface (UI).
- This application contains additional fields for accessing and configuring Custom Fields, RAM Disk, Auto Logon, CAD Map, and System Shortcuts.
- By default, the RAM Disk size is set to 512 MB.



WIE10 0A52 build behavior

Internet Explorer 11

- **Performance enhancements:** IE 11 is the quickest version of the browser yet. Microsoft has included support for web standards like CSS animations, HTML5 spell checking, and improved JavaScript performance.
- **Security enhancements:** The main security addition to IE 11 is **Enhanced Protected Mode**, which locks down parts of the Windows operating system, preventing the browser from accessing the OS.

IE Customizations:

- 1 First run customizations are disabled.
- 2 IE 11 enhanced protection mode is enabled.
- 3 Start page and default page set to www.dell.com/wyse.
- 4 IE Cookies and Cache are redirected to z : RAM Disk.
- 5 Cache content to 250 MB.
- 6 Clears browsing history on IE exit.

Citrix Receiver

USB redirection always works for all users of the client machine with all the published XenDesktop, irrespective of the setting **Simplify device connections for me** in the XenDesktop connection preferences UI.

ENERGY STAR specification

This product meets the ENERGY STAR version 6.0 of the thin client requirement.

The following are the values by default, set in the **Control Panel** applet of the Power options:

- Power option when plugged-in:
 - Supports WOL Power off states.
 - Supports Idle State wake.
 - Screen off timer is set to 10 minutes.
 - Sleep timer is set to 15 minutes.

Microsoft SCCM 2016 R2 information

SCCM is supported for standard deployment of images. SCCM is used to upgrade WES7P to WIE10 on Wyse 5060 thin client with custom procedure for pulling the WIE10 image and BIOS.

For more details, see *Dell Wyse Configuration Admin Guide*.

vWorkspace

After installation of vWorkspace, install.txt file is created in C:\.



Ctrl+Alt+Del (CAD) mapping tool

By default the build contains CAD tool, but in a disabled state.

To enable the CAD tool, do the following:

- 1 Log in to the system using Admin account.
- 2 Disable the Write Filter.
- 3 Launch command prompt in elevated mode.
- 4 Run `cd c:\windows\system32`.
- 5 Run `DWKBFilterMon.exe -enable` and reboot.

Fixed issues

The following table lists the fixed issues in this release:

| Sl.no | Issue description |
|-------|--|
| 1 | WIE10: Windows may not respond for 1-2 minutes when accessing the file browser or any windows Applications/settings. |
| 2 | Sysprep tool not working. |
| 3 | BitLocker protection should suspend on executing <code>WIE10_CustomSysprep4man.ps1</code> |
| 4 | WIE10 clients are not discovered in SCCM server. |

Known issues

The following table lists the known defects in this release:

Table 1. Known issues

| Sl.no | Issue description | Work around—if any |
|-------|---|------------------------------------|
| 1 | Domain login configuration during Custom Sysprep will prompt four warning messages if you click on submit without entering the details. | The functionality is not affected. |
| 2 | Admin password change during sysprep needs confirmation option. | Enhancement |
| 3 | Build Master script terminates abruptly when alphabets or special characters are entered instead of numbers while selecting the type of sysprep | The functionality is not affected. |
| 4 | WIE10 RS (zh-TW) - Run Time Commands not localized in respective language | The functionality is not affected. |
| 5 | WIE10 RS (zh-CN) - Run Time Commands not localized in respective language | The functionality is not affected. |
| 6 | WIE10 RS (ko-KR) - Run Time Commands not localized in respective language | The functionality is not affected. |
| 7 | Web camera is not redirected inside vWorkspace session. | Vworkspace EOL |
| 8 | Reports Icon in WDM WebUI to be changed | The functionality is not affected. |



| Sl.no | Issue description | Work around—if any |
|-------|--|--|
| 9 | No capital letters are supported in Image name field (WDM 5.7.2 WebUI) | The functionality is not affected. |
| 10 | WIE10 RS (pt-BR) - Run Time Commands not localized in respective language | The functionality is not affected. |
| 11 | WIE10 RS (fr-FR) - Run Time Commands not localized in respective language | The functionality is not affected. |
| 12 | WIE10 RS (es-ES) - Run Time Commands not localized in respective language | The functionality is not affected. |
| 13 | WIE10 RS (ja-JP) - Run Time Commands not localized in respective language | The functionality is not affected. |
| 14 | WIE10 RS (it-IT) - Run Time Commands not localized in respective languages | The functionality is not affected. |
| 15 | WIE10 RS (fr-CA) - Run Time Commands not localized in respective language | The functionality is not affected. |
| 16 | WIE10 RS (de-DE) - Run Time Commands not localized in respective language | The functionality is not affected. |
| 17 | Wyse 5060 RS - In UWF, after second warning without any time delay system gets reboot | The functionality is not affected. |
| 18 | Client reboots two times without any notification on screen when clear TPM is initiated from BIOS, and TPM status remains initialized. | The functionality is not affected. |
| 19 | Item specific help does not describe about Roll Back option in BIOS. | The functionality is not affected. |
| 20 | Unable to configure common image in USB imaging tool. | USB Solution is under testing |
| 21 | Data wipe information is not appearing on screen when disk wipe is selected in BIOS. | The functionality is not affected. |
| 22 | PAD imaging is not working on Solano 5060–WIE10_RS. | Add-on Fix will be released |
| 23 | AMD installer update dialog appears while executing first boot scripts. | The functionality is not affected. |
| 24 | Domain join fails in first boot script when domain user password is set to dellwyse. | Do not use the password during custom sysprep with any character ending with d, e, l, w, y, and s |
| 25 | Auto login fails while executing first boot script if password is set to password. | Do not use the password during custom sysprep with any character ending with p, a, s, w, o, r, and d |

Test environment

Table 2. SFP modules details

| Platform | SFP module |
|----------------------------|---|
| Dell Wyse 5060 thin client | <ul style="list-style-type: none"> · DELL 09DN5J –100 MBPS · DELL-0GF76J –1.0 GBPS · DELL-0J6FGD –1.0 GBPS |



Build details

Table 3. General build details

| | |
|--------------------------|---|
| Platform | Dell Wyse 5060 thin client |
| Product | WIE10 |
| Build version | 12.0 |
| Build number | 0A52 |
| Localization | English, French France, German, Italian, French Canada, Spanish, Japanese, Chinese Simplified, Chinese traditional, Korean, Portuguese Brazil |
| WSI/Wizard compatibility | 5.0.4 (build 259) |
| WDM | 5.7.2 |
| BA version | 3.4.7 |
| USB Imaging tool | 2.1.4 (under testing) |

Table 4. Platform specific build details—WDM package

| | |
|------------------------|---|
| Version | 12.0 |
| Build number | 0A52.32GB |
| Build WSI Package Name | 5060_0A52_32GB.exe |
| Build size (Bytes) | 12,903,030,114 |
| Localization | English, French France, German, Italian, French Canada, Spanish, Japanese, Chinese Simplified, Chinese traditional, Korean, Portuguese Brazil |

Table 5. BIOS details

| | |
|-----------------|-----------------------|
| Platform | Wyse 5060 thin client |
| Version | 1.0F |
| Build File Name | 1.0F |

Tested peripherals

Table 6. Tested peripherals

| |
|--|
| Product |
| Dell Pro Stereo Headset UC300 |
| Dell USB Sound bar AC511 |
| Dell 2.0 Speaker System AE215 |
| Jabra Pro 935 MS Wireless headset (Mono) |
| Jabra Pro 930 MS Wireless headset |



| Product |
|--|
| Logitech B525HD webcam |
| Dell Tray Load CD/DVD player(DW316) |
| Dell USB Wired Keyboard - KB216 |
| Dell USB Wired Optical Mouse - MS116 |
| Dell USB Wired Keyboard with Smart Card reader - KB813 |
| Dell Wireless Mouse - WM326 |
| Dell 24 Monitor - E2417H |
| Dell 23 Monitor- E2316H |
| Dell 22 Monitor - E2216H |
| Dell 20 Monitor - E2016H |
| Dell 20 Monitor - E2016 |
| Dell 19 Monitor - E1916H |
| Dell 19 Monitor - E1916HV |
| Dell 27 Monitor - P2717H |
| Dell 24 Monitor - P2417H with stand |
| Dell 24 Monitor - P2417H without stand |
| Dell 23 Monitor - P2317H |
| Dell 22 Monitor - P2217H with stand |
| Dell 22 Monitor - P2217H without stand |
| Dell 22 Monitor - P2217 |
| Dell 22 Monitor - P2217 without stand |
| Dell 20 Monitor - P2016 |
| Dell 19 Monitor - P1917S |
| Dell 24 Monitor - U2415 |
| Dell 25 Monitor- U2515H |
| Dell 27 Monitor - U2717D |
| Dell 27 Monitor - U2717DA |
| Dell 43 Monitor - P4317Q |
| Dell 24 Monitor - MR2416 |
| Dell 27 monitor - P2715Q 4K2K (UHD) monitor |
| Dell 24 Monitor - P2415Q 4K2K (UHD) monitor |
| Dell 30 Monitor – UP3017 |
| Power adapter + 3 foot power cord |
| Dell Mono Unmanaged Printer - E515dn |



| Product |
|---------------------------------------|
| Dell Color Unmanaged Printer - E525w |
| Dell Color Managed Printer - S5840cdn |
| DP to HDMI converter |
| DP to DVI converter |
| DP to VGA converter |

Used and free space details

Table 7. Used and free space details

| Platform | Flash size | Used Space (C: Drive) | Free space |
|----------------------------|------------|-----------------------|------------|
| Dell Wyse 5060 thin client | 64 GB | 15.7 GB | 43.1 GB |

OS components

Table 8. Driver details

| | |
|----------------------------------|---|
| BIOS | 1.0F |
| Display Adapter | AMD Radeon (TM) R5E Graphics —16.300.2501.0 |
| Ethernet Adapter | Realtek PCIe GBE Family Controller - 10.16.323.2017 |
| Audio | <ul style="list-style-type: none"> AMD High Definition Audio Device — 10.0.1.0 Realtek High Definition Audio — 6.0.1.7898 |
| Wireless Adapter | Intel® Dual Band Wireless AC 7265 - 19.10.0.9 |
| Bluetooth | 19.1.1627.3533 |
| USB xHCI driver | AMD USB 3.0 eXtensible Host Controller -1.0 (Microsoft) -10.0.14393.0 |
| Dell Keyboard driver application | For KM632 and KB212-B |
| Wyse RAM Disk driver | 5.0.2183.5 Default value is 512 MB. |
| Flash.sys | 1.0.71 |
| Dell Open Print Driver | 1.91.7882.0 |

Common application/features/files

Table 9. Common application/features/files

| Application/features/files | Version—if applicable |
|----------------------------|-------------------------------|
| RDC | 10.0.14393—RDP 10.2 Supported |



| Application/features/files | Version—if applicable |
|--|--|
| | 10.0.14393.0—In Dell Thin Client Application |
| Citrix Receiver—Standard | 4.6.0.12010—In Citrix About |
| | Citrix Online Plugin -14.6.0.12010—In Client Application , Programs, and Features |
| Citrix HDX Real Time Media Engine | 2.1.200 |
| VMware Horizon Client | 4.3.0.4209—In Client Application, Programs, and Features |
| | 4.3.0—In VMware Horizon Client about |
| vWorkspace client | 8.6.309.4062 |
| Ericom PowerTerm Interconnect for Thin Clients | 12.0—In Client Application, Programs, and Features |
| SCCM client | SCCM 2016 client-5.00.8412.1307—In control panel > Configuration manager |
| Windows Media Player | 12.0.14393—In Client Info |
| Internet Explorer | 11.00.14393—About Internet Explorer |
| Adobe Flash player 21 NPAPI | 21.0.0.213—programs and features |
| Tight VNC | 2.6.4—In Client Info, About |
| Ericom connect web connect | 7.5.1—In programs and features, and Client Application |
| .NET Framework | 4.6.2 |
| WDA | 12.1.5.6 |
| Bit locker with TPM | Supported |
| Windows Multi touch | Supported |
| Windows Defender with latest definition | 1.239.1256.0 |
| Microsoft Management Console | Management Console 3.0 |
| | Version 1607—OS Build 14393.5 |
| Microsoft Silverlight | 5.1.50905.0 |
| Background Intelligent Transfer Service (BITS) | Supported |
| MSXML | Supported |
| XML Paper Specification (XPS) | Supported |
| Network Access Protection | Not Supported |



| Application/features/files | Version—if applicable |
|---|---|
| Credential Roaming | Supported |
| WPA2 | Supported |
| CredSSP | Supported |
| Dell Wyse Wallpaper on All Users | Supported |
| DirectX | 12 |
| DellThinClientApplication.exe —NewClient Application | 10.0.0.11 |
| Unified Write Filter manager -Uwfmgr.exe —File Version | 10.0.14393.0 |
| UWF system tray UI – UWFTray.exe | 1.0.4.6 |
| UWF Service – UWFSvc.exe | 1.0.4.6 |
| NetXClean.exe | 3.0.0.8 |
| Disk_Size.exe | 3.0.0.5—in setup |
| DeleteFreeSpace.exe | 1.2.1.0—in setup |
| Custom Sysprep support in scripts | Supported |
| Windows Time Service | Supported |
| FI Core changes | Scripts changes are part of the build but not validated as per the scope of this build. |
| WinPing | 1.0.0.5 |
| Dell Open printer driver | 1.91.7882.0 |
| Dell CAPS Lock indicator application | 2.1.10.0604 |
| CAD MAP Application | 2.3.0.1 |
| DWKbFilter.sys | 2.2.0.4 |
| DWKbFilterMon.exe | 2.2.0.4 |
| DWKbFilterWatchdog.exe | |

QFEs added in the release

| Security Update |
|------------------------|
| KB4016635 |
| KB3202790 |



Copyright © 2017 Dell Inc. or its subsidiaries. All rights reserved. Dell, EMC, and other trademarks are trademarks of Dell Inc. or its subsidiaries. Other trademarks may be trademarks of their respective owners.

