

## AVAYA PARTNER ACS R7.0 (5X9) CONTROL UNIT (700316474) Introduced to the Partner family (July 2004)

Maximum system configurations: 11 outside lines x 48 station, 31 outside lines x 25 stations

The PARTNER ACS processor module provides the software intelligence that controls the system's features. It has jacks for 5 outside lines and 9 extensions, a Music- On-Hold audio source, a grounding screw, a jack that supports an adjunct for two Contact Closures, and a jack for a call reporting (SMDR) device, such as a printer. You can connect a loudspeaker paging system to any line jack on the PARTNER system. (If your loudspeaker paging system requires a "dry contact relay," you must connect the loudspeaker paging system to line jack 5.) The processor module also has two PC Card slots, a two-color red and green light-emitting diode (LED), and two AAA user-replaceable batteries to retain customer memory translations (programming) for around 6 months without power being supplied to the unit. The module provides support for integrated Caller ID information on system display telephones.



### Features:

- ✓ All features of Partner ACS R6.0 & earlier

**The PARTNER ACS 509 processor module**, which contains up to five lines and nine extensions.

**Loudspeaker Paging Line** to allow you to connect a loudspeaker paging system to any linejack on any PARTNER module.

**Enhanced backup/restore capabilities** to allow you to back up the PARTNER system programming to either the internal memory of the PARTNER ACS R7.0 processor module or a PC Card.

**An RJ-45 serial port** (Admin port) on the PARTNER ACS R7.0 processor module to allow you to connect to the PARTNER system either directly from the COM port of a PC or via an external modem that is connected to the Admin port and administer the system via PARTNER ACS R7.0 PC Administration software.

### Voicemail Capabilities:

- ✓ Partner VS Mail (all releases)
- ✓ Partner mail (all releases)
- ✓ Partner Messaging (all releases)
- ✓ PC Messaging (release 2.0 & higher)
- ✓ 3<sup>rd</sup> party voicemail interface through any extension of the ACS or an extension on the 206 module R3.1 or higher/each port requires a station

## Hardware Compatibilities:

### Modules:

Compatible with the following modules using a 2 slot carrier or 5 slot carriers:

- ✓ 012 E
- ✓ 206 E R1.0, R2.0, R3.0, R3.1, R4.0, R4.1
- ✓ 206 EC R3, R3.1, R4.1
- ✓ 200 E R2.0, R3.1
- ✓ 308 EC R1.0, R3.0
- ✓ 362 EC (supports 3 lines caller ID x 8 Endeavor telephones)
- ✓ 400 E R2.0, R3.1
- ✓ 400 EC R3.0, R3.1
- ✓ 1600 DSL (only 1 per system)

### Telephone sets:

System is compatible with the following telephone sets:

- |                              |                                       |
|------------------------------|---------------------------------------|
| ✓ MLS-6                      | ✓ Partner 6D (series II)              |
| ✓ MLS-12                     | ✓ Partner 18D (series II)             |
| ✓ MLS-12D                    | ✓ Partner 34D (series II)             |
| ✓ MLS-18D                    | ✓ CA-24 (Call assistant)              |
| ✓ MLS-34D                    | ✓ CA-48 (Call assistant)              |
| ✓ Partner 6 button           | ✓ Partner cordless MLC-6/905 cordless |
| ✓ Partner 18 button          | ✓ Partner cordless MLC-6/905 cordless |
| ✓ Partner 18D                | ✓ Transtalk 9000/MDW 9000 cordless    |
| ✓ Partner 34D                | ✓ Transtalk 9030/9031/9040            |
| ✓ Partner Endeavor 6 button  | ✓ 3910 Wireless                       |
| ✓ Partner Endeavor 18 button | ✓ Partner Door Phone                  |
| ✓ Partner Endeavor 18D       | ✓ Contact Closure Adjunct             |
| ✓ Partner Endeavor 34D       |                                       |

*Single line sets (LED message waiting light only supported – no neon message waiting lights supported)*

**Remote Administration Software capabilities**