

KF750Px/KF755Px Processor Settings

January 2, 2006



OUTPUT	Name
GAIN	(dB)
DELAY	(ms)
POLARITY	
HPF	Freq (Hz)
	Slope (dB)
	Shape
LPF	Freq (Hz)
	Slope (dB)
	Shape
PEQ1	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ2	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ3	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ4	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ5	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)

KF750Px bi-amp

LF	MF/HF
5.0	-4.0
0.00	0.00
Positive	Positive
40	177
24	24
Linkwitz-Riley	Butterworth
177	21983
24	24
Linkwitz-Riley	Linkwitz-Riley
	1335
	4.5
	Parametric
	2.38
	0.42
	630
	-2.0
	Parametric
	3.56
	0.28
	2448
	1.5
	Parametric
	6.35
	0.16
	315
	4.0
	Parametric
	3.78
	0.26
	6169
	1.0
	Parametric
	2.00
	0.50

KF755Px bi-amp

LF	MF/HF
7.0	-4.0
0.00	0.00
Positive	Positive
40	193
24	24
Linkwitz-Riley	Butterworth
193	21983
24	24
Linkwitz-Riley	Linkwitz-Riley
	149
	-3.5
	Parametric
	3.56
	0.28
	687
	-3.0
	Parametric
	5.04
	0.20
	334
	2.0
	Parametric
	4.76
	0.21
	5657
	2.0
	12 dB Hi Shelf
	n/a
	n/a
	4000
	-1.0
	Parametric
	2.00
	0.50

NOTE: To use system with sub, high pass LF @ 80-100 Hz (24 dB Butterworth).

Output gains assume all amplifiers have the same voltage gain