

SERVICE BULLETIN PNFSB0027

Models: Refer to chart on second page.

Symptom: Dead Set - Open fuse

Cause: 200V zener diode located just after the bridge rectifier shorted.

Cure: Remove the diode, replace fuse. Do not replace the diode. Perform any additional repairs if necessary.

Diode location on the chart located on the next page.

Brand	Model	Diode to Delete
Philips	19PFL3505D/F7	D620
Philips	22PFL4505D/F7	D606
Philips	32HFL3663S/F7	D621
Philips	32PFL3505D/F7	D621
Philips	32PFL3506/F7	D621
Philips	32PFL3515D/F7	D621
Philips	40HFL3683S/F7	D1208
Philips	40PFL3505D/F7	D1208
Philips	40PFL3705D/F7	D1208
Philips	40PFL3706/F7	D1208
Philips	40PFL5706/F7	D1208
Philips	46HFL3683S/F7	D1208
Philips	46PFL3706/F7	D1208
Philips	46PFL5706/F7	D1208
Philips	55PFL5706/F7	D1208
Magnavox	19MD301B/F7	D612
Magnavox	19MD311B/F7	D612
Magnavox	19MD350B/F7	D606
Magnavox	19ME360B/F7	D606
Magnavox	19ME601B/F7	D601
Magnavox	19MF301B/F7	D610
Magnavox	22MD311B/F7	D612
Magnavox	22ME360B/F7	D606
Magnavox	22ME601B/F7	D601
Magnavox	22MF330B/F7	D606
Magnavox	26MD301B/F7	D612
Magnavox	26MD311B/F7	D622
Magnavox	26MD350B/F7	D606
Magnavox	26MF330B/F7	D606
Magnavox	32MD301B/F7	D620
Magnavox	32MD311B/F7	D620
Magnavox	32MF301B/F7	D611
Magnavox	37MD311B/F7	D620
Magnavox	37MF301B/F7	D620
Magnavox	40MF401B/F7	D1208
Magnavox	40MF430B/F7	D1208
Emerson	LC190EM2	D610
Emerson	LC220EM1	D606
Emerson	LC220EM2	D611

Emerson	LC260EM1	D606
Emerson	LC260EM2	D620
Emerson	LC260EM2	D622
Emerson	LC320EM2	D611
Emerson	LC320EM2F	D611
Emerson	LC401EM2	D1208
Emerson	LC401EM2F	D1208
Emerson	LC407EM1	D1208
Emerson	LD190EM1	D606
Emerson	LD190EM2	D612
Emerson	LD260EM1	D606
Emerson	LD320EM1	D606
Emerson	LD320EM2	D620