

## VISTA-250FBP/V250FBP-24

COMMERCIAL PARTITIONED FIRE AND  
BURGLARY ALARM CONTROL PANEL



Now UL864 9th Edition Approved

Designed to integrate seamlessly with CCTV, access control and Honeywell's full range of fire and burglary components, the new VISTA-250FBP provides the ultimate protection of life and property. The UL Listed commercial fire and burglary control panel supports up to eight partitions and up to 250 zones/points using hardwired, wireless and V-Plex®

addressable technologies. A diverse line of Honeywell initiating devices, notification circuits, communication devices, keypads, RF receivers and relays are also supported. The VISTA-250FBP has been designed to mount quickly and easily in an attack resistant cabinet, and is available in 12V and 24V models.

## FEATURES

- Comes standard with eight hardwired zones, expandable to 242 V-Plex addressable points/zones or 250 wireless points/zones
- Can control eight separate areas independently (eight partitions)
- Supports commercial wireless fire and burglary devices
- Stores up to 1,000 events
- Supports V-Plex addressable VistaKey access control (up to 15 doors)
- Accommodates 150 user codes and up to 500 access card holders using VistaKey
- Two on-board notification (bell) circuits delivering 2.3A @ 12V or 3.4A @ 24V
- Automatic smoke detector sensitivity maintenance testing
- Four-wire smoke reset using onboard J2 output trigger
- Supports Dynamic Signaling for AlarmNet communicators used in conjunction with the phone line
- Supports remote control via AlarmNet Total Connect Services\*
- Supports Internet Alarm Reporting\*
- Notification Appliance Circuits (two):
  - Programmable
  - Individually silenceable
- Programmable on-board auxiliary relay
- False alarm reduction features:
  - Exit error logic
  - Exit delay reset
  - Cross zoning
  - Call waiting defeat
  - Recent close report
- Hardwired zones:
  - Provides eight style B hardwired zones
  - Supports N.O. or N.C. sensors
  - Individually assignable to any partition – Up to 32 two-wire smoke detectors each on zones one and two (64 total)
  - Up to 50 two-wire glassbreak detectors on zone eight
  - EOLR supervised for Fire and UL burglary installations
- Listed to UL864 9th Edition
- Upload/download via Ethernet\*
- Carbon Monoxide (CO) zone support

\*When used with AlarmNet devices.

# VISTA-250FBP/ V250FBP-24

COMMERCIAL PARTITIONED FIRE AND  
BURGLARY ALARM CONTROL PANEL

# Honeywell

## ADDITIONAL FEATURES

---

- Patented addressable polling loop technology
  - Supports 242 two-wire zone points
  - Global polling technology for faster processing
  - Supervised by panel
  - Zones individually assignable to partitions, notification circuit (bell) output or auxiliary relay
  - 4,000 ft. capability without the use of shielded cable
  - Extender/Isolation bus modules
  - Eight zone – Class A and B expander module
  - Eight zone – Class B expander module
  - One zone supervised contact monitor module
- UL Listed wireless expansion
  - Supports up to 250 wireless zones/points
  - Supervised by control for check-in signals
  - Tamper protection for transmitters
  - Individually assignable up to eight partitions
- Access Control Integration
  - Full integration with PassPoint Access Control System
- Up to 15 doors using VistaKey Access Control
- Event reporting
- Local printer of access or VISTA related events
- Communication
  - Phone mapping by zone response type
  - Panel operation during download

### Applications

Supported by a diverse line of Honeywell initiating devices, the VISTA-250FBP is the ideal integrated fire and burglary control for applications where a high level of security is necessary. Some examples of applications include: medical and professional buildings, supermarkets, churches, synagogues, schools, universities, strip malls, factories, warehouses, and larger residences.

## SPECIFICATIONS

---

### Electrical

- Primary power: 18VAC @ 72VA  
ADEMCO No. 1451
- Control Panel quiescent current draw: 300mA
- Backup battery:
  - 12VDC, 12AH min to 34.4AH max
  - Lead acid battery (gel type)
- Alarm power: 12VDC, 1.7A max for each notification (bell) circuit output  
Total 2.3A @ 12V
- Aux. standby pwr: 12VDC, 1A max
- Total power: 2.3A at 12VDC, 3.4A at 24VDC from all sources
- Standby time: 24 hours with 1A standby load using 34.4AH battery
- Fusing: Battery input, aux. and notification (bell) circuit outputs are protected using PTC circuit protectors. All outputs are power limited
- Optional 24-volt power supply, PS 24 supplies two 24 VFW, 1.7A full wave rectified, unfiltered outputs

### Main Dialer

- Line seize: Double Pole
- Ringer equiv.: 0.7B
- Formats: ADEMCO Low Speed, ADEMCO 4+2 Express, ADEMCO High Speed, ADEMCO Contact ID, Sescoa and Radionics
- Dual phone line capability (using 5140DLM module)

### Cabinet Dimensions

- 18" H X 14.5" W X 4.3" D

### Environmental

- Storage temp:  
14° F to 158° F  
(-10° C to 70° C)
- Operating temp:  
32° F to 122° F  
(0° C to 50° C)
- Humidity: 85% RH
- EMI: Meets or exceeds the following requirements:
  - FCC Part 15, Class B Device
  - FCC Part 68
  - IEC EMC Directive

### Agency Listings

- UL609 Grade A Local Mercantile Premises and Mercantile Safe and Vault
- UL611/1610 Grades A, AA, Central Station
- UL365 Grades A, AA Police Connect
- UL864/NFPA72 Local, Central Station and Remote Station
- UL985
- Factory Mutual
- California State Fire Marshal
- MEA
- CAN/ULC S304 – Central and Monitoring Station Burglar Alarm Unit
- CAN/ULC S527 – Central Unit for Fire Alarm Systems
- CAN/ULC S303 – Local Burglar Alarm Unit
- CAN/ULC S525 – Audible Signal Appliances

# VISTA-250FBP/V250FBP-24

COMMERCIAL PARTITIONED FIRE AND BURGLARY ALARM CONTROL PANEL

## COMPATIBLE DEVICES

### Auxiliary Devices

- 4204 – Relay Module, four form C contacts
- 4204CF – Two supervised output circuits
- 5881 Series RF receiver
- 5883H RF receiver
- 6220S – System printer used with 4100SM serial module
- 6160CR-2 – Red Fire Keypad
- 6160 – Burglary Keypad

### Two-Wire Smoke Detectors Conventional

- System Sensor
- ESL
- DSC

### Horn/Strobes

- System Sensor
- Wheelock
- Gentex

### Manual Pull Stations

- 5140MPS-1
- 5140MPS-2

### V-Plex (Addressable) Zone Expanders

- 4101SN Single Relay/Zone Module

- 4190SN Remote Point Module – two zones
- 4193SN Two Zone Serial Interface Module
- 4208SNF Class A/B Expander Module
- 4208U Loop Expansion Module – eight zones
- 4293SN One Zone Serial Interface Module

### V-Plex Extender/Isolation Modules

- 4297 Extender/Isolator Module
- VSI Isolator Module

### V-Plex Smoke Detectors

- 5193SD
- 5193SDT

### V-Plex Passive Infrared Detectors

- 998MX
- IS2500SN
- DT7500SN

### V-Plex (Addressable) Contacts

- 4939SN-WH
- 4944SN-WH
- 4959SN

### V-Plex Glassbreak Detectors

- FG1625SN

### Optional 24V Power Supply

- PS24 – 24V power supply – 3.4A

### Commercial Wireless Devices

- 5808W3 – Photoelectric Smoke/Heat Detector
- 5806W3 – Photoelectric Smoke Detector
- 5809 – Wireless Heat Detector
- 5817CB – Wireless Commercial Transmitter
- 5869 – Hold up Transmitter
- 5881ENHC – RF Receiver
- 5883H – RF Receiver

### Access Control

- VistaKey V-Plex (addressable) Access Control
- VistaKey-SK Starter Kit
- VistaKey-EX Expansion Kit

### Alarm Communications

- 7845i-ENT – Internet/Intranet Communicator
- 7845GSM – Digital Cellular Communicator
- 7845i-GSM – Internet and Digital Cellular Communicator
- GSMCF/iGSMCF – Commercial Fire Communication Kits (when available)

Product specifications subject to change.

## ORDERING

### V250FBP-9

Commercial Fire and Partitioned Burglary Alarm Control Panel 12V Model

### V250FBP9-24

Commercial Fire and Partitioned Burglary Alarm Control Panel 24V Model

For more information: [www.honeywell.com/security/hsc](http://www.honeywell.com/security/hsc)

### Automation and Control Solutions

Honeywell Security & Communications  
2 Corporate Center Dr. Suite 100  
Melville, NY 11747  
1.800.467.5875  
[www.honeywell.com](http://www.honeywell.com)



L/VSTA250FBPD/D  
September 2009  
© 2009 Honeywell International Inc.