

# SuperTooth **BTD4**



**Bluetooth™**

## SuperTooth BT4

SuperTooth BT4 is a portable, powerful wireless speaker featuring NFC technology. Users can stream music wirelessly from any cell phone, tablet, computer, laptop or Mp3 player supporting Bluetooth A2DP\*. The SuperTooth BT4 comes with 3.5 mm stereo jack cable for devices that do not support Bluetooth A2DP.

### Product Overview



### Charging the SUPERTOOTH BT4

1. Connect the charger's plug into the Charger Port of the SuperTooth BT4. Connect the charger to an external power source or to your computer USB.
2. The Charge Indicator will light red while charging.

### Turning the SUPERTOOTH BT4 On and Off

**Power On:** Press and hold the MFB button for 3 seconds. A power on beep will be heard on the speaker.

**Note:** At first time use, turning on the SuperTooth BT4 will automatically go to pairing mode (ready to be pair).

**Power Off:** Press and hold the MFB button for 3 seconds. A power off beep will be heard on the speaker.

\*A2DP (Advanced Audio Distribution Profile) is a technology enabling to stream stereo sound from an audio source (phone, computer or laptop) to a stereo speaker or headset via Bluetooth. To do so both devices must support this profile.

## Pairing the SuperTooth BT4 with your Bluetooth A2DP phone

Pair the SuperTooth BT4 to your phone to create the link or audio connection between the two. Pairing should be done at first connection to a phone.

### NFC Pairing:



1. Turn "ON" the SuperTooth BT4.
2. Place your NFC supported phone on top of the speaker (see image above).
3. The speaker will go to pairing mode (a pairing beep will be heard on the speaker and the LED indicator will turn red/blue alternately) and your phone will prompt for pairing connection.
4. Follow the pairing prompts on your phone until pairing is finished.
5. Pairing is successful if the LED indicator blinks blue every 3 seconds.
6. The SuperTooth BT4 is now ready to use with your phone.

### Pairing from Off:

1. From Off, Press and hold the MFB button for 8 seconds until the LED indicator flashes red/blue alternately. This indicates that the SuperTooth BT4 is ready to be paired.
2. While the SuperTooth BT4 is in pairing mode, access the Bluetooth menu of your phone. Turn on its Bluetooth function then execute a Bluetooth search to find the SuperTooth BT4. (See your phone's manual).
3. When the phone displays the list of Bluetooth devices, select ST DISCO4.
4. If the phone asks for the password/pin code, enter 0000 and press OK.
5. Pairing is successful if the LED indicator blinks blue every 3 seconds.
6. The SuperTooth BT4 is now ready to use with your phone/device.

### Pairing from On:

1. From On, Press and hold the MFB button for 5 seconds until the LED indicator flashes red/blue alternately. This indicates that the SuperTooth BT4 is ready to be paired.

Note: if the button is released at 3 seconds, it will just turn off the speaker.

2. Follow the step no. 2 up to 5 of "Pairing from Off".
3. The SuperTooth BT4 is now ready to use with your phone/device.

## Using the SUPERTOOTH BT4 with your Bluetooth A2DP phone

**IMPORTANT:** The SuperTooth BT4 needs to be “paired” with your phone first. Please refer to Pairing the SuperTooth BT4 with your Phone.

### Streaming Music from an A2DP Phone

1. Go to your phone’s music player and play a track by pressing “Play” on your player or short press the MFB button on the speaker. If the SuperTooth BT4 is connected, the music will be heard directly in the speaker. See your phone’s manual if needed.
2. Audio is now on the SuperTooth BT4. At this point, the LED indicator blink blue slowly every 3 seconds indicating that phone is streaming with the SuperTooth BT4.

### SUPERTOOTH BT4 Button Functions (for Bluetooth connections only)

The SuperTooth BT4 can play and pause through MFB Button.

- ▶ To **play** a track, short press the MFB Button on the speaker.
- ▶ To **pause** a track, short press the MFB Button on the speaker.

Other control functions can be done through your phone (like: volume adjustment, go to next or previous song, rewind or fast forward of music). See your phone’s manual if needed.

### Reconnecting the SUPERTOOTH BT4 with a Bluetooth A2DP phone

1. Turning ON the SuperTooth BT4 will automatically reconnect to the last use device.
2. When you leave the Bluetooth operating range while the SuperTooth BT4 is ON, it will disconnect from your phone (the speaker LED indicator will be blinking green). To reconnect, you have 2 options:
  - a. short press the MFB Button of the speaker to reconnect on your phone or
  - b. simply place your NFC featured phone on top of the speaker. A connected beep will be heard and the speaker LED indicator will turn to blinking blue.

## Using the SUPERTOOTH BT4 with a Non-Bluetooth Mp3 Player

You can connect directly a MP3 player via Stereo Line Input at the back of the SuperTooth BT4.

1. Plug the audio cable into the Stereo Line Input found at the back of the SuperTooth BT4 and the other end to the output of your music player.
2. Press play on your music player to stream music directly to the SuperTooth BT4.
3. Please use the buttons of your music player directly to control your music.

## Clear pairing list

### To clear the pairing list of the speaker

Turn the speaker to pairing mode (LED indicator flashes red/blue alternately) then double press the MFB button. A beep will be heard and the LED indicator will blink violet shortly then will flash red/blue alternately again. The pairing List is now erased.

### Correct Disposal of This Product (Waste Electrical & Electronic Equipment)

(Applicable in the European Union and other European countries with separate collection systems).



This marking shown on the product or its literature, indicates that it should not be disposed with other household wastes at the end of its working life. To prevent possible harm to the environment or human health from uncontrolled waste disposal, please separate this from other types of wastes and recycle it responsibly to promote the sustainable reuse of material resources.

Household users should contact either the retailer where they purchased this product, or their local government office, for details of where and how they can take this item for environmentally safe recycling.

Business users should contact their supplier and check the terms and conditions of the purchase contract. This product should not be mixed with other commercial wastes for disposal.

This product has an embedded, non-replaceable battery, do not attempt to open the product or remove the battery as this may cause injury and damage the product. Please contact the local recycling facility for removal of the battery. The embedded, non-replaceable battery is designed to last the life time of the product.

+

**FCC/IC statements :**

Federal Communications Commission (FCC) Statement

Industry Canada (IC) Statement

15.21

You are cautioned that changes or modifications not expressly approved by the part responsible for compliance could void the user's authority to operate the equipment.

15.105(b)

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC/IC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures :

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with Industry Canada licence-exempt RSS standard(s)

Operation is subject to the following two conditions :

- 1) This device may not cause interference and
- 2) This device must accept any interference, including interference that may cause undesired operation of the device.

**FCC/IC RF Radiation Exposure Statement :**

This equipment complies with FCC/IC radiation exposure limits set forth for an uncontrolled environment. End users must follow the specific operating instructions for satisfying RF exposure compliance. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

The *Bluetooth*® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by Euro-CB is under license. Other trademarks and trade names are those of their respective owners.

# C € 0560

**English**

Hereby, Euro CB Phils inc, represented by MARCHANT, CEO, declares that the MODEL BT4, is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC of the European Parliament and of the Council of 9 March 1999 on radio equipment and telecommunications terminal equipment and the mutual recognition of their conformity.

For the whole declaration please visit :

<http://www.SuperTooth.net/download>

Euro CB Phils inc

SFB2, MEPZ1

6015 Lapu-lapu city

**Cebu Philippines**

NCC Statement:

根據低功率電波輻射性電機管理辦法規定:

第十二條: 經型式認證合格之低功率射頻電機, 非經許可, 公司、行號或使用者均不得擅自變更頻率, 加大功率或變更原設計之特性及功能。

第十四條: 低功率射頻電機之使用不得影響飛航安全及干擾合法通信; 經發現有干擾現象時, 應立即停用, 並改善至無干擾時方得繼續使用。

**低功率射頻電機須忍受合法通信或工業、科學及醫療用電波輻射性電機設備之干擾。**