

BTF4XT

Bluetooth Headset for Motorcycle

Features

*VOX Technology
A2DP Music Streaming
Auto-Volume Level Adjusting*



A. PRODUCT DESCRIPTION:

BTF4XT is a Bluetooth Headset designed for motorcycle rider or passenger who wishes to have reliable hands-free, wireless and clear communications while driving. This headset is equipped with hi-tech features such as: VOX Technology, **A2DP** (Advance Audio Distribution Profile) music streaming and Auto-Volume Level Adjusting.

1. **MFB or Multi-Function Button**
(power on & off / pairing / answer / hang-up / reject / voice dial / etc.)
2. **Headset Plug**
3. **Front button - Volume Up**
4. **Back button - Volume Down**
5. **Up button - Next**
6. **Down button - Previous**
7. **Status Indicator**
8. **Left/Right (L/R) Ear Speaker**
9. **Microphone** (On the flexible boom)
10. **Charger and Headset Socket**
11. **Hook**

B. CHARGING:

1. When the **Status Indicator (7)** turns Red, the battery is low. Charge the unit using the provided charger.
2. Connect the charger's plug to the **Charger Socket (8)** of the **BTF4XT**. Then, plug the charger to an external power source. (*Note: **Status Indicator (7)** turns Red when charging.*)
3. When the **Status Indicator (7)** turns Green, charging is complete.
4. Disconnect the charger.█

C. POWER ON OR OFF:

Power On: Press the **MFB (1)** until **Status Indicator (7)** turns blue. Or press for approximately 3 seconds, a beep will be heard.

Power Off: Press the **MFB (1)** until **Status Indicator (7)** turns red. Or press for approximately 5 seconds, a beep will be heard.

D. PAIRING TO YOUR BLUETOOTH MOBILE PHONE:

1. From OFF, press and hold the **MFB (1)** of the **BTF4XT** until the **Status Indicator (7)** turns blinking red/blue.
2. While the headset is in pairing mode, access the Bluetooth menu of your phone. Turn on the Bluetooth function then execute a Bluetooth search. (See your phone's manual).
3. When the phone displays the list of Bluetooth devices, select **BTF4XT** then enter **0000** and press ok. Pairing is successful if the alternating red/blue lights of the **Status Indicator (7)** changes to blinking blue.

*Note: Some phones do not connect automatically to the kit after pairing. You need to press the **MFB (1)** (1st beep) to connect.*

Or use the menu of your phone:

*Go back to **Bluetooth** > **Paired devices** > highlight the name of this headset (**BTF4XT**) > press **Options** > then press **Connect**.*

The **BTF4XT** is now ready to use.

E. BASIC OPERATION:

IMPORTANT:

The **BTF4XT** needs to be 'paired' with your Bluetooth mobile phone before you can use the following functions. (See **Pairing to your Bluetooth Mobile Phone** on section D.)

Make a Call:

- Dial the number using your phone. Audio will automatically be on the headset.

*Note: With some phones, audio is always on the phone during an outgoing call. You will need to press the **MFB (1)** to transfer the audio to your headset.*

Answer a Call:

- Assuming the **VOX** is activated: Accept a call by loudly saying a word within 10 seconds. (Example: When you receive the ring tone, Say loudly "**Ok!**") The call will be answered. Audio will be on the headset. (See **VOX Activation / Deactivation** on section F.)
- You also have the option to answer the call normally by pressing the **MFB (1)** for 1 second (1st beep).

End a Call:

- Press the **MFB (1)** for 1 second to end the call (1st beep).

Reject a Call (For Handsfree Profile Phones only):

- Assuming the **VOX** is activated: Reject a call by being silent for 10 seconds. The call will automatically be rejected. (See **VOX Activation / Deactivation** on section F.)
- You also have the option to reject the call normally by pressing the **MFB (1)** for 3 second (2nd beep).

Voice Dial:

IMPORTANT: First, make sure to activate the voice dial function of your phone. Record at least one **voice tag**. (Kindly refer to the procedure in your phone's manual.)

Note: Voice dialing entries must be stored in the phone's memory, not on the SIM card!

1. Press the **MFB (1)** for 1 second (1st beep) to make a voice dial. A voice dial tone/ beep will be heard on the headset prompting the user to say the voice tag of the contact to call.
2. Say the voice tag. The voice will be played back to you, and then the phone will dial the number automatically.

Redial:

- Press the **MFB (1)** for 3 seconds (2nd beep). The last dialed number will be redialed.

Audio Transfer (For Handsfree Profile Phones only):

- During an ongoing call, you can transfer the audio.

Headset to Phone: Press and hold the **MFB (1)** for 3 seconds (2nd beep) and the audio will be transferred to the phone.

Phone to Headset: Press the **MFB (1)** for 1 second (1st beep) and the audio will be transferred to the headset.

Note: For some phones, you may need to accept a connection prompt on the phone before automatic transfer takes place.

Set the Volume:

- Press the **Volume Up (3)** or **Down (4)** button repeatedly until the desired level is reached.

F. SPECIAL FEATURE: VOX Activation / Deactivation:

- When activated, the user can accept a call by saying any word within 10 seconds. The user can also reject a call by being silent for 10 seconds.
- When deactivated, use the **MFB (1)** to answer a call.

The **Voice Answer Mode** can be enable or disable when the kit is in standby mode (no ongoing call and close any multi media player).

Activation:

1. From Connected and standby, press and hold the **Volume Up (3)** button for 5 seconds.
2. A beep will be heard. Then release.

Deactivation:

1. From Connected and standby, press and hold the **Volume Down (4)** button for 5 seconds.
2. A beep will be heard. Then release.

G. STREAM MUSIC FROM YOUR A2DP BLUETOOTH MOBILE PHONE:

If a phone supports **A2DP**, you can stream music from your phone to the **BTF4XT**.

*Note: The **BTF4XT** needs to be 'paired' with your Bluetooth mobile phone before you can use the following functions. (See **Pairing to your Bluetooth Mobile Phone** on section D.)*

Using A2DP Music Streaming

To Stream Music:

- Go to your phone's music player and play a track via A/V bluetooth. (See *your phone's manual*).
- Or Long Press the **UP button (5)** to play/pause music streaming.

To Choose Music File:

- Press the **UP button (5)**, music will go to the next music file.
- Press the **DOWN button (6)**, music will go back to the previous music file.

To Set the Volume:

- Press the **Volume Up (3)** or **Down (4)** button repeatedly until the desired level is reached.

To prevent possible hearing damage, do not listen at high volume levels for long periods.



FCC/IC statements :

Federal Communications Commission (FCC) Statement

Industry Canada (IC) Statement

15.21

You are cautioned that changes or modifications not expressly approved by the part responsible for compliance could void the user's authority to operate the equipment.

15.105(b)

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC/IC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures :

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC rules and Industry Canada licence-exempt RSS standard(s)

Operation is subject to the following two conditions :

- 1) This device may not cause interference and
- 2) This device must accept any interference, including interference that may cause undesired operation of the device.

FCC/IC RF Radiation Exposure Statement :

This equipment complies with FCC/IC radiation exposure limits set forth for an uncontrolled environment. End users must follow the specific operating instructions for satisfying RF exposure compliance. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

The *Bluetooth*® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by Euro-CB is under license. Other trademarks and trade names are those of their respective owners.

C € 0560

English

Hereby, EURO COMMUNICATION EQUIPEMENTS, represented by MARCHANT, CEO, declares that the Interphone MODEL BTF4XT, is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC of the European Parliament and of the Council of 9 March 1999 on radio equipment and telecommunications terminal equipment and the mutual recognition of their conformity.

For the whole declaration please visit :
<http://www.SuperTooth.net/download>
Euro Communication Equipements Sas
Route de Foix D117
11 500 NEBIAS
FRANCE

Déclarations FCC / IC :

Commission Federale des Communications (FCC)

Déclaration Industrie Canada (IC)

15,21

Vous êtes averti que les changements modifications non expressément approuvés par la partie responsable de la conformité pourraient annuler l'autorité de l'utilisateur d'exploiter cet équipement.

15.105 (b)

Cet équipement a été testé et jugé conforme aux limites pour un appareil numérique de classe B, conformément à la partie 15 des règles de la FCC / IC. Ces limites sont conçues pour fournir une protection raisonnable contre les interférences nuisibles dans une installation résidentielle. Cet équipement génère, utilise et peut émettre des fréquences radio et, s'il n'est pas installé et utilisé conformément aux instructions, peut causer des interférences nuisibles aux communications radio. Cependant, il n'existe aucune garantie que ces interférences ne se produiront pas dans une installation particulière. Si cet équipement provoque des interférences nuisibles à la réception radio ou télévision, ce qui peut être déterminé en éteignant et rallumant l'équipement, l'utilisateur est encouragé à essayer de corriger l'interférence par une ou plusieurs des mesures suivantes:

- Réorienter ou déplacer l'antenne réceptrice.
 - Augmenter distance entre l'équipement et le récepteur.
 - Brancher l'équipement dans une sortie sur un circuit différents-de celui sur lequel est branché le récepteur.
- Consulter le revendeur ou un technicien radio / TV qualifié.

Cet appareil est conforme a la partie 15 des regles FCC et aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence.

L'opération est soumise aux deux conditions suivantes:

- 1) Cet appareil ne peut causer d'interférences et
- 2) Cet appareil doit accepter toute interférence, y compris les interférences qui peuvent causer un mauvais fonctionnement de l'appareil.

FCC / IC Déclaration d'exposition aux radiations RF:

Cet équipement est conforme aux normes FCC / IC limites d'exposition aux radiations dans un environnement non contrôlé. Les utilisateurs doivent suivre les instructions de fonctionnement spécifiques de la conformité d'exposition aux RF. Cet émetteur ne doit pas être co-localisés ou fonctionnant en conjonction avec une autre antenne ou transmetteur.

The *Bluetooth*® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by Euro-CB is under license. Other trademarks and trade names are those of their respective owners.

C € 0560

Par la présente, Euro Communication Equipements, représentée par Xavier Marchant, Président Directeur Général, déclare que l'appareil Interphone, MODELE BTF4XT, est conforme aux exigences essentielles de la directive 1995/5/EC du Parlement Européen et du Conseil du 9 Mars 1999 concernant les équipements hertziens et les équipements terminaux de télécommunications et la reconnaissance mutuelle de leur conformité.

Pour la déclaration complète visitez :
<http://www.SuperTooth.net/download>
Euro Communication Equipements Sas
Route de Foix D117
11 500 NEBIAS