

4. Notes:
- Handle the headset gently. Excessive force may damage the headset, buttons and functionality.
 - Be sure the USB plugs are aligned properly before charging. Forcing the plugs may result in damage.
 - If you encounter interference with the Bluetooth signal, delete the headset from the paired devices on your phone. Restart your phone and repair the headset.
 - Be sure to turn off the headset power when not in use to extend battery life.
 - Avoid exposing the headset to moisture or high temperatures.
 - Do not shake, violently mishandle or drop the headset. This may cause damage and affect functionality.



Limited Warranty
 We hope you enjoy this quality Prime Line® product. This item is guaranteed against any manufacturing defects for 1 year after purchase. If it malfunctions, return it for replacement of the same or a similar model free of charge. Please include \$10.00 for shipping and handling and send to:
 Prime Service Center
 1100 Boston Ave.
 Bridgeport, CT 06610



Bluetooth speaker Model: E3183



About PL-4825
 PL-4825 is a stereo headset with Bluetooth technology. It supports the following Bluetooth profiles:
 HFP—Hands-free Profile
 A2DP—Advanced Audio Distribution Profile
 AVRCP—Audio/Video Remote Control Profile

SPECIFICATIONS			
Model NO	SX-8252	Ver.	Bluetooth V3.0+EDR
Bluetooth Profiles	HSP, HFP, A2DP, AVRCP	Effective Range	➤ 10 Meters
Music Time	➤ 10 Hours	Talk Time	➤ 10Hours
Standby Time	➤ 180 Hours	Input	DC:5V/400mAh
Charge Time	About 2 - 3 hours	Charge Port	USB
Battery Type	Lithium	Battery Capacity	250mAh
Microphone	Support	Sensitivity	-58±3dB
Speaker Material	NdfeB	Diameter	40mm
Sensitivity	105dB±3 dB	Distortion	≤1% At 1KHz
Power To Bear	30mW	Resistance	32 Ω
Dimensions	17*17.5*8 (3) CM	N.W	About 215g

BUTTON, INTERFACE, SWITCH		
ON/OFF	Power on / off	Stop and run the system
M	Connect / Hang Up	Control calls action
▶	Pause / Play	Control music action
+	On / Volume+	Short press, on a song / Long press, the volume increases
-	Next / Volume-	Short press, the next song / Long press, the volume down
DO	Audio I/O Interface	External device audio input earphone speaker, headphone audio output to external speakers
USB	Charging	Connect the charger USB charge

2. Charging the battery:
 Switch the power off the headset before charging. Using the charging cable provided, connect the micro USB to the headset and the standard USB to a computer or other USB port with a power source. The LED will light RED to indicate a successful connection and that the headset is charging. The headset comes with a battery capacity detection system. The LED will go out automatically when charging is complete.

Low battery indication – the LED will blink RED, BLUE and GREEN when the battery is low. Recharge the headset.

NOTE: Do not attempt to open the headset. This may cause damage to the headset hardware and battery.

3. Pairing:
- Press the ON/OFF switch to power the headset. The LED will blink RED and BLUE. This indicates the headset is searching for a Bluetooth® connection.
 - Open the Bluetooth menu on your mobile device. Select the headset to pair. Once connection is established the LED will blink slowly in BLUE. This indicates a successful pairing.
 - If pairing is not successful, switch off the headset and try pairing again.
 - After pairing there will be no need to reconnect the devices unless pairing information is deleted. To pair the headset with another device, simply follow the steps above.
 - Multilink technology allows simultaneous connection to two different devices.

Reconnecting to a Bluetooth Device:
 • Every time the headset is switched on it will automatically connect to the nearest and most recently connected device.

Manual connection to last paired device:
 • When the headset is in standby mode and is not connected to any device, quickly press the “M” button to automatically connect to the last paired device.

- Phone function:
- To answer an incoming call, quickly press the “M” button. The headset features an internal microphone. To complete the call, quickly press the “M” button again.
 - To reject a call, press and hold the “M” button.

FCC Warning

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE 1: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

NOTE 2: Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.