

FCC and Industry Canada Identifications Numbers (and label locations)

FAMILY 1: FCC ID: J5XT3HEP

Industry Canada ID: 5916A-T3HEP



FCC ID: J5XT3HEP

IC: 5916A-T3HEP

Safety Certifications

Intrinsically Safe, Sécurité Intrinsèque

II 1 G Ex ia IIC T4 Ga

CE 0891

TRAC11ATEX1129X

-40°C ≤ T_A ≤ 40°C Um(max) 250VAC

IP67

FCC ID: J5XT3HEP -- Meets FCC Part 15

IC: 5916A-T3HEP -- Complies with Canadian ICES-003

WARNINGS!

WARNING! Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

WARNING! To prevent ignition of a hazardous atmosphere, battery must only be charged in an area known to be nonhazardous.

WARNING! Substitution of components may impair intrinsic safety.

AVERTISSEMENT! Les changements ou modifications non expressément approuvés par la partie responsable de la conformité pourraient annuler l'autorité de l'utilisateur à utiliser cet équipement.

AVERTISSEMENT! Pour éviter l'inflammation d'une atmosphère dangereuse, les batterie doivent être chargées seulement dans une zone connu comme être non dangereuse.

AVERTISSEMENT! La substitution de composants peut compromettre la sécurité intrinsèque.

FCC Statements

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.


Industry Canada Statements

This Class A digital apparatus complies with Canadian ICES-003.

This device complies with Industry Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

Cet appareil numérique de la classe A est conforme à la norme NMB-003 du Canada.(select the class for your device)

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes : (1) l'appareil ne doit pas produire de brouillage, et (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.



Battery Charging LED Display

Charging: When the charging key is in place and plugged into a power source, a steady Green LED will glow below the left side button (left side when facing the TPASS®3-R unit).

Charging Complete: Unit is fully charged when the steady green glow is replaced by a flashing Green display.

Pre-Alert and Alarm Time Periods		
Alarm Time	Pre-Alert	Alarm
30 seconds	Pre-Alert 18 to 23 seconds	30 to 35 seconds to Alarm
60 seconds	Pre-Alert 48 to 53 seconds	60 to 65 seconds to Alarm
90 seconds	Pre-Alert 78 to 83 seconds	90 to 35 seconds to Alarm
120 seconds	Pre-Alert 108 to 113 seconds	120 to 125 seconds to Alarm

The Low Battery Alarm will sound when the battery has been exhausted to 20% of capacity (indicating approx. 1 hour operating time remains). Charging the battery is necessary when low battery alarm sounds.

The low battery alarm is an easily recognized series of two audio beep tones enunciated every five seconds when the TPASS®3-R is in the Sensing Mode.

Grace Industries, Inc. assumes no liability for mechanical, electrical, or other types of battery failure.

Warranty Information

Grace Industries, Inc. warrants TPASS®3-R to be free from defects in workmanship and materials for a period of one year from date of purchase. This warranty is valid only when the returned TPASS®3-R is accompanied by a sales receipt or other proof of purchase that states the date and location of purchase. Grace Industries, Inc. will not repair or replace any merchandise under warranty which has been damaged because of accident, misuse or abuse of the TPASS®3-R while in possession or control of the consumer or outside of Grace Industries Inc's control. This warranty is void if any attempt to repair or replace parts was made or attempted by other than qualified Grace Industries, Inc. personnel. This warranty is void if any of the sealed compartments are opened or tampered with. Send all returned merchandise, prepaid and accompanied by proof of purchase to: Grace Industries, Inc., Repair Division, 305 Bend Hill Road, Fredonia, PA 16124. Customer is responsible for return shipping. Grace Industries, Inc. shall not be liable for any direct, incidental or other consequential loss or damage arising out of the failure of the device to operate.

The sole and exclusive remedy under all guarantees or warranties, expressed or implied, is strictly limited to repair or replacement as herein provided. ALL IMPLIED WARRANTIES, INCLUDING BUT NOT LIMITED TO, WARRANTIES OF FITNESS AND MERCHANTABILITY, ARE HEREBY LIMITED IN DURATION TO A PERIOD ENDING ONE (1) YEAR FROM THE DATE OF PURCHASE. The warranty and liability set forth in the prior paragraphs are in lieu of all other warranties, expressed or implied, in law or in fact, including implied warranties of merchantability and fitness for a particular purpose. Some states do not allow limitations on how long an implied warranty lasts, so the above limitations may not apply to you.

This warranty gives you specific legal rights and you may also have other rights which may vary from state to state.

The information contained in this booklet is believed to be accurate and reliable. Grace Industries, Inc. provides this information as a guide only.

TPASS®3-R technical assistance is available by contacting Grace Industries, Inc. at (724) 962-9231 or by email at info@graceindustries.com.

For training purposes a copy of this information is available by contacting Grace Industries, Inc.

TPASS®3 RECHARGEABLE USER'S INFORMATION

Only To Be Removed By End User



MADE IN USA

Grace Industries, Inc.
www.graceindustries.com
Ph. 724-962-9231 • Fax 724-962-3611




GRACE INDUSTRIES, INC.
Solutions for Life Safety

TPASS®3 Intrinsically Safe Rechargeable

TPASS®3 may be utilized as part of an Automated Accountability System when used with other Grace monitoring equipment.

TPASS®3 Operating Instructions (120 seconds to Alarm used for example)

Always test the unit prior to each use



Auto-ON Activation

ACTIVATING TPASS®3-R: When the TPASS®3-R is removed from a storage position, the Accountability Key automatically detaches, activating TPASS®3-R into the motion **Sensing Mode**.


During activation, an operational signal of escalating audio tones will be heard and an alternating display of yellow LEDs indicates the TPASS®3-R is in **Sensing Mode**. When TPASS®3-R is activated, its internal radio transmits signals that are received by the MX900.

PRE-ALERT MODE: After approximately 108 to 113 seconds of no motion, TPASS®3-R begins an audible Pre-Alert sound and the alternating yellow LED display is interrupted by the pulsing of two red LEDs. The Pre-Alert sound progressively becomes louder, indicating TPASS®3-R is closer to going into **Alarm**.

ALARM MODE: There are two methods of activating the Alarm Mode.

1) MOTION-ALARM: After 120 to 125 seconds of no motion, TPASS®3-R enters the **Alarm Mode** as indicated by a rapid pulsing of two red LEDs while sounding a rapidly modulated, loud audio alarm. During Alarm, an emergency radio signal is transmitted to MX900, alerting personnel outside the immediate area that personnel may need assistance

2) PANIC ALARM: Panic Alarm can be activated at any time (from **Sensing Mode** or **Off Mode**) by pressing the Emergency Alarm Button.



Reset the Alarm Mode and return TPASS®3-R to **Sensing Mode** by simultaneously pressing both side buttons.

TURN OFF: To turn TPASS®3-R **OFF**, replace Accountability Key and press both side buttons simultaneously.

Mode Selection

AUTO-ON ACTIVATION

- Remove Accountability Key to automatically activate the unit into **Sensing Mode**.

ALARM


- Alarm Mode** can be manually activated at any time (from **Sensing Mode** or **Off Mode**) by pressing the Emergency Alarm Button.

RESET

- When in **Alarm**, the TPASS®3-R can be reset to **Sensing Mode** by simultaneously pressing both side buttons.

OFF

- Turn OFF TPASS®3-R by replacing the Accountability Key and then pressing both side buttons simultaneously.



Manual Activation

ACTIVATING TPASS®3-R: Simultaneously press both side buttons to activate TPASS®3-R into the motion **Sensing Mode**.

During activation, an operational signal of escalating audio tones will be heard and an alternating display of yellow LEDs indicates the TPASS®3-R is in **Sensing Mode**. When TPASS®3-R is activated, its internal radio transmits signals that are received by the MX900.

PRE-ALERT MODE: After approximately 108 to 113 seconds of no motion, TPASS®3-R begins an audible Pre-Alert sound and the alternating yellow LED display is interrupted by the pulsing of two red LEDs. The Pre-Alert sound progressively becomes louder, indicating TPASS®3-R is closer to going into **Alarm**.

ALARM MODE: There are two methods of activating the Alarm Mode.

1) MOTION-ALARM: After 120 to 125 seconds of no motion, TPASS®3-R enters the **Alarm Mode** as indicated by a rapid pulsing of two red LEDs while sounding a rapidly modulated, loud audio alarm. During Alarm, an emergency radio signal is transmitted to MX900, alerting personnel outside the immediate area that personnel may need assistance

2) PANIC ALARM: Panic Alarm can be activated at any time (from **Sensing Mode** or **Off Mode**) by pressing the Emergency Alarm Button.

Reset the Alarm Mode and return TPASS®3-R to **Sensing Mode** by simultaneously pressing both side buttons.

TURN OFF: When in Sensing Mode, the TPASS®3-R can be turned **OFF** by pressing both side buttons simultaneously.

Using an accountability key (w/ 6" tether) may help prevent accidental activation of the Emergency Alarm.

Mode Selection

MANUAL ACTIVATION

- Simultaneously press both side buttons to activate TPASS®3-R into the motion **Sensing Mode**.

ALARM

- Alarm Mode** can be manually activated at any time (from **Sensing Mode** or **Off Mode**) by pressing the Emergency Alarm Button.

RESET

- When in **Alarm**, the TPASS®3-R can be reset to **Sensing Mode** by simultaneously pressing both side buttons.

OFF

- When in Sensing Mode, the TPASS®3-R can be turned **OFF** by pressing both side buttons simultaneously

Visual / Audio Mode Display

OFF

- No LED display.

ON (Sensing Mode)

- A series of escalating, loud audio tones.
- Followed by yellow alternating LED display.

PRE-ALERT

- No motion sensed for 108 - 113 seconds.
- Yellow alternating LED display interrupted by the pulsing of two red LEDs.
- Accompanied by progressively louder, sweeping audio tones.

ALARM

- No motion sensed for 120 - 125 seconds.
- Rapid pulsing of two front red LEDs.
- Accompanied by a rapidly modulated, loud (92dBA) audio alarm.
- Audio alarm signal is between 1,000 and 2,000 Hertz and cycles at 5.25 seconds on and .75 seconds off as an aid for determining direction when personnel need assistance.

TPASS®3-R Maintenance

TPASS®3-R requires minimum maintenance and will provide years of service.

Please Observe These Guidelines

- At the end of each use, clean unit with a damp cloth. **DO NOT use cleaning solvents.**
- After each use, inspect unit for signs of physical damage. **Remove TPASS®3-R from service if physical damage is observed.**
- Store TPASS®3-R in a dry, well ventilated area consistent with battery manufacturer requirements. Recommended storage conditions are: 50° to 77°F (10° to 25°C) at no more than 65% relative humidity.
- Units contaminated by chemical or radioactive materials must be disposed of or decontaminated in accordance with all applicable regulatory standards.
- DO NOT mark or apply paint to TPASS®3-R.**

Specifications

Dimensions: 2-1/8" wide, by 2-1/4" deep (with clip), 4-1/8" high (with antenna)

Weight: 7.3 ounces with battery

Alarm Audio Output: approx. 92 dBA @ 10 feet

Case: rugged, high temperature, impact resistant, translucent, Apache Yellow polycarbonate. .

Methods of Attachment: rugged Grip Clip and D-ring for versatility in attaching to gear.

Antenna: short threaded antenna for easy replacement

Alarm Transmission: a 1.5 second burst of RF transmissions occurring every 4.5 seconds.

Battery: Intrinsically safe Lithium-ion.

Battery Life: estimated at 80 hrs in Sensing Mode and 4 to 6 hours in the Alarm Mode.

Battery Charging: 12VDC (std) or 120 VAC (optional adapter required) may be used

Battery Charging Time: 6 to 8 hrs

Battery Charging Cycles: 500

Product Life: Approximately 3 to 5 years or longer, depending on fitness for use. Fitness for use is best determined by the end user through a proper inspection and maintenance program. Product should be retired from service when damaged or returned to Grace Industries for evaluation and repair if applicable.

For TPASS®3 with Alarm Monitoring

The Alarm Monitoring feature allows personnel to monitor the status of other personnel working in the same general area, when they are equipped with Grace Telemetry products. TPASS®3-AM **MUST** be in the Sensing Mode to receive Alarm signals from other Grace Telemetry products. When one telemetry unit goes into "Alarm" and an Alarm Monitoring TPASS®3 receives the signal, the receiving TP3-AM will sound a rapid ringing tone and provide a visual indication with a flashing yellow LED at the base of the antenna. The Alarm Monitoring display may be momentarily silenced for one minute by pressing both side buttons simultaneously. Other units which go into alarm during the one minute period will reactivate the Alarm Monitoring audio sound signature and display. After one minute if the original unit is still in alarm, the alarm monitoring feature and display will be reactivated. This cycle will continue until the telemetry unit in Alarm is reset or shut off. TPASS®3-AM has an orange case.

Limitations

To reduce risk of serious injury or loss of life, ensure TPASS®3-R is fully operational by testing and inspecting the unit prior to use. Use of a TPASS®3-R maintenance and training program including recharging exhausted or low batteries is required for safe and proper use.

After charging battery, always test TPASS®3-R with the MX900 to ensure proper operation.

If proper operation of TPASS®3-R is questionable, remove unit from service and contact Grace Industries for assistance.

The TPASS®3-R is Not available in a temperature sensing model.