

HP GK300 Wired Gaming Mechanical keyboard Specification

Features:

- Elegant and minimalist style, integrated metal bezel that is oxidation resistant and scratch resistant.
- Highly durable Double-shot injection molding keycaps.
- Thick keyboard with responsive keys, 2.0mm trigger route.
- Up to 50 million times ultra-long lifetime mechanical switch, comfortable hand feel.
- Multicolor back-lighting for virtually unlimited game customization.
- Intelligence auto sleep mode: Keyboard goes into sleep mode to turn off all LED after 10 minutes of idle. Press any key to wake up.
- Mainframe goes into sleep mode or standby mode, keyboard backlight turn off, once restart the computer, keyboard backlight restore to previous setting.
- User-friendly design with a set of shortcut function keys cooperated with Fn key.
- Keyboard backlight can be self-defined and recorded. Players can built his own backlight style mechanical keyboard.
- Default to factory settings by press FN+ESC combo keys 3s.

■Standard shortcut key functions:

Fn+	F1	F2	F3	F4	F5	F6
Shortcut function	Previous	Play/Pause	Next	Stop	Mute	V-
Fn+	F7	F8	F9	F10	F11	F12
Shortcut function	V+	Lighting effect mode switch (Auto)	Self-defined lighting effect profile 1	Self-defined lighting effect profile 2	Self-defined lighting effect profile 3	
Fn+	PRTSC	SCRLK	PAUSE	INS	HOME	PGUP
Shortcut function	Breath	Full keyboard Marquee	corner to corner Marquee	Typing key lights up	Full keyboard Solid	Flowing backlight
Fn+	DEL	END	PGDN	左 WIN	- —	= +
Shortcut function	Snake marquee	Full keyboard off	Rippling	WINLOCK Lock/Unlock Windows key	Lighting effects slow down	Lighting effects Speed up
Fn+	↑	↓	←	→	ESC	

Shortcut function	Backlight brightness increase	Backlight brightness decrease	Lighting effect from right to left	Lighting effect from left to right	Default setting	
-------------------	-------------------------------	-------------------------------	------------------------------------	------------------------------------	-----------------	--

How to record self-defined backlight:

1. Press FN+F9 to show self-defined backlight at last time
2. Press FN+F9 again goes into recording status, Winlock LED will turn on to indicate can record self-define backlight keys again.
3. After recording, press FN+F9 to exit WINLOCK LED will turn off to indicate new settings have been stored.
4. The method for recording FN+F10 and FN+F11 is the same as FN+F9.

Specifications:
● Keyboard size: 486 (L) ×180 (W) ×43 (H) ±0.5mm
● Keyboard weight: 1.4Kg
● Connector: USB
● Number of keys : 104
● Key route: 4.0mm
● Key force: 60±10g
● Rate voltage/current: DC 5V/ <200mA
Operation System:
● WIN7/WIN 8/win10/MAC OS