



- For roller conveyors
- The approach direction of the data carrier can be transversal as well as longitudinal to the read/write head.
- Rectangular, 80 x 800 mm, height 25 mm
- Active face on top
- Plastic, PBT-GF30-V0
- Powered and operated only via BL ident interface module
- Male M12 x 1, only for use with BL ident extension cable


Connectors .../S2503



Connectors .../S2500



Connectors .../S2501



Functional principle

The HF read/write heads operating at a frequency of 13.56 MHz form a transmission zone the size of which (0...500 mm) varies, depending on the combination of read/write head and data carrier.

The read/write distances mentioned here only represent standard values measured under laboratory conditions.


The read/write distances of the data carriers for mounting in metal TW-R**-(MF) were determined in metal.

Attainable distances may vary by up to 30 % due to component tolerances, mounting conditions, ambient conditions and material qualities (especially when mounted in metal)

Testing of the application under real operating conditions is therefore essential, especially with read/write on-the-fly!

Type code	TNLR-Q80L800-H1147
Ident no.	7030522
Mounting conditions	non-flush
Ambient temperature	-25...+70 °C
Operating voltage	19.2...28.8VDC
Data transfer	inductive coupling
Operating frequency	13.56 MHz
Radio communication and protocol standards	ISO 15693
Output function	4-wire, read/write
Construction	rectangular, Q80L800
Dimensions	800x 80x 25mm
Housing material	plastic, PBT, black
Material active area	plastic, Black
Connection	male, M12
Vibration resistance	55 Hz (1 mm)
Shock resistance	30 g (11 ms)
IP Rating	IP67
Power-on indication	LED green
Diagnostic display	Functional description of yellow range-restricted LED: If the read/write head is supplied with voltage, it briefly checks to see whether its resonance frequency is affected by surrounding metal. If this is the case, the resonant circuit off-tunes its frequency to reach again the (optimum) resonance frequency. However, this is only possible within a certain range. If too much metal is in the environment, the read/write head cannot re-tune or the surrounding metal takes too much energy from the field and due to the reduced range the communication between the read/write head and the data carrier is cut off (the orange range-restricted-LED lights up). If the LED is off, this does not mean conversely, that no reduction in range occurs. The lit LED is rather an indication of too much metal in the environment and a greatly reduced range (about 50% less).
Packaged quantity	1


BL
ident





Qty 1 Type **TNLR-Q80L800-H1147**

CE

Ident-No. **7030522**



24 VDC



1615H

Warning: Hazardous voltage can cause electrical shock and burns. Disconnect power before proceeding with any work on this equipment.
Made in Germany
Hans Turck GmbH & Co. KG · Witzlebenstraße 7 · 45472 Mülheim/Ruhr · Germany
Phone +49 208 49 52-0 · Fax +49 208 49 52-264 · more@turck.com · www.turck.com

FCC/IC Digital Device Limitations

M/N: **TNLR-Q80L800-H1147**
FCC ID: **YQ7-TNLRQ80L800**
IC: **8821A-TNLRQ80L800**

This device complies with Industry Canada licence-exempt RSS standard(s) and part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) this device may not cause interference, and
(2) this device must accept any interference, including interference that may cause undesired operation of the device.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes :
(1) l'appareil ne doit pas produire de brouillage, et
(2) l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.