



With horizontal 360° vertical 180° viewing angle through pan-tilt function, you can remotely control the camera without needing line of sight.



- Download and install APP**
  - Download the APP by searching "Lenovo Home" on the App Store or Google Play.
  - Remember to turn the cell phone screen on and the camera is powered on.
  - Run the APP and click register to get a new account if you are the first time to use.



- Add camera**
  - Please ensure that your phone is connected to the 2.4GHz WiFi and the camera connects to same WiFi as the phone.
  - When the status light is showing a blinking orange light, open the APP → select the "Device" → click "Add" → The camera orange light is "Blinking" → select "WiFi password" → click "Next" → then wait for your mobile phone to search for the device.



- Wait for the status light to start from blinking red to solid white with white. When the status light is showing a solid white light, the device is connecting to the internet.
- When the device name shows up on the device list, click "Add" to add the device.



- About the device name that you wish to use for identifying the device, then you can start to use the device in the APP.
- Please read the notes carefully to avoid unnecessary connecting to the device.
- Check whether the router is turned on network function, which may cause the device failed to connect to network, you could turn off the network function temporarily and restore the router settings after the device is successfully connected.
- For Android mobile phone users, ensure your mobile phone is connected to the 2.4GHz network.
- Bluetooth/WiFi is recommended, which is more stable than Bridge WiFi. 4G/5G network/WiMAX/WiFi are not supported. Please choose other WiFi.

For more information about this product, please visit the website [www.lenovo.com](http://www.lenovo.com)



- ### FAQ
- How to turn on/off the device via the button?**  
A short press on the button to turn on the device. Press and hold the button for 2 seconds to turn off the device. **manually** the voice prompt "Shutting Down" is being played.
  - How to restore this device to the factory default settings?**  
When the device is turned on, press and hold the switch button for 8 seconds until hear the voice prompt "Reset Success".
  - What does the indicator mean in different status?**

Indicator	Meaning
Constant Orange	Camera is activating
Blinking Orange	Ready for installation
Blinking White	Device is connecting with internet router
Flash Blinking White	Device has connected with router successfully and is connecting with cloud service (optional)
Constant White	Camera is online
Change and White light (Intermittent)	Firmware upgrading
Blinking White per 5 seconds	In Sleep Mode, can't keep network connection for quick response
  - What capacity TF card does the camera support?**  
The maximum size of TF card can be supported. To ensure the stability of TF card, please choose the genuine high speed card.
  - What should be paid attention to when using the camera normally?**  
For better night vision effect, please avoid the straight front and side view of the lens near the night vision light such as the glass, wall, etc., in order to avoid causing the screen dark or white.

### After-sales Service

Product warranty information			
Product	Warranty scope	Warranty period(months)	Type of service
Lenovo Smart Camera	Camera	12	Provide warranty service within the warranty period.
	Power adapter		
	Charging cable		

- For all of warranty service, please contact local Authorized Distributors in your country.

- Warranty policy exception**
  - Outside of warranty time period.
  - Damages caused by improper use, maintain, storage and unauthorized repair.
  - Damages or malfunction caused by force majeure circumstances.
  - The normal deterioration and wear in using is not covered by the warranty policy.
- Contact us**
  - Email: [FC@support.lenovo.com](mailto:FC@support.lenovo.com)

### Warranty Card

User information

Name \_\_\_\_\_ Phone Number \_\_\_\_\_

Email \_\_\_\_\_ Post code \_\_\_\_\_

Address \_\_\_\_\_

Product information

Name \_\_\_\_\_ Model \_\_\_\_\_

Color \_\_\_\_\_ Serial No. \_\_\_\_\_

Required service  Return  Replace  Maintenance

Failure information \_\_\_\_\_

Service date \_\_\_\_\_ Signature \_\_\_\_\_

### Technical Specifications

Product Name	Lenovo Smart Camera
Product Model	R1
Power Input	DC 5V/500mA
Resolution	HD 1080P
Camera Angle	180°
Micro SD Card Support	Max Support 64G
Cloud Service	Optional (Need purchase)
Working Power	~200mA
Working Temperature	+5°~40°C
Working Humidity	10%~90%
WiFi Standard	802.11b/g/n, 2.4GHz

### Warning

- Using unapproved or incompatible power supply may cause fire, explosion or other hazards.
- The product line disconnector contains some small parts. Please keep them unattached from children, to avoid in case of inadvertent contact to the product or other objects to children.
- This product is not a toy, children should use the product under adult supervision.
- Place on the product within the temperature range of 0°C-40°C. When the ambient temperature is too high or too low, it may cause product failure.
- Do not expose the product and accessories to rain or moisture, thus prevent your personal data from being affected.
- For the safety of you and your family, please make sure that the product is not found by an unauthorized person. Lenovo will take strict measures to protect the information security of you and your family.

### FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into a wall outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

To assure continued compliance, any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment. Changes use only shielded enclosure unless otherwise containing the computer or peripheral device.

This equipment complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- The device may not cause harmful interference, and
- The device must accept any interference received, including interference that may cause undesired operation.

**FCC Radiation Exposure Statement:**  
This equipment complies with FCC Radiation exposure limits set forth for uncontrolled environments. This equipment should be installed and operated with minimum distance 20cm between the radiator and your body.

