

311TX Channel Assignments

The LightSPEED 311TX Transmitter is compatible with the following PHONAK™ MicroLink™ Band NB frequencies:

LightSPEED Channel	PHONAK™ Designation	Frequency
1	N01	216.0125
2	N08	216.1875
3	N09	216.2125
4	N12	216.2875
5	N13	216.3125
6	N16	216.3875
7	N17	216.4125
8	N18	216.4375
9	N61	216.5125
10	N62	216.5375
11	N64	216.5875
12	N65	216.6125
13	N72	216.7875
14	N76	216.8875
15	N77	216.9125
16	N80	216.9875

Note: The LightSPEED 311TX Transmitter is not compatible with the PHONAK™ Band J (185-201 MHz) or Band NA (207-209 MHz) Frequencies.