

Beacon / iBeacon / MiniBeacon

Datasheet V1.0.0

FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

The device has been evaluated to meet general RF exposure requirement.

The device can be used in portable exposure condition without restriction.

Model	Description
E5-W	Round shape, white case with 3M adhesive sticker, including 2pcs ER12450 battery and industrial package, special for indoor location, RoHS

The Location MiniBeacon E5 is an enterprise-level iBeacon with ARM core chipset nRF51822 and leverage BLE 4.0 technology; it has a strong case, accurate hardware and robust firmware. It is designed for the commercial advertising and indoor location-based service.

MiniBeacon broadcasts 2.4GHz radio signals at regular and adjustable intervals. MiniBeacon can be heard and interpreted by iOS and Android BLE-enabled devices that are equipped with many mobile apps.

FEATURES

- Programmed MiniBeacon standard firmware
- Included 2pcs ER12450 battery, total 2400mAh
- The max. 100 meters advertising distance
- Ultra-low power consumption chipset nRF51822 with ARM core
- Easy to replace the battery without any tools
- High location accuracy specialized for the indoor navigation application
- Supports the magnetic adsorption deployment

PICTURE



E5 Location MiniBeacon

Image 1

CERTIFICATIONS

- iBeacon MFi License (iBC-14-00582)
- FCC Regulation (FCC Part 15.)
- CE Regulations (Included EN300328/301489/60950/62479)

SPECIFICATION

Compatibility

- Supported iOS 7.0+ and Android 4.3+ system;
- Compatible with Apple iBeacon™ standard;
- Compatible with all Bluetooth 4.0 (BLE) devices;

Long Battery Lifetime and Battery Level

- 5 years, with the default settings;
- LED will be flashing when battery low;
- Easy to get the real-time battery level notification;

Soft-reboot

- Reboot the device via command without any tools;

OTA and J-Link

- Supported upgrade via Over-The-Air;
- Reserved J-Link port on the board for programming;

Connection Mode

- Advertising mode, non-connectable;
- Configuration mode, connectable;

Configurable Parameters

- UUID, Major, Minor, Device Name, Password etc.
- Special Configuration APP;

Transmission Power Levels

- 8 adjustable levels, range from 0 to 7
- Transmission power range: -30dBm to +4dBm;

Long Range

- The max. Range 100 meters in the open space;
- The range depends on the physical environment;

Security

- 8 characters password (Lock/Unlock parameters);
- Broadcast the encrypted data if needed;
- AES HW encryption

Mounting

- 3M branded adhesive for direct mounting to wall;
- Supports magnetic adsorption deployment;

TURN ON/OFF E5

1. Turn on E5

- 1.1 Open the case;
- 1.2 Press the BUTTON and keep holding 5 seconds, the Blue LED will Light on 5 seconds and then off; it means that MiniBeacon wakes up and starts to broadcasting.

2. Turn off E5

- 2.1 Open the case;
- 2.2 Press the BUTTON and keep holding 5 seconds, the Blue LED will flash 5 times and then off; it means that MiniBeacon is on the sleeping mode and stops broadcasting.

TECHNICAL SUPPORT

Item	Version	File Name	Updated Date
Datasheet	V1.00	E5_MiniBeacon Datasheet_1.00.pdf	8 th April, 2017
Instruction	V2.03	Instructions_MiniBeacon_V2.03.pdf	25 th May, 2015
SDK	V5.1	iOS & Android SDK	8 th April, 2017
APP Tools	V2.0	BeaconSET	3 rd March, 2015

* Minew sales team will send you these documents after the sample arrived.

CONFIGURABLE PARAMETERS

Characteristic	Item	Default Settings
0xFFF1	UUID	E2C56DB5-DFFB-48D2-B060-D0F5A71096E0 (Proximity)
0xFFF2	Major	0
0xFFF3	Minor	0
0xFFF4	Measured Power	-59 (0xC5)
0xFFF5	Transmission Power	6 (0dBm)
0xFFF6	Change Password	minew123 (Must be 8 characters)
0xFFF7	Broadcasting Interval	9(900mS)
0xFFF8	Serial ID	Random (Unique serial ID for beacon)
0xFFF9	iBeacon Name	MiniBeacon_ (the maximum 12 characters)
0xFFFE	Connection Mode	0 (connectable, configuration mode)
0xFFFF	Soft Reboot	minew123 (it is same as the value of Change Password)

ELECTRONIC PARAMETERS

Item	Value	Remarks
Case Color	white	Other colors can be customized
Battery Model	ER14250	2pcs ER14250, 2400mAh, 3.6V
Operation Voltage	1.8-3.6V	DC
Transmission Circuit	10.5mA (Max.)	Tested at 0dBm transmission power
Transmission Range	100 meters	Maximum
Antenna	50ohm	On board / PCB Antenna
Accessories	Double adhesive	1pc, high-strength, 3M brand;
Net Weight	39.0g	With 2pcs batteries but without package
Size	∅ 50×20.5mm	Null

PACKING INFORMATION



Image 6

Details	Box	Carton
Quantity(E5)	20pcs / box	200pcs / carton
Net Weight	0.78Kg	7.8Kg
Gross Weight	1.0Kg	10.0Kg
Size	30.5 x 11 x 7.5 cm	32 x 23 x 40 cm

APPDENDIX

1. J-LINK Programmer Kit;
2. Over-the-Air Function;

Please contact Minew sales team to ask more related information if needed.

DECLARATION

The contents of this datasheet are subject to change without prior notice for further improvement. Minew team reserves the right to explain all the terms of this datasheet.

<END>