

TABLE OF CONTENTS

APPLICANT: BESCO ELECTRONIC MFG., CO., LTD.

FCC ID: GXKBS3100RX

TEST REPORT:

PAGE 1-2.....TEST PROCEDURE AND CIRCUIT DESCRIPTION
PAGE 3.....RADIATION INTERFERENCE TEST DATA

EXHIBITS:

EXHIBIT 1.....POWER OF ATTORNEY LETTER
EXHIBIT 2.....LETTER CONFIRMING MODIFICATIONS
EXHIBIT 3.....BLOCK DIAGRAM
EXHIBIT 4.....SCHEMATIC
EXHIBIT 5A-5B.....PARTS LIST
EXHIBIT 6A-6B.....USERS MANUAL
EXHIBIT 7.....SAMPLE OF FCC ID LABEL
EXHIBIT 8.....FCC ID LABEL LOCATION
EXHIBIT 9.....EXTERNAL PHOTO-FRONT SIDE
EXHIBIT 10.....EXTERNAL PHOTO- BACK SIDE
EXHIBIT 11.....INTERNAL PHOTO-COMPONENT SIDE
EXHIBIT 12.....INTERNAL PHOTO-COPPER SIDE
EXHIBIT 13.....TEST SET UP PHOTO

APPLICANT: BESCO ELECTRONIC MFG., CO., LTD.
FCC ID: GXKBS3100RX
REPORT #: F:\CUS\B\BESCO\BES258H8.RPT
PAGE #: TABLE OF CONTENTS

APPLICANT: BESCO ELECTRONIC MFG., CO., LTD.
FCC ID: GXKBS3100RX

TEST EQUIPMENT LIST

1. Spectrum Analyzer: Hewlett Packard 8566B - Opt 462, w/ preselector 85685A, & Quasi-Peak Adapter HP 85650A, & HP 8449B - OPT H02 Cal. 6/26/98
2. Signal Generator, Hewlett Packard 8640B, cal. 6/26/98
3. Eaton Biconnical Antenna Model 94455-1
20-200 MHz Serial No. 0997 Cal. 5/15/98
4. Electro-Metric Dipole Kit, 20-1000 MHz, Model TDA 25 cal. 5/15/97
5. Electro-Metric Horn 1-18 GHz, Model RGA-180, Cal. 8/15/98
6. Electro-Metric Antennas Model TDS-25-1, TDS-25-2, 5/15/97
7. Electro-Metric Line Impedance Stabilization Network Model No. EM-7821, Serial No. 101; 100KHz-30MHz 50uH. 12/3/97
8. Electro-Metric Line Impedance Stabilization Network Model No. EM-7820, Serial No. 2682; 10KHz-30MHz 50uH. 12/3/97

TEST PROCEDURE

GENERAL: This report shall NOT be reproduced except in full without the written approval of TIMCO ENGINEERING, INC.

RADIATION INTERFERENCE: The test procedure used was ANSI STANDARD C63.4-1992 using a HEWLETT PACKARD spectrum analyzer with a preselector. The bandwidth of the spectrum analyzer was 100 kHz with an appropriate sweep speed. The analyzer was calibrated in dB above a microvolt at the output of the antenna. The resolution BW was 100KHz and the video bandwidth was 300KHz up to 1.0GHz and RBW was 1.0MHz with a VBW of 3.0MHz above 1.0GHz. The ambient temperature of the UUT was 84.0oF with a humidity of 80%.

FORMULA OF CONVERSION FACTORS: The Field Strength at 3m was established by adding the meter reading of the spectrum analyzer (which is set to read in units of dBuV) to the antenna correction factor supplied by the antenna manufacturer. The antenna correction factors are stated in terms of dB. The gain of the Preselector was accounted for in the Spectrum Analyzer Meter Reading.

Example:

Freq (MHz)	METER READING + ACF = FS
33	20 dBuV + 10.36 dB = 30.36 dBuV/m @ 3m

POWER LINE CONDUCTED INTERFERENCE: The procedure used was ANSI STANDARD C63.4-1992 using a 50uH LISN. Both lines were observed. The bandwidth of the spectrum analyzer was 10kHz with an appropriate sweep speed. The ambient temperature of the UUT was &tempc& with a humidity of &humc&.

APPLICANT: BESCO ELECTRONIC MFG., CO., LTD.
FCC ID: GXKBS3100RX
REPORT #: F:\CUS\B\BESCO\BES258H8.RPT
PAGE #: 1

TEST PROCEDURES CONTINUED

APPLICANT: BESCO ELECTRONIC MFG., CO., LTD.

FCC ID: GXKBS3100RX

ANSI STANDARD C63.4-1992 10.1.7 MEASUREMENT PROCEDURES: The unit under test was placed on a table 80 cm high and with dimensions of 1m by 1.5m. The table used for radiated measurements is capable of continuous rotation.

When an emission was found, the table was rotated to produce the maximum signal strength. At this point, the antenna was raised and lowered from 1m to 4m. The antenna was placed in both the horizontal and vertical planes.

The situation was similar for the conducted measurement except that the table did not rotate. The EUT was setup as described in ANSIC63.4-1992 with the EUT 40 cm from the vertical ground wall.

RULES:2.1033(b)(4) CIRCUIT DESCRIPTION

This unit is a super regenerative receiver for a low power security device system. The signal comes in on the antenna to the super regenerative detector Q1. From Q1 the detected signal is fed to the amplifier Q4/Q3. From Q4/Q3 the signal is fed thru Q2 into the microprocessor IC2. The output of IC2 in conjunction with the timer NE555 turns the security light on & then off 60 seconds later.

ANTENNA & GROUND:

This unit makes use of a 3 inch long piece of 14AWG wire as an antenna. The antenna is self contained, no provision is made for an external antenna. the unit is powered from a 12 volt battery.

The unit relies on the ground tract of the printed circuit board.

APPLICANT: BESCO ELECTRONIC MFG., CO., LTD.

FCC ID: GXKBS3100RX

REPORT #: F:\CUS\B\BESCO\BES258H8.RPT

PAGE #: 2

APPLICANT: BESCO ELECTRONIC MFG., CO., LTD.
 FCC ID: GXKBS3100RX
 NAME OF TEST: RADIATION INTERFERENCE
 RULES PART NO.: 15.109
 REQUIREMENTS: 30-88 MHz 40.0 dBuV/m measured at 3 meters
 88-216 MHz 43.5 dbuV/m
 216-960 MHz 46.0 dbuV/m
 ABOVE 960 MHz 54.0 dbuV/m

TEST DATA:

TUNED FREQ. MHz	EMISSION FREQUENCY MHz	METER READING @ 3m dBuV	COAX LOSS dB	A.C.F. dB	PEAK FIELD STRENGTH dBuV/m@3m	MARGIN dB	ANT.
360.40	351.78	19.50	1.40	15.60	36.50	9.50	H
360.40	353.02	20.70	1.40	15.64	37.74	8.26	H
360.40	357.56	22.60	1.40	15.77	39.77	6.23	H
360.40	360.72	26.20	1.40	15.86	43.46	2.54	H
360.40	362.68	22.40	1.40	15.92	39.72	6.28	H
360.40	364.60	19.40	1.40	15.97	36.77	9.23	H
360.40	366.56	13.30	1.40	16.03	30.73	15.27	H
360.40	368.52	11.00	1.40	16.09	28.49	17.51	H

METHOD OF MEASUREMENT: The procedure used was ANSI STANDARD C63.4-1992. The spectrum was scanned from 30 MHz to at 2 GHz. The spectrum analyzer was as specified in ANSI STANDARD C63.4-1992. The receiver was put into a coherent mode.

- 1) Resolution bandwidth 100 kHz to 1 GHz and 1 MHz above 1 GHz
- 2) Frequency scan per division 1 MHz/division
- 3) Scan time was set to 20 mS/division
- 4) A preselector was a part of the spectrum analyzer system for the frequency range.
- 5) A weak, on frequency signal was used to place the receiver in the coherent mode.
- 6) The line spectrum of pulse analysis was used.

SAMPLE CALCULATION: $FSdBuV/m = MR(dBuV) + ACFdB.$

TEST RESULTS: The unit DOES meet the FCC requirements.

PERFORMED BY: _____ DATE TESTED: SEPTEMBER 4, 1998

APPLICANT: BESCO ELECTRONIC MFG., CO., LTD.
 FCC ID: GXKBS3100RX
 REPORT #: F:\CUS\B\BESCO\BES258H8.RPT
 PAGE #: 3