




2. Multi point setting

※ It's possible to connect and use 2 devices simultaneously

1) Setting Multi point

- Please pair Bluetooth earphone to the first device according to the pairing process. (Refer to pairing process.)
- Turn off Bluetooth headphone.
- Press  button for around 4 seconds till blue LED is continuously on.
- Please pair Bluetooth earphone to 2nd device according to pairing process.
- Then, turn off Bluetooth headphone and turn on again, it will be connected 2 devices.

2) To use multi point

- At the status of connecting two devices, press  button to answer a call if there's incoming call.
- At the status of connecting two devices, press  button to listen the music that was played lately.
- ※ During multi point status, please refer that App related functions are not workable.

3. Call

1) Answering a call

- Press  button to answer a call.

2) Ending a call

- Press  button shortly to end a call.


3) Rejecting a call

- During an incoming call, press  button for about 1 second.

4) Converting a call

During call with mobile, press  button to convert to headphone.
(To call with mobile again, use your mobile phone menu.)

5) Volume control

- With  /  button, you can control volume.

6) Microphone Mute

- During call, if you press  or  button for about 1 second, the microphone becomes mute.
- During mute, it will be released, if you press  or  button for about 1 second.

※ Depending on mobile phone models, the above functions may be different.
Please refer to mobile phone manual.

4. Factory Reset

Press $\oplus + \ominus \rightarrow \oplus + \ominus \rightarrow \oplus + \ominus \rightarrow \odot + \ominus$ buttons in order, then, purple LED glitters and headset will be initialized.
Pair the headset again to use after factory reset.

5. Playing music

※ To enjoy the best audio quality, please set 70~80% from the max volume in your device.

- On first purchasing, the volume sets in level 10 of all 15 levels.
(Please adjust with \oplus / \ominus button for volume.)

- Play / Pause : Press \odot button shortly
- Stop : Give a \odot button long press
- Volume up : Press \oplus button shortly
- Volume down : Press \ominus button shortly
- Next song : Give a \oplus button long press
- Previous song : Give a \ominus button long press

6. Changing EQ

- While playing music, if you press MFB button and (\odot or $\oplus + \ominus$) button at the same time for 1 second, the EQ changes.
- MSTSTM Tuning technology together with lossless compression apt-X codec enables you to enjoy not only MobiFren sound but similar sound quality of various kinds of famous high end wired headphones and you can select EQ for your preference. Now you can enjoy music with the optimum sound quality like as CD in wireless.

Special EQ modes supplied by MobiFren

- MobiFren Mode (Normal) : MobiFren's pursuing tune
- Bass Boost Mode : for those who like deep bass
- Cinema Mode : for those who want to enjoy 3D surround sound

※ There are several kinds of bit rate even though it's the same MP3 file.
If the file source is higher bit rate(320K) for listening, you can feel the real worth for our Bluetooth headphone. And, if the speaker is not good even with good source, the sound quality will not be good, and if the speaker is good with inferior source, the sound quality can't touch to the listener.
The MobiFren headphone of optimized tuning supplies you high quality sound, but, we also recommend you to use high resolution source file (320K) to enjoy touching sound.

7. Using Android App.

For more convenient and easy use of the headphone, please download "MobiFren_GT" at Google play store

- TTS caller ID

If you press ⊕ or ⊖ button shortly when there's an incoming call, you can listen the caller's name via mobile phone speaker.

- SMS/SNS message TTS

- After setting Message TTS, in automatic mode, it reads you message after the setting time, and in manual mode, you can hear message by using headset button.

(When you set this function, it goes to mobile phone's accessibility menu automatically, then, select MobiFren_GT in accessibility service.)

Stop while playing TTS : TTS playing stop.

While reading TTS message, press ⊙, ⊕ + ⊖ button to stop playing.

Manual mode : It reads you message by pressing headset button.

Press MFB button and ⊙, ⊕ + ⊖ at the same time to hear message manually.

- Last Call (Direct call to the latest number)

It's for direct call to the latest number that you used.

- Hot call (Prompt call)

It's for prompt call to the frequent number.

Last Call /Hot Call

- Press ⊙ button shortly for 2 times.

- Find mobile phone

If you can't remember well where you placed your mobile phone, press ⊕ and ⊖ buttons at the same time for about 1 second to find out your mobile phone. Then, the mobile phone will ring.

- Camera Remote control

Press ⊕ or ⊖ button shortly to take a picture after running application. (It needs additional MobiFren camera application.)

4. What does LED color mean?

Status	LED indication
Standby	LED OFF (If press button, blue LED blinks once.)
Battery is running low	Blinks red light
Charging	Red light ON
Fully charged	Blue light ON
Pairing mode	Blue light ON

5. FAQ & Troubleshooting

※ I hear crackling noises

- For the best audio quality, always locate your headphone close to mobile phone.

※ I cannot hear anything

- Increase the volume on the headphone.
- Ensure that the headphone is paired with the phone.
- Make sure that the phone is connected to the headphone.
- If the headphone fails to connect when you pressed MFB, try to connect again following the pairing procedure.

※ I have problems with pairing even though my phone indicates otherwise.

- Please delete the headphone paired in your mobile and pair the headphone again.
Please refer to set up "Pairing mode".

※ Will the MobiFren GBH-S3000 series work with other Bluetooth equipment?

- The MobiFren GBH-S3000 series is designed to work with Bluetooth mobile, computer or portable audio devices which are built in. It can also work with other Bluetooth devices that are compliant with Bluetooth version 1.1/ 1.2/ 2.0/2.1+EDR/3.0 and that support HSP, HFP, A2DP and AVRCP.

※ Is the enclosed charging cable for only specified device?

- It's compatible with all standardized micro USB charger, and in general, compatible with Android mobile phone charger.
- ※ When you use the headphone in the car, the handsfree can be affected by the internal noise.

6. Handle MobiFren with care

OFF

- Always store the MobiFren ear phone with the power off and protect safely when it's not in use.
-



- can affect the MobiFren's battery life and may be the cause of malfunction.
 - High temperature may also degrade performance.
-



- Do not expose the MobiFren earphone to rain or other liquids
-



- Prevent baby, children or pets to bite or suck this headset
-



- Please do not disassemble at user's option
-

5V, 140mA

- Please make sure to use certified charger. (Rated Voltage : 5V)
-

7. Certification and safety approvals

FCC ID : UZCGBH-S3100

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules.

These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

CAUTION : Changes or modifications not expressly approved by the manufacturer responsible for compliance could void the user's authority to operate the equipment.

This device complies with part 15 of FCC rules.

Operation is subject to the following two conditions:

- This device may not cause harmful interference.
- This device must accept any interference received, including interference that may cause undesired operation.

8. Specifications

• Model	GBH-S3000 Series
• Talk time	About 9 hrs
• Music play time	About 7.5 hrs
• Standby time	About 10 days
• Charging time	about 1.5 hours
• Size	9.8mm(W) X 58mm(L) X 6.2mm(T)
	570mm(cable length)
• Battery	Rechargeable Lithium Polymer(DC 3.7 V)
• Weight	about 13g
• Operation range	Within 10m
• Bluetooth profile	Headset profile
	Headset profile
	A2DP
	AVRCP
	SPP
• Bluetooth profile	Ver. 3.0

※Operation time may be variable, depending on connected device or setting status.

Made in Korea

In accordance with the R & TTE Directive 1999 / 5 / EC of 09. March 1999

9. Warranty

※ The conditions and our responsibilities under this warranty are as follows :

- The warranty is limited to the original purchaser.
- A copy of your receipt or other proof of purchase is required.
- The warranty is void if the serial number, date code label or product label is removed, or if the product has been subject to physical abuse, improper installation, modification, or repair by unauthorized third parties.
- The responsibility of MobiFren products shall be limited to the repair or replacement of the product at its sole discretion.
- Any implied warranty on MobiFren products is limited to one year from the date of purchase on all parts, including any cord and connector. But, battery warranty is limited to 6 months.
- Specifically exempt from any warranty are limited-life consumable components subject to normal wear and tear, such as microphone windscreens, ear cushions, decorative finishes, batteries, and other accessories.
- MobiFren is not liable for any incidental or consequential damages arising from the use or misuse of any MobiFren product.
- This warranty gives you specific rights and you may have other rights which vary from area to area.
- Unless otherwise instructed in the User Manual, the user may not, under any circumstances, attempt to perform service, adjustments or repairs on this unit, whether in or out of warranty. It must be returned to the purchase point, factory or authorized service agency for all such work.
- MobiFren will not take any responsibility for any loss or damage incurred in shipping. Any repair work on MobiFren products by unauthorized third parties voids any warranty.

*"Contribute to our communities
with good technology and good product"*

NabiFren

NabiFren

MobiFren

www.mobifren.com

GT Telecom Co., Ltd.

(Gupyeong Dong A & B dong), 88, Indong 52 Gil,

Gumi City, Gyeongbuk, Korea 730-300

TEL : 82-54-474-2220 FAX : 82-54-474-2251

ISO 9001 Quality Management System
Certified Company



MSIP-CRM-GTT-GBH-S3100

3.7V $\frac{---}{---}$, 140mA



MADE IN KOREA