

2.4GHz 2 way fast digital RF  
1000 dpi precise wireless optical mouse  
Up to 10 Meter working distance  
64 auto hopping channels with 65K ID  
Long battery life for Keyboard 1 year and mouse 3 months  
Cordless Freedom: Feel confident with a reliable wireless connection  
Easy USB connectivity: Connects quickly and easily to any PC or notebook  
Smart auto link: Easy setup, no software installation and reset buttons  
Motion wake up while in sleeping mode  
Spill resistant keyboard: offers protection against a liquid is spilled on keyboard  
Space-saving keyboard design: Saves space without sacrificing a bit of comfort  
Stand profile keys provide comfortable & silent touch

## Features

Long battery life  
Nano receiver

## RF Specifications

Number of Channels: 64  
Carrier Frequencies: 2408MHz~2474MHz  
Modulation: FSK  
ID: 65536  
Transmission Range: up to 10 Meter, 360°  
Max. Rated Output Power: 94.85 dBµV/m

## Keyboard Specifications

Keys: 104  
Travel Length: 3.0mm  
Input Power: 1.5V, 1\*AA  
Power Consumption:  
4mA (key pressed)

## Mouse Specifications

Buttons: Left, Right, Middle  
Resolution: 1000 dpi  
Tracking Speed: up to 14 inch/second  
Input Power 3V, 2\*AAA  
Power Consumption: 10mA

## Receiver Specifications

Input Power: 5V DC  
Interface: USB 1.1

## System Requirement

IBM PC or compatible  
Available USB port  
Microsoft® Windows® 2000/XP/VISTA/7

## Package Contains

\* Wireless keyboard  
\* Wireless optical mouse  
\* Nano receiver  
\* 1\*AA and 2\*AAA batteries

## Installation:

1. Plug the Nano receiver into a USB port of your computer
2. Insert battery into your mouse and keyboard
3. Move the mouse to get connected with the receiver
4. Click the keyboard key to get connected with the receiver

## Caution:

**Before your mouse and keyboard is connected with the receiver. You need to keep the mouse and keyboard at a distance or less than 2 meter to the receiver to finished the initial connection.**

## Trouble shooting

1. Check nano receiver connection: try to inserting nano receiver to another USB port on your computer.
2. No connection between the mouse / keyboard and the nano receiver: Re-insert the nano receiver. Take out the battery from the mouse / keyboard and re-install it.

## **Federal Communication Commission Interference Statement**

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one of the following measures:

- . Reorient or relocate the receiving antenna.
- . Increase the separation between the equipment and receiver.
- . Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- . Consult the dealer or an experienced radio/TV technician for help.

***FCC Caution:*** To assure continued compliance, any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment. (Example - use only shielded interface cables when connecting to computer or peripheral devices).