

# **User manual**

**Model:K2**

**Brand:CIRO**

**Welcome!**

PLEASE READ THIS INFORMATION BEFORE USING THE PHONE TO MAKE A BETTER USE OF YOUR PHONE. WE ARE NOT RESPONSIBLE FOR ANY DAMAGE DUE TO YOUR MISUNDERSTANDING OF THIS INFORMATION AND MISACTTING.

We are endeavoring to improve our products and services and we reserve all the rights to revise and change the description of this product and its software as well as this user manual without obligation to notify any person of such revisions and changes.

This user manual is for your better use of this phone not an approval of any accessories. All the pictures in this manual are for reference only. There may be slight difference between the appearance of phone and keys and contents of display used in this manual and those of your phone. Please refer to your phone for actuality. Some features introduced in this manual are network or subscription-dependent features. Please contact your service provider.

## Contents

1. Functions .....	4
2. Phone Book .....	6
2.1 Search contact .....	6
2.2 Add number .....	7
2.3 Copy All .....	7
2.4 Delete .....	8
2.5 Extra groups .....	8
2.6 Extra numbers .....	8
2.7 Settings .....	8
3. Message .....	9
3.1 MMS .....	9
3.2 SMS .....	12
4. Call History.....	15
4.1 Call history .....	15
4.2 Delete call logs .....	15
4.3 Call timers .....	15
4.4 Call cost .....	16
4.5 The text message counter .....	16
5. Fun&Games.....	16
6. Services .....	17
7. Multimedia.....	18
7.1 Image viewer .....	18
7.2 Camera .....	19
7.3 Audio player .....	20
7.4 Video player .....	20
7.5 Video recorder .....	20
7.6 FM radio.....	21
7.7 File manager.....	22

8. Organizer .....	23
8.1 Calendar .....	23
8.2 Alarm .....	24
8.3 Flashlight.....	24
8.4 Tasks .....	24
8.5 Bluetooth.....	25
9. Profiles .....	25
10. Settings .....	26
10.1 Phone settings.....	26
10.2 Dual SIM settings .....	27
10.3 Network settings.....	27
10.4 Security settings .....	28
10.5 Call settings .....	28
10.6 Restore factory settings.....	29

## 1. Functions

This phone offers you many functions. Under the sleep mode you can press the OK key then slide the "side to unlock" button to main menu.

### 1 Phone Book

- 1-1 Search contact
- 1-2 Add number
- 1-3 Copy All
- 1-4 Delete
- 1-5 Caller groups
- 1-6 Extra numbers
- 1-7 Settings

### 2 Message

#### 2-1 MMS

- 2-1-1 New MMS
- 2-1-2 Inbox
- 2-1-3 Sent
- 2-1-4 Outbox
- 2-1-5 Draft
- 2-1-6 Message Settings
- 2-1-7 About us

#### 2-2 SMS

- 2-2-1 Write message
- 2-2-2 Inbox
- 2-2-3 Outbox
- 2-2-4 Templates
- 2-2-5 SMS settings

### 3 Call History

- 3-1 Missed call
- 3-2 Dialed number
- 3-3 Received calls
- 3-4 Rejected calls
- 3-5 Delete call logs
- 3-6 Call timers
- 3-7 Call cost
- 3-8 Text message counter

### 4 Fun & Games

- 4-1 Games
- 4-2 Game Settings

### 5 Services

### 6 Multimedia

- 5-1 Image viewer
- 5-2 Camera
- 5-3 Audio player
- 5-4 Video player
- 5-5 Video recorder
- 5-6 FM radio
- 5-7 File manager

### 7 Organizer

- 7-1 Calendar
- 7-2 Alarm
- 7-3 Flashlight
- 7-4 Tasks
- 7-5 Bluetooth
- 7-6 Calculator

### 8 User Profiles

- 8-1 General

- 8-2 Meeting
- 8-3 Outdoor
- 8-4 Indoor
- 8-5 Headset
- 8-6 Bluetooth

## 9 Setting

- 9-1 Phone settings
- 9-2 Dual SIM settings
- 9-3 Network settings
- 9-4 Security setting
- 9-5 Call settings
- 9-6 Restore factory settings

## 2. Phone Book



Select Phone Book to enter phone book.

The phone book consists of phone storage and SIM card storage and you can use both of them.

Phone Storage: With name, default number, family number, company name, email address, company number, fax number, birthday date and group/individual ring in each item.

SIM card Storage: The capacity depends on your SIM card type and there is only name and one business number in each item. For details, please contact your service provider.

### 2.1 Search contact

Choose the Search in the Phone Book, input the name you want to search, then through the Option-Search menu to lookup the item qualifying in the phonebook.

You can directly call one number by pressing **send**

**key** in phone book screen and you can also press option to make following operations:

**IP Dial** Automatically add the IP number before the number when make a call.

**Send SMS** Send messages to the item.

**View** View all the information about the name.

**Edit** Edit the information of the name.

**Delete** Delete the record.

**Copy** Copy the names stored in the phone storage/SIM card storage to the SIM card storage/phone storage (copy between the two storages).

**Move** Move the names stored in the phone storage/SIM card storage to the SIM card storage/phone storage.

## **2.2 Add number**

You can add new names in your phonebook by this function and save to the phone storage or SIM card storage.

Only names and call numbers can be added when you add new contact to SIM card storage.

## **2.3 Copy All**

You can copy all the names and switch between SIM cards

and phone storage.

Note: When copy the names stored in the phone storage to SIM card, only names and default numbers can be saved.

## 2.4 Delete

You can do following operation:

From SIM	Delete all the names stored in SIM card
From Phone	Delete all the names stored in the phone storage
One By One	Delete the selected names one by one

## 2.5 Extra groups

You can set Owner Number in this menu.

Note: this feature must be supported by your SIM card. For details please contact your service provider.

## 2.6 Extra numbers

SIM owner number  
SIM service dialing number  
SIM SOS number

## 2.7 Settings

You can perform following operations on the phonebook:

Memory Status	Check the capacity of the phonebook, including SIM card memory and phone memory.
Preferred Storage	Select SIM card memory or phone memory as the default storage location



when adding new entry.


Fields Select the items of information that the Card shows.

Tip: you can also choose another storage location when you add new entry.

### 3. Message

You can receive and send messages, and can also use broadcast message and voice mail box.

Messages make it possible for you to exchange messages

with other wireless phone users. Select  Messages to perform operation.

#### 3.1 MMS

##### New MMS

Select New MMS, you can see the following options:

- |          |   |
|----------|---|
| TO       | Edit number or email address of receivers (up to 10) the MMS is sent to |
| CC       | Edit number or email address of receivers (up to 10) the MMS is cc to   |
| BCC      | Edit number or email address of receivers (up to 10) the MMS is bcc to  |
| Sub      | Edit subject of the MMS   |
| Insert   | Edit MMS  |
| Content  |   |
| Creation | Free: allow user to add any content by default                          |
| Mode     | Warning: Show one warning message to user that                          |

the content class is violated


Restricted: User is not allowed to violate the content class setting

Content Class Include text class, image basic, image rich, video basic, video rich

Select Insert Content to enter MMS editing interface, press Option to perform the following operations:

Add Image	Add image to MMS
Add Audio	Add audio to MMS
Add Attachment	Add attachment to MMS
Edit Text	Edit text of MMS
Add Slide	Add slide to MMS
Delete Image	Delete existing image
Delete Audio	Delete existing audio
Set Slide Timer	Set time interval between slides
Delete Slide	Delete selected slide
Template	Insert template to MMS
Preview	Preview MMS
Send	Send MMS
Save	Save MMS to Draft

## Inbox

The Inbox is for storing received MMS. Depending on the selected mode, the phone vibrates or rings when you get a new MMS with screen showing the new message icon and prompt lights flickering. After you go back to idle,  shows on the top of the status bar till you read the new MMS.

Against the MMS in the inbox, you can operate the following operations:

View	View the MMS
Reply	Edit MMS to reply the sender

Reply by SMS	Reply the sender with SMS
Reply All	Reply all senders
Forward	Edit the corresponding information including the recipient, address of the current MMS then send to others
Delete	Delete the MMS
Delete All	Delete all the MMS in the inbox
Properties	View the details of the message

## Outbox

Enter outbox to view the MMS that you saved and you can perform following operations:

View	View the MMS
Forward	Edit the corresponding information including recipient, address of the MMS then send to others
Edit	Enter the MMS edit interface
ReSend	Send the MMS again
Delete	Delete the MMS
Delete All	Delete all the MMS in the outbox
Properties	View the details of the message


## Message Settings

You can setup your MMS through the menu by your need as following:

Server Profile	Start or edit the service, when you fail to send the MMS, please change online-pattern of the server to WAP.
Compose	Edit Auto Signature and Signature.
Send	Include validity period, delivery report,

Retrieve read report, priority, slide timing, delivery time etc.  
Include Home network, read report, delivery report.

## 3.2 SMS

You can enter the SMS menu through the  message.


### Writing Messages

You can write a new text message send to others, and also can insert template in the message.

Select the Option after editing a text message:

Send Only	Send the message
Save and Send	Save the message while sending
Save	Save the message
Send To Many	Send the message to many
Send By Group	Send the message to all the link of the selected group

### Inbox


The Inbox is for storing received messages. Depending on the selected mode, the phone vibrates or rings when you get a new message with screen showing the new message icon and prompt lights flickering. After you go back to idle,  shows on the top of the status area till you read the new message.

While reading a message, you can perform following operations:

Reply:	Reply a message to the sender
Delete:	Delete this message
Edit:	Edit this message

Forward:	Send this message to somebody else
Copy to Phone*:	Copy the message from SIM card to the phone memory
Copy to SIM*:	Copy the message from phone memory to SIM card memory
Move to Phone*:	Move the message from SIM card to the phone memory
Move to SIM*:	Move the message from phone memory to SIM card memory
Delete All:	Delete all the messages in the inbox
Copy All:	Copy all the messages from SIM card or phone memory to phone memory or SIM Card
Move All:	Move all the messages from SIM card or phone memory to phone memory or SIM Card
Use Number:	Extract the number from this message and perform operation on it

Tip: the menus marked with\* may not appear depending on the storage location in use.

Note:  keeps flickering in idle when you inbox is full. Please delete some messages to receive new messages.

## Outbox

Enter outbox to view the sent messages that you saved and you can perform following operations:

Send:	Send this message to one contact
Edit:	Edit this message
Delete:	Delete this message
Copy to Phone*:	Copy the message from SIM card to the phone memory

Copy to SIM*:	Copy the message from phone memory to SIM card memory
Move to Phone*:	Move the message from SIM card to the phone memory
Move to SIM*:	Move the message from phone memory to SIM card memory
Delete all:	Delete all the messages in outbox
Copy All:	Copy all the messages from SIM card or phone memory to phone memory or SIM Card
Move All:	Move all the messages from SIM card or phone memory to phone memory or SIM Card
Use Number:	Extract the number from this message and perform operation on it
Use URL:	Extract the link from this message and operate on it

## Message Settings

You can setup the message from the menu, as following:

Profile Setting:	Offer you four profiles and you can edit their names, set SC Address and Valid Period etc.
Common Setting:	Set delivery report on or off
Memory Status:	Check the capacity of messages storage
Preferred Storage:	Set the default message storage location to phone or SIM card.

Note: you need support from the service provider to receive delivery reports.

## 4. Call History



Enter the main menu Call History, select SIM1 or SIM 2 to view the dialed calls and answered calls, can also examine the call time, cost and the use of the messages.

### 4.1 Call history

Your phone keeps lists of incoming and outgoing calls, even for calls that didn't connect. The most recent calls are listed first.

Tip: the phone keeps the only latest call of the same number.

To view detailed information or perform other operations:

Find the lists of Dialed Calls, Received Calls, Missed Calls

Press OK key to view the detail information: times etc.

Press Option key to perform following operation:

Delete: Delete this record.

Save: Save the number of this record to phone book.

Dial: Dial the number of this record.

Edit: Enter the number edit screen, you can modify, save or dial the number.

Send SMS: Send messages to the number of the item.

### 4.2 Delete call logs

You can delete the all the records of the missed calls, dialed calls and answered calls, you can also choose delete all to delete all the records of the three parts.

### 4.3 Call timers

You can examine the call time record of the phone up to now

through the menu.

Last Call Time

Show the last call time.

Total Sent

Show the dialed calls time.

Total Received

Show the answered calls time.

Reset All Time

Reset the last call time, total dialed time and total inhale time.

## 4.4 Call cost

You can examine the call cost of the phone up to now through the menu.

Last Call Cost

Examine the last call cost.

Total Cost

Examine the total call cost.

Reset Cost

Input the PIN2 code, and then can cleanup all the cost.

Max Cost

Show the limitation of the currently cost, "0" means no limit. Tap setting can setup the limitation of the cost.

Price Per Unit

Tap setting to setup the unit time rates.

**Note:** The call cost function must be supported by the network service provider. Reset the cost, setup the maximum cost and rates need to input the PIN2 code, please connect with your network provider to gain the password.

## 4.5 The text message counter

You can examine the number of the sent and received SMS currently.

## 5. Fun&Games

The phone provides you more application software, and it makes you more convenient.



Enter from menu Games, the phone provides you many games interesting, which make your life wonderful.

To the rules of the built-in games, you can refer to the notes of the games.

And you can setup the sound and the shock through the game settings.

Note: you can set easy, normal and hard level in Game Level about some games through Game Settings.

## **6. Services**

Services show different contents according to different service provider. For more information, please consult your SIM provider.

### **WAP**

Your phone support WAP (Wireless Application Protocol) based services that provide you WAP services such as news, weather forecast and flight info, etc. All these services are designed for mobile phone and maintained by WAP service provider.

WAP service need support from network operator, please consult network operator or our service provider for WAP availability, pricing and usage.

### **Homepage**

Select it, your phone will try to connect to the homepage you set, if you never set a homepage before, the phone will connect to the default website set by network operator.

### **Favorites**

You can add websites to Favorites.

### **Recent Visits**

The menu lists the website records your recently visit to

facilitate your visit to the site.

## **Go to URL**

Enter the menu, after inputting the URL address of the WAP service that you want to visit, tap the option button and select Go. The phone automatically logs on the website you input.

## **Settings**

You can set the following parameters:

Activate	Select and start network configuration.
Profile	
Options	Set timeout, set graphics, cache and cookie on/off.
Clear Cache	Clear the records in the cache.
Clear Cookie	Clear cookie records.
Select SIM Card	Set to always ask, SIM1 or SIM2.

## **About us**

List basic info about WAP browser

## **7. Multimedia**

Your phone offers multimedia applications and you can select Media from main menu to open it.

### **7.1 Image viewer**

You can perform the following operations:

View	View album
Browse	Set the view mode
Style	

Forward	Send the current photo to wallpaper list, screen saver list and power on/off display list, Bluetooth
Rename	Change name of the photo
Delete	Delete the photo
Delete All	Delete all photos
Sort	Arrange the photos by name, type, time, size or random
Storage	Store to phone or Memory Card

## 7.2 Camera

Your phone has a hi-Mega pixel camera that you can take photos whenever and wherever you like. After taking photos, store them in the phone memory or memory card (if any).

### Camera Settings

Press left soft key/Option in viewfinder interface and make detailed settings:

Album	Switch to the album and show the photo files stored in the current album.
Camera Setting	Set the status of shutter sound, EV, Banding, delay timer and Cont-shot
Image Setting	Adjust the photo's size and quality.
Effect Setting	Set effect to Normal, Sepia, Sepia Red, Sepia Green, Sepia Blue, Monochrome, Color Invert.
Frame	Select frame.
Cont Shot	Set it to 1 Shot, 3 Shot or 5 Shot.
Delay Timer	Set delay time to 5 sec, 10 sec, 15 sec.
Storage	Set the storage location.
Restore	Use the default settings.
Default	

## Take a Photo

In the camera viewfinder interface, take the scene in the frame; press OK to take a photo.

After photographing, select save to store the photo, then back to the viewfinder state; Tap back to give up saving and back to the viewfinder state.

Tips: All the photos are stored in the Photos file.

## 7.3 Audio player

You can use the audio player to play music. Press up direction key to play the current music, and press it again to pause the current music; Press the left direction key to switch to the previous one, and right direction key to switch to the next. You can adjust the volume of the MP3 player through the "\*" or "#" key and down direction key.

## 7.4 Video player

Tap Video Player to open it and view all video files. Press the Option and perform following operations on the selected video: play, forward, details, rename, delete, delete all files or sort.

During playing, press the 4-way navigation key up and down to adjust the speed, press the left or right key to control playing rate, press "\*" to full screen, press "#" to mute.

## 7.5 Video recorder

Open Video Recorder to view the sound files in AMR or WAV format. If there is no file, your phone prompts Empty.

Press the Option and perform following operations on the video file:

Record: start recording and during recording, you can press the pause option to pause and press again to continue. Press the stop option to stop recording and go to save display, press

the Option and then select Add video. If you prefer not to save it, press the Clear option to go back.

Tip: the video files are stored in the video file.

## 7.6 FM radio

Choose Radio menu to turn the radio function.

### Tune in the Radio

Turn on the radio function, the idle shows the position number, name (if saved), frequency of the broadcast channel.

Note: for saved channel, you can choose the position by press the corresponding numeric key quickly.

### Search the Channel


Press the left direction key, right direction key to inch the HZ, select frequency you need, the radio will find the channel. Use the upper key to set it, use the down key for searching, use the \* key, # key to adjust the volume.

You can also choose automatic search under the radio idle, the radio will search the channels which can receive presently.

Note: Automatic search needs times, please wait bovine.

### Basic method


The radio function the phone provides supports the background play.

While quit the interface when the  shows, you can also tune the radio in.

Note: While tuning the radio in, you can dial or hear the call normally. When on the phone, the radio will become silent automatically.

## 7.7 File manager



Tap  from the main menu to open it and you can find the storage devices and the capacity of total space and free space. On different objects, there are different operations.

Storage devices: press Option to perform following operations:

- |                   |  |
|-------------------|--|
| <b>Open</b>       | List all the folders and files   |
| <b>New Folder</b> | Create a new folder and edit its name  |
| <b>Format</b>     | Format the storage devices, the operation will delete all the data stored in the storage devices |

Folders: press Option to perform following operations:

- |                   |  |
|-------------------|--|
| <b>Open</b>       | Show the file tree in this folder and list all files             |
| <b>New folder</b> | Create a new folder and edit its name                            |
| <b>Rename</b>     | Change the folder's name   |
| <b>Delete</b>     | Delete the folder  |
| <b>Sort</b>       | Arrange the folders or files by name, type, time, size or random |

Files: press Option to perform following operations:

- |                |  |
|----------------|--|
| <b>View</b>    | View the image files stored in certain formats; If the phone is nonsupport, it will tip that format error.     |
| <b>Play</b>    | For the multi-media files the phone supports, it show the menu; you can play the multi-media files by the menu |
| <b>Forward</b> | Send the file to Bluetooth   |

<b>Rename</b>	Edit the file's name
<b>Copy</b>	Copy this file to any other folder in the same storage device
<b>Move</b>	Move this file to any other folder in the same storage device
<b>Delete</b>	Delete this file
<b>Delete all</b>	Delete all the files in current folder
<b>Files</b>	
<b>Detail</b>	Show the updating time and its size
<b>Sort</b>	Arrange the folders or files by name, type, time, size or random

Tip: the options may differ depending on the object types.

## 8. Organizer

Your phone provides you more management tools including Calendar, Alarm, To do list, Currency Converter, Unit Converter, Stopwatch and Notepad. Enter from main menu



Organizer.

### 8.1 Calendar

The screen shows current date framed by special color box when entering Calendar. Press the 4-way navigation key up, down, left or right to move to different date. Press OK key or left soft key to enter the corresponding menu and you can find View Tasks, Jump To Date and Lunar Calendar (only when setting Chinese as phone language).

## 8.2 Alarm

Your phone has an alarm clock with 5 separate alarms that you can set to alert you at the time(s) you specify. To set an alarm clock, select one alarm and press left soft key to turn it on/off, set time, period, ring and reminding mode.

## 8.3 Flashlight

Open/Close the Flashlight

## 8.4 Tasks

You can schedule and organize events such as appointments and meetings by Notepad in your phone as it always reminds you of the preset tasks on time if your phone is power on. Enter Notepad from Organizer and you can check all tasks. While the task list is empty, press left soft key to "Add" new tasks or open calendar display, enter Option and select Jump To Date to add new tasks. While viewing a task, you can also enter Option by pressing left right key to perform following operation:

### **View**

View the content of selected task

### **Add**

Select Add to create a new task. You can edit its date, time, note, alarm mode and reminding mode etc.

Edit Task

Edit the content of selected task

### **Delete Task**

Delete the content of selected task

### **Delete All**

Delete all the tasks



Note: there is fixed room for storing tasks and when no "Add" shows in "Option", please delete some indifferent tasks to save room for important ones.

## 8.5 Bluetooth

This phone supports Bluetooth function.

Bluetooth technology allows you to connect your phone using radio waves to a compatible Bluetooth device within 10 meters.

There may be restrictions on using Bluetooth technology in some locations. Check with your local authorities or service provider.

 indicates that Bluetooth is active.

Enter Bluetooth menu, you can perform the operations:

Activate	Turn on/off Bluetooth
Inquiry Audio Device	Search compatible Bluetooth audio device and select one device
My Device	Search all Bluetooth devices
Active Device	Paired Bluetooth devices
Setting	Change device name, set visibility, authentication, audio path, FTP setting
About	Detailed info about Bluetooth

Note: with Bluetooth turned on, it will consume battery.

## 9. Profiles

Enter Profiles and there are several profiles that you can edit the contents as you like: General, Meeting, Outdoor, Indoor, and Headset. Once you pair your phone with an earphone, the Headset is automatically activated and meanwhile the profile in use is deactivated.

You can choose any profile as you like and customize the selected one:

- Tone Setup:** Set the incoming call tone, incoming message tone and keypad tone
- Volume:** Set the volume of ring tone and key tone
- Alert Type:** Set ring, vibration only, vibration and ring, vibration then ring or silent
- Ring Type:** Set single ring, repeat ring or ascending ring
- Answer Mode:** Turn any key answer (except for power on/off key and right soft key) on or off (only in Headset Mode).

## 10. Settings

You can set your favorite wallpaper, ring or some other function.

### 10.1 Phone settings

Enter Settings, select Phone Setup and then you can set following items:

- Time and Date** Set your current time zone, time, date and their display format.
- Schedule** You can set up to 4 power on/off time.
- Power On/Off**
- Language** Set the display language.
- Pref. input Methods** Select the preferred input method as you like.
- Display** You can find submenus such as wallpaper, power on display, and power off display, show LCD backlight.
- Contact**

**Handwriting**      Set pen speed and Pen color.


Note: your choice of time zone does not change the time and date you have setup. The setting of Schedule Power On/Off won't be activated if you set the same time for them.

## 10.2 Dual SIM settings

Enter this menu, you can set the mode to be Dual SIM, Only SIM1, Only SIM2, Flight mode.

## 10.3 Network settings

When dual SIM mode is activated, you can perform network

setup for SIM1 and SIM2 separately. Enter  Settings, select Network Setup and then you can perform following operations:

**Network**      New search, Select Network, Selection Mode

**Selection**

**Preferred**      Set the preferred network during searching.

**Networks**

**GPRS**      Set the way how GPRS is connected.

**Connection**

## 10.4 Security settings



Enter Settings, select Security Setup and then you can perform following operation:

- SIM Lock** Set a password to lock/unlock your SIM card.
- Phone Lock** Set a password to lock/unlock your phone and the default password is 0000.
- Auto Keypad Lock** Set auto keypad lock on or off and a time after which the keypad is locked.
- Fixed Dial** Edit fixed dial list of SIM card.
- Barred Dial** Set the condition for calls that can not be made.
- Change Password** Change the Pin Password, Pin2 Password and Phone Lock Password.

Note: for Pin Password, please contact your service provider; Fixed Dial and Barred Dial must be supported by your SIM card. For details, please contact your service provider.

## 10.5 Call settings



Enter Settings from main menu, select Call Setup and then you can perform some operations as following:

- Own** Preset, conceal, send own number

<b>Number</b>	
<b>Call Waiting</b>	Setup the call waiting function.
<b>Call Divert</b>	Setup the call divert function.
<b>Call Limit</b>	Setup the call limit function.
<b>Line Switching</b>	Switch your current line and there are 2 lines available
<b>Call Time Reminder</b>	Set the call time reminder on or off and its type and period
<b>Call Time Display</b>	Set if call time shows during calls or not.
<b>Auto Redial</b>	Set Auto Dial on or off. While it is on, the phone automatically redials 10 times in occasion that the line is busy or can not be answered and you can press Abort to cancel redialing.
<b>Blacklist</b>	Set 5 numbers; While it is on, the phone automatically shields the incoming calls from the members in blacklist.
<b>IP Dial</b>	Set IP dial on or off, edit IP number
<b>Missed Call Reminder</b>	Set to remind or not when there are missed calls

## 10.6 Restore factory settings



Enter Settings, select Restore Factory Settings and then you can restore initialized settings for wallpaper, screen saver, ring etc.

## FCC Warning

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

**Note:** This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try

to correct the interference by one or more of the following measures:

- ▶ -Reorient or relocate the receiving antenna.
- ▶ -Increase the separation between the equipment and receiver.
- ▶ -Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- ▶ -Consult the dealer or an experienced radio/TV technician for help.

### **Specific Absorption Rate (SAR) information:**

This Mobile phone meets the government's requirements for exposure to radio waves. The guidelines are based on standards that were developed by independent scientific organizations through periodic and thorough evaluation of scientific studies. The standards include a substantial safety margin designed to assure the safety of all persons regardless of age or health.

### **FCC RF Exposure Information and Statement**

The SAR limit of USA (FCC) is 1.6 W/kg averaged over one

gram of tissue. Device types: Mobile phone (FCC ID:2AFM5K2) has also been tested against this SAR limit. The highest SAR value reported under this standard during product certification for use at the ear is 1.121W/kg and when properly worn on the body is 0.664W/kg. This device was tested for typical body-worn operations with the back of the handset kept 10mm from the body. To maintain compliance with FCC RF exposure requirements, use accessories that maintain a 10mm separation distance between the user's body and the back of the handset. The use of belt clips, holsters and similar accessories should not contain metallic components in its assembly. The use of accessories that do not satisfy these requirements may not comply with FCC RF exposure requirements, and should be avoided.

### **Body-worn Operation**

This device was tested for typical body-worn operations. To comply with RF exposure requirements, a minimum separation distance of 1cm must be maintained between the user's body and the handset, including the antenna. Third-party belt-clips, holsters, and similar accessories used by this device should not contain any metallic components. Body-worn accessories that do not meet these requirements may not comply with RF exposure requirements and should be avoided. Use only the supplied or an approved antenna.