

Menu item table

Menu			Item	Factory setting		Selection items	
				FullAuto	Manual1 to 3		
Top Menu	Camera	Scene	Scene	FullAuto		FullAuto, Manual1, Manual2, Manual3	
			Contrast	Contrast Mode	----	Auto	Auto, Manual
				Contrast Level	0	0	-5 to +5
				Shutter Mode	----	----	Off, Step, Synchro
				Step/Synchro (When "Step" is selected as the "Shutter Mode")	----	----	1/100, 1/250, 1/500, 1/1000, 1/2000, 1/4000, 1/10000
				Step/Synchro (When "Synchro" is selected as the "Shutter Mode")	----	----	60.24Hz to 646.21Hz (1 to 255step)
				Frame Mix	----	----	Auto, Off, 6dB, 12dB, 18dB
				AutoF.Mix Max Gain	----	18dB	0dB, 6dB, 12dB, 18dB
				Gain	----	Auto	Auto, 0dB, 3dB, 6dB, 9dB, 12dB, 15dB, 18dB
		AGC Max Gain	----	18dB	6dB, 12dB, 18dB		
		Picture	Picture 1/2	Chroma Level	----	0	-3 to +3
				AWB Mode	----	AWB A	ATW, AWB A, AWB B
				Detail	----	High	Off, Low, High
				Flesh Tone Mode	----	Off	Off, Low, High
				Color Matrix	----	EBU	Normal, EBU, NTSC
	Picture 2/2		Pedestal	----	0	-10 to +10	
			DRS	----	Off	Off, Low, High	
			Gamma Type	----	Normal	Off, Normal, Cinema	
			Gamma Level	----	Mid	Low, Mid, High	
			Back Light COMP.	----	----	Off, On	
	System	Genlock (AW-HE50S only)	Horizontal Phase	0		-206 to +49	
			Subcarrier Phase				
			Coarse	90°		0° to 315°	
			Fine	0		-127 to +127	
			H Phase.SC Fine Step	1		1 to 10	
		Output	Format	1080i		1080i, 720p, 480i	
			Down CONV. Mode	Squeeze		Squeeze, SideCut, LetterBox	
HDMI Color (AW-HE50H only)			YCbCr422		RGB-NOR, RGB-ENH, YCbCr422, YCbCr444		
Other		Other 1/2	Install Position	Desktop		Desktop, Hanging	
			Preset Speed	10		1 to 30	
			Preset Scope	Mode A		Mode A, Mode B, Mode C	
			Digital Zoom	Disable		Disable, Enable	
	Speed With Zoom POS.		On		Off, On		
	Focus Mode		Auto		Auto, Manual		
	Focus ADJ With PTZ.		---		Off, On		
	Other 2/2	Tally Enable	Enable		Disable, Enable		
		OSD Off With Tally	Off		Off, On		
		OSD Status	Off		Off, On		
Maintenance	Firmware Version	Wireless Control	Enable		Disable, Enable		
		CPU Software					
		Camera Main	Version shipped		----		
		Pan/Tilt	Version shipped		----		
		Network	Version shipped		----		
		PLD					
		Camera	Version shipped		----		
	Output	Version shipped		----			
	Initialize	----	CANCEL		CANCEL, OK		