

# GRAFIK 3000 SERIES



FEATURING THE  
**NEW**

GRAFIK  
integrale™


**MULTI-SCENE** PRESET LIGHTING CONTROL SYSTEM  
CONTROLS ALL MODERN LIGHT SOURCES WITHOUT INTERFACES

SMALL COMMERCIAL APPLICATIONS

RESIDENTIAL APPLICATIONS



 **LUTRON®**



ANY LIGHT SOURCE.  
ONE LIGHTING CONTROL.







# CONTENTS

## GRAFIK 3000® SERIES

1-2	New Features
3-4	GRAFIK Integrale/ The Only Lighting Control
5-6	Features/Applications
7-8	Scenes/Zones
9-10	Model Numbers/Wiring Diagrams

11-12	Expand The Possibilities
13-16	Accessory Controls
17-18	Dimensions and Mounting
19-20	Specifications
Fold out	How To Order Colours, Finishes and Engraving



## GRAFIK 3000® SERIES ■

MULTI-SCENE PRESET LIGHTING CONTROL SYSTEM

# GRAFIK 3000 SERIES HAS A POWERFUL NEW ADDITION... GRAFIK INTEGRALE™

*ALL THE FEATURES  
OF THE GRAFIK EYE® MODELS...*

GRAFIK EYE

### SET UP AND RECALL

Create lighting scenes for common activities all at the touch of a button.

### SMOOTH TRANSITIONS

Fade between lighting scenes--  
from instantly to one hour.

### EXPAND THE SYSTEM

Accessory controls allow one-touch control from any location.

### INTEGRATION

Integrates easily with touchscreens and other AV equipment.

### RTISS™ TECHNOLOGY INCLUDED

Compensates for incoming line voltage variations, frequency shifts, harmonics, and line noise.

*PLUS...*

### NEW FEATURES

GRAFIK INTEGRALE

### ONE CONTROL

Just one model provides control of all modern light sources.

### RELIABILITY

Control is able to withstand short between load hot and either neutral or earth without damage.

# THE ONLY LIGHTING CONTROL... YOU'LL EVER NEED TO SPECIFY

GRAFIK integrale™

## EASE OF PROGRAMMING

Simply adjust zone buttons to set lights to match any activity and save as a preset scene. Recall exact scenes from the same unit or matching accessory wallstation.

## EASE OF INSTALLATION

One unit controls Electronic Low Volt; Magnetic Low Voltage; Incandescent/Tungsten; 0-10V, DSI, and DALI Fluorescent loads; neon; and non-dim lighting loads.


## SOURCES




Incandescent/  
Tungsten



Electronic  
Low Voltage




Fluorescent



Magnetic  
Low Voltage



Neon



Non-Dim

C O N T R O L A N Y L I G H T S O U R C E

NO INTERFACE  
NEEDED FOR ANY  
LIGHT SOURCE



# GRAFIK 3000® SERIES ■

MULTI-SCENE PRESET LIGHTING CONTROL SYSTEM



Choice of Translucent or Opaque cover

Fade Time Buttons

Master Raise/Lower Buttons

Scene Select Buttons

All Off

Zone Intensity Buttons

Built-in Infrared Receiver

Choice of colours or metallic/metal finishes



## CHOOSE AN ACCESSORY STYLE

### CREATE THE PERFECT ENVIRONMENT

Lutron offers stylish accessory controls to enhance the beauty of any space and to control lighting from more than one location.

## WIRELESS REMOTE CONTROL

### ADD FLEXIBILITY


Includes built-in Infrared Receiver for use with optional wireless Remote Control to select scenes from anywhere in a room.

## POWER BOOSTERS

### INCREASE POWER

Increase individual zone capacities in larger spaces with Lutron Power Boosters.

# FEATURES



- One stylish control replaces multiple switches and dimmers
- Eliminate the guesswork of setting separate switches and dimmers every time
- Slowly fade between lighting scenes — eyes have time to comfortably adjust
- Add accessory wallstations to recall preset scenes from additional locations
- Add interfaces for integration with AV systems and other equipment





# APPLICATIONS

## THE GRAFIK 3000® DIFFERENCE

### HOME CINEMA

The movie cannot begin until the lights dim.

### LOUNGES

Entertain guests, spend time with family, or watch TV.

### DINING ROOM

Create the right lighting for intimate dining, family occasions, cocktail parties.

### CONFERENCE ROOM



Instantly transform a room for a general meeting, set up, AV presentation, or video conference.

### CAFÉ

Create the perfect ambience for lunch meetings, cocktail hour, elegant dinners and clean-up.

### EXECUTIVE OFFICE

Create dynamic work spaces, reduce computer screen glare, and add infrared remote dimming.



GRAFIK 3000® SERIES ■

MULTI-SCENE PRESET LIGHTING CONTROL SYSTEM

# CREATE A MOOD . . . AT THE TOUCH OF A BUTTON


ENTERTAIN SCENE




MOVIE SCENE



## RESIDENTIAL APPLICATIONS



LIGHTING ZONE LEVELS



**A ZONE** is a light or group of lights controlled by the same switch or dimmer.

With GRAFIK Eye® and GRAFIK Integrale™, each zone in a space is set at the appropriate level for the activity and saved together as one scene, retrievable later at the touch of a button.

**A SCENE** is a programmed lighting environment designed to enhance a particular activity.

## GRAFIK 3000® SERIES ■

MULTI-SCENE PRESET LIGHTING CONTROL SYSTEM

### SET THE SCENE

The secret to great lighting is being able to control it.

Match your activity or mood to your visual environment. Set the lights as you need them and the setting is automatically saved as one of your custom scenes. Retrieve it later at the touch of a button; no individual switches or dimmers to adjust again and again.


SPECIAL EVENT SCENE




ALL-ON SCENE



## COMMERCIAL APPLICATIONS



LIGHTING ZONE LEVELS





# GRAFIK 3000<sup>®</sup> SERIES

## MODEL NUMBERS



**GRAFIK Eye<sup>®</sup>/GRAFIK Integrale<sup>™</sup>** Control Units have both a maximum

power capacity limit per zone and a maximum power capacity limit per unit. Each zone cannot exceed the total Watts/VA listed below, and each unit cannot exceed the total Watts/VA outlined in the chart below. However, the maximum unit capacity can be allocated among each individual zone in the unit.

For example, on a 4-zone unit at 230V with a maximum zone capacity of 800W and a maximum unit capacity of 2300W, some zones will not reach the individual zone maximum because the total unit maximum cannot exceed 2300W. Check total unit maximums before ordering Model Nos.

### SYSTEM CAPABILITIES

*Link up to 8 Control Units for up to 32 zones of control (Grafik Integrale) and 48 zones of control (Grafik Eye)*

*16 programmable scenes plus Off per Control Unit, 128 scenes plus Off per system*

*Maximum of 16 accessory Wallstations per system*

	MODEL NO.	NO. OF ZONES	WALLBOX SIZE*	MAXIMUM WATTS	
				230V (-CE)	120V**
<b>GRAFIK Integrale- Available Model For All Sources</b>	<b>GXI-3104-</b>	<b>4</b>	<b>200mm X 95mm</b>	<b>2300</b>	<b>-</b>
<b>GRAFIK Eye - Available Models For Incandescent Only</b>	<i>GRX-3102- GRX-3502-</i>	<i>2</i>	<i>200mm X 95mm</i>	<i>1600</i>	<i>1200</i>
	<i>GRX-3103- GRX-3503-</i>	<i>3</i>	<i>200mm X 95mm</i>	<i>2300</i>	<i>1500</i>
	<i>GRX-3104- GRX-3504-</i>	<i>4</i>	<i>200mm X 95mm</i>	<i>2300</i>	<i>2000</i>
	<i>GRX-3106- GRX-3506-</i>	<i>6</i>	<i>200mm X 95mm</i>	<i>2300</i>	<i>2000</i>

#### Individual Zone Maximums

Voltage	Zone Capacity
230V	3.5A/800W/VA <sup>†</sup>
120V	6.7A/800W/VA

\* Mount in Lutron multiple gang wallbox, 70mm (2.75") deep minimum, 89mm (3.5") deep recommended. Supplied with product.

\*\* For 120V applications, Control Unit dimensions are: 2 zone unit- 123mm (4.9375") x 46mm (1.8125")  
3 zone unit- 168mm (6.6875") x 92mm (3.625")  
4 zone unit- 208mm (8.3125") x 138mm (5.4375")

<sup>†</sup> 20 Ballast Maximum for fluorescent loads




**GRAFIK EYE  
3500 MODELS**

Offer the precision of setting light levels in 1% increments and can be programmed at the Control Unit or from a PC or laptop with Lutron's Liaison<sup>™</sup> Software


# GRAFIK 3000® SERIES

## WIRING DIAGRAMS


### CONTROL UNIT WIRING




### POWER BOOSTER AND INTERFACE WIRING



### GRX-TVI(0-10V) BOOSTER WIRING



### SYSTEM WIRING



# EXPAND THE POSSIBILITIES OF YOUR SYSTEM



Ceiling-Mounted Photosensor

## DAYLIGHT CONTROL/ ENERGY SAVINGS

Select preset scenes automatically in response to ambient daylight to achieve optimal light levels and energy savings. Best suited for areas with large windows or skylights, such as atriums, perimeter office spaces, malls, and classrooms.



Infrared Remote Control

## WIRELESS CONTROL

Add control flexibility in a space from an Infrared Wireless Remote Control. Ideal for lecture halls, conference rooms, and home cinemas.



RS232 Interface

## TOUCHSCREEN/ CENTRALIZED CONTROL

Integrate GRAFIK 3000 Series with user-supplied PC or digital AV equipment for seamless one-touch control. Select preset light scenes, dim or brighten lights, monitor system status, and receive button feedback. Ideal for conference rooms, home cinemas and video conferencing rooms.



DMX512 Interface

## DMX INTEGRATION

Control DMX, fiber optic, and LED fixtures when these fixtures are incorporated in an architectural lighting plan.







## GRAFIK 3000® SERIES ■

MULTI-SCENE PRESET LIGHTING CONTROL SYSTEM



seeTouch™ Wallstation

### BACK LIT, ENGRAVED WALLSTATIONS

Large buttons and a variety of engraving options—including backlit characters—in Lutron's seeTouch™ series of controls offers easy-to-use functionality and additional control points in a space. Ideal for darkened rooms such as AV presentation rooms and home cinemas.



PRG Interface

### TIME SCHEDULING

Turn lights on and off automatically based on a user-defined schedule. Base events on time-of-day or on sunrise and sunset. Ideal for office spaces, restaurants, retail spaces, and hotels.



AV Interface

### SEQUENCING

Create dynamic lighting effects by continuously cycling preset lighting scenes automatically. Ideal for retail displays, store front windows, landscape lighting, artwork lighting, and museum exhibit lighting.







Partition Control

### PARTITIONING






Adapt lighting controls to coordinate with the status of moveable partition walls. Operate controls in each "room" independently when walls are closed or together when walls are open. Ideal for hotels, convention centers, ballrooms, and meeting rooms.



# ACCESSORY CONTROLS

	DESCRIPTION	FUNCTIONS
	<p><b>GRX-IT, GRX-8IT*</b> Handheld Infrared Wireless Remote Control Transmitters</p>	<p>Controls 4 (or 8) scenes plus master raise/lower and Off. Recalls scenes or fine tunes light levels. Turns lights on or off. <b>Note: Not included in 16 accessory maximum.</b></p>
	<p><b>NTGRX-2B-SL</b> Two-Button Entrance Control</p> <p><b>EGRX-2B-SL</b> European-style Two-Button Entrance Control</p>	<p>Turns lights (scene 1) On or Off. Selects 2 scenes (either 1/Off, 9/10 or 13/14), partition opened/closed, panic station, sequencing, or raise/lower.</p>
	<p><b>NTGRX-4S, NTGRX-4S-IR, NTGRX-4B</b> Scene Selection Control with and without Infrared Receiver; Four-Button Control</p>	<p>Activates 4 scenes; master raise/lower and Off. Recalls or fine tunes light levels. Activates scenes 1-4, 5-8, 9-12, or 13-16; operates one or more GRAFIK Eye/GRAFIK Integrale Control Units. Scenes can be activated via infrared transmitter (on NTGRX-4S-IR only).</p>
	<p><b>EGRX-4S, EGRX-4S-IR</b> European-style Scene Selection Control with and without Infrared Receiver</p>	<p>Activates 4 scenes; master raise/lower and Off (-4S and -4S-IR only). Recalls or fine tunes light levels. Activates scenes 1-4, 5-8, 9-12, or 13-16; operates one or more GRAFIK Eye/GRAFIK Integrale Control Units. Scenes can be activated via infrared transmitter (on EGRX-4S-IR only).</p>

\* All GRAFIK Eye/GRAFIK Integrale Control Units are equipped with an IR Receiver for use with Lutron GRX-IT and GRX-8IT handheld remote controls. The IR frequency for all Control Units is 40KHz. Any other device continuously operating in the frequency range from 30KHz to 50KHz may cause either no response or unwanted scene changes on the Control Unit.

FUNCTIONS	DESCRIPTION	
<p>Wallstations with large, rounded buttons and easy-to-read backlit engraving option; IR models available; available in one- to seven-button configurations.</p>	<p><b>SG-2B-WH-</b>_, <b>SG-4SN-WH-</b>_ seeTouch™ Scene Selection Controls</p>	
<p>Activates scenes 1-4; master raise/lower and Off. Recalls or fine tunes light levels. Ideal for door jambs. Operates one or more GRAFIK Eye/GRAFIK Integrale Control Units. For Architrave with clear finish option, order GRX-4S-DW-ACR-WH.</p>	<p><b>GRX-4S-DW</b> Architrave™ Door Jamb Control, Wide</p>	
<p>NTGRX-4M activates scene 1 or Off for up to eight GRAFIK Eye/GRAFIK Integrale Control Units, and all On or all Off. NTGRX-4PS provides 4 buttons to operate selected GRAFIK Eye/GRAFIK Integrale Control Units independently, or in combination to reflect partition status.</p>	<p><b>NTGRX-4M, NTGRX-4PS</b> Master Control; Partition Control</p>	
<p>Provides access to scenes 1-4 or 5-8 based on external contact closure (example: to control partitioned spaces).</p>	<p><b>NTGRX-SI4S-IR</b> Infrared Receiver/Scene Control/Switch Interface</p>	
<p>Recalls preset light levels for eight scenes (1-8, 5-12, 9-16, or 13-4) plus Off; fine-tuning of light levels with master raise/lower buttons; operates one or more GRAFIK Eye/GRAFIK Integrale Control Units; scenes can be activated via infrared transmitter (on EGRX-8S-IR only).</p>	<p><b>EGRX-8S-</b>, <b>EGRX-8S-IR</b> European-style, 8-Scene Selection Control, with and without Infrared Receiver</p>	



	DESCRIPTION	FUNCTIONS
	<p><b>GRX-KP5</b> 5-Button Scene Selection Control with Slim Buttons</p>	<p>Recalls preset light levels for 4 scenes (1-4 or 6-9) plus Off with fine-tuning or 5 scenes (1-5 or 6-10) plus Off with Full On (Scene 16); amber status LEDs standard.</p>
	<p><b>GRX-KP-10</b> 10-Button Scene Selection Control with Slim Buttons</p>	<p>Recalls preset light levels for 9 scenes (1-9 or 6-14) plus Off with fine-tuning or 10 scenes (1-10 or 6-15) plus Off with Full On (Scene 16); amber status LEDs standard.</p>
	<p><b>GRX-KP-15</b> 15-Button Scene Selection Control with Slim Buttons</p>	<p>Recalls preset light levels for scenes 1-14 plus Off with fine-tuning or scenes 1-15 plus Off with Full On (Scene 16); amber status LEDs standard.</p>
	<p><b>GRX-LB6</b> 6-Button Scene Selection Control with Large Buttons</p>	<p>Recalls preset light levels for 3 scenes (1-3 or 9-11) plus Off with fine-tuning of light levels or 5 scenes (1-5 or 9-13) plus Off; amber status LEDs standard.</p>
	<p><b>GRX-LB9</b> 9-Button Scene Selection Control with Large Buttons</p>	<p>Recalls preset light levels for 6 scenes (1-6 or 9-14) plus Off with fine-tuning of light levels or 8 scenes (1-8 or 9-16) plus Off; amber status LEDs standard.</p>



## CONTROL UNIT

For a specific Model No. in the Grafik Eye (GRX) Series, place a 1 or 5 in the blank space, i.e. GRX-3104.

MODEL NO.	A	B
GXI-3104	208mm (8.3125")	138mm (5.4375")
GRX-3_02†	208mm (8.3125")	138mm (5.4375")
GRX-3_03†	208mm (8.3125")	138mm (5.4375")
GRX-3_04	208mm (8.3125")	138mm (5.4375")
GRX-3_06	208mm (8.3125")	138mm (5.4375")
GRX-DACPI	208mm (8.3125")	138mm (5.4375")

† For 120V applications, Control Unit dimensions are:  
 2 zone unit– 123mm (4.9375") x 46mm (1.8125")  
 3 zone unit– 168mm (6.6875") x 92mm (3.625")  
 4 zone unit– 208mm (8.3125") x 138mm (5.4375")

\* For faceplate width size add 16mm (5/8") to dimension A.

### Main Control Unit

**GXI-3104**—Mounts in U.S. four-gang wallbox (200mm X 95mm) 70mm (2.75") deep minimum, 89mm (3.5") deep recommended.


**GRX-3000**—Mounts in U.S. 4-gang wallbox (200mm X 95mm), 70mm (2.75") deep minimum, 89mm (3.5") deep recommended.

### Automatic Daylight Control (GRX-DACPI)

Mount in Lutron-supplied wallbox.

### Spacing Requirements

If multiple GRAFIK Eye/GRAFIK Integrale Control Units and/or Power Boosters are mounted one above the other, a space of 12cm (4.5") minimum must be allowed between the faceplates. If mounted in an electrical enclosure, consult Lutron.



# DIMENSIONS AND


## ACCESSORIES

FIG.	MODEL NO.	A	B	C	D
1	EGRX-4S-IR, -4S, -2B-SL, -8S-IR, -8S	86mm (3.38")	86mm (3.38")	13mm (.5")	10mm (.375")
2	NTGRX-2B-SL NTGRX-4S, -4B, -4SIR NTGRX-4M NTGRX-4PS	70mm (2.75")	116mm (4.5625")	8mm (.3125")	29mm (1.13")
3	seeTouch™ Wallstations	70mm (2.75")	116mm (4.5625")	7.6mm (.30")	36mm (1.39")
4	GRX-LB6 GRX-KP5 GRX-KP10	70mm (2.75")	114mm (4.50")	9mm (0.35")	29mm (1.16")
5	GRX-KP15 GRX-LB9	114mm (4.50")	114mm (4.50")	9mm (0.35")	29mm (1.16")
6	GRX-4S-DW	44mm (1.75")	114mm (4.5")	6mm (.25")	35mm (1.375")
7	GRX-4S-DN	38mm (1.50")	131mm (5.16")	3mm (0.13")	31mm (1.19")
8	NGRX-PB GRX-FDBI/ELVI	116mm (4.5625")	116mm (4.5625")	17mm (.6875")	48mm (1.875")
9	GRX-AV, GRX-RS232, GRX-PRG	127mm (5")	197mm (7.75")	64mm (2.5")	—

## MOUNTING NOTES:


- (1) Mounts in U.S. single-gang wallbox 70mm (2.75") deep minimum, 89mm (3.5") deep recommended (Lutron Part No. SB-1G).
- (2) Lutron supplies backbox (Part No. 241-399).
- (3) Mounts on U.S. 102 x 102mm (4"x4") junction box (Lutron Part No. 241-496).
- (4) Mounts in U.S. two-gang wallbox; 70mm (2.75") deep minimum, 89mm (3.5") deep recommended. (Two each of Lutron Part No. SB-1G).

FIG. 1




**European-style Wallstation (EGRX-4S-IR shown)**  
Mount in single-gang UK/German wallbox.

FIG. 5




**2-gang Scene Selection Control with Large or Slim Buttons (GRX-LB9 shown)**  
Mount in U.S. wallbox. (4)

FIG. 2



**Single-gang Scene Selection Control (NTGRX-4S shown)**  
Mount in U.S. wallbox. (1)


FIG. 6



**Architrave Door Jamb Control-Wide (GRX-4S-DW)**  
Mounts directly in door jamb. (2)


# MOUNTING

FIG. 7




**Architrave Door Jamb Control-Narrow (GRX-4S-DN)**  
Mounts directly in door jamb. (2)

FIG. 3




**seeTouch (SG-4SN-WH- shown)**  
Mount in U.S. wallbox. (1)

FIG. 8




**Power Booster (NGRX-PB, NGRX-ELVI)**  
Mount in U.S. wallbox. (4)

FIG. 4



**Single-gang Scene Selection Control with Large or Slim Buttons (GRX-LB6 shown)**  
Mount in U.S. wallbox. (1)

FIG. 9



**Interface Control (GRX-AV, -PRG, -RS232)**  
Mounts on 102mm (4")-square utility box. (3)

SEE INSTRUCTION SHEETS FOR DETAILS



# GRAFIK 3000® SERIES SPECIFICATIONS



## GENERAL SPECIFICATIONS


- The entire lighting control system shall be CE, U.L., or CSA marked as appropriate. Manufacturer shall maintain ISO 9001 certification. Dimming system shall be covered by a minimum one-year warranty from time of purchase.
- Manufacturer shall be capable of providing on-site service support as required.
- Premium Temperature Margins: Panels operate at a minimum of 20 degrees Celsius below the power conducting component temperature rating. Electronic components live twice as long for every 10 degrees Celsius below the rating at which they operate both increasing semiconductor reliability and ensuring the system's design life span.

## KEY PERFORMANCE FEATURES FOR SYSTEM COMPONENTS



LUTRON Quality Systems Registered to ISO 9001 • Safety standards listed above apply to one or more products in the GRAFIK 3000® product line.



<b>WHITE</b>	<b>WH</b>	
<b>BEIGE</b>	<b>BE</b>	
<b>IVORY</b>	<b>IV</b>	
<b>GRAY</b>	<b>GR</b>	
<b>BROWN</b>	<b>BR</b>	
<b>BLACK</b>	<b>BL</b>	
<b>SATIN BRASS</b>	<b>SB</b>	
<b>BRIGHT BRASS</b>	<b>BB</b>	
<b>ANTIQUÉ BRASS</b>	<b>QB</b>	
<b>ANTIQUÉ BRONZE</b>	<b>QZ</b>	
<b>BRIGHT CHROME</b>	<b>BC</b>	
<b>SATIN CHROME</b>	<b>SC</b>	
<b>SATIN NICKEL</b>	<b>SN</b>	
<b>BRIGHT NICKEL</b>	<b>BN</b>	
<b>CLEAR ANODIZED ALUMINUM</b>	<b>CLA</b>	
<b>BLACK ANODIZED ALUMINUM</b>	<b>BLA</b>	
<b>BRASS ANODIZED ALUMINUM</b>	<b>BRA</b>	

*Due to printing limitations, colour swatches may not be exact.*

# HOW TO ORDER COLOURS, FINISHES AND ENGRAVING



Choice of translucent or opaque cover.

Engrave scene name beneath each button, i.e. Room Setup, General Meeting, A/V Presentation, etc.

Your company name or logo here.

Choice of six distinct colours and three metallic/metal finishes.

\* Example: Model GRX-3104-T-BC shown above

When ordering a GRAFIK Eye® or Grafik Integrale™ Control Unit, add the appropriate code suffix to all model numbers for colour choice and global power requirements.

The Control Unit Cover can be specified as either (T) for Translucent Black or (A) for Opaque to match the colour of the Control Unit base. (Note: When specifying the cover as Opaque, the LEDs cannot be viewed through the front cover.)

All 230V GRAFIK Eye/GRAFIK Integrale model numbers require that the code CE be added as the suffix.

For example, when ordering a four-zone GRAFIK Integrale Control Unit with a Satin Nickel finish and a translucent cover in 230V, order GXI-3104-T-CE-SN.

When ordering a GRAFIK Eye 120V 6-zone Control Unit with a Opaque Cover (A) to match a White base (WH), the model number would be GRX-3104-A-WH.

*Consult your Lutron representative for help in ordering custom finishes and engraving options.*

Engraving is available in the following typestyles:

**HELVETICA BOLD**  
**ROMAN BLOCK**  
GOTHIC

Engraving is available in the following colours:

White, Beige, Black, Brown, Gray





## WORLDWIDE HEADQUARTERS

Lutron Electronics Co., Inc.  
7200 Suter Road  
Coopersburg, PA 18036-1299  
USA  
Toll-free: 1 888 LUTRON1  
TEL: +1 610 282 3800  
FAX: +1 610 282 1243  
intsales@lutron.com

## EUROPEAN HEADQUARTERS

Lutron EA Ltd.  
6 Sovereign Close  
London, E1W 3JF  
UK  
FREEPHONE: 0800 282 107  
TEL: +44 (0)20 7702 0657  
FAX: +44 (0)20 7480 6899  
lutronlondon@lutron.com

## ASIAN HEADQUARTERS

Lutron GL Ltd.  
#07-03 Tower Fifteen  
15 Hoe Chiang Road  
Singapore 089316  
TEL: +65 6220 4666  
FAX: +65 6220 4333  
lutronsea@lutron.com

## INTERNATIONAL OFFICES

*Brazil: São Paulo*  
TEL: +55 11 4327 3800

*China: Beijing*  
TEL: +86 10 5877 1818

*China: Hong Kong*  
TEL: +852 2104 7733

*China: Shanghai*  
TEL: +86 21 6288 1473

*France: Paris*  
TEL: +33 1 56 59 16 64

*Germany: Berlin*  
TEL: +49 (0)30 971045-90

*India: Bangalore*  
TEL: +91 80 4030 0485

*India: Mumbai*  
TEL: +91 22 4070 0867

*India: Delhi*  
TEL: +91 124 471 1900

*Italy: Milan*  
FREEPHONE: 800 979 208

*Japan: Minato-ku*  
TEL: +81 3 5575 8411

*Spain: Barcelona*  
TEL: +34 93 496 57 42

*Spain: Madrid*  
TEL: +34 91 567 84 79

*UAE: Dubai*  
TEL: +971 4 299 1224

## SERVICE AND SUPPORT

Lighting control application engineers are available 24 hours/7 days a week to assist you. For help with application, layout, or installation, call the Lutron office near you.

Lutron's STAR Program provides the assurance that every Lutron product and system is backed by Lutron's commitment to quality, service and performance. Ask about Lutron's 8-year Replacement Parts Program.



[www.lutron.com/europe](http://www.lutron.com/europe)

