


Access Control Power Supply

EAP-5D1Q 1 Output, 5A@12VDC, 2.5A@24VDC

EAP-5D1MQ PC Board only from EAP-5D1Q



Dimensions: 12-3/16" x 12-7/16" x 3-9/16"

Features:

- ▶ AC power failure supervision relay.
- ▶ Battery failure supervision relay.
- ▶ Selectable 2.2K-Ohm End-of-Line (EOL) resistor for AC failure and battery failure supervision relays.
- ▶ Selectable delay timer (5 sec., 5 min., 5 hours) for AC failure supervision relay.
- ▶ LED overload indicator and automatic shutdown for short-circuit protection.
- ▶ Fuse-protected AC input.
- ▶ Built-in back-up battery charger
- ▶ Automatically switch to back-up battery if AC fails.
- ▶ Individual AC input and DC output LED status indicators.


Power

- ▶ Field selectable for 12VDC or 24VDC output.
- ▶ Operating input voltage 110~240 VAC.
- ▶ Adjustable voltage range (11~15 VDC, 23~26 VDC) to compensate for voltage drop.
- ▶ Supply current: 5 Amps @ 12VDC, 2.5 Amps @ 24VDC.
- ▶ AC input fuse rating 3.15 Amps (glass fuse).
- ▶ DC output overload sensing with red LED indicator and automatic shutdown during short circuit.

Enclosure

- ▶ Heavy-duty steel case to protect the power connections.
- ▶ Removable steel cover for easy access.
- ▶ Ventilation holes to prevent heat build-up.
- ▶ Enclosure has enough room for two 7AH batteries.
- ▶ 6-foot power cord and battery leads included.
- ▶ Dimensions: 12-3/16" x 12-7/16" x 3-9/16".
- ▶ Knock-out on the cover for optional cam lock.

Connections:



Copyright 2009 SECO-LARM U.S.A., Inc. All rights reserved.

The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.