








<h1 style="text-align: center;">Hello</h1> <p style="text-align: center;">1mi B03 Bluetooth Transmitter and Receiver 2-in-1 User Guide</p>	<p><b>Contents</b></p> <ul style="list-style-type: none"> <li>1. Product Specifications ..... 2</li> <li>2. Package Contents ..... 4</li> <li>3. Product Overview &amp; Control Functions ..... 5</li> <li>4. LED indicators ..... 7</li> <li>5. Use as a transmitter (TX mode) Installation diagram ..... 9</li> <li>6. Use as a Receiver (RX mode) Installation diagram ..... 11</li> <li>7. Bypass mode (Non-Bluetooth) Installation diagram ..... 13</li> <li>8. Pair and Connect two Devices Simultaneously ..... 15</li> <li>9. Restore Factory Default Settings ..... 16</li> <li>10. Troubleshooting ..... 16</li> <li>11. Warnings ..... 17</li> <li>12. Disposal ..... 17</li> <li>13. FCC Notice ..... 18</li> </ul> <p style="text-align: center;">- 1 -</p>	<p><b>1. Product Specifications</b></p> <p>1mi B03 is a wireless long range audio transmitter &amp; receiver incorporating the latest "AptX low-latency" technology for CD-quality sound with virtually no delay. Multifunctional, supporting optical, bypass and voice prompts. Providing the best solution to enable your TV or home audio system to wirelessly stream hi-fi audio directly to any wireless headphones or speakers.</p> <ul style="list-style-type: none"> <li>• BT version: 4.2</li> <li>• Supports profiles: A2DP, AVRCP</li> <li>• Audio codec: AptX, AptX LL, SBC</li> <li>• Operational range: Class I, up to 70 meters</li> <li>• Input voltage/ current: Micro USB DC5.0V/500mA</li> <li>• Operating temperature: -10°C ~ 45°C</li> <li>• Storage temperature: 20°C ~ 60°C</li> <li>• Support sampling rate in optical mode: 548KHz</li> <li>• Product size: 126*94*29mm</li> <li>• Product weight: 124g</li> </ul> <p style="text-align: center;">- 2 -</p>	<p><b>aptX® Low Latency</b></p> <p>To take advantage of the better performance of the aptX Low Latency Codec, the other side device must support the same codec. If the other side device only supports the normal aptX codec, or the SBC one, those codecs will be used instead.</p> <p><b>Audio delay when paired with different headphones/receiver:</b></p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th>Headphones/receiver support</th> <th>The audio delay will be</th> </tr> </thead> <tbody> <tr> <td>aptX Low Latency codec</td> <td>~ 40ms</td> </tr> <tr> <td>aptX codec</td> <td>~ 70ms</td> </tr> <tr> <td>SBC codec (most standard Bluetooth audio)</td> <td>~ 220ms</td> </tr> </tbody> </table> <p style="text-align: center;">- 3 -</p>	Headphones/receiver support	The audio delay will be	aptX Low Latency codec	~ 40ms	aptX codec	~ 70ms	SBC codec (most standard Bluetooth audio)	~ 220ms																				
Headphones/receiver support	The audio delay will be																														
aptX Low Latency codec	~ 40ms																														
aptX codec	~ 70ms																														
SBC codec (most standard Bluetooth audio)	~ 220ms																														
<p><b>2. Package Contents:</b></p> <ul style="list-style-type: none"> <li>A. 1mi B03 Hi-Fi Bluetooth Transceiver</li> <li>B. Power adapter</li> <li>C. 5V Power Cable</li> <li>D. Optical cable</li> <li>E. 3.5mm audio cable</li> <li>F. 3.5mm female to RCA male cable</li> <li>G. User manual</li> <li>H. Quick User Guide</li> </ul>  <p style="text-align: center;">- 4 -</p>	<p><b>3. Product Overview &amp; Control Functions</b></p>  <p style="text-align: center;">- 5 -</p>	<table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th>Button</th> <th>Function</th> <th>Operation</th> </tr> </thead> <tbody> <tr> <td rowspan="2">Power switch</td> <td>Power on</td> <td>Slide to "ON" to turn on the device.</td> </tr> <tr> <td>Power off</td> <td>Slide to "OFF" to turn off the device.</td> </tr> <tr> <td rowspan="3">Mode switch</td> <td>Transmitter mode</td> <td>Slide to TX to enter transmitting mode.</td> </tr> <tr> <td>Receiver mode</td> <td>Slide to RX to enter receiving mode.</td> </tr> <tr> <td>Bypass mode</td> <td>Slide to "Bypass" to enter Bypass mode.</td> </tr> <tr> <td rowspan="2">Enter pairing mode</td> <td>Enter pairing mode</td> <td>Hold this button for about 3 seconds.</td> </tr> <tr> <td>Reconnect</td> <td>Short press once.</td> </tr> <tr> <td rowspan="2">Optical / AUX switch</td> <td>Optical / AUX switch</td> <td>Short press once to switch between AUX (3.5mm) and Optical audio mode.</td> </tr> <tr> <td>Volume down/ Previous song</td> <td>In AUX audio mode, short press once (TX mode doesn't support).</td> </tr> <tr> <td rowspan="2">Volume up/ Next song</td> <td>Volume up/ Next song</td> <td>In AUX audio mode, short press once (TX mode doesn't support).</td> </tr> </tbody> </table> <p style="text-align: center;">- 6 -</p>	Button	Function	Operation	Power switch	Power on	Slide to "ON" to turn on the device.	Power off	Slide to "OFF" to turn off the device.	Mode switch	Transmitter mode	Slide to TX to enter transmitting mode.	Receiver mode	Slide to RX to enter receiving mode.	Bypass mode	Slide to "Bypass" to enter Bypass mode.	Enter pairing mode	Enter pairing mode	Hold this button for about 3 seconds.	Reconnect	Short press once.	Optical / AUX switch	Optical / AUX switch	Short press once to switch between AUX (3.5mm) and Optical audio mode.	Volume down/ Previous song	In AUX audio mode, short press once (TX mode doesn't support).	Volume up/ Next song	Volume up/ Next song	In AUX audio mode, short press once (TX mode doesn't support).	<p><b>4. LED indications</b></p>  <p style="text-align: center;">- 7 -</p>
Button	Function	Operation																													
Power switch	Power on	Slide to "ON" to turn on the device.																													
	Power off	Slide to "OFF" to turn off the device.																													
Mode switch	Transmitter mode	Slide to TX to enter transmitting mode.																													
	Receiver mode	Slide to RX to enter receiving mode.																													
	Bypass mode	Slide to "Bypass" to enter Bypass mode.																													
Enter pairing mode	Enter pairing mode	Hold this button for about 3 seconds.																													
	Reconnect	Short press once.																													
Optical / AUX switch	Optical / AUX switch	Short press once to switch between AUX (3.5mm) and Optical audio mode.																													
	Volume down/ Previous song	In AUX audio mode, short press once (TX mode doesn't support).																													
Volume up/ Next song	Volume up/ Next song	In AUX audio mode, short press once (TX mode doesn't support).																													
	<table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th>Indicator</th> <th>Status</th> </tr> </thead> <tbody> <tr> <td>RX</td> <td>In receiving mode Flashes Blue and Red alternately to indicate 1mi B03 is in pairing mode</td> </tr> <tr> <td>TX</td> <td>In transmitting mode Flashes Blue and Red alternately to indicate 1mi B03 is in pairing mode</td> </tr> <tr> <td>Bypass</td> <td>Bypass mode</td> </tr> <tr> <td>OPT</td> <td>Optical audio mode</td> </tr> <tr> <td>AUX</td> <td>AUX audio mode</td> </tr> </tbody> </table> <p style="text-align: center;">- 8 -</p>	Indicator	Status	RX	In receiving mode Flashes Blue and Red alternately to indicate 1mi B03 is in pairing mode	TX	In transmitting mode Flashes Blue and Red alternately to indicate 1mi B03 is in pairing mode	Bypass	Bypass mode	OPT	Optical audio mode	AUX	AUX audio mode	<p><b>5. Use as a transmitter (TX mode) Installation diagram</b></p>  <p style="text-align: center;">- 9 -</p>	<ol style="list-style-type: none"> <li>1) Connect audio source (TV, DVD etc.) to 1mi B03 "From TV" port with the audio cables provided (optical or AUX/RCA).</li> <li>2) Connect 1mi B03 to a power source (TV, PC USB socket or power adapter) with a USB cable.</li> <li>3) Slide Power switch to the "ON" position.</li> <li>4) Slide Mode switch to the "TX" position.</li> <li>5) Select the correct audio input mode (AUX/OPT) by short pressing the button (Very Important)</li> <li>6) Pairing : Pair 1mi B03 with your Bluetooth-enabled headphones/speakers.       <ul style="list-style-type: none"> <li>• Set 1mi B03 into pairing mode, TX LED flash Blue / Red alternately fast.</li> <li>• First-time use: 1mi B03 will auto enter pairing mode (with clear memory).</li> <li>• Afterward: press button for 3 seconds.</li> <li>• Set your headphones/speakers to pairing mode refer to its user manual.</li> <li>• Wait until connected (For quick pairing, better keep them within 1 meter when pairing)</li> </ul> </li> </ol> <p style="text-align: center;">- 10 -</p>	<p><b>6. Use as a Receiver (RX mode) Installation diagram</b></p>  <p style="text-align: center;">- 11 -</p>															
Indicator	Status																														
RX	In receiving mode Flashes Blue and Red alternately to indicate 1mi B03 is in pairing mode																														
TX	In transmitting mode Flashes Blue and Red alternately to indicate 1mi B03 is in pairing mode																														
Bypass	Bypass mode																														
OPT	Optical audio mode																														
AUX	AUX audio mode																														
<ol style="list-style-type: none"> <li>1) Connect your speaker to 1mi B03 "To Speaker" port with the audio cable provided (optical or AUX/RCA).</li> <li>2) Connect 1mi B03 to a power source with USB cable and adapter.</li> <li>3) Slide Power switch to the "ON" position.</li> <li>4) Slide Mode switch to the "RX" position.</li> <li>5) Select the correct audio input mode (AUX/OPT) by short pressing the button (Very Important)</li> <li>6) Pairing : Pair 1mi B03 with your Bluetooth-enabled phone/PC/tablet.       <ul style="list-style-type: none"> <li>• Set 1mi B03 into pairing mode, RX LED flash Blue / Red alternately fast.</li> <li>• First-time use: 1mi B03 will auto enter pairing mode (with clear memory).</li> <li>• Afterward: press button for 3 seconds to enter.</li> <li>• Active Bluetooth on your phone or another device to find "1mi B03" to connect.</li> <li>• Wait and connected (For quick pairing, better keep them within 1 meter when pairing)</li> </ul> </li> <li>• NFC enabled phones can connect this device easily with Near Field Communication (NFC) function.</li> </ol> <p style="text-align: center;">- 12 -</p>	<p><b>7. Bypass mode (Non-Bluetooth) Installation diagram</b></p>  <p style="text-align: center;">- 13 -</p>	<p>Bypassing means using 1mi B03 as a non-Bluetooth device which connects the TV and speaker via wires directly. This design enables you to switch between wired (bypass mode) and wireless (Bluetooth mode) with just one switch without the need to disconnect any cables.</p> <ol style="list-style-type: none"> <li>1) Connect audio source (TV, DVD etc.) to 1mi B03 "From TV" port with the audio cables provided (optical or AUX/ RCA).</li> <li>2) Connect your speaker to 1mi B03 "To Speaker" port with your own audio cable (optical or AUX/RCA).</li> <li>3) Connect 1mi B03 to a power source with USB cable and adapter.</li> <li>4) Slide Power switch to the "ON" position.</li> <li>5) Slide the Mode switch to the "Bypass" position.</li> <li>6) Press the button (OPT/AUX) to choose the right connection from 4 modes.       <ul style="list-style-type: none"> <li>• Aux in/Aux out: Aux LED on.</li> <li>• Opt in/Opt out: Opt LED on.</li> <li>• Aux in/Opt out: Aux LED on first and then Opt LED on.</li> <li>• Opt in/Aux out: Opt LED on first and then Aux LED on.</li> </ul> </li> <li>7) Ready for use.</li> </ol> <p style="text-align: center;">- 14 -</p>	<p><b>8. Pair and Connect two Devices Simultaneously</b></p> <p><b>In TX mode</b></p> <ol style="list-style-type: none"> <li>1) Pair with the first device by following the previous instructions in the "Use as a Transmitter (TX mode)" section.</li> <li>2) Pair with the second device       <ul style="list-style-type: none"> <li>• Set second headphones/speaker to pairing mode.</li> <li>• Set 1mi B03 to pairing mode again, press the button for 3s until the TX LED flashes Blue and Red.</li> <li>• Wait until connected.</li> </ul> </li> </ol> <p><b>In RX mode</b></p> <ol style="list-style-type: none"> <li>1) Pair with the first device by following the previous instructions in the "Use as a Receiver (RX mode)" section.</li> <li>2) Pair with the second device       <ul style="list-style-type: none"> <li>• Set 1mi B03 to pairing mode again, press the button for 3s until the RX LED flashes Blue and Red.</li> <li>• Active Bluetooth on the second device to find "1mi B03" to connect.</li> <li>• Wait until connected.</li> </ul> </li> </ol> <p><b>Note:</b> Only one device can play music at any time. You must stop the music on one device to play on the other.</p> <p style="text-align: center;">- 15 -</p>																												
<p><b>9. Restore Factory Default Settings</b></p> <p>You may need to reset 1mi B03 if it is not working as expected. When 1mi B03 is reset to factory default settings, all the paired device information will be cleared.</p> <ul style="list-style-type: none"> <li>• Press and hold the buttons S5 until the RX/TX LED flashes Blue and Red.</li> </ul> <p><b>10. Troubleshooting</b></p> <p>1) I am having trouble pairing and connecting to my Bluetooth device. Please check the following:</p> <ol style="list-style-type: none"> <li>1. Your wireless device supports the wireless profiles listed in the specifications.</li> <li>2. 1mi B03 and your device are next to each other or within 3 feet / 1 meter.</li> <li>3. Make sure both 1mi B03 and the wireless device are in pairing mode.</li> </ol> <p>2) After connecting and pairing with my wireless device, I cannot hear any music from my sound system.</p> <ol style="list-style-type: none"> <li>1. Make sure you select the correct audio input mode (AUX/OPT) by short pressing the button.</li> <li>2. Make sure to remove the protective head on optical cable.</li> <li>3. In optical mode, 1mi B03 support device with sampling rate under 48kHz.</li> </ol> <p style="text-align: center;">- 16 -</p>	<p><b>11. Warnings</b></p> <p>Warranty service is limited to normal use. Any man-made damages such as from connecting to an unsuitable power source, using an unsuitable device, or not following the instructions, as well as damages that did not occur during shipping, repairs and adjustments not approved by the company, damages from misuse, installation, or improper installation may cause the warranty to be ineffective immediately. This warranty does not include shipping fees.</p> <p><b>12. Disposal</b></p> <p>Always dispose of the used appliance at a recycling centre. Do not dispose the used appliance together with household waste.</p> <p style="text-align: center;">- 17 -</p>	<p><b>13. FCC Notice</b></p> <p>This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:</p> <p>(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.</p> <p><b>NOTE 1:</b> This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If the equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:</p> <ul style="list-style-type: none"> <li>- Reorient or relocate the receiving antenna.</li> <li>- Increase the separation between the equipment and receiver.</li> <li>- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.</li> <li>- Consult the dealer or an experienced radio/TV technician for help.</li> </ul> <p><b>NOTE 2:</b> Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.</p> <p style="text-align: center;">- 18 -</p>	<p>803</p>  <p><b>Global customer services:</b></p> <p><b>North America:</b> E-Mail: Support@1mi.com (80) Support@csk@1mi.com (CA)</p> <p><b>Europe:</b> E-Mail: Support@uk@1mi.com (UK) Support@de@1mi.com (DE) Support@fr@1mi.com (FR) Support@es@1mi.com (ES) Support@it@1mi.com (IT)</p> <p><b>Asia:</b> E-Mail: Support@jp@1mi.com (JP)</p> <p><b>MANUFACTURER</b> Shenzhen 1mi Technology Co., Ltd Address: #102, Building Zhongshan Industrial Park, Nantou, Baoan, Shenzhen, China. FCC ID: 2AUR37727 CE R04 RoHS WEEE RECYCLE</p>																												

**FCC Warning**

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE 1: Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.