
简体中文

产品使用手册 «

适用于任何智能手机的无线便携式音箱,平板电脑,MP3播放器, 有蓝牙功能的PC或MAC

简体中文 目录 ≫

使用前 使用中 其他信息 电子设备配对 产品规格参数 包装盒内物品 控制键 与其他音频设备配合适用 07 对讲电话功能 人门指南 LED状态





• 请检查您的设备是否支持蓝牙

*A2DP:高级音频分发模式

HSP:耳机模式

HFP:免提模式

• 非A2DP和其他非蓝牙设备可使用3.5mm音频线连接.

注意:使用3.5mm音频线连接设备时,对讲电话功能不

● 接听/拒绝来电 ② 播放/暂停 ③ 音量减/下一曲 ④ 音量增/上一曲 ⑤ 充电配对指示灯 ● 电源开关(ON /OFF) **●** 辅助设备接人(LINE IN)端口 ● USB充电(DC IN)端口

● MICRO SD卡

03 使用前

蓝牙2.1 with A2DP/HFP/HSP • 使用无线便携式音箱和支持蓝牙的设备,您可以无线播放音乐或使用对讲电话功能. 04 使用前

电子设备配对

LED状态

关闭电源

打开电源

LED同步指示灯(顶面)

• 启动设备上的蓝牙功能

• 蓝牙设备上将出现 "S201"

• 如果设备配对成功,LED灯将停止闪烁.

产品功能

• 无线便携式音箱

• 电话对讲功能

• 可充电锂离子电池

· LINE IN 端口,用于其他音乐播放

• 高达8小时的电池使用时间

• 确保您的便携式蓝牙音箱已充满电或将其连接到电源,同

• 设备将自动寻找,此时音箱顶部的LED灯开始闪烁.

注意:A01在任何给定的时间内只能与一个电子设备配对.

LED灯不亮

LED灯亮(蓝色)

激活启用

・ 将迷你USB线插人直流输人(DC IN)端口 • 要启用音箱,打开位于音箱背后的电源开关. 然后将USB线另一端插入PC/MAC 的USB端口或
 如需要音箱和蓝牙无线设备共同使用时必须进行配对.
 USB电源适配器

注意:当音箱充电时,音箱顶部的LED指示灯会同时显示蓝色 和红色.充电完成后,LED指示灯只会显示蓝色.

将音频线的一端连接到您的个人电子设备,另一端插入音响背面附属设备接人端口(LINE IN)端口.

对讲电话功能 接听电话-按())键 拒绝来电-长按())键2秒. 结束通话-按())键.

配对模式 LED灯慢闪烁(蓝色) LED灯常亮(蓝色) LED充电指示灯(顶面) 充电过程中 LED灯交替闪烁(蓝色/红色) LED灯亮(红蓝色同时亮) 充电完成 08 使用中

07 使用中

··品规格	参数		
产品名称		信噪比	≥75dB
电池规格	可充电式锂电池 (3.7V,1800mAh)	喇叭	4Ω2W
输入	5V/1000mAh	产品尺寸	205.5L*56.5W*66.5H mm
充电时间	大约 3-4 小时	工作条件	<85%, Temp:-20°C to 60°C
使用时间	在70%音量大小下大约5个小时	摆放温度	-10°C-45°C
频率	100Hz-20KHz	储存湿度	75%
失真度	THD+N15% (3.2W)	蓝牙版本	BLUETOOTH V2.1+EDR

ENGLISH

PRODUCT MANUAL «




CATALOG >>

Before use

product function

Operate Guide

Other info In use Electronic device pairing o6 Product specifications o6 02 Other audio equipment with applicable 07 04 Intercom function 05 LED statement







the other end is inserted into the PC/MAC

Notice: when the speaker when charging, LED indicates the exhibit of lanterns speaker at the top while show blue

and red. After charging, LED indicator will display only the blue.

The answer / reject a call play/pause volume down / FF volume up / REW o charge / pairing indication light 6 power key (ON /OFF) LINE IN 8 LINE OUT O DC IN MICRO SD card

03 before use

 Wireless portable speaker Recharge Lion battery Telephone intercom function • LINE IN ,For other music resources 5 hours of battery life

Product function

device, you can use the wireless music or intercom function.

HFP : Hands free mode

3.5mm audio line connection. Notice: use 3.5mm audio line connecting equipment, i ntercom function Can not be used. *A2DP :Advanced audio distribution mode BLUETOOTH 2.1 with A2DP/HFP/HSP HSP :Headset mode

Please check your device is Bluetooth support

Non A2DP and other non Bluetooth device can use

04 before use

Electronic device pairing

 Trun on the initiating device Bluetooth function • Make sure that the Bluetooth portable speakers you have been charged or be connected to the power supply, also need to open the switch.

• Trun on your Bluetooth device, the device will automatically find, LED lamp at the speaker at the top began flashing. • Bluetooth devices will be show "S201"

• If the equipment is the pairing is successful, the LED light will stop flashing.

Note: the Ao1 can only be used at any given time and an electronic device pairing. and the blue transmission distances is :10m

The need for common use must be paired as speakers

and Bluetooth wireless equipment.

With other audio equipment used Connect the audio line to the end of your personal electronic device, the other end is inserted into the audio back accessory equipment access ports (LINE IN) port.

Intercom function Answer the phone-push()) Reject a call- push()) 2 seconds

End the call-push()).

Operate Guide

o7 in use

• The mini USB cable into the DC input (DC IN) port

• To enable the speaker, turn on the power switch is

• Then the USB port or USB power adapter USB line, located behind the speakers

Turn off the power Turn on the power

LED statement

No bright bright (blue) Twinkle(blue) Pairing mode LED charging indicator (top) In the process of charging Twinkle (blue and red in turn) The charging is completed bright (blue and red)

o8 in use

Product specifications Product descripe wireless portable speaker Battery spec Recharge Lion battery (3.7V, 1800mAh) Speaker 4Ω2W DC IN 5V/1000mAh 205.5L*56.5W*66.5H mm Product size Battery use time about 5hours under 70% volume play music Storage temperature -10°C-45°C 100Hz-20KHz THD+N15% (3.2W) Storage Humidity 75% Bluetooth version BLUETOOTH V2.1+EDR

FCC Warning Statement Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures: --Reorient or relocate the receiving antenna. --Increase the separation between the equipment and receiver. --Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. --Consult the dealer or an experienced radio/TV technician