



#### Overview of the product

- Multifunction button  
Handling call functions
- Indicator Light  
Status indication with yellow light
- Charger connector
- Earpieces
- Volume + button
- Volume - button
- Microphone

#### 8. How-to-wear the headset

Your Iqua BHS-702 is designed to be comfortably worn around your neck with the earphone wire, just like wear a necklace. The performance of the device overall is most optimal when the headset is raised to the highest position, closest to the mouth

#### Sales package contents

- Headset
- Wall charger
- 3 pairs of Earplug (1 pair is on headset)
- User guide

#### Product specifications

Model	BHS-702
Size	60 x 28 x 11 mm
Weight	20 g
Talk time	Up to 9 hours
Music time	Up to 7 hours
Standby time	Up to 150 hours
Charging time	Within 2 hours
Battery type	Rechargeable battery with 2.0mm DC jack
Bluetooth Standard	Bluetooth 2.0 EDR
Supported BT profiles	Handsfree (HFP)1.5 and Headset (HSP)1.1
Paired devices	Up to 8, one at a time
Operating Distance	10 meters
Operating temperature range	-10°C to +60°C
Storage temperature range	-40°C to +85°C

#### Getting started

##### Charging the battery

Before using BHS-702, you must charge it for approximately 2 hours. When the battery is fully charged, it provides up to 9 hours of talk time and up to 150 hours of standby time. Always use the charger provided in the sales package.

- Connect the charger cable to BHS-702.
- Plug the charger into a wall socket. The yellow light will turn on.
- When the battery is fully charged, the yellow light will turn off.

##### Switching on and off

###### To switch on the BHS-702

When the headset is powered off, press the Multifunction -button until the yellow light starts flash.

###### To switch off the BHS-702

When the headset is powered on, press the Multifunction -button until the yellow light flashes twice and then turns off.

##### Pairing the Bluetooth headset to a Bluetooth mobile phone

Pairing is the process for linking BHS-702 with your Bluetooth enabled mobile phone. After this process is completed, you can use the BHS-702 with the paired mobile phone. If you want to use the BHS-702 with another mobile phone, you must repeat the pairing process. Even though BHS-702 can be paired with up to 8 compatible phones it can only be connected to one phone at a time. Once it is paired with 8 phones, the 9th paired device will replace the 1st paired device.

- When the headset is powered off, press and hold the Multifunction -button until the yellow light starts flashing rapidly.
- Release the button. BHS-702 is now in pairing mode, waiting for your mobile phone to contact it.
- Complete the pairing with your mobile phone. Please refer your mobile phone manual for details on how to search and pair. When phone has found the headset, it will show Iqua Pendant on its screen. In order to pair with the phone, enter the PIN code 0000.
- After pairing, BHS-702 will automatically connect to your mobile phone. After pairing, some phones do not automatically connect to the headset. If this is the case, please ensure that you connect the phone to the headset (please refer to your mobile phone manual). Once pairing and connection are completed, the yellow light starts flashing.

\* For latest compatibility information please visit [www.iqua.com](http://www.iqua.com)

##### Disconnecting BHS-702 and your phone

Easiest way to disconnect BHS-702 and your phone is simply switch off the BHS-702.

##### Reconnecting the paired headset to a compatible phone

To reconnect the BHS-702 to the last connected phone, simply switch on the headset and it will automatically connect to your phone. Otherwise, make the connection in the phone menu as instructed in the user guide of the phone. If it can't be reconnected then press and hold Vol+ button to reconnect.

#### Call Functions

##### Answer a call

When you receive a call, you hear a ringing tone through the headset. Press the Multifunction -button briefly to answer the incoming call. You will hear a tone once the call is answered.

##### End a call

To end an active call, press the Multifunction -button. You will hear a tone when the call is ended.

##### Reject a call

When you receive an incoming call that you do not want to answer, simply press the Multifunction-button until you hear a sound and call is rejected.

##### Redial the last dialed number

To place a call to the last dialed number, press the Vol+ button when no call is in progress. You will hear a high tone. Please note some phone models do not support redial. With some phone models, press the Vol + button again to dial the number displayed on the phone.

##### Voice dialing (when supported by the phone)

To activate a voice dialing feature of your phone, press the Vol- button when there is no call in active. You can hear a high tone. This will indicate that you can start saying the voice tag. Refer to the mobile phone manual for details. Please note, some phone models do not support voice dialing.

##### Call Waiting

If a new call comes in during another call you want to answer, you can hold the current call and answer to incoming call by pressing the multifunction- button briefly. You will hear a sound when the new call is answered. When you want to end the new call and switch back to the first call press the Multifunction-button until the call is transferred.

##### Call Transferring(supported depends on the mobile phone)

To transfer an active call from the BHS-702 to your mobile phone, press the Vol+ button until the call is transferred to your phone. To transfer an active call from your mobile

phone to the BHS-702, press the Vol+ button or use the functions of your phone as instructed in its user guide.

##### Adjusting volume

Press the Vol+ button briefly to increase the volume. Press the Vol- button briefly to decrease the volume.

##### Mute setting

You can mute the BHS-702 during an ongoing call by pressing the Vol- button until you hear a voice tone. You can unmute the call by pressing the Vol- button.

##### Reset Hardware

In case the headset is jammed you may do hardware reset and restart the headset. Briefly press Multifunction button and Vol+ buttons simultaneously. The headset will be powered off(light turns off) once the hardware is reset.

##### Erase Paired Devices

The BHS-702 can be paired with up to 8 Bluetooth devices, if you want to pair it with more devices, you need to erase the paired device information. To reset the pairing list to BHS-702, press and hold both Vol+ and Vol- buttons simultaneously.

##### Music functions (supported depends on the mobile phone)

###### Start Play

Make sure your headset is connected in A2DP (Advanced Audio Distribution Profile). While listening to music, simply press Multifunction-button briefly to play the music.

###### Pause

While listening the music, press Multifunction-button briefly to pause the music.

###### Skip one track forward

While listening the music, press the Vol+ button to change to the next song.

###### Skip one track back

While listening the music, press the Vol- button to change to the previous song.

###### Stop play

Press the multifunction button until the music stopped.

##### Light indication summary

The BHS-702's LED light is yellow and usually accompanied by a sound signal.

Power on but no Bluetooth connection	Yellow light flashes rapidly
Bluetooth connection on	Yellow light flashes slowly
Pairing mode	Yellow light flashes continuously
Battery low	Yellow light flashes four times and a low tone is played
Battery charging	Yellow light is on continuously in the power off condition

##### Power management

This product is powered by a built-in rechargeable battery which can not be changed. Do not attempt to replace the battery. Rechargeable battery can be charged and discharged hundreds of times, but it will eventually wear out. After a period of time that will vary depending on the use and usage conditions you may find that the built-in battery will power your product for only a couple of hours requiring you to charge more frequently. Do charge your device only with the charger provided in the sales package. Unplug the charger when not in use. Do not leave the device connected to the charger for longer period than needed, since overcharging may shorten the battery lifetime. If left unused a fully charged battery will discharge itself over time. Temperature extremes may affect the ability of the battery to charge. Always try to keep the device between 15 °C and 25 °C (59 °F and 77 °F). Leaving the device in hot or cold places such as in closed car in summer or winter conditions will reduce the capacity and lifetime of the battery. A device with hot or cold battery may not work for a while even when the battery is fully charged. Battery performance is particularly limited in temperatures well below freezing. Do not charge in humid environment.

##### Care and Maintenance

- Do not expose the device to liquid, moisture or humidity as it is not waterproof.
- Do not use or store the device in dusty, dirty areas. Its moving parts and electronic components can be damaged.
- Do not store the device in hot areas. High temperatures can shorten the life of electronic devices, damage batteries, and warp or melt certain plastics.
- Do not store the device in cold areas. When the device returns to its normal temperature, moisture can form inside the device and damage electronic circuit boards.
- Do not drop, knock, or shake the device. Rough handling can break internal circuit boards and fine mechanics.
- Do not use harsh chemicals, cleaning solvents, or strong detergents to clean the device.
- Use a soft, clean, dry cloth to clean any lenses.
- Do not expose your device to contact with sharp objects as this will cause





























environment.

End users must follow the specific operating instructions for satisfying RF exposure compliance. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter. The Bluetooth word mark and logos are owned by Bluetooth® SIG, Inc. and any use of such marks by IQUA is licensed. Other trademarks and trade names belong to their respective owners. Under no circumstances does IQUA assume any liability for loss of or damage to or corruption of data, for any loss of profit, loss of business, revenues, contracts, anticipated savings increased costs or expenses or for any indirect, special, incidental or consequential damages howsoever caused.

The Bluetooth word mark and logos are owned by Bluetooth® SIG, Inc. and any use of such marks by IQUA is licensed. Other trademarks and trade names belong to their respective owners.

Under no circumstances does IQUA assume any liability for loss of or damage to or corruption of data, for any loss of profit, loss of business, revenues, contracts, anticipated savings increased costs or expenses or for any indirect, special, incidental or consequential damages howsoever caused.

Copyright © 2007 Iqua Ltd