

## ADDENDUM TO INSTRUCTION MANUAL

NOTES	ADD NO.	REV.	SEC.
	AA201-00-00	110	2


The information in this manual modifies the RS-232 programming cable used on some models of the V1500X-SCCS System Controller as stated in the manual, XX201.

On some versions of the system controller, the pin for the RS-232 GND connection is not wired according to the standard RS-232 and must be modified when programming the system console using a standard RS-232 cable. To know if you have one of these units:

1. Turn the unit so that the bottom side is facing up.
2. Locate the DIP port hole and remove the black cover.



3. If there are jumpers around the DIP switch, this indicates that the RS-232 cable must be modified.



There are two options to “work around” the GND wiring.

1. Use a standard RS-232 cable but connect a separate ground jumper wire (with alligator clips on either side) between the chassis of the system console and the chassis of the programming PC.

**Note:** *The grounding scheme to the PC chassis may vary from one model to another; therefore, option 1 may not work. In this case, proceed to option 2.*

2. Create a custom cable and connect the pins of the connectors as shown in the user manual that is supplied with the system console (refer to *Flash Upgrade Software*) except on the keypad side, connect the GND wire to pin 7 instead of pin 5.

Copyright © 2010 Vicon Industries Inc. All rights reserved.  
Product specifications subject to change without notice.  
Vicon and its logo is a registered trademarks of Vicon Industries Inc.

Vicon part number 8009-5201-00-00 Rev 110

**VICON INDUSTRIES INC., 89 ARKAY DRIVE, HAUPPAUGE, NEW YORK 11788**  
**TEL: 631-952-CCTV (2288) FAX: 631-951-CCTV (2288) TOLL FREE: 800-645-9116**  
**24-Hour Technical Support: 800-34-VICON (800-348-4266)**  
**UK: 44/(0) 1489-566300 WEB: www.vicon-cctv.com**

## **Vicon Industries Inc.**

### **Corporate Headquarters**

89 Arkay Drive  
Hauppauge, New York 11788  
631-952-CCTV (2288) 800-645-9116  
Fax: 631-951-CCTV (2288)

### **Vicon Europe Headquarters**

Brunel Way  
Fareham, PO15 5TX  
United Kingdom  
44/(0) 1489/566300  
Fax: 44/(0) 1489/566322

### **Vicon Germany**

Kornstiege 3  
D-24537 Neumuenster  
Phone: +49 (0) 4321 8790  
Fax: +49 (0) 4321 879 97

### **Vicon China**

Unit 5, 17/F, Metropole Square  
8 On Yiu Street, Shatin  
New Territories,  
Hong Kong  
(852) 2145-7118  
Fax: (852) 2145-7117

**Internet Address: [www.vicon-cctv.com](http://www.vicon-cctv.com)**

