

Noise Reduction Bluetooth® Headset

Instruction Manual



The Bluetooth® word mark and logos are owned by the Bluetooth SIG, Inc. All other trademarks and trade names are those of their respective owners.

Before using this product, read this manual carefully and retain it for future reference.

1. About Bluetooth Technology

Bluetooth wireless technology is set to revolutionize the personal connectivity by providing freedom from wired connections-enabling links and connectivity between notebook/laptop, mobile phones, portable handheld devices and other Bluetooth enabled devices within 10 meters. Utilizing global sound & digital data 2.4GHz ISM transmission, it makes global communication in the way you've never dreamed of!


2. Getting to Know Your Bluetooth Headset

To use your Bluetooth Headset, please follow these simple steps:

- (1) Charge your Headset. Prior to using the Headset, it is recommended to charge the battery fully for the first time. Normal full charge time is 2 hrs. (approx.)
- (2) Place your Headset and a Bluetooth-enabled mobile phone within 1 meter for pairing.
- (3) Ensure your Headset and mobile phone is placed within 10 meters Bluetooth sensing distance. (Obstruction could cause shorter sensing distance.)

3. Appearance and Function

- (1) Speaker
- (2) Microphone
- (3) Charging Socket
- (4) Multi-Function Button (MFB)
- (5) Volume Increase (V+)
- (6) Volume Decrease (V-)



4. Charging Your Bluetooth Headset

The Bluetooth Headset comes with a built-in rechargeable battery. Prior to using the headset, it is recommended to charge the battery fully for the first time. Normal full charge time is 2 hrs. (approx.)

IMPORTANT:

- (1) Charging indication will be delayed for a few minutes if the headset has not been used for a long period time or the battery is drained. To prolong durability of battery, it is recommended to charge the headset whenever a low battery signal is encountered. When battery becomes low, the LED will flash red every 3 seconds. Under a low battery condition, if headset is continuously used, it will decrease the durability of battery as well as the standby time. This causes a longer charge time than the normal 2 hours and the headset will power off.
- (2) The red LED will flash on while charging, and blue LED will flash on when charging is completed.

5. Turning ON/OFF the Headset

POWER ON:

When the headset is in off mode, press and hold the "MFB" for 3 seconds until you hear a short beep. The blue LED will flash 5 times, and then the headset will automatically re-connect to the last connected mobile phone.

POWER OFF:

When headset is in standby mode, press and hold the "MFB" button for 3 seconds until you hear a short beep. The red LED will flash 5 times before turning off.

6. Pairing

Prior to using the headset for the first time, you must pair it with a Bluetooth-enabled mobile phone. The steps below describe pairing instructions for a typical Bluetooth-enabled mobile phone.

- (1) Place the headset and mobile phone no more than 1 meter apart.
- (2) Ensure the headset is in OFF mode.
- (3) Press and hold the "MFB" button for 6 seconds until the red and blue LED flashes. It is now ready for pairing.
- (4) Activate the Bluetooth function on your mobile phone. (Refer to your mobile phone owner's manual).
- (5) Select "BT Headset" from the list.
- (6) Enter the pre-programmed code "0000" and press "OK" to pair the headset and the phone. When pairing is completed, the red LED will stop flashing and the headset is now in standby mode with the blue LED flashing every 3 seconds.

- (7) Press "Return" to go back to your mobile phone's main menu. Place the mobile phone and headset within 10 meters for recommended sensing distance.

NOTE: If the pairing is not completed within 2 minutes after pairing mode is activated, the headset will power off automatically. You will have to repair the headset using the steps above.

7. Connection/Link between Headset and Mobile Phone

After pairing is completed, headset is always under standby mode. Before you place or answer a call, if the headset icon is not shown on phone screen, please follow the steps below to activate the Bluetooth connection/link through your mobile phone or headset until the headset icon is on the screen.

- (1) On phone: Select the "BT Headset" from the paired list on your phone screen.
- (2) On headset: Short press "MFB" and select "Accept" on phone screen to accept connection.

8. Disconnection between Headset and Mobile Phone

When you need to connect your headset with another Bluetooth-enabled mobile phone, please follow the steps below to disconnect the headset with the pre-paired mobile phone.

- (1) Power off the Headset.
- (2) Select "Disconnecting" on the Bluetooth device list of your mobile phone to remove the connection.

Note: When losing the connection/link, the headset will be automatically power off in 10 minutes. The blue LED will flash twice in every 3 seconds when the headset is not connected with mobile phone.

9. Using the Headset

- (1) ANSWERING CALL
When receiving a phone call, press the "MFB" button to answer the call.
- (2) ENDING CALL
Press the "MFB" button to end a call.
- (3) REJECT CALL
When you hear the ringing tone, press and hold the "MFB" button for 3 seconds to reject the call.
- (4) VOICE DIAL
If your mobile phone is voice dialing enabled, in standby mode, press the "MFB" button and say the voice tag after you hear a beep.

NOTE: Please make sure to record voice tag into the mobile phone before using voice dial function. Functionality varies depending on the mobile phone models. (Refer to your mobile phone owner's manual.)

- (5) LAST NUMBER RE-DIALING
In standby mode, press the "MFB" button twice for last number redial.
- (6) ADJUSTING THE VOLUME
During a call, press the "V+" or "V-" buttons repeatedly until you reach the desired volume level.
- (7) MUTE & UN-MUTE
 - a. Mute: During a call, press and hold the "V-" button for 3 seconds to mute the headset. The red LED will flash on during mute mode.
 - b. Un-Mute: press and hold the "V-" button 3 seconds to un-mute the headset.
- (8) TRANSFERRING CALLS
 - a. Headset to Mobile Phone: During a call, press and hold the "V+" button for 3 seconds. The call is routed to your mobile phone.
 - b. Mobile Phone to Headset: Press and hold the "V+" button for 3 seconds to route the call to the headset.
- (9) HOLD THE CALL
During a call, press the "MFB" button twice to hold the phone call. Press "MFB" button again to resume conversation.
- (10) Answer the Second Call
 - a. When receiving a second call, press "MFB" button twice to hold the first call on line and answer the second call.
 - b. When receiving a second call, press "MFB" button once to end the first call and answer the second call.
- (11) Reject the Second Call
When receiving a second call, press and hold the "MFB" button for 2 seconds to reject the second call.
- (12) Switch Between 2 Phone Calls
 - a. When having 2 calls on the line, press "MFB" button twice to switch between these 2 phone calls.
 - b. When having 2 calls on the line, press "MFB" button once to end the first call and stay with the second call.

10. MultiPoint Feature

- (1) Activate Multipoint Connection
The default setting of headset's multipoint function is off. Please activate the multipoint function for connecting with 2 mobile phones in the same time.
 - a. Multipoint On: Under standby mode, press and hold "V+" button for 6 seconds until you hear a beep. After turn on the multipoint function, the headset will automatically connect to the last 2 mobile phones that has been paired before.

- b. Multipoint Off: Under standby mode, press and hold "V-" button for 6 seconds until you hear a beep. The headset will turn off the multipoint function and power off automatically. When power on the headset again, it will only connect to the last connected Bluetooth device.
- (2) Multipoint Pairing
 - a. FIRST MOBILE PHONE : Pair the headset with one of the Bluetooth-enabled mobile phones.
 - b. SECOND MOBILE PHONE : Power off the headset. Press and hold the "MFB" button for 6 seconds to enter pairing mode again to pair and connect with the second mobile phone.
 - c. Connect with the first paired mobile phone to the headset.

- (3) Multipoint Connection/Link with 2 Mobile Phones
After the multipoint function is activated, please follow the steps below to connect with 2 Bluetooth enabled mobile phones at the same time.

- a. When power on the headset, it will automatically search and connect the last 2 mobile phones that have been connected before.
- b. In standby mode, press and hold "V+" button for 3 seconds until you hear a beep, then the headset will automatically connect the last 2 mobile phones that have been connected before.

- (4) Using the Secondary Mobile Phone through Headset

When connected with 2 Bluetooth mobile phones, the first connected one is primary phone that can use "MFB" button for voice dial and redial. The second connected phone is the secondary phone that will use "V+" button for voice dialing and redialing.

- a. VOICE DIAL : Press "V+" button once to activate the secondary phone's voice dialing function.
- b. RE-DIALING : Press "V+" button twice to redial the last outgoing number of secondary phone.

NOTE:

1. When the headset is in Multipoint off mode and connected with only one mobile phone, it can also enter voice dial function by pressing the "V+" button once, or make last outgoing number re-dialing by pressing "V+" button twice.

11. Low Voltage Protection of Battery

When the voltage of the battery is decreased to 3.3 V, the red LED will flash every 3 seconds, and the headset will be powered off automatically when the voltage is less than 3.0 V.

12. Restore to Default Setting

Follow the steps below to reset the headset to its original setting and remove all previous pairings and connections.

- (1). Ensure the headset is under standby mode.
- (2). Press and hold both of "V+" and "V-" buttons for 6 seconds until the red LED and blue flashes 5 times, then the headset will resume in standby mode. The headset is now back to its original setting. After powering on the headset again, it will enter pairing mode automatically.

NOTES:

If the headset is connected with a mobile phone before restoring to original default setting, it will enter pairing mode automatically after restored to default. If the headset is not connected to the mobile phone before restoring to original default setting, it will be in standby mode after restored to default setting.

13. LED Indication

Headset Status	LED Indication
Power Off Mode	Off
Power On	Blue LED flash 5 times rapidly
Power Off	Red LED flash 5 times rapidly
Standby Mode	Blue LED flash once every 3 seconds
Standby (Disconnect Bluetooth device)	Blue LED flash twice every 3 seconds
Standby-Low Voltage	Red LED flash once every 3 seconds
Talk in progress	Blue LED flash once every 6 seconds
Mute	Red LED steady on
Pairing in progress	The red and blue LED flash on alternately
Charging in progress	Red LED steady on
Charging completed	Blue LED steady on

14. Product Specifications

Bluetooth Compliance: Bluetooth V2.1 + EDR specifications
 Operating Frequency Band: 2.4 GHz ~ 2.48 GHz unlicensed ISM band
 Output Power: Class 2 Power Output, up to 10 meters
 Support Profiles: HSP and HFP1.5 profiles
 Support Multiple Paired Device: Up to 8 Bluetooth Phone can be paired
 Stand-by Time: Up to 150 hours
 Talk Time: Up to 4 hours
 Battery Charging Time: About 2 hours
 Charger Voltage: DC5.0V, 300mA
 Battery: 85 mAh, (Rechargeable Lithium-ion battery)

Manufactured for your Military Exchanges
 ©2012 Exchange
 P.O. BOX 660202
 Dallas, TX 75266-0202
www.shopmyexchange.com
 Printed in China

Please also inform the grantee, that the regulatory text as shown in the manual provided, is not good.
The correct content must be as given below.
It is important that they correct this before placing the product on the US and Canadian market.

FCC Information:

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

1. This device may not cause harmful interference, and 2. This device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B Digital Device, pursuant to Part 15 of the FCC Rules. These limits are designed to this equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the radio or television off and on, the user is encouraged to try to correct interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on another circuit.
- Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.