

TRANSFERRING CALLER ID RECORDS IN MEMORY

1. Make sure the phone is OFF (in standby mode).
2. Press the CALLER ID/VOL (- or +) button to scroll to the desired caller ID.
3. Press the MEM button.
4. Press a number key (0 - 9) to store the number in that memory location. You will hear a confirmation tone.

NOTE: It is important that you format the caller ID records correctly before storing in memory. It is not possible to re-format caller ID records stored in memory.

TO REPLACE AN OLD MEMORY WITH A NEW CID RECORD

1. Repeat steps 1 through 4 in Transferring Caller ID Records in Memory. After you enter the memory location, *REPLACE MEMO?* shows in the display.
2. Press the MEM button again, and the new CID record replaces the old memory in that location. You will hear a confirmation tone.

DELETING THE CURRENT CID RECORD

1. Make sure the phone is **OFF** (not in TALK mode).
2. Use the CALLER ID/VOL (- or +) button to scroll to the desired record.
3. Press DEL/CHAN. The display shows *DELETE CALL ID?*
4. Press DEL/CHAN again to erase the record and the next Caller ID record shows in the display. You will hear a confirmation tone.

DELETING ALL CID RECORDS

1. Make sure the phone is **OFF** (not in TALK mode).
2. Use the CALLER ID/VOL (- or +) button to display any Caller ID record.
3. Press and hold the DEL/CHAN button until *DELETE ALL?* shows in the display.
4. Press DEL/CHAN again to erase all records. You will hear a confirmation tone. The display shows *NO CALLS*.

DIALING A CALLER ID NUMBER

1. Make sure the phone is **OFF** (not in TALK mode).
2. Use the CALLER ID/VOL (- or +) button to display the desired record.
3. Press TALK/END/CALLBACK. The number dials automatically.

CHANGING THE TELEPHONE NUMBER FORMAT

The **FORMAT** button lets you change the format of the displayed telephone number. The available formats are as follows.

- 7-digit** 7-digit telephone number.
- 10-digit** 3-digit area code + 7-digit telephone number.
- 11-digit** long distance code "1" + 3-digit area code + 7-digit telephone number.

1. Use the CALLER ID/VOL (- or +) button to scroll to the number you want to call back.
2. Press TALK/END/CALLBACK. The number dials automatically.

NOTE: If the telephone number cannot be dialed, press the format button to adjust the number, and try again.

MEMORY

Store up to ten 24-digit 15-character numbers in memory for quick dialing. This memory feature is in addition to the CID memory log, which stores up to 40 CID records.

STORING A NAME AND NUMBER IN MEMORY

1. Make sure the phone is **OFF** (not in TALK mode).
2. Press the MEM button.
3. Press the desired memory location (0 through 9) or use CALLER ID/VOL (+ or -) to scroll to the desired memory location.

NOTE: If the memory location is occupied, the memory location number and its contents show in the display.

4. Press the MEM button again. The display shows *ENTER NAME*.

NOTE: If you don't want to enter the name, skip step 5.