

Call transfer using Intercom

While on an outside call, you can use the intercom feature to transfer the call from one handset to another.

- Press **MENU** on your handset during a call.
- Press **↵** or **↵** to scroll to **Intercom**, and then press **SELECT**. The current call is put on hold. Use the dialing keys to enter a destination handset number.
- To answer the intercom call, press **HOME**, **CALL**, **☎**, or any dialing key on the destination handset. You can now have a private conversation before transferring the call.
- To transfer the call, press **OFF** on the initiating handset or place the initiating handset back in the telephone base or charger.
- To end the call, press **OFF** on the destination handset or place the destination handset back in the telephone base or charger.

Phonebook

The phonebook can store up to 1000 entries, which are shared by all handsets. Each entry may consist of a telephone number up to 30 digits, and a name up to 15 characters.

Add a phonebook entry

- Press **MENU** when the handset is not in use.
- Scroll to **Phonebook** then press **SELECT**.
- Press **SELECT** again to choose **Add new entry**.
- Use the dialing keys to enter the number (up to 30 digits).
- Press **SELECT** to move to the name.
- Use the dialing keys to enter the name (up to 15 characters). For optimum daily performance, avoid other characters of that particular key.
- Press **SELECT** to save.

While entering numbers and names, you can:

- Press **DELETE** to erase a digit or character.
- Press and hold **DELETE** to erase the entire entry (entering phone numbers only).
- Press **↵** or **↵** to move the cursor to the left or right.
- Press and hold **PAUSE** to insert a dialing pace (for entering phone numbers only).
- Press **↵** to add **X** (if appears) or **#** to add **#** (if appears) (entering phone numbers only).
- Press **0** to add a space (for entering names only).

Expand your telephone system

You can add new handsets (**DS6700**), cordless headsets (**IS6100**, **IS6200** or **AT&T TL7900**) or speakerphones (**MA3222** or **AT&T TL6013**) to your telephone system. All accessories are sold separately. Your telephone base supports a maximum of five devices.

For more details, refer to the user's manual that comes with your new device.

ECO mode

This power conserving technology reduces power consumption for optimal battery performance. The ECO mode activates automatically whenever the handset is synchronized with the telephone base.

General product care

Taking care of your telephone
Your cordless telephone contains sophisticated electronic parts, so it must be treated with care. Avoid rough treatment.

Place the handset down gently. Save the original packing materials to protect your telephone if you ever need to ship it.

Avoid water

Your telephone can be damaged if it gets wet. Do not use the handset outdoors in the rain, or handle it with wet hands. Do not install the telephone base near a sink, bathtub or shower.

Electrical storms
Electrical storms can sometimes cause power surges harmful to electronic equipment. For your own safety, take caution when using electrical appliances during storms.

Cleaning your telephone
Your telephone has a durable plastic casing that should retain its luster for many years. Clean it only with a dry non-abrasive cloth. Do not use dampened cloth or cleaning solvents of any kind.

Frequently asked questions

The following are the questions most frequently asked about the cordless telephone. If you cannot find the answer to your question, visit our website at www.vtechphones.com or call **1 (800) 995-9511** for customer service. In Canada, go to www.vtechcanada.com or call **1 (800) 267-7377**.

My telephone does not work at all.

The display shows **No line**. I cannot hear the dial tone.

The display shows **HS**.

I cannot add and connect my cord to the telephone base.

The cell phone reception in my house is poor and I cannot connect it to my **DS6722**.

The answering system does not record messages.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The display shows **HS**. I cannot hear the dial tone.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

The remote voice control feature does not work.

Temporary ringer silencing

When the telephone is ringing, you can temporarily silence the ringer of the handset without disconnecting the call. The next call rings normally at the preset volume.

- Press **OFF** or **MUTE** on the handset. The handset displays **☎**.

About answering system and voicemail service

For message recording, your telephone has a built-in answering system, and it also supports voicemail service offered by your telephone service provider (subscription is required, and fee may apply).

The main features between them are:

Category Built-in answering system Voicemail from telephone service

Storage Messages are stored in the telephone base. Your messages will not be deleted automatically. You have to delete your messages manually. Messages are stored in a server or system provided by your telephone service provider. Your messages may be automatically deleted after a period of time. Contact your telephone service provider for more details.

Method to retrieve messages When you received new messages, usually there are two ways: • Press **▶** on the telephone base, or • Access remote service provided by your service provider. When you received new messages, usually there are two ways: • Press **▶** on the telephone base, or • Access remote service provided by your service provider.

Ringer tone

You can choose from different ringer tones.

- Press **MENU** when the handset is not in use.
- Scroll to **Ringers**, and then press **SELECT**.
- Scroll to choose **Home ringtone** or **Cell ringtone**, and then press **SELECT**.
- Use the dialing keys to edit the name, and then press **SELECT** to save.

☎NOTE

• If you turn off the ringer volume, you will not hear ringer tone samples.

Handset ringer volume

You can adjust the ringer volume level, or turn the ringer off.

- Press **MENU** when the handset is not in use.
- Scroll to **Ringers**, and then press **SELECT**.
- Scroll to choose **Home volume** or **Cell volume**, and then press **SELECT**.
- Scroll to adjust the volume, and then press **SELECT** to save.

☎NOTE

• If the handset ringer volume is set to off, that handset is silenced for all incoming calls except paging tone.

Telephone base ringer volume

You can adjust the telephone base volume level by pressing **VOL ▲** / **VOL ▼** on the telephone base when idle.

Set your built-in answering system

Your answering system has various features, read below for the basic settings.

The answering system can record and store up to 99 messages. Each message can be up to three minutes in length. The total storage capacity for the announcement, messages and memos is approximately 23 minutes. The actual recording time depends on individual message characteristics.

Your answering system allows you to set your announcement, to save and delete messages, activate call screening, to set number of rings before pick up, and to access remotely.

The announcement can be up to 90 seconds in length.

1. Press **MENU** when the handset is not in use.

2. Scroll to **Answering sys** and then press **SELECT** twice.

3. The handset announces, "To play, press 2. To record, press 7."

4. Press 7 to record. The handset announces, "Record after the tone. Press 5 when you are done." After the tone, speak towards the handset microphone.

5. Press 5 when done.

Play the announcement

1. Press **MENU** when the handset is not in use.

2. Scroll to **Answering sys** and then press **SELECT** twice.

3. The handset announces, "To play, press 2. To record, press 7."

4. Press 2 to play the announcement.

Delete the announcement

1. Press **MENU** when the handset is not in use.

2. Scroll to **Answering sys** and then press **SELECT** twice.

3. The handset announces, "To play, press 2. To record, press 7."

4. Press 3 to delete your own recorded announcement.

Set number of rings

You can set the answering system to answer an incoming call after 2, 3, 4, 5 or 6 rings; or toll saver. If you choose toll saver, the answering system answers a call after 2 rings when you have new messages, or after 4 rings when you have no new messages.

1. Press **MENU** when the handset is not in use.

2. Scroll to **Answering sys** then press **SELECT**.

3. Scroll to **Ans sys setup** then press **SELECT**.

4. Scroll to **# of rings** then press **SELECT**.

5. Scroll to choose 2, 3, 4, 5, 6 or **Toll saver**.

6. Press **SELECT** to save and you hear a confirmation tone.

☎NOTE

• If you have muted the first ring, you will hear one ring less before the answering system answers the incoming calls.

☎NOTE

• If you have muted the first ring, you will hear one ring less before the answering system answers the incoming calls.

☎NOTE

• If you have muted the first ring, you will hear one ring less before the answering system answers the incoming calls.

☎NOTE

• If you have muted the first ring, you will hear one ring less before the answering system answers the incoming calls.

☎NOTE

• If you have muted the first ring, you will hear one ring less before the answering system answers the incoming calls.

☎NOTE

• If you have muted the first ring, you will hear one ring less before the answering system answers the incoming calls.

☎NOTE

• If you have muted the first ring, you will hear one ring less before the answering system answers the incoming calls.

☎NOTE

• If you have muted the first ring, you will hear one ring less before the answering system answers the incoming calls.

☎NOTE

• If you have muted the first ring, you will hear one ring less before the answering system answers the incoming calls.

☎NOTE

• If you have muted the first ring, you will hear one ring less before the answering system answers the incoming calls.

☎NOTE

• If you have muted the first ring, you will hear one ring less before the answering system answers the incoming calls.

☎NOTE

• If you have muted the first ring, you will hear one ring less before the answering system answers the incoming calls.

☎NOTE

• If you have muted the first ring, you will hear one ring less before the answering system answers the incoming calls.

☎NOTE

• If you have muted the first ring, you will hear one ring less before the answering system answers the incoming calls.

☎NOTE

• If you have muted the first ring, you will hear one ring less before the answering system answers the incoming calls.

☎NOTE

☎NOTE

To turn on or off with the handset:

1. Press **MENU** when the handset is not in use.

2. Scroll to highlight **Answering sys**, and then press **SELECT**.

3. Scroll to highlight **Answer on/off**, and then press **SELECT**.

4. Scroll to highlight **On** or **Off**, and then press **SELECT** to save. You hear a confirmation tone.

Default announcement

The telephone is preset with a greeting that answers calls with "Hello, please leave a message after the tone." You can use this preset announcement, or replace it with your own.

Record your own announcement

The announcement can be up to 90 seconds in length.

1. Press **MENU** when the handset is not in use.

2. Scroll to **Answering sys** and then press **SELECT** twice.

3. The handset announces, "To play, press 2. To record, press 7."

4. Press 7 to record. The handset announces, "Record after the tone. Press 5 when you are done." After the tone, speak towards the handset microphone.

5. Press 5 when done.

Play the announcement

1. Press **MENU** when the handset is not in use.

2. Scroll to **Answering sys** and then press **SELECT** twice.

3. The handset announces, "To play, press 2. To record, press 7."

4. Press 2 to play the announcement.

Delete the announcement

1. Press **MENU** when the handset is not in use.

2. Scroll to **Answering sys** and then press **SELECT** twice.

3. The handset announces, "To play, press 2. To record, press 7."

4. Press 3 to delete your own recorded announcement.

Turn the answering system on or off

The answering system must be turned on to answer and record messages.

To turn on or off with the telephone base:

- Press **ANS ON** on the telephone base to turn the built-in answering system on or off.

To turn on or off with the telephone base:

- Press **ANS ON** on the telephone base to turn the built-in answering system on or off.

To turn on or off with the telephone base:

- Press **ANS ON** on the telephone base to turn the built-in answering system on or off.

To turn on or off with the telephone base:

- Press **ANS ON** on the telephone base to turn the built-in answering system on or off.

To turn on or off with the telephone base:

- Press **ANS ON** on the telephone base to turn the built-in answering system on or off.

To turn on or off with the telephone base:

- Press **ANS ON** on the telephone base to turn the built-in answering system on or off.

To turn on or off with the telephone base:

- Press **ANS ON** on the telephone base to turn the built-in answering system on or off.

To turn on or off with the telephone base:

- Press **ANS ON** on the telephone base to turn the built-in answering system on or off.

To turn on or off with the telephone base:

- Press **ANS ON** on the telephone base to turn the built-in answering system on or off.

To turn on or off with the telephone base:

- Press **ANS ON** on the telephone base to turn the built-in answering system on or off.

To turn on or off with the telephone base:

- Press **ANS ON** on the telephone base to turn the built-in answering system on or off.

To turn on or off with the telephone base: